SENSE DSW EXERCISER

TABLE OF CONTENTS

1. PURPOSE

        THE SENSE DSW PROGRAM IS DESIGNED TO CONTINUOUSLY SENSE THE DSW,
        USING THE AREA CODE SET INTO THE DATA ENTRY SWITCHES. THE PROGRAM
        WILL PRINT THE FIRST SENSE WORD RECEIVED AND THEREAFTER PRINT THE
        WORD RECEIVED ANYTIME IT CHANGES. THE INITIAL SENSE WILL BE
        NON-RESETABLE. THE PROGRAM WILL THEN SENSE RESETABLE, FOLLOWED BY A
        SENSE NON-RESETABLE. THEREAFTER ALL SENSES WILL BE NON-RESETABLE,
        UNLESS THE WORD RECEIVED CHANGES. FOLLOWING ANY CHANGE IN THE WORD,
        THE NEW WORD WILL BE PRINTED AND A RESETABLE SENSE ISSUED.

2. REQUIREMENTS

    2.1   PROGRAM REQUIREMENTS

        THE BASIC DIAGNOSTIC LOADER IS REQUIRED, TO LOAD THE SENSE DSW
        PROGRAM.

    2.2   EQUIPMENT REQUIREMENTS

        A.   1442 CARD READ/PUNCH OR 1054 PAPER TAPE READER.
        B.   1053/1816 TYPEWRITER, OR 1443 PRINTER.
        C.   1800 PROCESSOR/CONTROLLER.

SENSE DSW EXERCISER

3. OPERATING PROCEDURE

    3.1   PROGRAM LOADING

        REFER TO BASIC LOADER DOCUMENTATION FOR LOADING INSTRUCTIONS. AFTER
        LOADING PROGRAM WILL STOP AT WAIT 1. SEE SECT. 3.5, PROGRAM HALTS.

    3.2   OPERATION

    3.2.1 TYPICAL OPERATING PROCEDURE

        A.   WITH PROGRAM STOPPED AT WAIT 1, SET THE DESIRED AREA CODE PLUS
             ANY NECESSARY MODIFIERS IN THE DATA ENTRY SWITCHES EXACTLY AS
             THEY SHOULD APPEAR IN THE SENSE DSW IOCC WORD. SEE TABLE 1.

             NOTE. DO NOT SET THE FUNCTION IN THE SWITCHES. ONLY THE AREA
             CODE AND MODIFIERS SHOULD BE SET.

        B.   PRESS START BUTTON.
        C.   WITH PROGRAM STOPPED AT WAIT 2, SET OPTIONS PER TABLE 2.

                    TABLE 1 - AREA CODE - REQUIRED

        1. SWITCHES MAY BE SET PRIOR TO PROGRAM LOADING, OR AT WAIT 1.
        2. ONCE PROGRAM EXECUTION HAS STARTED ANY CHANGE IN THESE SWITCHES WILL
           BECOME EFFECTIVE ONLY IF STOP, RESET, AND START BUTTONS ARE PRESSED,
           WHICH WILL RETURN PROGRAM TO WAIT 1.

```
*********************************************************************
*   DATA ENTRY SWITCHES                                            *
* 0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 *      DESCRIPTION          *
*                                                                  *
*     X X X                             X   NOT TO BE USED         *
*                                                                  *
* Y Y Y Y Y..........................  DESIRED AREA CODE           *
*                                                                  *
*           M M M M M M M......  MODIFIERS AS NECESSARY            *
*                                                                  *
*********************************************************************
```

    3.2.2 OPERATING OPTIONS

        IF OPTIONS ARE DESIRED SET SWITCHES DESIRED FROM TABLE 2 AND
        DEPRESS THE START BUTTON.

                    TABLE 2 - OPERATING OPTIONS

        1. THESE SWITCHES MAY BE CHANGED AT ANY TIME.

```
*********************************************************************
*.   DATA ENTRY SWITCHES                *DESCRIPTION               *
* 0 1 2 3 4 5 6 7 8 9 10 11 13 14 15 *                             *
*                    1...........BYPASS PRINTOUT                   *
*                    1....................USE 1443 AS OUTPUT PRINTER*
*********************************************************************
```

    3.3   TERMINATING PROCEDURE

        THIS PROGRAM WILL RUN CONTINUOUSLY. TO TERMINATE, DEPRESS STOP BUTTON

3.4   RESTART PROCEDURE

DEPRESS STOP, RESET, AND START BUTTONS. PROGRAM SHOULD RETURN TO
WAIT 1. IF THIS DOES NOT OCCUR, PROGRAM MUST BE RELOADED.

3.5   PROGRAM HALTS

PROGRAM WAITS ARE USED IN THIS PROGRAM, AND ARE IDENTIFIED BY
REFERENCING THE B REG AND I REG.

A PROGRAM WAIT IS OF THE FORM,

    30XX, (B REG).

A DESCRIPTION OF THE INDIVIDUAL PROGRAM WAITS CAN BE FOUND AT THE
BEGINNING OF THE PROGRAM LISTING. A TYPICAL WAIT DESCRIPTION FOLLOWS.
IT IS INCLUDED TO SHOW THE FORMAT OF THE LISTING, AND IT IS NOT
NECESSARILY A DESCRIPTION OF AN ACTUAL WAIT.

****

3001 0 01ED   DC   WAIT1+1
              •   WAIT 1
              •
              •   ONE OF THE METERED I/O UNITS
              •   FAILED TO SEND A RESPONSE
              •   INTERRUPT TO THE PROGRAM. INDEX
              •   REGISTER 1 WILL HAVE THE ADDRESS
              •   OF THE IOCC. THE AREA CODE WILL
              •   INDICATE THE I/O UNIT NOT READY.
              •   IF A 2401/02 DRIVE IS NOT READY,
              •   PROGRAM WILL NOT STOP AT WAIT 1.

****

B REG, (FIRST 4 DIGIT GROUP) CORRESPONDS TO B REG READING.

I REG, (SECOND 4 DIGIT GROUP) CORRESPONDS TO I REG READING.

4. PRINTOUTS

THIS PROGRAM HAS ONLY ONE PRINTOUT. THIS PRINTOUT WILL OCCUR ON THE
INITIAL SENSE OF THE DSW AND ON ANY CHANGE OF THE SENSE WORD
RECEIVED. THE PRINTOUT APPEARS AS FOLLOWS,

PID MID DSW RECEIVED

BA00 A001 XXXX

5. COMMENTS

THIS PROGRAM IS DESIGNED PRIMARILY AS A SCOPING AID. THE PROGRAM HAS
NO DIAGNOSTIC ABILITY, BUT WILL MERELY SENSE DSW OF SPECIFIED
DEVICE. THE PRINTOUT IS PROVIDED AS A CONVENIENCE. ONE POSSIBLE USE
IS AT INSTALLATION, WHERE POINTS COULD BE SHORTED AND PROGRAM WOULD
PRINT WHAT IT RECEIVED.

6. APPENDIX (NONE)

```
028C                    ABS
                        ORG      /3001                                        8BA00000
                *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX                 8BA00010
                *XXXXXXXXXXXXXXXX PROGRAMMED WAITS XXXXXXXXXX                  8BA00020
                *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX                 8BA00030
                                                                             8BA00040
3001 0  0137            DC       WAIT1+1    WAIT FOR AREA CODE                8BA00050
                        .                   AND MODIFIER TO BE                8BA00060
                        .                   SET IN THE DATA SWS.              8BA00070
                        .                   PUSH START TO CONTINUE.           8BA00080
                        .                                                     8BA00090
3002 0  013D            DC       WAIT2+1    WAIT FOR PROGRAM CONTROL          8BA00100
                        .                   SWITCHES TO BE SET.               8BA00110
                        .                   PUSH START TO CONTINUE.           8BA00120
                        .                                                     8BA00130
3003 0  01DC            DC       WAIT3+1    1443 PRINTER IS NOT               8BA00140
                        .                   READY.  MAKE THE                  8BA00150
                        .                   PRINTER READY AND                 8BA00160
                        .                   PUSH START TO                     8BA00170
                        .                   CONTINUE.                         8BA00180
                        .                                                     8BA00190
3004 0  0263            DC       WAIT4+1    THE TYPEWRITER IS                 8BA00200
                        .                   NOT READY.  MAKE THE              8BA00210
                        .                   TYPEWRITER READY AND              8BA00220
                        .                   PUSH START TO CONTINUE.           8BA00230
                        .                                                     8BA00240
3005                    ORG      300                                          8BA00250
012C 0  BA00            DC       /BA00      PID                               8BA00260
012D 00 0C0001EC  BEGN  XIO  L   MASK0      MASK ALL INTRPTS                  8BA00265
012F 00 0C0001EE        XIO  L   MASK1                                        8BA00270
0131 0  C856            LDD      REST       GET RESTART                       8BA00280
0132 00 DC000000        STD  L   0          SET IN ZERO                       8BA00290
                *                                                             8BA00300
0134 0  1000      START NOP                                                   8BA00310
0135 0  C051            LD       DSW+1      GET SNSE IOCC                     8BA00320
0136 0  3001      WAIT1 WAIT     1          WAIT FOR SW SETTING               8BA00330
0137 0  084C            XIO      RDBSW      READ DATA SWS                     8BA00340
                *                                                             8BA00350
0138 0  C051            LD       BSW        GET DATA SWS                      8BA00360
0139 0  F04C            EOR      DSW        SET IN SENSE IOCC                 8BA00370
013A 0  D04C            STO      DSW+1      SAVE                              8BA00380
013B 0  C04B            LD       DSW+1      GET AREA CODE                     8BA00390
013C 0  3002      WAIT2 WAIT     2          WAIT FOR CONTROL SWS              8BA00400
                *                                                             8BA00410
013D 0  0848            XIO      DSW        SENSE DEVICE                      8BA00420
013E 0  D04C            STO      DSW1       SAVE                              8BA00430
                *                                                             8BA00440
013F 0  0844      PRINT XIO      RDBSW      READ DATA SWS                     8BA00450
0140 0  C049            LD       BSW        GET SWS                           8BA00460
0141 0  1802            SRA      2                                            8BA00470
0142 0  4804            BSC      E                                            8BA00480
0143 0  7013            MDX      BYPAS      IS BYPASS PRINT ON                8BA00490
0144 0  C046            LD       DSW1       YES                               8BA00500
0145 00 D400018E        STO  L   HEXWD      GET SENSE WD                      8BA00510
0147 00 440001A4        BSI  L   HEXCV      STORE IN CONV RTN                 8BA00520
0149 00 CC0001C4        LDD  L   HEXCD      GO CONVERT TO HEX   SRC           8BA00530
014B 00 DC000196        STD  L   MSG        GET CONVERTED WD                  8BA00540
                *                           SET IN MSG                        8BA00550
014D 0  0836            XIO      RDBSW      READ DATA SWS                     8BA00560
014E 0  C03B            LD       BSW        GET SWS                           8BA00570
014F 0  1009            SLA      9                                            8BA00580
0150 0  4828            BSC      +Z                                          8BA00590
0151 0  7003            MDX      PR143      SKIP = USE TYPE                   8BA00600
0152 00 440001F2        BSI  L   LOGC       CONVERT AND TYPE    SRC           8BA00610
0154 0  7002            MDX      BYPAS                                        8BA00620
0155 00 440001D6  PR143 BSI  L   PR43       PRINT ON 1443       SRC           8BA00630
0157 0  C02F      BYPAS LD       DSW+1      GET SENSE IOCC                    8BA00640
0158 0  F034            EOR      ONE        ADD RESET BIT                     8BA00660
```

```
0159 0  D02D            STO      DSW+1      SAVE                              8BA00670
                *                                                             8BA00680
015A 0  082B            XIO      DSW        SENSE WITH RESET                  8BA00690
015B 0  D02F            STO      DSW1       SAVE                              8BA00700
                *                                                             8BA00710
015C 0  C02A      SNNRS LD       DSW+1      GET SENSE IOCC                    8BA00720
015D 0  1801            SRA      1          ELIMINATE RESET BIT               8BA00730
015E 0  1001            SLA      1                                            8BA00740
015F 0  D027            STO      DSW+1      SAVE                              8BA00750
                *                                                             8BA00760
0160 0  0825            XIO      DSW        SENSE-NO RESET                    8BA00770
0161 0  D02A            STO      DSW2       SAVE                              8BA00780
C162 0  F028            EOR      DSW1                                         8BA00790
0163 00 4C18015C        BSC  L   SNNRS,+-   HAS WD CHANGED                    8BA00800
0165 0  C026            LD       DSW2       GET NEW DSW                       8BA00810
0166 0  D024            STO      DSW1       SAVE                              8BA00820
0167 0  081C            XIO      RDBSW      READ DATA SWS                     8BA00830
0168 0  C021            LD       BSW        GET SWS                           8BA00840
0169 0  1802            SRA      2                                            8BA00850
016A 00 4C04017F        BSC  L   BPAS1,E    BRANCH = BYPASS PRINT             8BA00860
016C 0  C01E            LD       DSW1       GET DSW                           8BA00870
016D 00 D40001BE        STO  L   HEXWD      SET                               8BA00880
016F 00 440001A4        BSI  L   HEXCV      GO CONVERT          SRC           8BA00890
0171 00 CC0001C4        LDD  L   HEXCD      GET CONVERTED WD                  8BA00900
0173 00 DC000196        STD  L   MSG        SET IN MSG                        8BA00910
0175 0  080E            XIO      RDBSW      READ DATA SWS                     8BA00920
0176 0  C013            LD       BSW        GET SWS                           8BA00930
0177 0  1009            SLA      9                                            8BA00940
0178 00 4C28017D        BSC  L   PR433,+Z   BRANCH = USE 1443                 8BA00950
017A 00 440001F2        BSI  L   LOGC       CONVERT AND TYPE    SRC           8BA00960
017C 0  7002            MDX      BPAS1                                        8BA00970
017D 00 440001D6  PR433 BSI  L   PR43       PRINT ON 1443       SRC           8BA00980
017F 0  C007      BPAS1 LD       DSW+1      GET SENSE IOCC                    8BA00990
0180 0  F00C            EOR      ONE        SET RESET BIT                     8BA01000
0181 0  D005            STO      DSW+1      SAVE                              8BA01010
0182 0  0803            XIO      DSW        SENSE WITH RESET                  8BA01020
0183 0  70D8            MDX      SNNPS                                        8BA01030
                *                                                             8BA01040
                *                                                             8BA01050
                *                                                             8BA01060
                *                                                             8BA01070
0184    0000            BSS  E   0                                            8BA01080
0184 0  018A      RDBSW DC       BSW        READ DATA SWS IOCC                8BA01090
0185 0  0240            DC       /0240                                        8BA01100
                *                                                             8BA01110
0186 0  0700      DSW   DC       /0700      SENSE DSW IOCC                    8BA01120
0187 0  0000            DC       /0000                                        8BA01130
                *                                                             8BA01140
0188 00 4C00012D  REST  BSC  L   BEGN       RESTART                           8BA01150
                *                                                             8BA01160
018A 0  0000      BSW   DC       0          DATA SW STORAGE                   8BA01170
018B 0  0000      DSW1  DC       0          1ST DSW STORAGE                   8BA01180
018C 0  0000      DSW2  DC       0          2ND DSW STORAGE                   8BA01190
018D 0  0001      ONE   DC       1          CONSTANT ONE                      8BA01200
                *                                                             8BA01210
                *                                                             8BA01220
018E    0000            BSS  E   0                                            8BA01230
018E 0  0009      PRARO DC       9          WORD COUNT                        8BA01240
018F 0  3231      PRAR1 DC       /3231      B  A                              8BA01250
0190 0  0A0A            DC       /0A0A      0  0                              8BA01260
0191 0  0000            DC       /0000                                        8BA01270
0192 0  310A            DC       /310A      A  0                              8BA01280
0193 0  0A01            DC       /0A01      0  1                              8BA01290
0194 0  0000            DC       /0000                                        8BA01300
0195 0  0000            DC       /0000                                        8BA01310
0196 0  0000      MSG   DC       /0000                                        8BA01320
0197 0  0000            DC       /0000                                        8BA01330
                                                                             8BA01340
```

SENSE DSW EXERCISER

0198 0 FFFF	TERM	DC	/FFFF	TERMINATOR	8BA01350
	*				8BA01360
0199 0 8121	OUTP1	DC	/8121	TPWRITER MSG AREA	8BA01370
019A 0 0000	OUTPT	DC	0		8BA01380
019B 0 0000		DC	0		8BA01390
019C 0 0000		DC	0		8BA01400
019D 0 0000		DC	0		8BA01410
019E 0 0000		DC	0		8BA01420
019F 0 0000		DC	0		8BA01430
01A0 0 0000		DC	0		8BA01440
01A1 0 0000		DC	0		8BA01450
01A2 0 0000		DC	0		8BA01460
01A3 0 FFFF		DC	/FFFF		8BA01470
	*				8BA01480
	*			HEXADECIMAL CONVERSION	8BA01490
	*				8BA01500
01A4 0 0000	HEXCV	DC	0	SE	8BA01510
01A5 0 6204		LDX	2 4	CONVERSION INDEX	8BA01520
	*				8BA01530
01A6 0 C017		LD	HEXWD	GET WORD TO CONVERT	8BA01540
01A7 0 1890		SRT	16	SET IN Q	8BA01550
01A8 0 1010		SLA	16	CLEAR A	8BA01560
01A9 0 1084	HEXC1	SLT	4	GET CHARACTER	8BA01570
01AA 0 D001		STO	HEXC1+3		8BA01580
01AB 00 67000000		LDX	L3 0	SET CODE TABLE INDEX	8BA01590
	*				8BA01600
01AD 00 C70001C6		LD	L3 CODEH	GET CHARACTER	8BA01610
01AF 00 D60001BE		STO	L2 HEX00-1	SAVE	8BA01620
01B1 0 1010		SLA	16		8BA01630
	*				8BA01640
01B2 0 72FF		MDX	2 -1	CHECK IF DONE	8BA01650
01B3 0 70F5		MDX	HEXC1		8BA01660
	*				8BA01670
01B4 0 C00D		LD	HEX00+3	PACK CODED WORDS	8BA01680
01B5 0 1008		SLA	8		8BA01690
01B6 0 E80A		OR	HEX00+2		8BA01700
01B7 0 D00C		STO	HEXCD		8BA01710
01B8 0 C007		LD	HEX00+1		8BA01720
01B9 0 1008		SLA	8		8BA01730
01BA 0 E804		OR	HEX00		8BA01740
01BB 0 D009		STO	HEXCD+1		8BA01750
	*				8BA01760
01BC 00 4C8001A4		BSC	I HEXCV	RETURN TO USER SX	8BA01770
	*				8BA01780
	*			CONSTANTS	8BA01790
	*				8BA01800
018E 0 0000	HEXWD	DC	0	WORD TO CONVERT	8BA01810
01BF 0 0000	HEX00	DC	0	*	8BA01820
01C0 0 0000		DC	0	* UNPACKED CODED	8BA01830
01C1 0 0000		DC	0	* WORD	8BA01840
01C2 0 0000		DC	0	*	8BA01850
	*				8BA01860
01C4 0000		BSS	E 0		8BA01870
	*				8BA01880
01C4 0 0000	HEXCD	DC	0	* PACKED CODED WORD	8BA01890
01C5 0 0000		DC	0	*	8BA01900
	*				8BA01910
	*			CONVERSION TABLE	8BA01920
	*				8BA01930
01C6 0 000A	CODEH	DC	/000A	0	8BA01940
01C7 0 0001		DC	/0001	1	8BA01950
01C8 0 0002		DC	/0002	2	8BA01960
01C9 0 0003		DC	/0003	3	8BA01970
01CA 0 0004		DC	/0004	4	8BA01980
01CB 0 0005		DC	/0005	5	8BA01990
01CC 0 0006		DC	/0006	6	8BA02000
01CD 0 0007		DC	/0007	7	8BA02010
01CE 0 0008		DC	/0008	8	8BA02020

SENSE DSW EXERCISER

01CF 0 0009		DC	/0009	9	8BA02030
01D0 0 0031		DC	/0031	A	8BA02040
01D1 0 0032		DC	/0032	B	8BA02050
01D2 0 0033		DC	/0033	C	8BA02060
01D3 0 0034		DC	/0034	D	8BA02070
01D4 0 0035		DC	/0035	E	8BA02080
01D5 0 0036		DC	/0036	F	8BA02090
	*				8BA02100
	*				8BA02110
	*			PRINT ON 1443 PRINTER	8BA02120
	*				8BA02130
01D6 0 0000	PR43	DC	0	SE	8BA02140
01D7 0 C012		LD	SNSPR	GET SENSE IOCC	8BA02150
01D8 0 D012		STO	SNSPR+1	SET	8BA02160
	*				8BA02170
	*				8BA02180
01D9 0 0810		XIO	SNSPR	CK FOR PRINTER READY	8BA02190
01DA 0 4804		BSC	E		8BA02200
01DD 0 3003	WAIT3	WAIT	3	PRINTER IS NOT READY	8BA02210
01DC 0 0813		XIO	WRPR	WRITE	8BA02220
	*				8BA02230
01DD 0 080C	PR431	XIO	SNSPR	WAIT FOR NOT COMPLTE	8BA02240
01DE 0 1002		SLA	2		8BA02250
01DF 0 4810		BSC	-	IS PRINTER COMPLETE	8BA02260
01E0 0 70FC		MDX	PR431	NO	8BA02270
	*				8BA02280
01E1 0 C009		LD	SNSPR+1	GET IOCC	8BA02290
01E2 0 F0AA		EOR	ONE	SET BIT 15	8BA02300
01E3 0 D007		STO	SNSPR+1	SAVE	8BA02310
	*				8BA02320
01E4 0 0805	PR432	XIO	SNSPR	SENSE	8BA02330
01E5 0 1801		SRA	1		8BA02340
01E6 0 4804		BSC	E	IS PRINTER BUSY	8BA02350
01E7 0 70FC		MDX	PR432	YES	8BA02360
	*				8BA02370
01E8 00 4C8001D6		BSC	I PR43	EXIT SX	8BA02390
	*				8BA02400
	*			CONSTANTS	8BA02410
	*				8BA02420
01EA 0000		BSS	E 0		8BA02430
01EA 0 3700	SNSPR	DC	/3700	SENSE IOCC	8BA02440
01EB 0 0000		DC	0		8BA02450
	*				8BA02460
01EC 0 FFFF	MASKO	DC	/FFFF	MASK IOCCS	8BA02470
01ED 0 0480		DC	/0480		8BA02480
01EE 0 FFFF	MASK1	DC	/FFFF		8BA02490
01EF 0 0481		DC	/0481		8BA02510
	*				8BA02520
01F0 0 018E	WRPR	DC	PRARO	WRITE IOCC	8BA02530
01F1 0 3500		DC	/3500		8BA02540
	*				8BA02550
	*			ROUTINE TO CONVERT PRINTER	8BA02560
	*			PACKED CODE TO PACKED TYPE	8BA02570
	*				8BA02580
01F2 0 0000	LOGC	DC	0	SE	8BA02590
01F3 0 1010		SLA	16		8BA02600
01F4 0 D036		STO	LOX00	CLEAR HALF WD SW	8BA02610
01F5 0 692E		STX	1 LOGC7+1	SAVE IX 1	8BA02620
01F6 0 6A2F		STX	2 LOGC8+1	SAVE IX 2	8BA02630
01F7 0 6B30		STX	3 LOGC9+1	SAVE IX 3	8BA02640
01F8 00 67000000		LDX	L3 /0000	IX 3 = MSG WORD	8BA02650
01FA 00 C700018F	LOGC1	LD	L3 PRAR1	GET WD TO CONVERT	8BA02660
01FC 0 D02F		STO	LOX02	SAVE	8BA02670
01FD 00 F4000198		EOR	L TERM		8BA02680
01FF 0 4818		BSC	+-	IS IT A TERM	8BA02690
0200 0 7022		MDX	LOGC7	YES	8BA02700

SENSE DSW EXERCISER

```
0201 0  C02A     LOGC2 LD      LOX02     GET WD                88A02710
0202 0  180C           SRA     12        SAVE ZONE             88A02720
0203 0  D001           STO     LOGC3+1                         88A02730
0204 00 65000000 LOGC3 LDX  L1 0         IX 1 = ZONE           88A02740
0206 00 C500022E       LD   L1 LOX04     GET ADRS OF ZONE      8PA02750
0208 0  D007           STO     LOGC5+1   SAVE                  88AC2760
0209 0  C022           LD      LOX02     GET WD TO CONVERT     88A02770
020A 0  1004           SLA     4         SAVE POSITION         88A02780
020B 0  180C           SRA     12                              88A02790
020C 0  D001           STO     LOGC4+1                         88A02800
020D 00 66000000 LOGC4 LDX  L2 0         IX 2 = POSITION       88A02810
020F 00 C6000000 LOGC5 LD   L2 0         GET TYPEWRITER CODE   88A02820
0211 00 7400022B       MDX  L  LOX00,0   IS THIS FIRST HALF    88A02830
0213 0  7007           MDX     LOGC6     NO                    88A02840
0214 0  D018           STO     LOX03     YES                   88A02850
0215 00 7401022B       MDX  L  LOX00,1   SET TO SECOND HALF    88A02860
0217 0  C014           LD      LOX02     GET WD TO CONVERT     88A02870
0218 0  1006           SLA     8         SET TO SECOND HALF    88A02880
0219 0  D012           STO     LOX02     SAVE                  8BA02890
021A 0  70E6           MDX     LOGC2     GO CONVERT            88A02900
         *                                                     88A02910
         *                SECOND HALF WORD                     88A02920
         *                                                     88A02930
021B 0  1808     LOGC6 SRA     8         MOVE TO SECOND HALF   88A02940
021C 0  F010           EOR     LOX03     COMBINE WITH FIRST    88A02950
021D 00 D700019A LOGCB STO  L3 OUTPT     SET IN MSG            88A02960
021F 0  1010           SLA     16                              88A02970
0220 0  D00A           STO     LOX00     SET TO FIRST HALF     88A02980
0221 0  7301           MDX     3 1       IX 3 = NEXT WD        88A02990
0222 0  70D7           MDX     LOGC1     CONVERT NEXT WD       88A03000
         *                                                     88A03010
         *              FOUND A TERMINATOR                     88A03020
         *                                                     88A03030
0223 00 65000000 LOGC7 LDX  L1 0         RESTORE IX 1          88A03040
0225 00 66000000 LOGC8 LDX  L2 0         RESTORE IX 2          88A03050
0227 00 67000000 LOGC9 LDX  L3 0         RESTORE IX 3          88A03060
0229 00 4C00025F       BSC  L  LOGOO     GO PRINT              88A03070
         *                                                     88A03080
         *                CONSTANTS                            88A03090
         *                                                     88A03100
022B 0  0000     LOX00 DC      0         HALF WORD SW          88A03110
022C 0  0000     LOX02 DC      0         TEMP STORAGE FOR      88A03120
         *                               WORD TO CONVERT       88A03130
022D 0  0000     LOX03 DC      0         TEMP STORAGE FOR      88A03140
         *                               TYPEWRITER CODE       88A03150
022E 0  0234     LOX04 DC      PROO      ADRS OF ZONE 0        88A03160
022F 0  023D           DC      PRO1-2    ADRS OF ZONE 1        88A03170
0230 0  0248           DC      PRO2      ADRS OF ZONE 2        88A03180
0231 0  0254           DC      PRO3-1    ADRS OF ZONE 3        88A03190
         *                                                     88A03200
         *                                                     88A03210
         *                                                     88A03220
0232 0  C02B     LOGCA LD      PRSP      GET CARRIAGE RETURN   88A03230
0233 0  70E9           MDX     LOGCB                           88A03240
         *                                                     88A03250
         *           PRINTER CODE TO TYPEWRITER                88A03260
         *           CODE CONVERSION TABLE                     88A03270
         *                                                     88A03280
0234 0  2100     PROO  DC      /2100     BLANK                 88A03290
0235 0  FC00           DC      /FC00     1                     88A03300
0236 0  D800           DC      /D800     2                     88A03310
0237 0  DC00           DC      /DC00     3                     88A03320
0238 0  F000           DC      /F000     4                     88A03330
0239 0  F400           DC      /F400     5                     88A03340
023A 0  D000           DC      /D000     6                     88A03350
023B 0  D400           DC      /D400     7                     88A03360
023C 0  E400           DC      /E400     8                     88A03370
023D 0  E000           DC      /E000     9                     88A03380
```

SENSE DSW EXERCISER

```
023E 0  C400           DC      /C400     0                     88A03390
023F 0  9A00     PRO1  DC      /9A00     S                     88A03400
0240 0  9E00           DC      /9E00     T                     88A03410
0241 0  B200           DC      /B200     U                     88A03420
0242 0  B600           DC      /B600     V                     88A03430
0243 0  9200           DC      /9200     W                     88A03440
0244 0  9600           DC      /9600     X                     88A03450
0245 0  A600           DC      /A600     Y                     88A03460
0246 0  A200           DC      /A200     Z                     88A03470
0247 0  2100           DC      /2100     BLANK                 88A03480
0248 0  BE00     PRO2  DC      /BE00     -                     88A03490
0249 0  7E00           DC      /7E00     J                     88A03500
024A 0  5A00           DC      /5A00     K                     88A03510
024B 0  5E00           DC      /5E00     L                     88A03520
024C 0  7200           DC      /7200     M                     88A03530
024D 0  7600           DC      /7600     N                     88A03540
024E 0  5200           DC      /5200     O                     88A03550
024F 0  5600           DC      /5600     P                     88A03560
0250 0  6600           DC      /6600     Q                     88A03570
0251 0  6200           DC      /6200     R                     88A03580
0252 0  4200           DC      /4200     -                     88A03590
0253 0  4000           DC      /4000     $                     88A03600
0254 0  0600           DC      /0600     .                     88A03610
0255 0  3E00     PRO3  DC      /3E00     A                     88A03620
0256 0  1A00           DC      /1A00     B                     88A03630
0257 0  1E00           DC      /1E00     C                     88A03640
0258 0  3200           DC      /3200     D                     88A03650
0259 0  3600           DC      /3600     E                     88A03660
025A 0  1200           DC      /1200     F                     88A03670
025B 0  1600           DC      /1600     G                     88A03680
025C 0  2600           DC      /2600     H                     88A03690
025D 0  2200           DC      /2200     I                     88A03700
025E 0  8100     PRSD  DC      /8100     CARRIAGE RETURN       88A03710
         *                                                     88A03720
         *                TYPEWRITER ROUTINE                   88A03730
         *                                                     88A03740
025F 0  0824     LOGOO XIO     SENSE     SENSE FOR READY       88A03750
0260 0  180A           SRA     10                              88A03760
0261 0  4804           BSC     E                               88A03770
         *                                                     88A03780
0262 0  3004     WAIT4 WAIT    4         TYPEWRTR IS NOT READY 88A03790
         *                                                     8BA03800
0263 0  1010           SLA     16                              88A03810
0264 0  D022           STO     WRDSW     CLEAR HALF WD SW      88A03820
0265 0  6300           LDX     3 0                             88A03830
         *                                                     88A03840
0266 00 C7000199 LOGO1 LD   L3 OUTP1     GET PRINT WD          88A03850
0268 0  D01D           STO     IOARA     SET IN OUTPUT AREA    88A03860
         *                                                     88A03870
0269 00 F4000198       EOR  L  TERM      CK FOR TERMINATOR     88A03880
026B 00 4C18027F       BSC  L  LOGO2,+-  EXIT                  88A03890
         *                                                     88A03900
         *                OUTPUT A CHARACTER                   88A03910
         *                                                     88A03920
026D 0  0814     XIOWR XIO     WRITE     WRITE CHARACTER       88A03930
         *                                                     88A03940
026E 0  0815     XIOSN XIO     SENSE     CHECK BUSY            88A03950
         *                                                     88A03960
026F 0  180B           SRA     11                              88A03970
0270 0  4804           BSC     E                               88A03980
0271 0  70FC           MDX     XIOSN     BUSY                  88A03990
         *                                                     8BA04000
         *                                                     88A04010
         *                CHECK FOR 1ST 1/2 WORD               88A04020
         *                                                     88A04030
0272 0  C014           LD      WRDSW     GET 1/2 WORD SWITCH   88A04040
0273 0  4804           BSC     E         SKIP = FIRST HALF     88A04050
0274 0  7006           MDX     LOGO3     GO SETUP FOR NEXT WD  88A04060
```

```
                    •                                              8BA04070
                    •                                              8BA04080
                    •                  SET UP FOR 2ND 1/2 WORD      8BA04090
                    •                                              8BA04100
0275 0  C010        LD      IOARA      GET WORD IN IO AREA         8BA04110
0276 0  1008        SLA     8          POSITION 2ND 1/2 WD         8BA04120
0277 0  D00E        STO     IOARA                                  8BA04130
0278 00 74010287    MDX  L  WRDSW,1    BUMP WORD SWITCH            8BA04140
027A 0  70F2        MDX     XIOWR      GO WRITE 2ND 1/2 WD         8BA04150
                    •                                              8BA04160
                    •                  SET UP FOR NEXT WORD        8BA04170
                    •                                              8BA04180
027B 0  7301  LOGO3 MDX     3 1        NEXT WORD INDEX             8BA04190
027C 00 74010287    MDX  L  WRDSW,1    BUMP WORD SW                8BA04200
027E 0  70E7        MDX     LOGO1      GO GET NEXT WORD            8BA04210
                    •                                              8BA04220
                    •                  EXIT                        8BA04230
                    •                                              8BA04240
027F 00 4C8001F2 LOGO2 BSC I LOGC      EXIT                  SX    8BA04250
                    •                                              8BA04260
                    •                  CONSTANTS                   8BA04270
                    •                                              8BA04280
0282    0000        BSS  E  0                                      8BA04290
0282 0  0286  WRITE DC      IOARA      WRITE IOCC                  8BA04300
0283 0  0902        DC      /0902                                  8BA04310
0284 0  0000  SENSE DC      /0000      SENSE IOCC                  8BA04320
0285 0  0F03        DC      /0F03                                  8BA04330
0286 0  0000  IOARA DC      0          OUTPUT AREA                 8BA04340
0287 0  0000  WRDSW DC      0          HALF WORD SW                8BA04350
0288    012D        END     BEGN                        8BA0435 8BA04360
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BEGN	012D	0188,0288
BPAS1	017F	016A,017C
BSW	018A	0138,0140,014E,0168,0176,0184
BYPAS	0137	0143,0154
CODEH	01C6	01AD
DSW	0186	0135,0139,013A,013B,013D,0157,0159,015A,015C,015F,
		0160,017F,0181,0182
DSW1	C18B	013E,0144,015B,0162,0166,016C
DSW2	018C	0161,0165
HEXCD	01C4	0149,0171,01B7,01BB
HEXCV	01A4	0147,016F,01BC
HEXC1	01A9	01AA,01B3
HEXWD	018E	0145,016D,01A6
HEXOO	01BF	01AF,01B4,01B6,01B8,01BA
IOARA	0286	0268,0275,0277,0282
LOGC	01F2	0152,017A,027F
LOGCA	0232	
LOGCB	021D	0233
LOGC1	01FA	0222
LOGC2	0201	021A
LOGC3	0204	0203
LOGC4	020D	020C
LOGC5	020F	0208
LOGC6	021B	0213
LOGC7	0223	01F5,0200
LOGC8	0225	01F6
LOGC9	0227	01F7
LOGO0	025F	0229
LOGO1	0266	027F
LOGO2	027F	026B
LOGO3	027B	0274
LOX00	022B	01F4,0211,0215,0220
LOX02	022C	01FC,0201,0209,0217,0219
LOX03	022D	0214,021C
LOX04	022E	0206
MASK0	01EC	012D
MASK1	01EE	012F
MSG	0196	014B,0173
ONE	018D	0158,0180,01E2
OUTPT	019A	021D
OUTP1	0199	0266
PRAR0	018E	01F0
PRAR1	018F	01FA
PRINT	013F	
PRSP	025E	0232
PRO0	0234	022E
PRO1	023F	022F
PRO2	0248	0230
PRO3	0255	0231
PR143	0155	0151
PR43	01D6	0155,017D,01E8
PR431	01DD	01E0
PR432	01E4	01E7
PR433	017D	0178
RDBSW	0184	0137,013F,0140,0167,0175
REST	0188	0131
SENSE	0284	025F,026E
SNNRS	015C	0163,0183
SNSPR	01EA	01D7,01D8,01D9,01DD,01E1,01E3,01E4
START	0134	
TERM	0198	01FD,0269
WAIT1	0136	3001
WAIT2	013C	3002
WAIT3	01DB	3003
WAIT4	0262	3004

SENSE DSW EXERCISER

```
WRDSW    0287       0264,0272,0276,027C
WRITE    0282       026D
WRPR     01F0       01DC
XIOSN    026E       0271
XIOWR    026D       027A
```

TABLE OF CONTENTS

1.0 PURPOSE

TO PROVIDE THE CUSTOMER ENGINEER WITH A PROGRAM THAT SETS CORE TO SELECTED
PATTERNS TO ALLOW V (REF) TO BE OPTIMIZED AS SPECIFIED ON LOGIC PAGE SA022
(SJ-2 ADJUSTMENT PROCEDURE) OR LOGIC PAGE SD011 (SJ-4 ADJUSTMENT PROCEDURE).

2.0 PRERQUISITES

2.1   EQUIPMENT REQUIREMENT

1442 CARD READ-PUNCH OR 1054 PAPER TAPE READER.

2.2   PROGRAM REQUIREMENT

1800 BASIC DIAGNOSTIC LOADER.

3.0 USE PROCEDURE

3.1   LOADING

TWO PROGRAM DECKS ARE PROVIDED. THE ONLY DIFFERENCE BETWEEN THE TWO
DECKS IS THE CORE LOCATIONS INTO WHICH THEY ARE LOADED. THE FIRST
DECK (O8CO--LOW CORE ADJUSTMENT PROGRAM) LOADS INTO THE LAST 2K OF
LOWER 32K CORE AND IS USED TO ADJUST THE FIRST 8K OF CORE.
(NOTE. THE FIRST DECK IS ASSEMBLED FOR A 32K MACHINE, THE USER
SHOULD IGNORE HIGHER ORDER BITS WHEN REFERENCING THE LISTING AND
DOCUMENTATION.)

THE SECOND DECK (O8C1 -- HIGH CORE ADJUSTMENT PROGRAM) LOADS INTO THE
FIRST 2K OF CORE AND IS ONLY USED TO ADJUST ABOVE 8K. (THIS DECK IS
NOT USED IF THE MACHINE HAS 8K OR LESS.)

CLEAR ALL STORAGE PROTECTION BITS BEFORE LOADING EITHER PROGRAM.
SET SENSE/PROGRAM SWITCHES TO 00.
SEE 1800 BASIC DIAGNOSTIC LOADER DOCUMENTATION FOR LOADING PROCEDURE.

3.2   OPERATING

3.2.1 SELECT THE PROGRAM DECK THAT IS REQUIRED FOR THE 8K WHICH IS
      ASSOCIATED WITH THE V(REF) POTENTIOMETER THAT IS TO BE ADJUSTED. (SEE
      SECTION 3.1.1 FOR DECK SELECTION.)

3.2.2 LOAD PROGRAM WITH SENSE/PROGRAM SWITCHES SET TO 00.
      (SEE LOGIC PAGE SA022 OR SD011, FIGURE 1 FOR V(Z) VALUE.)
      PERCENT. (SEE LOGIC PAGE SA022 OR SD011, FIGURE 1 FOR V(Z) VALUE.)
      PROGRAM WILL STOP AT WAIT 1.

3.2.4 SET SENSE/PROGRAM SWITCHES TO 01. (SELECTING BEST CASE PATTERN .)

3.2.5 SET MODE SWITCH TO 'RUN'.

SET WRITE STORAGE PROTECT SWITCH TO 'YES'.
SET CHECK STOP SWITCH TO 'ON'.
DEPRESS THE RESET PUSHBUTTON.
DEPRESS THE START PUSHBUTTON.

3.2.6 PROGRAM COMPLETED AT WAIT 2.

SET MODE SWITCH TO 'DISPLAY'.
SET WRITE STORAGE PROTECT SWITCH TO 'NO'.
WHILE HOLDING DOWN THE CLEAR STORAGE PUSHBUTTON DEPRESS THE START
PUSHBUTTON.

3.2.7 LOWER V(REF) UNTIL A PARITY FAILURE OCCURS.

RECORD THE VALUE OF V(REF).

3.2.8 SET SENSE/PROGRAM SWITCHES TO 01.

3.2.9 SET V(REF) TO A POINT WITHIN THE OPERATABLE RANGE AND REPEAT STEPS
      3.2.5 AND3.2.6.

3.2.10 RAISE V(REF) UNTIL A PARITY ERROR OCCURS.
       RECORD THE VALUE OF V(REF).

3.2.11 SET SENSE/PROGRAM SWITCHES TO 02. (SELECTING COMPLEMENT BEST CASE
       PATTERN).

3.2.12 SET V(REF) TO A POINT WITHIN THE OPERATABLE RANGE AND REPEAT STEPS
       3.2.5, 3.2.6, AND 3.2.7.

3.2.13 SET SENSE/PROGRAM SWITCHES TO 02. (SELECTING COMPLEMENT BEST CASE
       PATTERN.)

3.2.14 SET V(REF) TO A POINT WITHIN THE OPERATABLE RANGE AND REPEAT STEPS
       3.2.5, 3.2.6, AND 3.2.10.

3.2.15 SET V(Z) AT V(Z) NOMINAL+6 PERCENT.

3.2.16 REPEAT SETS 3.2.4 THROUGH 3.2.14 FOR THIS VALUE OF V(Z).

3.2.17 TAKE THE HIGHEST OF THE 4 VALUES OF V(REF) FOUND BY LOWERING V(REF)
       AND THE LOWEST OF THE FOUR VALUES OF V(REF) FOUND BY RAISING V(REF).
       SET V(REF) TO THE VALUE WHICH IS THE AVERAGE OF THESE TWO VOLTAGES.

3.2.18 REPEAT STEPS 3.2.1 THROUGH 3.2.17 UNTIL ALL V(REF) POTENTIOMETERS
       HAVE BEEN ADJUSTED.

3.3   SENSE/PROGRAM SWITCHES

SETTING   MEANING

01   RUN BEST CASE PATTERN. A WAIT WILL OCCUR AFTER THE
            PATTERN HAS BEEN SET UP TO ADJUST V(REF).

02   RUN COMPLEMENT BEST CASE PATTERN. A WAIT WILL OCCUR
            AFTER THE PATTERN HAS BEEN SET UP TO ADJUST V(REF).
            DETERMINE AN UPPER LIMIT.

3.4   WAITS

3.4.1 NORMAL WAITS

PROGRAM WAITS ARE IDENTIFIED BY THE B AND I REGISTER AND ARE FOUND
AT THE BEGINNING OF THE LISTING.

3.4.2 ERROR WAITS - (NONE)

3.5   RESTART PROCEDURE. DEPRESSING 'RESET' AND THE 'START' PUSHBUTTON

WILL CAUSE THE PROGRAM TO BE RE-ENTERED AND THE SENSE/PROGRAM
SWITCHES READ.

4.0 PRINTOUTS   (NONE)

5.0 COMMENTS

5.1   PATTERNS

5.1.1 BEST CASE PATTERN. FOR EACH ADDRESS BIT 7 IS
EXCLUSIVE ORED WITH BIT 9. IF THE RESULT IS A ONE, FFFF IS WRITTEN
INTO THAT ADDRESS. IF THE RESULT IS A ZERO, 0000 IS WRITTEN INTO
THAT ADDRESS.
            THIS SHOULD SET UP GROUPS OF 64 POSITIONS OF EITHER ONES OR
            ZEROS IN THE FOLLOWING MANNER. SELECT X AND Y LINE ADDRESSES
            TO DETERMINE THE VALUE SET.

BIT VALUE FOR BEST CASE PATTERN

.X- LINE ADRS	.Y- LINE ADDRESS .0000000-0111111	.Y- LINE ADDRESS .1000000-1111111
.0 0 0 0 0 0	0	1
.0 0 0 0 0 1	0	1
.0 0 0 0 1 0	1	0
.0 0 0 0 1 1	1	0
.0 0 0 1 0 0	0	1
.0 0 0 1 0 1	0	1
. .	.	.
. .	.	.
.0 0 1 1 1 1	1	0
. A U X 0	0	1
. A U X 1	0	1
. A U X 2	0	1
. A U X 3	0	1
.1 0 0 0 0 0	1	0
.1 0 0 0 0 1	1	0
.1 0 0 0 1 0	0	1
. .	.	.
. .	.	.
.1 1 1 1 1 0	0	1
.1 1 1 1 1 1	0	1

5.1.2 COMPLEMENT BEST CASE PATTERN. CORE IS SET UP AS SPECIFIED BY 5.1.1,
THEN THE CONTENTS OF EACH CORE LOCATION ARE COMPLEMENTED.

5.2   SUBROUTINES

5.2.1 BEST CASE PATTERN AND COMPLEMENT BEST CASE PATTERN SUBROUTINE (BCP).

THIS SUBROUTINE IS ENTERING WITH INDEX REGISTER 1 SET TO 0000 AND
INDEX REGISTER 2 SET TO FFFF TO SET UP THE BEST CASE PATTERN AND
INDEX REGISTER 1 SET TO FFFF AND INDEX REGISTER 2 SET TO 0000 TO
SET UP THE COMPLEMENT BEST CASE PATTERN. SYMBOLIC LOCATION 'PLOC'
CONTAINS THE STARTING LOCATION OF AREA WHERE THE PATTERN IS TO BE
SET UP. INDEX REGISTER 3 CONTAINS A COUNT OF THE NUMBER OF CORE
WORDS TO BE SET UP.

5.2.2 SET STORAGE PROTECTION BITS SUBROUTINE (SPV).

THIS SUBROUTINE SETS SPV BITS IN THOSE CORE LOCATIONS WHICH
CONTAINS FFFF. INDEX REGISTER 1 CONTAINS THE STARTING LOCATION
OF THE AREA WHERE THE PATTERN IS SET UP.

INDEX REGISTER 3 CONTAINS A COUNT OF THE NUMBER OF CORE WORDS
CONTAINED IN THE PATTERN AREA.

BECAUSE OF THE ODD PARITY RESTRICTION IMPOSED BY THE HARD-WARE,
ONLY 17 BITS CAN BE ON OR OFF IN ANY CORE LOCATION.
HOWEVER EXECUTING THE COMPLEMENT OF A PATTERN CAUSES THE PARITY
BIT TO BE COMPLETELY CHECKED.

6. APPENDIX   (NONE)

-- LAST PAGE ----------------

```
                          ABS                                8C000020
         3001             ORG      /3001                     8C000030
                                                             8C000040
                     *                                       8C000050
                     *    1800 CORE ADJUSTMENT PROGRAM       8C000060
                     *                                       8C000070
                     *                                       8C000080
                     ****************** NOTES ****************** 8C000080
                     *                                       8C000090
                     *                                       8C000100
                     *    OPERATOR SHOULD CLEAR              8C000110
                     *    SPV BITS EACH TIME BEFORE          8C000120
                     *    THE CORE ADJUSTMENT PROG           8C000130
                     *    IS LOADED                          8C000140
                     *                                       8C000150
                     *    SET CK STOP SW TO ON.              8C000160
                     *                                       8C000170
                     *    SET WRITE STORAGE PROTECT          8C000180
                     *    SWITCH TO YES FOR                  8C000190
                     *    EXECUTING PROGRAM AND              8C000200
                     *    TO NO WHILE ADJUSTING              8C000210
                     *    V REF.                             8C000220
                     *                                       8C000230
                     *    SENSE/PROGRAM SW SETTINGS          8C000240
                     *                                       8C000250
                     *       01  SET UP BEST CASE            8C000260
                     *           PATTERN                     8C000270
                     *                                       8C000280
                     *       02  SET UP COMPLEMENT           8C000290
                     *           BEST CASE PATTERN           8C000300
                     *                                       8C000310
                     *                                       8C000320
                     *                                       8C000330
                     ****************************************** 8C000340
                     *                                       8C000350
                     ****************** WAITS ****************** 8C000360
                     *                                       8C000370
         3001 0 783B  DC      WAIT1&1    SELECT PATTERN      8C000380
                     *                                       8C000390
                     *    SET PATTERN NUMBER                 8C000400
                     *    OF DESIRED PATTERN                 8C000410
                     *    IN SENSE/PROG SWS                  8C000420
                     *                                       8C000430
                     *    DEPRESS RESET BUTTON               8C000440
                     *                                       8C000450
                     *    DEPRESS START BUTTON               8C000460
                     *                                       8C000470
                     *    NOTE-- ACCUMULATOR                 8C000480
                     *    SHOWS THE SETTING OF               8C000490
                     *    THE PRESENT SENSE/                 8C000500
                     *    PROGRAM SWITCHES                   8C000510
                     *                                       8C000520
                     *                                       8C000530
         3002 0 785E  DC      WAIT2&1    PROGRAM COMPLETED   8C000540
                     *                                       8C000550
                     *    ACCUMULATOR SHOWS                  8C000560
                     *    PATTERN NUMBER OF                  8C000570
                     *    PATTERN THAT WAS SET               8C000580
                     *    UP IN CORE.                        8C000590
                     *                                       8C000600
                     *    ADJUST V REF WHILE                 8C000610
                     *    CYCLING IN THE                     8C000620
                     *    AUTOMATIC DISPLAY                  8C000630
                     *    MODE.                              8C000640
                     *                                       8C000650
                     *    TO SET UP NEXT                     8C000660
                     *    PATTERN AFTER V REF                8C000670
                     *    HAS BEEN ADJUSTED--                8C000680
                     *                                       8C000690
```

```
                     *    PLACE NEXT PATTERN                 8C000700
                     *    NUMBER IN THE                      8C000710
                     *    SENSE/PROGRAM SWS                  8C000720
                     *                                       8C000730
                     *    TURN MODE SW TO                    8C000740
                     *    RUN ** PLUS **                     8C000750
                     *    TURN ON WR SPV SW                  8C000755
                     *                                       8C000760
                     *    DEPRESS RESET                      8C000770
                     *    PUSHBUTTON                         8C000780
                     *                                       8C000790
                     *    DEPRESS START                      8C000800
                     *    PUSHBUTTON                         8C000810
                     *                                       8C000820
                     *                                       8C000830
                     ****************************************** 8C000840
                     *                                       8C000850
                     *                                       8C000860
         7800         ORG      /7800                         8C000870
         7800 C C000  DC       /C000      PID                8C000880
                     ****************************************** 8C000890
                     *                                     * 8C000900
                     *         CORE SIZE DETERMINER        * 8C000910
                     *                                     * 8C000920
                     ****************************************** 8C000930
         7801 0 61C0  START LDX    1 0         SET CTRL INDEX 1      8C000940
         7802 0 C007        LD     STGCK&1     GET CONSTANT FFFF & SET 8C000950
         7803 0 D1FF        STO    1 -1        IN MAXIMUM ADDRESS     8C000960
                     *                                       8C000970
         7804 0 7500 1000 STGLP MDX L1 /1000   ADVANCE CONTROL INDEX  8C000980
         7806 0 1000        NOP    0           SAFETY NOP FOR 32K CORE 8C000990
         7807 0 1010        SLA    16          CLEAR ACCUMULATOR AND SET 8C001000
         7808 0 D1FF        STO    1 -1        IN 4K CORE BLOCK MAX ADDR 8C001010
                     *                                       8C001020
         7809 0 C400 FFFF STGCK LD   L /FFFF   GET MAX CORE ADDRESS DATA 8C001030
         780B 0 4C20 7804        BSC  L STGLP,Z CHECK IT FOR ZERO      8C001040
                     *                         BRANCH LOOP IF NOT MAX  8C001050
                     *                                       8C001060
         780D 0 71FF        MDX    1 -1        DECREMENT X1 TO ACTUAL  8C001070
                     *                         MAXIMUM ADDRESS THIS CPU 8C001080
                     *                                       8C001090
         780E 0 1000        NOP    0           SAFETY NOP FOR 32K CORE 8C001100
         780F 0 6D00 78A4    STX  L1 SIZE      SET PROPER LIMIT       8C001110
                     *                                       8C001120
                     *                                       8C001130
                     *         SET UP RESTART LINKAGE        8C001140
                     *                                       8C001150
                     *                                       8C001160
         7811 0 CC00 7898 SETLK LDD L LINK     LOAD RESTART ADDR      8C001170
         7813 0 DC00 0000        STD  L 0      * WITHOUT CORE SIZE CK 8C001180
                     *                                       8C001190
         7815 0 1010        SLA    16          CLEAR A REG            8C001200
         7816 0 D400 78AA    STO  L X3CTL      RESET CTRLS            8C001210
         7818 0 D001         STO    CSP&1      RESET CTRLS            8C001220
                     *                                       8C001230
         7819 0 2C40 0000  CSP  STS L 0,/40    CLEAR ALL SPV BITS     8C001240
         781B 0 C0FE         LD     CSP&1      GET CLEAR ADDR         8C001250
         781C 0 8400 78A1    A    L ONE        ADV ADDR PLUS ONE      8C001260
         781E 0 D0FB         STO    CSP&1      SAVE NEW ADDR          8C001270
         781F 0 F400 78A4    EOR  L SIZE       CK FOR ALL OF CORE     8C001280
         7821 0 4C20 7819    BSC  L CSP,Z      BR LOOP               8C001290
                     *                                       8C001300
                     *         ADJUST CORE SIZE AND          8C001310
                     *         * CONSTANTS                   8C001320
                     *                                       8C001330
         7823 0 C07B         LD     LLIM2      ADJUST CONSTANT       8C001340
         7824 0 E07F         AND    SIZE                             8C001350
         7825 0 D079         STO    LLIM2      SET LO LIMIT 2        8C001360
```

```
7826 0 C400 78A7        LD   L  ULIM1                                8C001370
7828 0 E07B             AND     SIZE                                 8C001380
7829 0 D07D             STO     ULIM1      SET UP LIMIT 1            8C001390
                *                           FIND LOOP CONTROLS        8C001400
782A 0 C07C             LD      ULIM1                                8C001410
782B 0 9072             S       LLIM1                                8C001420
782C 0 D073             STO     LOWRL      SET LO CTRL LIMIT         8C001430
782D 0 C076             LD      SIZE                                 8C001440
782E 0 9070             S       LLIM2                                8C001450
782F 0 9071             S       ONE                                  8C001460
7830 0 D077             STO     UPERL      UPPER LIMIT CONTROL       8C001470
                *                           READ SENSE/PROG SWITCHES  8C001480
7831 0 0868      READ   XIO     RDSWS                                8C001490
                *                                                     8C001500
                *                           CK SW VALIDITY            8C001510
                *                                                     8C001520
7832 0 1808             SRA     8                                    8C001530
7833 0 D06E             STO  .  PATNO      SAVE PATTERN NUMBER       8C001540
7834 0 4C18 783A        BSC  L  WAIT1,&-                             8C001550
7836 0 906F             S       TWO                                  8C001560
7837 0 4C04 783C        BSC  L  PIVOT,&                              8C001570
7839 0 C068             LD      PATNO                                8C001580
783A 0 3001      WAIT1  WAIT    1          SELECT SENSE/PROGRAM      8C001590
                *                           * SW OPTIONS AND          8C001600
                *                           * DEPRESS RESET AND       8C001610
                *                           * START PUSHBUTTONS       8C001620
                *                                                     8C001630
783B 0 70F5             MDX     READ                                 8C001640
                *                                                     8C001650
                *                           PIVOT ON SELECTED PATTERN 8C001660
                *                                                     8C001670
783C 0 C065      PIVOT  LD      PATNO                                8C001680
783D 0 4C04 7842        BSC  L  PAT01,E                              8C001690
                *                                                     8C001700
               *                           SET UP BCP OR COMPL. BCP  8C001710
                *                                                     8C001720
783F 0 61FF      PAT02  LDX   1 -1         SET FOR COMPL BCP         8C001730
7840 0 6200             LDX   2 0                                    8C001740
7841 0 7002             MDX     PAT01&2                              8C001750
7842 0 6100      PAT01  LDX   1 0          SET INDEXES FOR BCP       8C001760
7843 0 62FF             LDX   2 -1                                   8C001770
7844 0 C059             LD      LLIM1      SET UP TO START AT        8C001780
7845 0 D05D             STO     PLOC       * 1ST LOWER LIMIT         8C001790
7846 0 404C             BSI     X3CRS      RESET ADDR CTRL           8C001800
7847 0 6780 78A0        LDX  I3 LOWRL      SET UP LOOP CONTROL       8C001810
7849 0 4016             BSI     BCP        SET CORES                 8C001820
784A 0 C054             LD      LLIM2      SET UP TO START AT        8C001830
784B 0 D057             STO     PLOC       * 2ND LOWER LIMIT         8C001840
784C 0 4046             BSI     X3CRS      RESET ADDR CTRL           8C001850
784D 0 6780 78A8        LDX  I3 UPERL      SET UP LOOP CONTROL       8C001860
784F 0 4010             BSI     BCP        SET CORES                 8C001870
                *                                                     8C001880
                *                           SET SPV BITS              8C001890
                *                                                     8C001900
7850 0 6580 789E STSPV  LDX  I1 LLIM1      SET UP TO START AT        8C001910
                *                           * 1ST LOWER LIMIT         8C001920
7852 0 6780 78A0        LDX  I3 LOWRL      SET UP LOOP CONTROL       8C001930
7854 0 4020             BSI     SPV        SET SPV BIT SUBRT         8C001940
7855 0 403D             BSI     X3CRS      RESET ADDR CTRL           8C001950
7856 0 6580 789F        LDX  I1 LLIM2      SET UP TO START AT        8C001960
                *                           * 2ND LOWER LIMIT         8C001970
7858 0 6780 78A8        LDX  I3 UPERL      SET UP LOOP CONTROL       8C001980
785A 0 401A             BSI     SPV        SET SPV BIT SUBRT         8C001990
785B 0 4037             BSI     X3CRS      RESET ADDR CTRL           8C002000
                *                                                     8C002010
                *                           LOAD PATTERN NUMBER WHICH 8C002020
                .*                          HAS BEEN SET UP AND WAIT  8C002030
                *                           TO ALLOW CE TO MANUALLY   8C002040
```

```
                *                           ADJUST V REF              8C002050
                *                                                     8C002060
785C 0 C045      DONE   LD      PATNO      SET UP PATTERN NO.        8C002070
785D 0 3002      WAIT2  WAIT    2          END OF PROGRAM            8C002080
785E 0 4C00 7801        BSC  L  START                                8C002090
                *                                                     8C002100
                *                                                     8C002110
                *                           BCP AND COMPL. BCP  SUBRT 8C002120
                *                                                     8C002130
7860 0 0000      BCP    DC      0                                    8C002140
7861 0 6847             STX   3 X3HLD      SAVE X3 DATA              8C002150
7862 0 C040             LD      PLOC       EXCUSIVE OR BITS 7        8C002160
7863 0 1806             SRA     6          * AND 9                   8C002170
7864 0 D040             STO     TEMP                                 8C002180
7865 0 1802             SRA     2                                    8C002190
7866 0 F03E             EOR     TEMP                                 8C002200
7867 0 4C04 786C        BSC  L  ODD,E                                8C002210
7869 0 6D80 78A3        STX  I1 PLOC                                 8C002220
786B 0 7002             MDX     CDD&2                                8C002230
786C 0 6E80 78A3  ODD    STX  I2 PLOC                                8C002240
786E 0 7401 78A3        MDX  L  PLOC,1     INCREMENT ADDRESS         8C002250
7870 0 1000             SLA     0                                    8C002260
7871 0 4015             BSI     CKX3X      BR TO CK X3 CTRL          8C002270
7872 0 70EF             MDX     BCP&2      REPEAT                    8C002280
7873 0 4C80 7860        BSC  I  BCP        EXIT                      8C002290
                *                                                     8C002300
                *                                                     8C002310
                *                           SET SPV SUBRT             8C002320
                *                                                     8C002330
7875 0 0000      SPV    DC      0                                    8C002340
7876 0 6B32             STX   3 X3HLD      SAVE X3 DATA              8C002350
7877 0 6933             STX   1 PG4X       SAVE X1 VALUE             8C002351
7878 0 C032             LD      PGMX       GET X1 DATA               8C002352
7879 0 F02D             EOR     ULIM1      CK FOR START OF PGM       8C002353
787A 0 4C18 7883        BSC  L  SPVX,&-    BR IF START FO PGM        8C002354
787C 0 C100             LD    1 0          SET ADDR CTRL             8C002360
787D 0 4C18 7881        BSC  L  SPVB,&-    BRANCH IF CONTAINS 0      8C002370
787F 0 2D41 0000        STS  L1 0,/41      SET SPV                  8C002380
7881 0 7101      SPVB   MDX   1 1          INCREMENT ADDRESS         8C002390
7882 0 1000             SLA     0                                    8C002400
7883 0 4003      SPVX   BSI     CKX3X      BR TO CK X3 CTRL          8C002410
7884 0 70F2             MDX     SPV&2      REPEAT                    8C002420
7885 0 4C80 7875        BSC  I  SPV        EXIT                      8C002430
                *                                                     8C002440
                *                                                     8C002450
                *                                                     8C002460
7887 0 0000      CKX3X  DC      0          ENTRY                     8C002470
                *                                                     8C002480
7888 0 C021             LD      X3CTL                                8C002490
7889 0 8017             A       ONE        ADD TO ADV ADDR          8C002500
788A 0 D01F             STO     X3CTL                                8C002510
788B 0 F01D             EOR     X3HLD      TEST AGAINST CTRL MAX     8C002520
788C 0 4CA0 7887        BSC  L  CKX3X,Z    BR IF NOT ZERO           8C002530
788E 0 7401 7887        MDX  L  CKX3X,1    ADV FOR EXIT RETURN       8C002540
7890 0 1000             NOP     0          SAFTY NOP                 8C002550
7891 0 4C80 7887        BSC  I  CKX3X      RETURN TO EXIT RTN CTRL   8C002560
                *                                                     8C002570
                *                           RESET ADDR CTRL           8C002580
                *                                                     8C002590
7893 0 0000      X3CRS  DC      0          ENTRY                     8C002600
7894 0 1010             SLA     16         CLR A REG                8C002610
7895 0 D014             STO     X3CTL      RESET ADDR CTRL CTR       8C002620
7896 0 4C80 7893        BSC  I  X3CRS      RETURN EXIT               8C002630
                *                                                     8C002640
                *                                                     8C002650
7898   0000             BSS   E 0                                    8C002660
7898 0 4C00 7811 LINK   BSC  L  SETLK      RESTART LINKAGE ROUTINE   8C002670
789A 0 0000      RDSWS  DC      0          SENSE INTO A REG          8C002680
```

```
789B 0 0760              DC    /0760    SENSE/PROG SWS           8C002690
789C 0 6000    K6000 DC  /6000          24K CONSTANT             8C002700
789D 0 0800    K0800 DC  /0800          CONSTANT                 8C002710
789E 0 0002    LLIM1 DC  /0002          1ST LOWER LIMIT CTRL     8C002720
789F 0 78AC    LLIM2 DC  FNISH          2ND LOWER LIMIT CTRL     8C002730
78A0 0 0000    LOWRL DC  0              LO CORE BLOCK LOOP CTRL  8C002740
78A1 0 0001    ONE   DC  1              CONSTANT 1               8C002750
78A2 0 0000    PATNO DC  0              PATTERN NUMBER           8C002760
78A3 0 0000    PLOC  DC  0              PRESENT LOC              8C002770
78A4 0 0000    SIZE  DC  0              CORE SIZE & UPLIM2       8C002780
78A5 0 0000    TEMP  DC  0                                       8C002790
78A6 C 0002    TWO   DC  2              CONSTANT 2               8C002800
78A7 0 7801    ULIM1 DC  START          1ST UPPER LIMIT          8C002810
78A8 0 0000    UPERL DC  0              HI CORE BLOCK LOOP CTRL  8C002820
78A9 C 0000    X3HLD DC  0              X3 DATA HOLDER           8C002830
78AA 0 0000    X3CTL DC  0              CTRL ADDR UPLIM          8C002840
78AB 0 0000    PGMX  DC  0              PGM SPV CK WORK AREA     8C002850
78AC 0 0000    FNISH DC  0              LAST LOC OF PROG         8C002860
78AE   7801          END   START                                8C002870
    NO STATEMENTS FLAGGED IN THE ABOVE ASSEMBLY
```

```
BCP    7860   7849 784F 7872 7873
CKX3X  7887   7871 7883 788C 788E 7891
CSP    7819   7818 781B 781E 7821
DONE   785C
FNISH  78AC   789F
K0800  789D
K6000  789C
LINK   7898   7811
LLIM1  789E   782B 7844 7850
LLIM2  789F   7823 7825 782E 784A 7856
LOWRL  78A0   782C 7847 7852
ODD    786C   7867 786B
ONE    78A1   781C 782F 7889
PATNO  78A2   7833 7839 783C 785C
PAT01  7842   783D 7841
PAT02  783F
PGMX   78AB   7877 7878
PIVOT  783C   7837
PLOC   78A3   7845 784B 7862 7869 786C 786E
RDSWS  789A   7831
READ   7838
SETLK  7811   7898
SIZE   78A4   780F 781F 7824 7828 782D
SPV    7875   7854 785A 7884 7885
SPVB   7881   787D
SPVX   7883   787A
START  7801   785E 78A7 78AE
STGCK  7809   7802
STGLP  7804   780B
STSPV  7850
TEMP   78A5   7864 7866
TWO    78A6   7836
ULIM1  78A7   7826 7829 782A 7879
UPERL  78A8   7830 784D 7858
WAIT1  783A   3001 7834
WAIT2  785D   3002
X3CRS  7893   7846 784C 7855 7858 7896
X3CTL  78AA   7816 7888 788A 7895
X3HLD  78A9   7861 7876 788B
END OF ASSEMBLY
```

```
                    ABS                                      8C100020
        3001        ORG      /3001                           8C100030
                                                             8C100040
                    *                                        8C100050
                    *        1800 CORE ADJUSTMENT PROGRAM    8C100060
                    *                                        8C100070
                    *                                        8C100080
                    ****************** NOTES  *************   8C100090
                    *                                        8C100100
                    *        OPERATOR SHOULD CLEAR           8C100110
                    *        SPV BITS EACH TIME BEFORE       8C100120
                    *        THE CORE ADJUSTMENT PROG        8C100130
                    *        IS LOADED                       8C100140
                    *                                        8C100150
                    *        SET CK STOP SW TO ON.           8C100160
                    *                                        8C100170
                    *        SET WRITE STORAGE PROTECT       8C100180
                    *        SWITCH TO YES FOR               8C100190
                    *        EXECUTING PROGRAM AND           8C100200
                    *        TO NO WHILE ADJUSTING           8C100210
                    *        V REF.                          8C100220
                    *                                        8C100230
                    *        SENSE/PROGRAM SW SETTINGS       8C100240
                    *                                        8C100250
                    *          01  SET UP BEST CASE          8C100260
                    *              PATTERN                   8C100270
                    *                                        8C100280
                    *          02  SET UP COMPLEMENT         8C100290
                    *              BEST CASE PATTERN         8C100300
                    *                                        8C100310
                    *                                        8C100320
                    ****************************************  8C100330
                    *                                        8C100340
                    ****************** WAITS  *************   8C100350
                    *                                        8C100360
        3001 0 0167  DC      WAIT1&1      SELECT PATTERN     8C100370
                    *                                        8C100380
                    *        SET PATTERN NUMBER              8C100390
                    *        OF DESIRED PATTERN              8C100400
                    *        IN SENSE/PROG SWS               8C100410
                    *                                        8C100420
                    *        DEPRESS RESET BUTTON            8C100430
                    *                                        8C100440
                    *        DEPRESS START BUTTON            8C100450
                    *                                        8C100460
                    *        NOTE-- ACCUMULATOR              8C100470
                    *        SHOWS THE SETTING OF            8C100480
                    *        THE PRESENT SENSE/              8C100490
                    *        PROGRAM SWITCHES                8C100500
                    *                                        8C100510
                    *                                        8C100520
        3002 0 018A  DC      WAIT2&1      PROGRAM COMPLETED  8C100530
                    *                                        8C100540
                    *        ACCUMULATOR SHOWS               8C100550
                    *        PATTERN NUMBER OF               8C100560
                    *        PATTERN THAT WAS SET            8C100570
                    *        UP IN CORE.                     8C100580
                    *                                        8C100590
                    *        ADJUST V REF WHILE              8C100600
                    *        CYCLING IN THE                  8C100610
                    *        AUTOMATIC DISPLAY               8C100620
                    *        MODE.                           8C100630
                    *                                        8C100640
                    *        TO SET UP NEXT                  8C100650
                    *        PATTERN AFTER V REF             8C100660
                    *        HAS BEEN ADJUSTED--             8C100670
                    *                                        8C100680
                    *                                        8C100690
```

```
                    *        PLACE NEXT PATTERN              8C100700
                    *        NUMBER IN THE                   8C100710
                    *        SENSE/PROGRAM SWS               8C100720
                    *                                        8C100730
                    *        TURN MODE SW TO                 8C100740
                    *        RUN  ** PLUS **                 8C100750
                    *        TURN ON WR SPV SW               8C100755
                    *                                        8C100760
                    *        DEPRESS RESET                   8C100770
                    *        PUSHBUTTON                      8C100780
                    *                                        8C100790
                    *        DEPRESS START                   8C100800
                    *        PUSHBUTTON                      8C100810
                    *                                        8C100820
                    *                                        8C100830
                    ****************************************  8C100840
                    *                                        8C100850
                    *                                        8C100860
        012C         ORG      /012C                          8C100870
        012C 0 C100  DC       /C100        PID               8C100880
                    ****************************************  8C100890
                    *                                        8C100900
                    *            CORE SIZE DETERMINER      * 8C100910
                    *                                      * 8C100920
                    ****************************************  8C100930
        012D 0 6100 START LDX  1 0           SET CTRL INDEX 1 8C100940
        012E 0 C007       LD     STGCK&1     GET CONSTANT FFFF & SET 8C100950
        012F 0 D1FF       STO    1 -1        IN MAXIMUM ADDRESS 8C100960
                    *                                        8C100970
        0130 0 7500 1000 STGLP MDX L1 /1000  ADVANCE CONTROL INDEX 8C100980
        0132 0 1000       NOP    0           SAFETY NOP FOR 32K CORE 8C100990
        0133 0 1010       SLA    16          CLEAR ACCUMULATOR AND SET 8C101000
        0134 0 D1FF       STO    1 -1        IN 4K CORE BLOCK MAX ADDR 8C101010
                    *                                        8C101020
        0135 0 C400 FFFF STGCK LD  L /FFFF   GET MAX CORE ADDRESS DATA 8C101030
        0137 0 4C20 0130       BSC L STGLP,Z CHECK IT FOR ZERO 8C101040
                    *                         BRANCH LOOP IF NOT MAX 8C101050
                    *                                        8C101060
        0139 0 71FF        MDX    1 -1        DECREMENT X1 TO ACTUAL 8C101070
                    *                         MAXIMUM ADDRESS THIS CPU 8C101080
                    *                                        8C101090
        013A 0 1000        NOP    0           SAFETY NOP FOR 32K CORE 8C101100
        013B 0 6D00 01D0   STX L1 SIZE        SET PROPER LIMIT 8C101110
                    *                                        8C101120
                    *                                        8C101130
                    *        SETUP RESTART LINKAGE           8C101140
                    *                                        8C101150
                    *                                        8C101160
        013D 0 CC00 01C4 SETLK LDD L LINK     LOAD RESTART ADDR 8C101170
        013F 0 DC00 0000       STD L 0        * WITHOUT CORE SIZE CK 8C101180
                    *                                        8C101190
        0141 0 1010        SLA    16          CLEAR A REG    8C101200
        0142 0 D400 01D6    STO L X3CTL       RESET CTRLS    8C101210
        0144 0 D001         STO    CSP&1       RESET CTRLS   8C101220
                    *                                        8C101230
        0145 0 2C40 0000 CSP STS L 0,/40      CLEAR ALL SPV BITS 8C101240
        0147 0 C0FE        LD     CSP&1       GET CLEAR ADDR 8C101250
        0148 0 84C0 01CD    A  L ONE          ADV ADDR PLUS ONE 8C101260
        014A 0 D0FB         STO    CSP&1       SAVE NEW ADDR 8C101270
        014B 0 F400 01D0    EOR L SIZE        CK FOR ALL OF CORE 8C101280
        014D 0 4C20 0145    BSC L CSP,Z       BR LOOP        8C101290
                    *                                        8C101300
                    *        ADJUST CORE SIZE AND            8C101310
                    *        * CONSTANTS                     8C101320
                    *                                        8C101330
        014F 0 C07B        LD     LLIM2       ADJUST CONSTANT 8C101340
        0150 0 E07F        AND    SIZE                        8C101350
        0151 0 D079        STO    LLIM2       SET LO LIMIT 2 8C101360
```

```
0152 0 C400 01D3      1D    L   ULIM1                            8C101370
0154 0 E07B           AND       SIZE                             8C101380
0155 0 D07D           STO       ULIM1      SET UP LIMIT 1        8C101390
                  •                    FIND LOOP CONTROLS         8C101400
0156 0 C07C           LD        ULIM1                            8C101410
0157 0 9072           S         LLIM1                            8C101420
0158 0 D073           STO       LOWRL      SET LO CTRL LIMIT     8C101430
0159 0 C076           LD        SIZE                             8C101440
015A 0 9072           S         LLIM2                            8C101450
015B 9 9071           S         ONE                              8C101460
015C 0 D077           STO       UPERL      UPPER LIMIT CONTROL   8C101470
                  •                    READ SENSE/PROG SWITCHES   8C101480
015D 0 0868      READ XIO       RDSWS                            8C101490
                  •                                               8C101500
                  •                    CK SW VALIDITY             8C101510
                  •                                               8C101520
015E 0 1808           SRA       8                                8C101530
015F 0 D06E           STO       PATNO      SAVE PATTERN NUMBER   8C101540
0160 0 4C18 0166      BSC   L   WAIT1,6-                         8C101550
0162 0 906F           S         TWO                              8C101560
0163 0 4C08 0168      BSC   L   PIVOT,6                          8C101570
0165 0 C068           LD        PATNO                            8C101580
0166 0 3001      WAIT1 WAIT     1          SELECT SENSE/PROGRAM  8C101590
                  •                        • SW OPTIONS AND       8C101600
                  •                        • DEPRESS RESET AND    8C101610
                  •                        • START PUSHBUTTONS    8C101620
                  •                                               8C101630
0167 0 70F5           MDX       READ                             8C101640
                  •                                               8C101650
                  •                    PIVOT ON SELECTED PATTERN  8C101660
                  •                                               8C101670
0168 0 C065      PIVOT LD       PATNO                            8C101680
0169 0 4C04 016E      BSC   L   PAT01,E                          8C101690
                  •                                               8C101700
                  •                    SET UP BCP OR COMPL. BCP   8C101710
                  •                                               8C101720
016B 0 61FF      PAT02 LDX   1 -1        SET FOR COMPL BCP      8C101730
016C 0 6200           LDX   2 0                                  8C101740
016D 0 7002           MDX       PAT01&2                          8C101750
016E 0 6100      PAT01 LDX   1 0         SET INDEXES FOR BCP    8C101760
016F 0 62FF           LDX   2 -1                                 8C101770
0170 0 C059           LD        LLIM1      SET UP TO START AT    8C101780
0171 0 D05D           STO       PLOC       • 1ST LOWER LIMIT     8C101790
0172 0 404C           BSI       X3CRS      RESET ADDR CTRL       8C101800
0173 0 6780 01CC      LDX   I3  LOWRL      SET UP LOOP CONTROL   8C101810
0175 0 4016           BSI       BCP        SET CORES             8C101820
0176 0 C054           LD        LLIM2      SET UP TO START AT    8C101830
0177 0 D057           STO       PLOC       • 2ND LOWER LIMIT     8C101840
0178 0 4046           BSI       X3CRS      RESET ADDR CTRL       8C101850
0179 0 6780 01D4      LDX   I3  UPERL      SET UP LOOP CONTROL   8C101860
017B 0 4010           BSI       BCP        SET CORES             8C101870
                  •                                               8C101880
                  •                    SET SPV BITS               8C101890
                  •                                               8C101900
017C 0 6580 01CA STSPV LDX   I1 LLIM1      SET UP TO START AT    8C101910
                  •                        • 2ND LOWER LIMIT      8C101920
017E 0 6780 01CC      LDX   I3  LOWRL      SET UP LOOP CONTROL   8C101930
0180 0 4020           BSI       SPV        SET SPV BIT SUBRT     8C101940
0181 0 403D           BSI       X3CRS      RESET ADDR CTRL       8C101950
0182 0 6580 01CB      LDX   I1-LLIM2      SET UP TO START AT    8C101960
                  •                        • 2ND LOWER LIMIT      8C101970
0184 0 6780 01D4      LDX   I3  UPERL      SET UP LOOP CONTROL   8C101980
0186 0 401A           BSI       SPV        SET SPV BIT CTRL      8C101990
0187 0 4037           BSI       X3CRS      RESET ADDR CTRL       8C102000
                  •                                               8C102010
                  •                    LOAD PATTERN NUMBER WHICH  8C102020
                  •                    HAS BEEN SET UP AND WAIT   8C102030
                  •                    TO ALLOW CE TO MANUALLY    8C102040
```

```
                  •                    ADJUST V REF               8C102050
                  •                                               8C102060
0188 0 C045      DONE LD       PATNO      SET UP PATTERN NO.    8C102070
0189 0 3002      WAIT2 WAIT     2          END OF PROGRAM        8C102080
018A 0 4C00 012D      BSC   L   START                            8C102090
                  •                                               8C102100
                  •                                               8C102110
                  •                    BCP AND COMPL. BCP SUBRT   8C102120
                  •                                               8C102130
018C 0 0000      BCP  DC        0                                8C102140
018D 0 6847           STX   3   X3HLD      SAVE X3 DATA          8C102150
018E 0 C040           LD        PLOC       EXCUSIVE OR BITS 7    8C102160
018F 0 1806           SRA       6          • AND 9               8C102170
0190 0 D040           STO       TEMP                             8C102180
0191 0 1802           SRA       2                                8C102190
0192 0 F03E           EOR       TEMP                             8C102200
0193 0 4C04 0198      BSC   L   ODD,E                            8C102210
0195 0 6D80 01CF      STX   I1  PLOC                             8C102220
0197 0 7002           MDX       ODD&2                            8C102230
0198 0 6E80 01CF  ODD STX   I2  PLOC                             8C102240
019A 0 7401 01CF      MDX   L   PLOC,1     INCREMENT ADDRESS     8C102250
019C 0 1000           SLA       0                                8C102260
019D 0 4015           BSI       CKX3X      BR TO CK X3 CTRL      8C102270
019E 0 70EF           MDX       BCP&2      REPEAT                8C102280
019F 0 4C80 018C      BSC   I   BCP        EXIT                  8C102290
                  •                                               8C102300
                  •                                               8C102310
                  •                    SET SPV SUBRT              8C102320
                  •                                               8C102330
01A1 0 0000      SPV  DC        0                                8C102340
01A2 0 6B32           STX   3   X3HLD      SAVE X3 DATA          8C102350
01A3 0 6933           STX   I   PGMX       SAVE X1 VALUE         8C102351
01A4 0 C932           LD        PGMX       GET X1 DATA           8C102352
01A5 0 F02D           EOR       ULIM1      CK FOR START OF PGM   8C102353
01A6 0 4C18 01AF      BSC   L   SPVX,&-    BR IF START OF PGM    8C102354
01A8 0 C100           LD     1  0          SET ADDR CTRL         8C102360
01A9 0 4C18 01AD      BSC   L   SPVB,&-    BRANCH IF CONTAINS 0  8C102370
01AB 0 2D41 0C00      STS   L1  0,/41      SET SPV               8C102380
01AD 0 7101      SPVB MDX   1 1            INCREMENT ADDRESS     8C102390
01AE 0 1000           SLA       0                                8C102400
01AF 0 4003      SPVX BSI       CKX3X      BR TO CK X3 CTRL      8C102410
01B0 0 70F2           MDX       SPV&2      REPEAT                8C102420
01B1 0 4C80 01A1      BSC   I   SPV        EXIT                  8C102430
                  •                                               8C102440
                  •                                               8C102450
01B3 0 0000      CKX3X DC       0          ENTRY                 8C102460
                  •                                               8C102470
01B4 0 C021           LD        X3CTL                            8C102480
01B5 0 8017           A         ONE        ADD TO ADV ADDR       8C102500
01B6 0 D01F           STO       X3CTL                            8C102510
01B7 0 F01D           EOR       X3HLD      TEST AGAINST CTRL MAX 8C102520
01B8 0 4CA0 01B3      BSC   I   CKX3X,Z    BR IF NOT ZERO        8C102530
01BA 0 7401 01B3      MDX   L   CKX3X,1    ADV FOR EXIT RETURN   8C102540
01BC 0 1000           NOP       0          SAFTY NOP             8C102550
01BD 0 4C80 01B3      BSC   I   CKX3X      RETURN TO EXIT RTN CTRL 8C102560
                  •                                               8C102570
                  •                    RESET ADDR CTRL            8C102580
                  •                                               8C102590
01BF 0 0000      X3CRS DC       0          ENTRY                 8C102600
01C0 0 1010           SLA       16         CLR A REG             8C102610
01C1 0 D014           STO       X3CTL      RESET ADDR CTRL CTR   8C102620
01C2 0 4C80 01BF      BSC   I   X3CRS      RETURN EXIT           8C102630
                  •                                               8C102640
                  •                                               8C102650
01C4 0000             BSS   E   0                                8C102660
01C4 0 4C00 013D LINK BSC   L   SETLK      RESTART LINKAGE ROUTINE 8C102670
01C6 0 0000      RDSWS DC       0          SENSE INTO A REG      8C102680
```

```
01C7 0 0760              DC      /0760      SENSE/PROG SWS          8C102690
01C8 0 6000      K6000 DC        /6000      24K CONSTANT            8C102700
01C9 0 0800      K0800 DC        /0800      CONSTANT                8C102710
01CA 0 0002      LLIM1 DC        /0002      1ST LOWER LIMIT CTRL    8C102720
01CB 0 01D8      LLIM2 DC        FNISH      2ND LOWER LIMIT CTRL    8C102730
01CC 0 0000      LOWRL DC        0          LO CORE BLOCK LOOP CTRL 8C102740
01CD 0 0001      ONE   DC        1          CONSTANT 1              8C102750
01CE 0 0000      PATNO DC        0          PATTERN NUMBER          8C102760
01CF 0 0000      PLOC  DC        0          PRESENT LOC             8C102770
01D0 0 0000      SIZE  DC        0          CORE SIZE & UPLIM2      8C102780
01D1 0 0000      TEMP  DC        0                                  8C102790
01D2 0 0002      TWO   DC        2          CONSTANT 2              8C102800
01D3 0 012D      ULIM1 DC        START      1ST UPPER LIMIT         8C102810
01D4 0 00C0      UPERL DC        0          HI CORE BLOCK LOOP CTRL 8C102820
01D5 0 0000      X3HLD DC        0          X3 DATA HOLDER          8C102830
01D6 0 0000      X3CTL DC        0          CTRL ADDR UPLIM         8C102840
01D7 0 0000      PGMX  DC        0          PGM SPV CK WORK AREA    8C102850
01D8 0 0000      FNISH DC        0          LAST LOC OF PROG        8C102860
01DA   012D            END       START                             8C102870
       NO STATEMENTS FLAGGED IN THE ABOVE ASSEMBLY
```

```
BCP     018C    0175 017B 019E 019F
CKX3X   01B3    019D 01AF 01B8 01BA 01BD
CSP     0145    0144 0147 014A 014D
DONE    0188
FNISH   01D8    01CB
K0800   01C9
K6000   01C8
LINK    01C4    013D
LLIM1   01CA    0157 0170 017C
LLIM2   01CB    014F 0151 015A 0176 0182
LOWRL   01CC    0158 0173 017E
ODD     0198    0193 0197
ONE     01CD    0148 015B 0185
PATNO   01CE    015F 0165 0168 0188
PAT01   016E    0169 016D
PAT02   016B
PGMX    01D7    01A3 01A4
PIVOT   0168    0163
PLOC    01CF    0171 0177 018E 0195 0198 019A
RDSWS   01C6    015D
READ    015D    0167
SETLK   013D    01C4
SIZE    01D0    013B 014B 0150 0154 0159
SPV     01A1    0180 0186 01B0 01B1
SPVB    01AD    01A9
SPVX    01AF    01A6
START   012D    018A 01D3 01DA
STGCK   0135    012E
STGLP   0130    0137
STSPV   017C
TEMP    01D1    0190 0192
TWO     01D2    0162
ULIM1   01D3    0152 0155 0156 01A5
UPERL   01D4    015C 0179 0184
WAIT1   0166    0160 3001
WAIT2   0189    3002
X3CRS   01BF    0172 C178 0181 0187 01C2
X3CTL   01D6    0142 0184 0186 01C1
X3HLD   01D5    018D 01A2 01B7
END OF ASSEMBLY
```

-- LAST PAGE --

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

TABLE OF CONTENTS

1. PURPOSE

    THE MAGNETIC TAPE CRC FUNCTION TEST IS DESIGNED TO CHECK THE TAPE ERROR
    CORRECTION CIRCUITRY FOR PROPER OPERATION.

    THE PROGRAM IS ABLE TO TEST,

    1.   SYSTEMS WITH ONE OR TWO TAPE DRIVES.
    2.   DRIVES WITH 9 TRACK READ-WRITE HEADS.
    3.   MODELS 1, 2 OR 3 WITH 2 OR 4 MICROSECOND STORAGE.

    IF THE SYSTEM HAS TWO TAPE DRIVES WITH 9 TRACK HEADS, BOTH DRIVES MAY BE
    SEQUENTIALLY TESTED IN ONE CONTINUOUS RUN OF THE PROGRAM.

2. PREREQUISITES

    THIS PROGRAM ASSUMES THAT THE 2400 MAGNETIC TAPE FUNCTION TEST RUNS AND NO
    TAPE CONTROL ERRORS EXIST. EQUIPMENT REQUIRED CONSISTS OF,

    1.   1442 CARD READ/PUNCH OR 1054 PAPER TAPE READER.
    2.   1053 OR 1816 TYPEWRITER OR 1443 PRINTER.
    3.   1800 PROCESSOR CONTROLLER.
    4.   ONE OR TWO 2400 SERIES MAGNETIC TAPE DRIVES WITH 9 TRACK HEADS.
    5.   THIS PROGRAM REQUIRES THE RELOCATABLE DIAGNOSTIC LOADER FOR LOADING.

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

3. USE PROCEDURE

    3.1   PROGRAM LOADING

           PULL CARD 1C09 IN EACH TAPE DRIVE TO BE TESTED.

    3.1.1 ON TAPE DRIVE (S) TO BE TESTED,

           1. LOAD TAPE REEL.
           2. DEPRESS LOAD-REWIND KEY.
           3. DEPRESS START KEY.
               AFTER TAPE REWINDS TO LOAD POINT, DRIVE (S) SHOULD BECOME
               READY.

    3.1.2 REFER TO RELOCATABLE DIAGNOSTIC LOADER DOCUMENTATION FOR
           LOADING PROCEDURE.

    3.1.3 AFTER LOADING THE PROGRAM WILL HALT AT WAIT 2.

           IF OPTIONS ARE DESIRED, GO TO 3.2.2.
           IF NO OPTIONS ARE DESIRED, GO TO 3.2.1.

    3.2   OPERATION

    3.2.1 IF NO OPTIONS ARE SET THE PROGRAM ASSUMES,

           1. ALL 9 TRACK DRIVES ON THE SYSTEM ARE TO BE RUN.
           2. OUTPUT DEVICE IS TO BE 1C53 OR 1816 TYPEWRITER.
           3. ALL ERRORS ARE TO BE PRINTED.

               TO EXECUTE THE PROGRAM-DEPRESS THE START BUTTON.

    3.2.2 OPERATING OPTIONS

           IF OPTIONS ARE DESIRED, SET SWITCHES FROM TABLES 0 AND 1 AND
           DEPRESS THE START BUTTON.

                        TABLE 0-CONTROL SWITCHES

           1. SWITCHES MAY BE SET PRIOR TO PROGRAM LOADING
               OR AT WAIT 2.
           2. SWITCHES 0 AND 1 MAY BE CHANGED ONLY BY A RESET-START
               OPERATION, BUT ALL OTHER SWITCHES MAY BE CHANGED AT
               ANYTIME.

```
***********************************************************************
* DATA ENTRY SWITCHES                    * DESCRIPTION                *
* 0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15  *                           *
*     . .             .     .   . . .  1. HALT BEFORE ROUTINE         *
*     . .             .     .   . . 1. . .HALT ON ERROR               *
*     . .             .     .   . 1 . . . .BYPASS PRINTOUTS           *
*     . .             .     .   1. . . . . .LOOP ON ERROR             *
*     . .             .     1 . . . . . . .LOOP PROGRAM               *
*     . .             1 . . . . . . . . . .USE 1443 AS OUTPUT DEVICE  *
*     . .           1 . . . . . . . . . . .PRINT ONLY FIRST BAD DATA WORD *
*     . .                                  (THIS IS AUTOMATIC IF SW 12 IS ON) *
*     . 1 . . . . . . . . . . . . . . . . .DO NOT RUN DRIVE 1         *
*   1 . . . . . . . . . . . . . . . . . . .DO NOT RUN DRIVE 0         *
***********************************************************************
```

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

TABLE 1-LOOP ROUTINE

1. THESE SWITCHES MAY BE CHANGED AT ANYTIME.
2. IF ZERO IS ENTERED, THE PROGRAM WILL NOT LOOP ANY
   ROUTINE, BUT WILL RUN ALL ROUTINES IN SEQUENCE.
3. IF IT IS DESIRED TO START ON A ROUTINE OTHER THAN
   ROUTINE 1, AND CONTINUE THE PROGRAM FROM THAT POINT,
   A. SET STARTING ROUTINE PER TABLE 1.
   B. START PROGRAM.
   C. WHILE PROGRAM IS RUNNING SELECT ROUTINE 0.
      THE PROGRAM WILL COMPLETE THE SELECTED ROUTINE AND
      THEN RUN THE REMAINING ROUTINES IN THEIR NORMAL
      SEQUENCE.

```
*****************************************************************
*          PROGRAM/SENSE SWITCHES      * DESCRIPTION           *
* 0 1 2 3 4 5 6 7                       *                       *
* 0 0 0 X X X X X . . . . . . . . . . . .ROUTINE TO BE LOOPED  *
*                              (ENTER 0 THROUGH 15 HEXADECIMAL) *
*****************************************************************
```

3.3 TERMINATING PROCEDURE

1. THE PROGRAM WILL TERMINATE WHEN ALL DRIVES SELECTED HAVE BEEN
   TESTED, UNLESS LOOP PROGRAM SWITCH IS ON.

2. THE PROGRAM WILL TERMINATE IF CERTAIN ERRORS OCCUR. (SEE SECTION
   4-PRINTOUTS)

3. THE PROGRAM CAN BE MANUALLY TERMINATED AT ANY TIME BY DEPRESSING
   THE STOP BUTTON.

3.4 RESTART PROCEDURE

PRESS THE STOP, RESET AND START KEYS. THE PROGRAM SHOULD GO TO
WAIT 2. IF THIS DOES NOT OCCUR THE PROGRAM MUST BE RELOADED.

3.5 PROGRAM HALTS

PROGRAM WAITS ARE USED IN THIS PROGRAM, AND ARE IDENTIFIED BY
REFERENCING THE B REGISTER AND I REGISTER.

A PROGRAM WAIT IS OF THE FORM,

     30XX (B REGISTER)

A DESCRIPTION OF THE INDIVIDUAL PROGRAM WAITS CAN BE FOUND AT THE
BEGINNING OF THE PROGRAM LISTING. A TYPICAL WAIT DESCRIPTION
FOLLOWS. IT IS INCLUDED TO SHOW THE FORMAT IN THE LISTING, AND IT IS
NOT NECESSARILY A DESCRIPTION OF AN ACTUAL WAIT.

```
*****************************************************************
3001 0  01ED               DC      WAIT1+1
                 *
                 *         ONE OF THE METERED I/O UNITS FAILED
                 *         TO SEND A RESPONSE INTERRUPT TO THE
                 *         PROGRAM.  INDEX REGISTER 1 WILL
                 *         HAVE THE ADDRESS OF THE IOCC.  THE
                 *         AREA CODE WILL INDICATE THE I/O UNIT
                 *         NOT READY.  IF A 2401/02 DRIVE IS
                 *         NOT READY, PROGRAM WILL NOT STOP AT
                 *         WAIT 1.
*****************************************************************
```

B REG., (FIRST 4 DIGIT GROUP) CORRESPONDS TO B REG. READING.
I REG., (SECOND 4 DIGIT GROUP) CORRESPONDS TO I REG. READING.

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

4. PRINTOUTS

   4.1   COMMAND MESSAGES

PID MID RID RAD UNIT
BD00 CC00 XXXX XXXX 000X
                 DRIVE 0 IS SELECTED TO BE RUN BUT IS NOT READY.
                 PROGRAM IS TERMINATED.

BD00 C001 XXXX XXXX 000X
                 DRIVE 1 IS SELECTED TO BE RUN BUT IS NOT READY.
                 PROGRAM IS TERMINATED.

BD00 CC02 XXXX XXXX 000X
                 ALL ROUTINES ARE COMPLETE ON THE DRIVE INDICATED.

   4.2 INFORMATION MESSAGES

                        NUMBER OF
                        RETRYS
BD00 A001 XXXX XXXX 000X XXXX
                 RECOVERED WRITE ERROR. A CORRECT WRITE WAS ACCOMPLISHED AFTER THE
                 NUMBER OF RETRYS SHOWN.

BD00 A002 XXXX XXXX 000X YYXX
                 RECOVERED READ ERROR. A CORRECT READ WAS ACCOMPLISHED AFTER THE
                 NUMBER OF RETRYS SHOWN. NUMBER RETRYS = YY TIMES 10 PLUS XX.

   4.3   ERROR MESSAGES

                        A   B   C   D
BD00 EC01 XXXX XXXX 000X XXXX XXXX XXXX XXXX
                 DATA RECEIVED WAS NOT CORRECT

                        A-EXPECTED DATA
                        B-RECEIVED DATA
                        C-WORD NUMBER IN ERROR
                        D-TRACK BEING TESTED (FFFF=LOST CHARACTER RTN)

                        DSW
                        RECEIVED
BD00 E002 XXXX XXXX 000X XXXX
                 DRIVE WAS NOT READY PRIOR TO A WRITE.
                 PROGRAM IS TERMINATED-SUGGEST RUNNING THE 2400 F. T.

BD00 E003 XXXX XXXX 000X XXXX
                 COULD NOT WRITE CORRECTLY IN THREE TRIES.
                 PROGRAM IS TERMINATED-SUGGEST RUNNING THE 2400 F. T.

BD00 E004 XXXX XXXX 000X XXXX
                 DRIVE WAS NOT READY PRIOR TO A READ.
                 PROGRAM IS TERMINATED-SUGGEST RUNNING THE 2400 F. T.

BD00 E005 XXXX XXXX 000X XXXX
                 UNCORRECTABLE READ ERROR.

BD00 E006 XXXX XXXX 000X XXXX
                 DSW INCORRECT AFTER BACKSPACE.
                 PROGRAM IS TERMINATED-SUGGEST RUNNING THE 2400 F. T.

BD00 E007 XXXX XXXX 000X XXXX
                 DRIVE WAS NOT READY PRIOR TO A BACKSPACE.
                 PROGRAM IS TERMINATED- SUGGEST RUNNING THE 2400 F. T.

BD00 E008 XXXX XXXX 000X XXXX
                 DRIVE WAS NOT READY PRIOR TO A REWIND.
                 PROGRAM IS TERMINATED-SUGGEST RUNNING THE 2400 F. T.

5. COMMENTS

THIS PROGRAM CONSISTS OF A SUPERVISOR ROUTINE, A SERIES OF COMMON MAGNETIC
TAPE ROUTINES AND A SERIES OF TESTS. SECTION 5.1 GIVES A DESCRIPTION OF
EACH SUBROUTINE AND ITS CALLING SEQUENCE. SECTION 5.2 GIVES A DESCRIPTION
OF EACH TEST ROUTINE.

5.1   COMMON SUBROUTINES

ALL ROUTINES ASSUME THAT INDEX REGISTER ONE CONTAINS THE NUMBER OF
THE TAPE DRIVE PRESENTLY BEING RUN.

NAME   CALL

BSP   BSI L BSP
       USE-BACKSPACE ONE RECORD ON THE DRIVE INDICATED BY INDEX REGISTER ONE.

DSL   BSI L DSL
       USE-RESET THE CRC CIRCUITRY BY SELECTING THE OTHER DRIVE.

HEXCV BSI L HEXCV
       USE-CONVERT A BINARY WORD TO ITS 1443 CODE HEXADECIMAL EQUIVILENT.

INTR   INTERRUPT ROUTINE
       USE-SENSE ILSW AND DSW. SAVES THE DSW WORD RECEIVED AND RESETS THE
           INTERRUPT LEVEL.

LOGC   BSI L LOGC
       USE-THIS ROUTINE IS ENTERED BY ROUTINE LOGOO. THIS ROUTINE PRINTS THE
           MESSAGE SET UP BY ROUTINE LOGOO, ON THE 1053 OR 1816 TYPEWRITER.

LOGOO BSI L LOGCO
       USE-THIS ROUTINE CONVERTS A 1443 CODED MESSAGE TO A 1053 OR 1816
           TYPEWRITER CODED MESSAGE. THIS ROUTINE THEN CALLS ON ROUTINE LOGC.

PR43   BSI L PR43
       USE-OUTPUT A MESSAGE ON THE 1443 PRINTER.

PRINT BSI L PRINT
       DC   MESSAGE ID
       DC   FORM NUMBER
       MDX   CONTINUE ADDRESS
       MDX   LOOP ON ERROR ADDRESS
       USE-SET UP THE DESIRED MESSAGE FROM THE MESSAGE ID AND FORM NUMBER.
           THIS ROUTINE THEN CALLS ON ROUTINE HEXCV. UPON COMPLETION OF THE
           CONVERSION THIS ROUTINE CALLS ON EITHER LOGOO OR PR43 DEPENDING ON
           THE OUTPUT DEVICE SELECTED. AFTER PRINTING IS COMPLETE THE HALT ON
           ERROR SWITCH IS CHECKED. IF ON, THE ROUTINE WAITS. FINALLY THE
           LOOP ON ERROR SWITCH IS CHECKED AND THE ROUTINE EXITS TO THE PROPER
           MDX INSTRUCTION FOLLOWING THE CALL.

RD   BSI L RD
       USE-READ A RECORD FROM THE TAPE DRIVE SPECIFIED BY INDEX REGISTER ONE.
           IF NO UNEXPECTED ERRORS EXIST THE ROUTINE BACKSPACES AND REREADS WITH
           CORRECTION. IF UNEXPECTED ERRORS EXIST ON EITHER READ, THE ROUTINE
           WILL RETRY ONE HUNDRED TIMES BEFORE PRINTING UNCORRECTABLE ERROR.

RWD   BSI L RWD
       USE-REWIND THE DRIVE SPECIFIED BY INDEX REGISTER ONE.

SNDSW BSI L SNDSW
       USE-SENSE THE DRIVE SPECIFIED BY INDEX REGISTER ONE. RETURN WITH THE
           DSW WORD RECEIVED IN THE A REGISTER.

SP7F   BSI L SP7F
       USE-SET THE FIRST EIGHT WORDS OF THE I/O AREA TO HEXADECIMAL 7F7F. ALSO
           SET WORDS TEN AND TWELVE TO HEXADECIMAL 007F AND ALL OTHER
           WORDS TO ZERO.

SP8F   BSI L SP8F
       USE-SET THE FIRST EIGHT WORDS IN THE I/O AREA TO HEXADECIMAL 8F8F. ALSO
           SET WORDS TEN AND TWELVE TO HEXADECIMAL 008F AND ALL OTHER WORDS
           TO ZERO.

SP80   BSI L SP80
       USE-SET THE FIRST EIGHT WORDS IN THE I/O AREA TO HEXADECIMAL 8080. ALSO
           SET WORDS TEN AND TWELVE TO HEXADECIMAL 0080 AND ALL OTHER WORDS TO
           ZERO.

WRT   BSI L WRT
       USE-WRITE ONE RECORD ON THE TAPE DRIVE SPECIFIED BY INDEX REGISTER ONE.
           IF ERRORS EXIST THE ROUTINE WILL BACKSPACE, ERASE AND REWRITE. IF
           THE ERROR STILL EXISTS AFTER THREE RETRYS IT IS AS UNCORRECTABLE
           WRITE ERROR.

5.2   TEST ROUTINES

CRC CHECKING METHOD USED BY THIS PROGRAM

THE FOLLOWING METHOD IS USED FOR CHECKING THE ERROR CORRECTION
CIRCUITRY IN THE MAGNETIC TAPE CONTROL UNIT. A RECORD IS SELECTED
SUCH THAT ITS DATA CHARACTERS, ITS CRC CHARACTER AND ITS LRC CHARACTER
DO NOT HAVE ANY BITS IN THE PARITY TRACK. FOR EXAMPLE, THE RECORD
CONSISTING OF THE SIXTEEN CHARACTERS 7F, 7F, ETC. WOULD ON A NORMAL
WRITE HAVE A CRC CHARACTER AND A LRC CHARACTER OF 7F. THIS RECORD
BY CHANGING ONE OR MORE OF THE CHARACTERS TO HAVE BAD PARITY WHEN NO
BY CHANGING ONE OR MORE OF THE CHARACTERS TO HAVE BAD PARITY WHEN NO
BY CHANGING ONE OR MORE OF THE CHARACTERS TO HAVE BAD PARITY WHEN NO
PARITY BIT IS WRITTEN. THE FOLLOWING CHARACTERS ARE SENT TO TAPE,

CHAR = 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25-625

TR																									
	*																*	*	*		*	*	*		* *
P	0 0 1 0 0 0 0 0 0 0	0	0	0	0	0	0	1	1	1	0	1	1	1	0	1 1
0	0 0 0 0 0 0 0 0 0 0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0 0
1	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0
2	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	1	0	0	0	0	1	0	0 0
3	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0
4	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0
5	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0
6	1 1 1 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0
7	1 1 0 1 1 1 1 1 1 1	1	1	1	1	1	0	0	0	1	0	0	0	1	0	0 0

WHEN THIS RECORD IS RECEIVED FROM TAPE, THE PARITY BITS (*) WILL NOT BE
READ. THIS WILL CAUSE CHARACTER 3 TO HAVE BAD PARITY ON TAPE.
CHARACTERS 17, 18 AND 19 WILL APPEAR AS NO BITS ON TAPE AS WILL
CHARACTERS 21, 22, 23 AND 25 THROUGH 625. WHEN READING THIS RECORD,
CHARACTER POSITIONS 17, 18 AND 19 WILL FORM A GAP SO THAT CHARACTER 20
WILL APPEAR AS THE CRC CHARACTER. THE GAP CAUSED BY THE NO BITS IN
CHARACTERS 21, 22 AND 23 WILL FORCE CHARACTER 24 TO BE TREATED AS A
LRC CHARACTER. THE ABSENCE OF BITS IN CHARACTERS 25 THROUGH 625 FORM
THE INTERRECORD GAP. WHEN CHARACTER 3 IS READ IT WILL ACTIVATE THE
ERROR CORRECTION CIRCUITRY AND CALCULATE THE TRACK IN ERROR. THIS
TRACK MUST BE TRACK 7 SINCE THE CRC CORRESPONDS TO CHARACTER 3 HAVING
A BIT IN TRACK 7.

IN A SIMILAR MANNER, TRACK IN ERROR DETECTION CAN BE FORCED IN ALL
TRACKS EXCEPT THE PARITY TRACK. IT MUST BE REALIZED THAT THIS PROGRAM
CANNOT CHECK THE PARITY TRACK SINCE A CARD IS REMOVED WHICH WILL PREVENT
THE PARITY BIT FROM BEING WRITTEN, TO ALLOW THIS METHOD OF CHECKING TO WORK.

DECIMAL ROUTINE NUMBER	HEXADECIMAL ROUTINE NUMBER	DESCRIPTION
1	1	SET THE I/O AREA TO 7F7F. THE ROUTINE THEN SETS A LOST BIT IN CHARACTER ONE, TRACK ONE AND WRITES THE DATA. THE RECORD IS THEN READ WITH CORRECTION AND THE DATA IS CHECKED TO SEE IF IT WAS CORRECTED. THE TEST IS THEN REPEATED UNTIL THE LOST BIT HAS BEEN PLACED IN EACH OF THE SIXTEEN CHARACTERS USED, IN TRACK ONE.
2	2	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK TWO.
3	3	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK THREE.
4	4	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK FOUR.
5	5	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK FIVE.
6	6	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK SIX.
7	7	THE SAME TEST AS ROUTINE ONE EXCEPT THE LOST BITS ARE PLACED IN TRACK SEVEN.
8	8	THE SAME TEST AS ROUTINE ONE EXCEPT THE PATTERN USED IS 8F8F AND LOST BITS ARE PLACED IN TRACK ZERO.
9	9	THIS ROUTINE SETS A PATTERN OF 8F70 IN THE EIGHT I/O WORDS. ALL BITS ON ONE TRACK ARE THEN SET TO ZERO INCLUDING THE CRC AND LRC CHARACTERS, THUS SIMULATING A DEAD TRACK. AFTER THE READ, THE DATA IS CHECKED TO SEE IF RECOVERY WAS CORRECT. THE TEST IS REPEATED UNTIL TRACKS 0 THROUGH 7 HAVE ALL BEEN TESTED AS DEAD TRACKS.
10	A	THIS ROUTINE SETS A PATTERN OF 8F70 IN THE I/O AREA. ALTERNATE PICKED AND DROPPED BITS ARE THEN SET IN TRACK 0. AFTER THE READ WITH CORRECTION THE DATA IS CHECKED. THE ROUTINE THEN REPEATS UNTIL TRACKS 0 THROUGH 7 HAVE BEEN CHECKED.
11	B	THE I/O AREA IS SET TO THE PATTERN OF 8080. ALL EVEN NUMBERED CHARACTERS EXCEPT CHARACTER 16 ARE THEN CLEARED TO SIMULATE LOST CHARACTERS. AFTER THE READ THE DATA IS CHECKED FOR PROPER RECOVERY.
12	C	THE I/O AREA IS SET TO THE PATTERN OF 8080. THE ROUTINE THEN SETS A PICKED BIT IN CHARACTER ONE, TRACK ONE AND WRITES THE DATA. THE RECORD IS READ WITH CORRECTION AND THE DATA IS CHECKED TO SEE IF IT WAS CORRECTED. THE TEST IS THEN REPEATED UNTIL THE PICKED BIT HAS BEEN PLACED IN EACH OF THE SIXTEEN CHARACTERS USED, IN TRACK ONE.
13	D	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK TWO.
14	E	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK THREE.

15	F	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK FOUR.
16	10	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK FIVE.
17	11	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK SIX.
18	12	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PICKED BITS ARE PLACED IN TRACK SEVEN.
19	13	THE SAME TEST AS ROUTINE TWELVE EXCEPT THE PATTERN USED IS 7F7F AND THE PICKED BITS ARE PLACED IN TRACK ZERO.
20	14	THIS ROUTINE SETS A PATTERN OF 8080 IN THE EIGHT I/O WORDS. ALL BITS OF ONE TRACK ARE SET TO ONE. AFTER THE READ THE DATA IS CHECKED TO SEE IF RECOVERY WAS MADE. THE TEST IS REPEATED UNTIL TRACK 1 THROUGH 7 HAVE BEEN TESTED.
21	15	THE SAME TEST AS ROUTINE TWENTY EXCEPT THE PATTERN IS 7F7F AND TRACK 0 IS TESTED.

6 APPENDIX

6.1 EDIT PROCEDURE

THE FOLLOWING PROCEDURE IS FOR CARD INPUT. FOR PAPER TAPE INPUT, REFER TO THE PAPER TAPE EDIT UTILITY PROGRAM DOCUMENTATION.

THE PROPER EDIT CARDS MUST BE THE LAST CARDS IN THIS PROGRAM DECK. THE FOLLOWING FORMS ARE PROVIDED TO AID IN MANUALLY PREPARING THESE EDIT CARDS OR UPDATING EXISTING EDIT CARDS. IF IT IS NECESSARY TO PREPARE OR MODIFY EDIT CARDS, FILL IN THE NECESSARY DATA IN THE FORMS PRIOR TO PUNCHING THE CARDS. CARD COLUMNS THAT ARE SHADED SHOULD BE LEFT BLANK.

ALL FIELDS SHOWN MUST BE PUNCHED IN THE CARD.

THE LAST CARD IS THE "END EDIT CARD". THE INFORMATION IN THIS CARD INCLUDES:

1. AN "E" IN COLUMN 1.
2. THE PID FOR THIS PROGRAM (COLUMNS 2 AND 3).
3. A TERMINATOR WORD OF "FFFF" (COLUMNS 7 - 10).

```
02BC                    ABS
                        ORG   /3001                              8BD00000
                    *                                            8BD00010
                    *                                            8BD00020
                    *          PROGRAMMED WAITS                  8BD00030
3001 0  0143            DC    WAIT1+1   LAST CARD OF THE         8BD00040
                    *                   DECK IS NOT AN END       8BD00050
                    *                   OF EDIT CARD. ARRANGE    8BD00060
                    *                   THE DECK AND RELOAD.     8BD00070
                    *                                            8BD00080
3002 0  015A            DC    WAIT2+1   WAIT FOR SWITCHES TO     8BD00090
                    *                   BE SET UP. SET DESIRED   8BD00100
                    *                   SWITCHES AND PRESS       8BD00110
                    *                   START.                   8BD00120
                    *                                            8BD00130
3003 0  0199            DC    WAIT3+1   HALT BEFORE ROUTINE.     8BD00140
                    *                   THIS WAIT WAS REACHED    8BD00150
                    *                   DUE TO SW. REQUEST.      8BD00160
                    *                   PUSH START TO CONTINUE.  8BD00170
                    *                                            8BD00180
3004 0  02E3            DC    WAIT4+1   LOST INTERRUPT AFTER     8BD00190
                    *                   WRITE.  PUSH RESET AND   8BD00200
                    *                   START TO RESTART THE     8BD00210
                    *                   PROGRAM.                 8BD00220
                    *                                            8BD00230
3005 0  02FB            DC    WAIT5+1   PROGRAM TERMINATED       8BD00240
                    *                   DUE TO LAST PRINTED      8BD00250
                    *                   ERROR.  SUGGEST THAT     8BD00260
                    *                   THE 2400 F. T. BE RUN.   8BD00270
                    *                   THIS PROGRAM CAN BE      8BD00280
                    *                   RETRIED BY PUSHING       8BD00290
                    *                   RESET AND START.         8BD00300
                    *                                            8BD00310
                    *                                            8BD00320
3006 0  0315            DC    WAIT6+1   LOST INTERRUPT AFTER     8BD00330
                    *                   ERASE.  PUSH RESET       8BD00340
                    *                   AND START TO RESTART     8BD00350
                    *                   THE PROGRAM.             8BD00360
                    *                                            8BD00370
3007 0  0340            DC    WAIT7+1   LOST INTERRUPT AFTER     8BD00380
3008 0  0349            DC    WAIT8+1   READ.  PUSH RESET        8BD00390
                    *                   AND START TO RESTART     8BD00400
                    *                   THE PROGRAM.             8BD00410
                    *                                            8BD00420
3009 0  03D6            DC    WAIT9+1   LOST INTERRUPT AFTER     8BD00430
                    *                   BACKSPACE.  PUSH RESET   8BD00440
                    *                   AND START TO RESTART     8BD00450
                    *                   THE PROGRAM              8BD00460
                    *                                            8BD00470
300A 0  0405            DC    WAITA+1   LOST INTERRUPT AFTER     8BD00480
                    *                   REWIND.  PUSH RESET      8BD00490
                    *                   AND START TO RESTART     8BD00500
                    *                   THE PROGRAM.             8BD00510
                    *                                            8BD00520
300B 0  04EA            DC    WAITB+1   WAIT BECAUSE HALT ON     8BD00530
                    *                   ERROR SWITCH IS ON       8BD00540
                    *                   AND AN ERROR HAS         8BD00550
                    *                   OCCURRED.  PUSH START    8BD00560
                    *                   TO CONTINUE THE          8BD00570
                    *                   PROGRAM.                 8BD00580
                    *                                            8BD00590
300C 0  0588            DC    WAITC+1   TYPEWRITER IS NOT        8BD00600
                    *                   READY.  MAKE IT          8BD00610
                    *                   READY AND PUSH START.    8BD00620
                    *                                            8BD00630
300D 0  05F9            DC    WAITD+1   1443 IS NOT READY.       8BD00640
                    *                   MAKE IT READY AND        8BD00650
                    *                   PUSH START.              8BD00660
                                                                 8BD00670
```

```
300E 0  0242            DC    WAITE+1   FOUND A BLANK ILSW       8BD00680
                    *                   AT INTERRUPT.  PUSH      8BD00690
                    *                   RESET AND START TO       8BD00700
                    *                   RESTART THE PROGRAM.     8BD00710
                    *                                            8BD00720
300F 0  038E            DC    WAITF+1   LOST INTRPT ON READ      8BD00730
                    *                   WHILE TRYING TO REST-    8BD00740
                    *                   ORE RECORD FOR RETRY     8BD00750
                    *                   AFTER PASSING CLEANER.   8BD00760
                    *                                            8BD00770
3010                    ORG   300                                8BD00780
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD00790
                    *                                            8BD00800
                    *          EDIT ROUTINE                      8BD00810
                    *                                            8BD00820
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD00830
012C 0  BD00            DC    /BD00     PID                      8BD00840
012D 00 67000152 START LDX   L3 EDT    IX 3 = LDR RETURN        8BD00850
012F 00 6F000124       STX   L3 /0124  STORE IN LOADER          8BD00860
0131 0  6050            LDX   X  /0050  GO TO LOADER             8BD00870
0132 0  62FB      EDT   LDX   2  -5     IX 2 = NO./ENTRIES       8BD00880
0133 0  C208      EDT1  LD    2  8      GET AN ENTRY             8BD00890
0134 00 D60001CB       STO   L2 EDIT+5 SET IN EDIT AREA         8BD00900
0136 0  7201            MDX   2  1      DECR IX 2                8BD00910
0137 0  70FB            MDX      EDT1   LOOP                     8BD00920
0138 00 6700013D       LDX   L3 EDT2   IX 3 = LDR RETURN        8BD00930
013A 00 6F000124       STX   L3 /0124  STORE IN LOADER          8BD00940
013C 0  6050            LDX   X  /0050  GO TO LOADER             8BD00950
013D 00 C4000001 EDT2  LD    L  /0001  GET LOC 1                8BD00960
013F 00 F4000513       EOR   L  TERM                            8BD00970
0141 0  4820            BSC   Z         IS THIS END EDIT         8BD00980
0142 0  3001      WAIT1 WAIT  1         NO                       8BD00990
                    *                                            8BD01000
0143 00 6700001B BEGIN LDX   L3 27     IX = NO LEVELS           8BD01010
0145 00 C400023E       LD    L  INTR2  GET COMMON INTR TRAP     8BD01020
0147 00 D7000007 BEGAN STO   L3 7      SET                      8BD01030
0149 0  73FF            MDX   3  -1     DECR IX 3                8BD01040
014A 0  70FC            MDX      BEGAN  LOOP                     8BD01050
014B 00 D4000001       STO   L  /0001  SET CE TRAP              8BD01060
014D 00 C400023F       LD    L  TPINT  GET TAPE TRAP            8BD01070
014F 00 D48001C8       STO   I  EDIT+2 SET                      8BD01080
0151 00 CC0001D0       LDD   L  RSTRT  GET RESTART              8BD01090
0153 00 DC000006       STD   L  /0006  SET RESTART              8BD01100
0155 00 C40001D2       LD    L  RSRT   GET RESTART MDX          8BD01110
0157 00 D4000000       STO   L  /0000  SET                      8BD01120
0159 0  3002      WAIT2 WAIT  2         WAIT FOR SWITCHES        8BD01130
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD01140
                    *                                            8BD01150
                    *          PROGRAM INITILIZATION             8BD01160
                    *                                            8BD01170
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD01180
015A 0  1010      MTST  SLA   16        CLEAR ALL NECESSARY      8BD01190
015B 0  D05C            STO   TAPE0     *LOCATIONS               8BD01200
015C 0  D05C            STO   TAPE1                              8BD01210
015D 00 D40004F1       STO   L  RID                             8BD01220
015F 00 D4000328       STO   L  WRERR                           8BD01230
0161 0  0858            XIO   UNMK0                              8BD01240
0162 0  0859            XIO   UNMK1     UNMASK ALL LEVELS        8BD01250
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD01260
                    *                                            8BD01270
                    *          SUPERVISOR ROUTINE                8BD01280
                    *                                            8BD01290
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX 8BD01300
0163 0  085E      SUPR  XIO   RDBSW     READ DATA SWS            8BD01310
0164 00 C40001CB       LD    L  SW0    GET SWS                  8BD01320
0166 0  4828            BSC   +Z        IS DRIVE 0 TO BE RUN     8BD01330
0167 0  700E            MDX   SUPR3     NO                       8BD01340
0168 00 C40001C9       LD    L  EDIT+3 GET NO TRACKS DR 0
```

```
016A 0  4820          BSC     Z           IS IT A 9 TRACK              88D01350
016B 0  700A          MDX     SUPR3       NO                          88D01360
016C 00 C40001C6      LD    L EDIT        GET AREA CODE               88D01370
016E 0  D049          STO     TAPE0       SAVE                        88D01380
016F 0  6100          LDX   1 0           SET IXING-DR 0              88D01390
0170 00 4400041E      BSI   L SNDSW       SENSE DRIVE           SRC   88D01400
0172 0  4804          BSC     E           IS DRIVE READY              88D01410
0'73 0  7034          MDX     SUPR4       NO                          88D01420
0174 00 440003F6      BSI   L RWD         REWIND DRIVE          SRC   88D01430
0176 00 C40001CA SUPR3 LD   L EDIT+4      GET NO TRACKS DR 1          88D01440
0178 0  4828          BSC     +Z          IS DR 1 AVAIL               88D01450
0179 0  7012          MDX     SUPR8       NO                          88D01460
017A 0  4820          BSC     Z           IS IT A 9 TRACK DR          88D01470
017B 0  7010          MDX     SUPR8       NO                          88D01480
017C 00 C40001CB      LD    L SW0         GET DATA SWS                88D01490
017E 0  1001          SLA     1                                       88D01500
017F 0  4828          BSC     +Z          IS DR 1 TO BE RUN           88D01510
0180 0  700B          MDX     SUPR8       NO                          88D01520
0181 00 C40001C6      LD    L EDIT        GET AREA CODE               88D01530
0183 0  F04A          EOR     MOD+1       SET DR 1 MOD                88D01540
0184 0  D034          STO     TAPE1       SAVE                        88D01550
0185 0  6101          LDX   1 1           SET IXING DR 1              88D01560
0186 00 4400041E      BSI   L SNDSW       SENSE DRIVE           SRC   88D01570
0188 0  4804          BSC     E           IS DR READY                 88D01580
0189 0  7026          MDX     SUPR6       NO                          88D01590
018A 00 440003F6      BSI   L RWD         REWIND DRIVE          SRC   88D01600
018C 0  C02B   SUPR8 LD       TAPE0       GET DR 0 AREA CODE          88D01610
018D 00 4C180191      BSC   L SUPR0,+-    IS IT ZERO                  88D01620
018F 0  6100          LDX   1 0           NO-SET TO DR 0              88D01630
0190 0  7004          MDX     SUPR1       START PROGRAM               88D01640
0191 0  C027   SUPR0 LD       TAPE1       GET DR 1 AREA CODE          88D01650
0192 00 4C1801F1      BSC   L RETR1,+-    BRANCH IF CLEAR             88D01660
0194 0  6101          LDX   1 1           SET IXING TO DR 1           88D01670
0195 0  082C   SUPR1 XIO      RDBSW       READ DATA SWS               88D01680
0196 0  C034          LD      SW0         GET SWS                     88D01690
0197 0  4804          BSC     E           IS HLT BEFORE RTN ON        88D01700
0198 0  3003   WAIT3 WAIT     3           YES                         88D01710
0199 0  082A          XIO      RDSSW      READ SNS/PRG SWS            88D01720
019A 0  C031          LD       SW1        GET SNS/PRG SWS             88D01730
019B 0  1808          SRA      8                                      88D01740
019C 00 4C2001A2      BSC   L SUPR2,Z     IS A RTN SEL                88D01750
019E 00 C40004F1      LD    L RID         NO-GET RTN NO               88D01760
01A0 00 84000684      A     L ONE         ADD ONE                     88D01770
01A2 00 D40004F1 SUPR2 STO  L RID         SET RTN NO                  88D01780
01A4 00 678004F1      LDX  I3 RID         IX 3 = ROUTINE NO           88D01790
01A6 00 4F8001D3      BSC  I3 CMRTT       GO TO ROUTINE               88D01800
                      *                                               88D01810
                      *             DRIVE 0 SELECTED BUT NOT          88D01820
                      *                   READY                       88D01830
                      *                                               88D01840
01A8 0  1010   SUPR4 SLA      16          CLEAR DR 0 AREA CODE        88D01850
01A9 0  D00E          STO      TAPE0                                  88D01860
01AA 00 4400043A      BSI   L PRINT       GO PRINT              SRC   88D01870
01AC 0  C000          DC       /C000      MSG 0                       88D01880
01AD 0  0002          DC       /0002      FORM 2                      88D01890
01AE 0  7094          MDX      BEGIN       CONTINUE                    88D01900
01AF 0  70B3   SUPR5 MDX      SUPR        LOOP ON ERROR               88D01910
                      *                                               88D01920
                      *             DRIVE 1 SELECTED BUT NOT          88D01930
                      *                   READY                       88D01940
                      *                                               88D01950
01B0 0  1010   SUPR6 SLA      16          CLEAR DR 1 AREA CODE        88D01960
01B1 0  D007          STO      TAPE1                                  88D01970
01B2 00 4400043A      BSI   L PRINT       GO PRINT              SRC   88D01980
01B4 0  C001          DC       /C001      MSG 1                       88D01990
01B5 0  0002          DC       /0002      FORM 2                      88D02000
01B6 0  708C          MDX      BEGIN      CONTINUE                    88D02010
01B7 0  70BE   SUPR7 MDX      SUPR3       LOOP ON ERROR               88D02020
```

```
                      *                                               88D02030
                      *                   CONSTANTS                   88D02040
                      *                                               88D02050
01B8    0000          BSS   E 0                                       88D02060
01B8 0  0000   TAPE0 DC      0            AREA CODE                   88D02070
01B9 0  00G0   TAPE1 DC      0            AREA CODE                   88D02080
01BA 0  0000   UNMK0 DC      0            UNMASK LOWER                88D02090
01BB 0  0480          DC      /0480                                   88D02100
01BC 0  0000   UNMK1 DC      0            UNMASK UPPER                88D02110
01BD 0  0481          DC      /0481                                   88D02120
01BE 0  FFFF   MK0   DC      /FFFF        MASK LOWER                  88D02130
01BF 0  0480          DC      /0480                                   88D02140
01C0 0  FFFF   MK1   DC      /FFFF        MASK UPPER                  88D02150
01C1 0  0481          DC      /0481                                   88D02160
01C2 0  01CB   RDBSW DC      SW0          READ DATA SWS               88D02170
01C3 0  0240          DC      /0240                                   88D02180
01C4 0  01CC   RDSSW DC      SW1          READ SNS/PRG SWS            88D02190
01C5 0  0260          DC      /0260                                   88D02200
01C6 0  0000   EDIT  DC      0            AREA CODE                   88D02210
01C7 0  0000          DC      0            ILSW BIT                    88D02220
01C8 0  0000          DC      0            INTR ADRS                   88D02230
01C9 0  0000          DC      0            TRKS DR 0                   88D02240
01CA 0  0000          DC      0            TRKS DR 1                   88D02250
01CB 0  0000   SW0   DC      0            DATA SW STORAGE             88D02260
01CC 0  0000   SW1   DC      0            SNS/PRG SW STORAGE          88D02270
01CD 0  0000   MOD   DC      0                                        88D02280
01CE 0  0020          DC      /0020        MOD FOR DR 1                88D02290
01D0    0000          BSS   E 0                                       88D02300
01D0 00 4C000143 RSTRT BSC  L BEGIN       RESTART BRANCH              88D02310
01D2 0  7005   RSRT  MDX   X /0005        RESTART MDX                 88D02320
                      *                                               88D02330
                      *                   ROUTINE TABLE               88D02340
                      *                                               88D02350
01D3 0  0016   CMRTT DC      22           NUMBER OF ROUTINES          88D02360
01D4 0  0624          DC      CMRT         ROUTINE 1                   88D02370
01D5 0  0624          DC      CMRT              2                     88D02380
01D6 0  0624          DC      CMRT              3                     88D02390
01D7 0  0624          DC      CMRT              4                     88D02400
01D8 0  0624          DC      CMRT              5                     88D02410
01D9 0  0624          DC      CMRT              6                     88D02420
01DA 0  0624          DC      CMRT              7                     88D02430
01DB 0  0689          DC      RTN8              8                     88D02440
01DC 0  06E3          DC      RTN9              9                     88D02450
01DD 0  0758          DC      RTN10             10                    88D02460
01DE 0  07B4          DC      RTN11             11                    88D02470
01DF 0  07F7          DC      CMR12             12                    88D02480
01E0 0  07F7          DC      CMR12             13                    88D02490
01E1 0  07F7          DC      CMR12             14                    88D02500
01E2 0  07F7          DC      CMR12             15                    88D02510
01E3 0  07F7          DC      CMR12             16                    88D02520
01E4 0  07F7          DC      CMR12             17                    88D02530
01E5 0  07F7          DC      CMR12             18                    88D02540
01E6 0  0855          DC      RTN19             19                    88D02550
01E7 0  08AD          DC      RT20              20                    88D02560
01E8 0  08F7          DC      RT21              21                    88D02570
01E9 0  01EA          DC      RETRN        END PROG                    88D02580
*XXXXXXXXXXX XXXXXXXX XXXXXXXXXXXXXXXX XXXXXXXXXXXXX                   88D02590
                      *                                               88D02600
                      *             ROUTINES RETURN HERE              88D02610
                      *                                               88D02620
*XXXXXXXXXXX XXXXXXXX XXXXXXXXXXXXXXXXXXXXX XXXXXXXXXXXX               88D02630
01EA 00 C40004F1 RETRN LD   L RID         GET RTN NUMBER              88D02640
01EC 0  F0E6          EOR     CMRTT                                   88D02650
01ED 00 4C1801F1      BSC   L RETR1,+-    BRANCH = ALL RTNS           88D02660
01EF 00 4C000195      BSC   L SUPR1       CONTINUE PROG               88D02670
01F1 00 4400043A RETR1 BSI  L PRINT       PRINT-PROG COMPLETE  SRC    88D02680
01F3 0  C002          DC      /C002        MSG 2                       88D02690
01F4 0  0032          DC      /0002        FORM 2                      88D02700
```

```
01F5 0   7000              MDX     RETR2       CONTINUE ADRS         88D02710
01F6 0   1010      RETR2   SLA     16          CLEAR AREA CODE       88D02720
01F7 00  D50001B8          STO  L1 TAPEO                             88D02730
01F9 00  C4000188          LD   L  TAPEO       GET DR 0 AREA CODE    88D02740
01FB 00  4C180203          BSC  L  RETR3,+-    IS IT CLEAR           88D02750
01FD 0   6100              LDX  1  0           NO-SET TO DR 0        88D02760
01FE 0   1010              SLA     16          CLEAR RTN NUMBER      88D02770
01FF 00  D40004F1          STO  L  RID                               88D02780
0201 00  4C000195          BSC  L  SUPR1       GO TO SUPERVISOR      88D02790
0203 00  C40001B9  RETR3   LD      TAPE1       GET DR 1 AREA CODE    88D02800
0205 00  4C18020D          BSC  L  END,+-      IS IT CLEAR           88D02810
0207 0   6101              LDX  1  1           NO-SET TO DR 1        88D02820
0208 0   1010              SLA     16          CLEAR ROUTINE NUMBER  88D02830
0209 00  D40004F1          STO  L  RID                               88D02840
020B 00  4C000195          BSC  L  SUPR1       GO TO SUPERVISOR      88D02850
                   *                                                 88D02860
020D 00  0C0001C2  END     XIO  L  RDBSW       READ DATA SWS         88D02870
020F 0   1010              SLA     16          CLEAR A REG           88D02880
0210 00  D40004F1          STO  L  RID         CLEAR RTN NO          88D02890
0212 00  C40001CB          LD   L  SWO         GET DATA SWS          88D02900
0214 0   1804              SRA     4                                 88D02910
0215 00  4C040163          BSC  L  SUPR,E      IS LOOP PROG ON       88D02920
0217 00  4C000143          BSC  L  BEGIN       NO                    88D02930
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D02940
                   *                                                 88D02950
                   *                        TAPE INTERRUPT ROUTINE   88D02960
                   *                                                 88D02970
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D02980
0219 0   0000      INTR    DC      0                              IE 88D02990
021A 0   2818              STS     TASS        SAVE STATUS           88D03000
021B 0   D81A              STD     TAAQ        SAVE A AND Q          88D03010
021C 0   081B              XIO     ILSW        SENSE ILSW            88D03020
021D 0   D01D              STO     TAILS       SAVE                  88D03030
021E 00  44180240          BSI  L  TERR,+-     BRANCH IF BLANK       88D0304C
0220 00  F40001C7          EOR  L  EDIT+1                            88D03050
0222 00  4C180227          BSC  L  INTR1,+-    BRANCH IF TAPE        88D03060
0224 00  44000242          BSI  L  SVINT       NOT TAPES             88D03070
0226 0   700B              MDX     INTR3                             88D03080
0227 0   C014      INTR1   LD      SDSW        GET FNC               88D03090
0228 00  F50001B8          EOR  L1 TAPEO       SET AREA CODE         86D03100
022A 0   D012              STO     SDSW+1      SAVE                  88D03110
022B 0   081D              XIO     SDSW        SENSE-NO RESET        88D03120
022C 0   C010              LD      SDSW+1      GET IOCC              89D03130
022D 00  F4000684          EOR  L  ONE         SET BIT 15            88D03140
022F 0   D00D              STO     SDSW+1      SAVE                  88D03150
0230 0   080B              XIO     SDSW        SENSE-RESET           88D03160
0231 0   D008              STO     DSW         SAVE SENSE WD         88D03170
0232 0   C803      INTR3   LDD     TAAQ        RESTORE A AND Q       88D03180
0233 0   2000      TASS    LDS     0           RESTORE STATUS        88D03190
0234 00  4CC00219          BOSC I  INTR        EXIT               IX 88D03200
0236 0   0000              BSS  E  0                                 88D03210
0236 0   0000      TAAQ    DC      0           A AND Q STORAGE       88D03220
0237 0   0000              DC      0                                 88D03230
                   *                                                 88D03240
0238 0   0000      ILSW    DC      0           SENSE ILSW IOCC       88D03250
0239 0   0300              DC      /0300                             88D03260
                   *                                                 88D03270
023A 0   0000      DSW     DC      0           DSW STORAGE           88D03280
023B 0   0000      TAILS   DC      0           ILSW STORAGE          88D03290
                   *                                                 88D03300
023C 0   0700      SDSW    DC      /0700       DSW IOCC              88D03310
023D 0   0000              DC      0                                 88D03320
                   *                                                 88D03330
023E 0   0242      INTR2   DC      SVINT       COMMON INT TRAP       88D03340
023F C   0219      TPINT   DC      INTR        TAPE INT TRAP         88D03350
                   *                                                 88D03360
0240 0   1000      TERR    NOP                                       88D03370
0241 0   300E      WAITE   DC      /300E       BLANK ILSW WAIT       88D03380
```

```
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D03390
                   *                                                 88D03400
                   *                          ROUTINE TO SERVICE NON-88D03410
                   *                          PROGRAM GENERATED      88D03420
                   *                          INTERRUPTS             88D03430
                   *                                                 88D03440
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D03450
0242 0   0000      SVINT   DC      0                              IE 88D03460
0243 00  0C0001BE          XIO  L  MKO         MASK ALL LVLS         88D03470
0245 00  0C0001C0          XIO  L  MK1                               88D03480
0247 0   D044              STO     SVIO        SAVE A REG            88D03490
0248 00  C400000A          LD   L  /000A       GET LOX 10            88D03500
024A 00  9400023E          S    L  INTR2       SUB ADRS SVINT        88D03510
024C 0   4818              BSC     +-          SKIP = ADRS 10        88D03520
024D 0   7006              MDX     SVIN3       NOT ADRS 10           88D03530
024E 00  C400000A          LD   L  /000A       GET ADRS 10           88D03540
0250 0   D0F1              STO     SVINT       SET RETURN            88D03550
0251 0   C0EC              LD      INTR2       RESTORE LOC 10        88D03560
0252 00  D400000A          STO  L  /000A                             88D03570
0254 00  0C000238  SVIN3   XIO  L  ILSW        RESET ILSW            88D03580
0256 00  7402028A          MDX  L  SV7,2       SET PASS SW           88D03590
0258 0   1010              SLA     16                                88D03600
0259 0   D02D              STO     SV4         CLEAR AREA CODE CTR    88D03610
025A 0   C02A              LD      SV2                               88D03620
025B 0   D02D              STO     SV6         SET IOCC IN USE SW     88D03630
025C 0   C027      SVINO   LD      SV1                               88D03640
025D 0   D02A              STO     SV5         SET MODIFIER CTR       88D03650
025E 0   C028      SVIN1   LD      SV4         *                     88D03660
025F 0   100B              SLA     11          *                     88D03670
0260 0   E827              OR      SV5         *BUILD IOCC            88D03680
0261 0   E827              OR      SV6         *                     88D03690
0262 0   D02A              STO     SVIO+1      *                     88D03700
0263 0   0828              XIO     SVIO        SENSE AND RESET DSW    88D03710
0264 00  74FF0288          MDX  L  SV5,-1                            88D03720
0266 0   70F7              MDX     SVIN1       BRANCH IF NOT ALL MD   88D03730
0267 00  74010287  SVIN2   MDX  L  SV4,1       INCREMENT AREA CODE    88D03740
0269 00  C40001C6          LD   L  EDIT        GET TAPE AREA CODE     88D03750
026B 0   180B              SRA     11                                88D03760
026C 0   901A              S       SV4                               88D03770
026D 0   4818              BSC     +-          SKIP = NOT TAPE        88D03780
026E 0   70F8              MDX     SVIN2       SET TO NEXT A C        88D03790
026F 0   C017              LD      SV4                               88D03800
0270 0   9012              S       SV0         CK IF ALL A C USED     88D03810
0271 0   4808              BSC     +                                 88D03820
0272 0   70E9              MDX     SVINO       GO USE NEXT A C        88D03830
0273 00  74FF028A          MDX  L  SV7,-1      SKIP IF SECOND PASS    88D03840
0275 0   7001              MDX     **+1                              88D03850
0276 0   7005              MDX     SVEXT                             88D03860
0277 0   C00E              LD      SV3                               88D03870
0278 0   D010              STO     SV6         SET IOCC FOR PI        88D03880
0279 0   1010              SLA     16                                88D03890
027A 0   D00C              STO     SV4         SET AC FOR NEXT        88D03900
027B 0   70E0              MDX     SVINO       *PASS                  88D0391C
027C 0   C00F      SVEXT   LD      SVIO        RESTORE ACCUM          88D03920
027D 00  0C0001BA          XIO  L  UNMKO       UNMASK ALL LEVELS      88D03930
027F 00  0C0001BC          XIO  L  UNMK1                             88D03940
0281 00  4CC00242          BOSC I  SVINT       EXIT               IX 88D03950
                   *                                                 88D03960
                   *                          CONSTANTS              88D03970
                   *                                                 88D03980
0283 0   001F      SV0     DC      /001F       NUMBER OF AREA CODES   88D03990
0284 0   00FF      SV1     DC      /00FF       NUMBER OF MODIFIERS    88D04000
0285 0   0701      SV2     DC      /0701       RESET DSW              88D04010
0286 0   0700      SV3     DC      /0700       RESET PISW             88D04020
0287 0   0000      SV4     DC      0           AREA CODE INDICATOR    88D04030
0288 0   0000      SV5     DC      0           MODIFIER INDICATOR     88D04040
0289 0   0000      SV6     DC      0           IOCC IN USE            88D04050
028A 0   0000      SV7     DC      0           PASS SWITCH            88D04060
```

L

```
028C   0000                BSS   E  0                                        88D04070
028C 0 0000        SVIO  DC       0           SENSE DSW IOCC                  88D04080
028D 0 0000              DC       0                                          88D04090
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX              88D04100
                   *                                                        88D04110
                   *              ROUTINE TO SET 7F PATTERN                 88D04120
                   *                                                        88D04130
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX         88D04140
028E 0 0000        SP7F  DC       0                                    SE   88D04150
028F 0 6308              LDX    3 8           IX 3 = 16 CHARACTERS          88D04160
0290 0 C012              LD       P7F         GET 7F7F                      88D04170
0291 00 D7000938   SP7F0 STO   L3 IOAA-1      SET IN I/O AREA              88D04180
0293 0 73FF              MDX    3 -1          DECR IX 3                    88D04190
0294 0 70FC              MDX      SP7F0       LOOP                         88D04200
0295 00 67000131        LDX   L3 305          IX 3= 608 CHARACTERS         88D04210
0297 0 1010              SLA      16          CLEAR A REG                  88D04220
0298 00 D7000940   SP7F1 STO   L3 IOAA+7      SET IN I/O AREA              88D04230
029A 0 73FF              MDX    3 -1          DECR IX 3                    88D04240
029B 0 70FC              MDX      SP7F1       LOOP                         88D04250
029C 0 C007              LD       CRC7F       GET 007F                     88D04260
029D 00 D4000942        STO   L  IOAA+9       SET AS CRC CHARACTER         88D04270
029F 00 D4000944        STO   L  IOAA+11      SET AS LRC CHARACTER         88D04280
02A1 00 4C80028E        BSC   I  SP7F         EXIT                     SX   88D04290
                   *             CONSTANTS                                  88D04300
                   *                                                        88D04310
                   *                                                        88D04320
02A3 0 7F7F        P7F   DC       /7F7F       PATTERN WORD                 88D04330
02A4 0 007F        CRC7F DC       /007F       CRC/LRC CHARACTER            88D04340
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX         88D04350
                   *                                                        88D04360
                   *              ROUTINE TO SET 8F PATTERN                 88D04370
                   *                                                        88D04380
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX         88D04390
02A5 0 0000        SP8F  DC       0                                    SE   88D04400
02A6 0 6308              LDX    3 8           IX 3 = 16 CHARACTERS          88D04410
02A7 00 C40006E1        LD    L  P8F          GET PATTERN                  88D04420
02A9 00 D7000938   SP8F0 STO   L3 IOAA-1      SET IN I/O AREA              88D04430
02AB 0 73FF              MDX    3 -1          DECR IX 3                    88D04440
02AC 0 70FC              MDX      SP8F0       LOOP                         88D04450
02AD 00 67000131        LDX   L3 305          IX 3= 608 CHARACTERS         88D04460
02AF 0 1010              SLA      16          CLEAR A REG                  88D04470
02B0 00 D7000940   SP8F1 STO   L3 IOAA+7      SET IN I/O AREA              88D04480
02B2 0 73FF              MDX    3 -1          DECR IX 3                    88D04490
02B3 0 70FC              MDX      SP8F1       LOOP                         88D04500
02B4 0 C006              LD       CRC8F       GET 008F                     88D04510
02B5 00 D4000942        STO   L  IOAA+9       SET AS CRC CHARACTER         88D04520
02B7 00 D4000944        STO   L  IOAA+11      SET AS LRC CHARACTER         88D04530
02B9 00 4C8002A5        BSC   I  SP8F         EXIT                     SX   88D04540
                   *             CONSTANTS                                  88D04550
                   *                                                        88D04560
                   *                                                        88D04570
02BB 0 008F        CRC8F DC       /008F       CRC/LRC CHARACTER            88D04580
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX         88D04590
                   *                                                        88D04600
                   *              SET I/O AREA TO 8080                      88D04610
                   *                                                        88D04620
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX         88D04630
02BC 0 0000        SP80  DC       0                                    SE   88D04640
02BD 0 6308              LDX    3 8           IX 3 = 16 CHARACTERS          88D04650
02BE 00 C40002D3        LD    L  P80          GET 8080                     88D04660
02C0 00 D7000938   RT11J STO   L3 IOAA-1      SET IN I/O AREA              88D04670
02C2 0 73FF              MDX    3 -1          DECR IX 3                    88D04680
02C3 0 70FC              MDX      RT11J       LOOP                         88D04690
02C4 00 67000131        LDX   L3 305          IX 3 = 608 CHARACTERS        88D04700
02C6 0 1010              SLA      16          CLEAR A REG                  88D04710
02C7 00 D7000940   RT11K STO   L3 IOAA+7      SET IN I/O AREA              88D04720
02C9 0 73FF              MDX    3 -1          DECR IX 3                    88D04730
02CA 0 70FC              MDX      RT11K       LOOP                         88D04740
```

```
02CB 0 C006              LD       CRC80       GET CRC/LRC CHARACTER         88D04750
02CC 00 D4000942        STO   L  IOAA+9       SET AS CRC CHARACTER         88D04760
02CE 00 D4000944        STO   L  IOAA+11      SET AS LRC CHARACTER         88D04770
02D0 00 4C8002BC        BSC   I  SP80         EXIT                     SX   88D04780
02D2 0 0080        CRC80 DC       /0080       CRC/LRC CHARACTER            88D04790
02D3 0 8080        P80   DC       /8080       PATTERN                      88D04800
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX        88D04810
                   *                                                        88D04820
                   *              WRITE ROUTINE                             88D04830
                   *                                                        88D04840
                   *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX        88D04850
02D4 0 0000        WRT   DC       0                                    SE   88D04860
02D5 00 C50001B8   WRT01 LD    L1 TAPE0       GET AREA CODE                88D04870
02D7 0 F04E              EOR      WRTCC       SET WRT FNC                  88D04880
02D8 0 D04A              STO      WRIOC+1     SAVE                         88D04890
02D9 0 C051              LD       WRTWC       GET WRT WD CT                88D04900
02DA 00 D4000938        STO   L  IOA         SET                          88D04910
                   *                                                        88D04920
02DC 00 4400041E   WRT02 BSI   L  SNDSW       SENSE DRIVE              SRC  88D04930
02DE 0 1801              SRA      1                                        88D04940
02DF 0 4804              BSC      E           IS DR READY                  88D04950
02E0 0 7011              MDX      WRT04       NO                           88D04960
                   *                                                        88D04970
02E1 0 0840              XIO      WRIOC       WRITE ONE RECORD             88D04980
02E2 0 3004        WAIT4 WAIT     4           WAIT FOR INTRPT              88D04990
                   *                                                        88D05000
02E3 00 C400023A        LD    L  DSW          GET SENSE WORD               88D05010
02E5 0 1802              SRA      2                                        88D05020
02E6 0 4804              BSC      E           IS TAPE MARKER ON            88D05030
02E7 0 7036              MDX      WRT11       YES                          88D05040
                   *                                                        88D05050
02E8 00 C400023A        LD    L  DSW          GET SENSE WD                 88D05060
02EA 0 E03C              AND      WRTSW                                    88D05070
02EB 0 4820              BSC      Z           IS WORD AS EXPECTED          88D05080
02EC 0 700E              MDX      WRT06       NO                           88D05090
                   *                                                        88D05100
02ED 0 C03A              LD       WRERR       GET ERROR COUNT              88D05110
02EE 0 4820              BSC      Z           WERE THERE ANY EPRS          88D05120
02EF 0 7026              MDX      WRT09       YES                          88D05130
02F0 00 4C8002D4   WRT03 BSC   I  WRT         EXIT                     SX   88D05140
                   *                                                        88D05150
                   *              DRIVE WAS NOT READY                       88D05160
                   *                                                        88D05170
02F2 00 4400043A   WRT04 BSI   L  PRINT       PRINT DR NOT READY           88D05180
02F4 0 E002              DC       /E002       ERROR 2                      88D05190
02F5 0 0003              DC       /0003       FORM 3                       88D05200
02F6 0 7001              MDX      WRT05       CONTINUE                     88D05210
02F7 0 70E4              MDX      WRT02       LOOP ON ERROR                88D05220
02F8 0 1010        WRT05 SLA      16          CLEAR ERROR CT               88D05230
02F9 0 D02E              STO      WRERR                                    88D05240
02FA 0 3005        WAIT5 WAIT     5           TERMINATE PROG               88D05250
                   *                                                        88D05260
                   *              DSW NOT AS EXPECTED                       88D05270
                   *                                                        88D05280
02FB 0 C02C        WRT06 LD       WRERR       GET ERROR CT                 88D05290
02FC 00 84000684        A     L  ONE          ADD ONE                      88D05300
02FE 0 D029              STO      WRERR       SAVE                         88D05310
02FF 0 9029              S        FOUR        SUB 4                        88D05320
0300 0 4820              BSC      Z           RETRIED 3 TIMES              88D05330
0301 0 7008              MDX      WRT08       NO                           88D05340
0302 00 C400023A        LD    L  DSW          GET SENSE WD                 88D05350
0304 00 D4000438        STO   I  SNSV         SAVE                         88D05360
0306 00 4400043A        BSI   L  PRINT        PRINT-CAN NOT WRITE      SRC  88D05370
0308 0 E003              DC       /E003       ERROR 3                      88D05380
0309 0 0003              DC       /0003       FORM 3                       88D05390
030A 0 70ED              MDX      WRT05       CONTINUE                     88D05400
030B 0 1010        WRT07 SLA      16          CLEAR ERR CT                 88D05410
030C 0 D018              STO      WRERR                                    88D05420
```

```
030D 00 440003C4   WRT08 BSI L BSP       GO BACKSPACE           88D05430
030F 00 C50001B8         LD  L1 TAPEO    GET AREA CODE          88D05440
0311 0 F012             EOR    ERA       SET ERASE FNC          88D05450
0312 0 D012             STO    ERA+1     SET                    88D05460
0313 0 0810             XIO    ERA       ISSUE ERASE            88D05470
                                                                88D05480
0314 0 3006        WAIT6 WAIT  6         WAIT FOR INTRPT        88D05490
                                                                88D05500
0315 0 70BF             MDX    WRT01     TRY AGAIN              88D05510
                                                                88D05520
                             HAD ERRORS                         88D05530
                                                                88D05540
0316 00 4400043A   WRT09 BSI L PRINT     PRINT RECOVERED WRT    88D05550
0318 0 A001             DC    /A001      MSG 1                  88D05560
0319 0 0004             DC    /0004      FORM 4                 88D05570
031A 0 7000             MDX   WRT10      CONTINUE               88D05580
031B 0 1010        WRT10 SLA   16        CLEAR ERROR CT         88D05590
031C 0 D00B             STO   WRERR                             88D05600
031D 0 70D2             MDX   WRT03      CO EXIT                88D05610
031E 00 440003F6   WRT11 BSI L RWD       GO REWIND         SRC  88D05620
0320 0 70B4             MDX   WRT01      WRITE                  88D05630
                                                                88D05640
                             CONSTANTS                          88D05650
                                                                88D05660
0322   0000             BSS E 0                                 88D05670
0322 0 0938        WRIOC DC    IOA       WRITE IOCC             88D05680
0323 0 0000             DC    0                                 6BD05690
                                                                88D05700
0324 0 0402        ERA   DC    /0402     ERASE IOCC             88D05710
0325 0 0000             DC    0                                 88D05720
                                                                88D05730
0326 0 0500        WRTCC DC    /0500     WRITE FNC              88D05740
0327 0 3DBF        WRTSW DC    /3DBF     DSW CK-WRITE           88D05750
0328 0 0000        WRERR DC    0         ERROR CT               88D05760
0329 0 0004        FOUR  DC    4         CONSTANT               88D05770
032A 0 000B        ELE   DC    11        CONSTANT               88D05780
032B 0 4139        WRTWC DC    /4139     WRT WD CT              88D05790
*XX XXXXXXXX XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D05800
                                                                88D05810
                                                                88D05820
                             READ ROUTINE                       88D05830
                                                                88D05840
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D05850
032C 0 0000        RD    DC    0                           SE   88D05860
032D 00 C50001B8         LD  L1 TAPEO    GET AREA CODE          88D05870
032F 00 F40003BE         EOR L RDFNC     SET READ FNC           88D05880
0331 00 D40003BD         STO L RDIOC+1   SAVE                   88D05890
0333 00 C40003BA         LD  L RDTWC     GET READ WD CT         88D05900
0335 00 D4000938         STO L IOA       SET                    88D05910
0337 00 6F000353         STX L3 RDE+1    SAVE IX 3              88D05920
0339 00 4400041E   RD001 BSI L SNDSW     SENSE DRIVE       SRC  88D05930
033B 0 1801             SRA   1                                 88D05940
033C 0 4804             BSC   E          IS DRIVE READY         88D05950
033D 0 7018             MDX   RD02       NO                     88D05960
                                                                88D05970
033E 0 087D             XIO   RDIOC      ISSUE READ             88D05980
                                                                88D05990
033F 0 3007        WAIT7 WAIT  7         WAIT FOR INTRPT        88D06000
                                                                88D06010
0340 00 C400023A         LD  L DSW       GET SENSE WD           88D06020
0342 0 E07C             AND   RD1DS                             88D06030
0343 0 4820             BSC   Z          IS DSW AS EXPECTED     88D06040
0344 0 7019             MDX   RD04       NO                     88D06050
                                                                88D06060
0345 00 440003C4         BSI L BSP       GO BACKSPACE      SRC  88D06070
                                                                88D06080
0347 0 0874             XIO   RDIOC      ISSUE READ             88D06090
                                                                88D06100
```

```
0348 0 3008        WAIT8 WAIT  8         WAIT FOR INTRPT        88D06110
                                                                88D06120
0349 00 C400023A         LD  L DSW       GET SENSE WD           88D06130
034B 0 E074             AND   RD2DS                             88D06140
034C 0 4820             BSC   Z          IS DSW OK              88D06150
034D 0 7010             MDX   RD04       NO                     88D06160
                                                                88D06170
034E 00 C4000328         LD  L WRERR     GET ERROR CT           88D06180
0350 0 4820             BSC   Z          ANY ERRORS             88D06190
0351 0 7059             MDX   RD07       YES                    88D06200
0352 00 67000000   RDE   LDX L3 0        RESTORE IX 3           88D06210
0354 00 4C80032C         BSC I RD        EXIT              SX   88D06220
                                                                88D06230
                       DRIVE IS NOT READY                       88D06240
                                                                88D06250
0356 00 4400043A   RD02  BSI L PRINT     PRINT-NOT READY        88D06260
0358 0 E004             DC    /E004      ERROR 4                88D06270
0359 0 0003             DC    /0003      FORM 3                 88D06280
035A 0 7001             MDX   RD03       CONTINUE               88D06290
035B 0 70DD             MDX   RD01       LOOP ON ERROR          88D06300
035C 00 4C0002F8   RD03  BSC L WRT05     GO TERMINATE PROG      88D06310
                                                                88D06320
                     SENSE WORD IS NOT CORRECT                  88D06330
                                                                88D06340
035E 00 C400023A   RD04  LD  L DSW       GET SENSE WORD         88D06350
0360 0 E060             AND   CORDS                             88D06360
0361 0 4820             BSC   Z          IS ERROR CORRECTABLE   88D06370
0362 0 7036             MDX   RD05       NO                     88D06380
0363 00 C4000328         LD  L WRERR     GET ERROR CT           88D06390
0365 0 E044             AND   RDTXO      SAVE RETRY CT          88D06400
0366 0 9042             S     K009       SUB 9                  88D06410
0367 0 4818             BSC   +-         IS CT = 9              88D06420
0368 0 7007             MDX   CLN        YES                    88D06430
0369 00 C4000328         LD  L WRERR     GET ERROR CT           88D06440
036B 00 84000684         A   L ONE       ADD 1                  88D06450
036D 00 D4000328         STO L WRERR     SAVE                   88D06460
036F 0 7044             MDX   RD09       GO RETRY               88D06470
                                                                88D06480
                        GO PAST CLEANER                         88D06490
                                                                88D06500
0370 00 C4000328   CLN   LD  L WRERR     GET ERROR CT           88D06510
0372 0 1808             SRA   8          SAVE CLEAN CT          88D06520
0373 0 9035             S     K009       SUB 9                  88D06530
0374 00 4C180399         BSC L RD05,+-   BRANCH = 9             88D06540
0376 0 8031             A     K010       ADD 10                 88D06550
0377 0 1008             SLA   8                                 88D06560
0378 00 D4000328         STO L WRERR     SAVE                   88D06570
037A 0 6305        CLN1  LDX   3 5       SET TO PASS CLEANER    88D06580
037B 0 6B08        CLN2  STX   3 CLN3+1  SAVE IX 3              88D06590
037C 00 440003C4         BSI L BSP       GO BACKSPACE      SRC  88D06600
037E 00 4400041E         BSI L SNDSW     SENSE DRIVE       SRC  88D06610
0380 0 1803             SRA   3                                 88D06620
0381 0 4804             BSC   E          IS DR AT LD PT         88D06630
0382 0 7010             MDX   CLN8       YES                    88D06640
0383 00 67000000   CLN3  LDX L3 0        RESTORE IX 3           88D06650
0385 0 73FF             MDX   3 -1       DECR IX 3              88D06660
0386 0 7CF4             MDX   CLN2       LOOP                   88D06670
0387 0 6305             LDX   3 5        SET TO RESTORE         88D06680
0388 0 6B06        CLN5  STX   3 CLN7+1  SAVE IX 3              88D06690
0389 0 73FF             MDX   3 -1       DECR IX 3              88D06700
038A 0 7001             MDX   CLN6                             88D06710
038B 0 70AD             MDX   RD01       GO RETRY RECORD        88D06720
038C 0 082F        CLN6  XIO   RDIOC     SKIP RECORD            88D06730
038D 0 300F        WAITF DC    /300F     WAIT FOR INTRPT        88D06740
038E 00 67000000   CLN7  LDX L3 0        RESTORE IX 3           88D06750
0390 0 73FF             MDX   3 -1       DECR IX 3              88D06760
0391 0 70F6             MDX   CLN5       GO SKIP                88D06770
0392 0 70F5             MDX   CLN5                             88D06780
```

```
                    *                                                     8BD06790
                    *           RESTORE TAPE TO THE                       8BD06800
                    *           RECORD IN ERROR                           8BD06810
0393 0  C013   CLN8  LD    K005       GET 5                               8BD06820
0394 0  90EF        S     CLN3+1     SUB PRESENT LOC                      8BD06830
0395 0  D0EE        STO   CLN3+1     SAVE                                 8BD06840
0396 00 67800384    LDX  I3 CLN3+1   LOAD IX 3                            8BD06850
0398 0  70EF        MDX   CLN5       GO RESTORE                           8BD06860
0399 00 C400023A RD05 LD  L  DSW     GET SENSE WD                         8BD06870
039B 00 D4000438     STO L  SNSV     SAVE                                 8BD06880
039D 00 4400043A     BSI L  PRINT    PRINT UNCORRECTABLE                  8BD06890
039F 0  E005        DC    /E005      ERROR 5                              8BD06900
03A0 0  0003        DC    /0003      FORM 3                               8BD06910
03A1 0  700E        MDX   RD08       CONTINUE                             8BD06920
03A2 0  1010   RD06  SLA   16         CLEAR ERROR CT                      8BD06930
03A3 00 D4000328     STO L  WRERR                                        8BD06940
03A5 00 4C0003B4     BSC L  RD09     LOOP ON ERROR                        8BD06950
03A7 0  0005   K005  DC    5          CONSTANT 5                          8BD06960
03A8 0  000A   K010  DC    10         CONSTANT 10                         8BD06970
03A9 0  0009   K009  DC    9          CONSTANT 9                          8BD06980
03AA 0  00FF   RDTXO DC   /00FF       SAVE RETRY CT                       8BD06990
                    *                                                     8BD07000
                    *           HAD PREVIOUS ERRORS                       8BD07010
                    *                                                     8BD07020
03AB 00 4400043A RD07 BSI L  PRINT    PRINT-RECOVERED READ SRC            8BD07030
03AD 0  A002        DC    /A002      MSG 2                                8BD07040
03AE 0  0004        DC    /0004      FORM 4                               8BD07050
03AF 0  7000        MDX   RD08       CONTINUE                             8BD07060
03B0 0  1010   RD08  SLA   16         CLEAR ERROR CT                      8BD07070
03B1 00 D4000328     STO L  WRERR                                        8BD07080
03B3 0  709E        MDX   RDE        GO EXIT                              8BD07090
                    *                                                     8BD07100
                    *           SET UP TO RETRY                           8BD07110
                    *                                                     8BD07120
03B4 00 440003C4 RD09 BSI L  BSP      GO BACKSPACE      SRC               8BD07130
03B6 00 44000617     BSI L  DSLT     GO DESELECT       SRC               8BD07140
03B8 00 4C000339     BSC L  RD01     GO RETRY                             8BD07150
                    *                                                     8BD07160
                    *           CONSTANTS                                 8BD07170
                    *                                                     8BD07180
                    *                                                     8BD07190
03BA 0  4008   RDTWC DC   /4008       READ WD CT                          8BD07200
03BC    0000        BSS E 0                                               8BD07210
03BC 0  0938   RDICC DC   IOA         READ IOCC                           8BD07220
03BD 0  0000        DC    0                                               8BD07230
                    *                                                     8BD07240
03BE 0  0602   RDFNC DC   /0602       READ FUNCTION                       8BD07250
03BF 0  3D9F   RD1DS DC   /3D9F       DSW CK-FIRST WORD                   8BD07260
03C0 0  3F9F   RD2DS DC   /3F9F       DSW CK-SECOND WORD                  8BD07270
03C1 0  3C0F   CORDS DC   /3C0F       DSW CK-CORRECTABLE                  8BD07280
03C2 0  0001   SELDR DC   1           SEL OTHER DR                        8BD07290
03C3 0  0000        DC    0                                               8BD07300
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX                          8BD07310
                    *                                                     8BD07320
                    *           BACKSPACE ROUTINE                         8BD07330
                    *                                                     8BD07340
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX                          8BD07350
03C4 0  0000   BSP   DC    0                          SE                  8BD07360
03C5 00 4400041E BSP01 BSI L SNDSW    SENSE DR         SRC                8BD07370
03C7 0  1801        SRA   1                                               8BD07380
03C8 0  4804        BSC   E          IS DR READY                          8BD07390
03C9 0  701D        MDX   BSP06      NO                                   8BD07400
03CA 0  1802        SRA   2                                               8BD07410
03CB 00 4C0403CE     BSC L  BSP02,E  IS DR AT LD PT                       8BD07420
03CD 0  7002        MDX   BSP03      NO                                   8BD07430
03CE 00 4C8003C4 BSP02 BSC I  BSP    EXIT             SRC                 8BD07440
03D0 00 C50001B8 BSP03 LD  L1 TAPEO  GET AREA CODE                        8BD07450
                                                                          8BD07460
```

```
03D2 0  F021        EOR   BSPIO      SET BSP FNC                          8BD07470
03D3 0  D021        STO   BSPIO+1    SAVE                                 8BD07480
                    *                                                     8BD07490
03D4 0  081F        XIO   BSPIO      ISSUE BACKSPACE                      8BD07500
03D5 0  3009   WAIT9 WAIT  9          WAIT FOR INTRPT                     8BD07510
                    *                                                     8BD07520
03D6 00 C400023A    LD  L  DSW       GET SENSE WD                         8BD07530
03D8 0  4804        BSC   E          IS DR READY                          8BD07540
03D9 0  7001        MDX   BSP04      NO                                   8BD07550
03DA 0  70F3        MDX   BSP02      YES-EXIT                             8BD07560
                    *                                                     8BD07570
                    *           DSW WRONG AFTER BSP                       8BD07580
03DB 00 C400023A BSP04 LD  L  DSW    GET SENSE WD                         8BD07590
03DD 00 D4000438     STO L  SNSV     SAVE                                 8BD07600
03DF 00 4400043A     BSI L  PRINT    PRINT WRONG DSW                      8BD07610
03E1 0  E006        DC    /E006      ERROR 6                              8BD07620
03E2 0  0003        DC    /0003      FORM-3                               8BD07630
03E3 0  7001        MDX   BSP05      CONTINUE                             8BD07640
03E4 0  70EB        MDX   BSP03      LOOP ON ERROR                        8BD07650
03E5 00 4C0002F8 BSP05 BSC L  WRT05  TERMINATE                            8BD07660
                    *                                                     8BD07670
                    *           DRIVE NOT READY                           8BD07680
                    *                                                     8BD07690
03E7 00 C400023A BSP06 LD  L  DSW    GET SENSE WD                         8BD07700
03E9 00 D4000438     STO L  SNSV     SAVE                                 8BD07710
03EB 00 4400043A     BSI L  PRINT    PRINT-NOT READY      SRC             8BD07720
03ED 0  E007        DC    /E007      ERROR 7                              8BD07730
03EE 0  0003        DC    /0003      FORM 3                               8BD07740
03EF 0  7001        MDX   BSP07      CONTINUE                             8BD07750
03F0 0  70D4        MDX   BSP01      LOOP ON ERROR                        8BD07760
03F1 00 4C0002F8 BSP07 BSC L  WRT05  TERMINATE                            8BD07770
                    *                                                     8BD07780
                    *           CONSTANTS                                 8BD07790
                    *                                                     8BD07800
03F4    0000        BSS E 0                                               8BD07810
03F4 0  0403   BSPIO DC   /0403      BACKSPACE IOCC                       8BD07820
03F5 0  0000        DC    0                                               8BD07830
*XXXXXXXXXXXXXXXXXXXX (XXXXXXXXXXXXXXXXXXXXXXXXXXXX                       8BD07840
                    *                                                     8BD07850
                    *           REWIND ROUTINE                            8BD07860
                    *                                                     8BD07870
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX                         8BD07880
03F6 0  0000   RWD   DC    0                          SE                  8BD07890
03F7 00 4400041E RWD01 BSI L SNDSW   SENSE DR          SRC                8BD07900
03F9 0  1801        SRA   1                                               8BD07910
03FA 0  4804        BSC   E          IS DR READY                          8BD07920
03FB 0  7014        MDX   RWD04      NO                                   8BD07930
03FC 0  1802        SRA   2                                               8BD07940
03FD 0  4804        BSC   E          IS DR AT LD PT                       8BD07950
03FE 0  700F        MDX   RWD03      YES                                  8BD07960
03FF 00 C50001B8    LD  L1 TAPEO     GET AREA CODE                        8BD07970
0401 0  F01A        EOR   RWDIO      SET FNC                              8BD07980
0402 0  D01A        STO   RWDIO+1    SAVE                                 8BD07990
                    *                                                     8BD08000
0403 0  0818        XIO   RWDIO      ISSUE REWIND                         8BD08010
                    *                                                     8BD08020
0404 0  300A   WAITA DC   /300A      WAIT FOR INTRPT                      8BD08030
                    *                                                     8BD08040
0405 00 4400041E RWD02 BSI L SNDSW   SENSE DR           SRC               8BD08050
0407 0  1801        SRA   1                                               8BD08060
0408 0  4804        BSC   E          IS REWIND COMPLETE                   8BD08070
0409 0  70FB        MDX   RWD02      NO                                   8BD08080
040A 0  1802        SRA   2                                               8BD08090
040B 0  4804        BSC   E          IS DR AT LD PT                       8BD08100
040C 0  7001        MDX   RWD03      YES                                  8BD08110
040D 0  70F7        MDX   RWD02      NO                                   8BD08120
                    *                                                     8BD08130
                                                                          8BD08140
```

```
040E 00 4C8003F6    RWD03 BSC  I  RWD          EXIT             SX   88D08150
                    *                                                88D08160
                    *                    DRIVE IS NOT READY           88D08170
                    *                                                88D08180
0410 00 C400023A    RWD04 LD   L  DSW          GET SENSE WD          88D08190
0412 00 D4000438          STO  L  SNSV         SAVE                  88D08200
0414 00 4400043A          BSI  L  PRINT        PRINT-NOT READY  SRC  88D08210
0416 0  E008             DC       /E008        ERROR 8               88D08220
0417 0  0003             DC       /0003        FORM 3                88D08230
0418 0  7001             MDX      RWD05        CONTINUE              88D08240
0419 0  70DD             MDX      RWD01        LOOP ON ERROR         88D08250
041A 00 4C0002F8    RWD05 BSC  L  WRT05        TERMINATE             88D08260
                    *                                                88D08270
                    *                    CONSTANTS                   88D08280
                    *                                                88D08290
041C    0000              BSS  E  0                                  88D08300
041C 0  0404        RWDIO DC       /0404        REWIND IOCC          88D08310
041D 0  0000              DC       0                                 88D08320
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D08330
                    *                                                88D08340
                    *               ROUTINE TO SENSE DRIVE           88D08350
                    *                                                88D08360
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D08370
041E 0  0000        SNDSW DC       0                           SE   88D08380
0420 0  6B13              STX   3  SNDS3+1      SAVE IX 3            88D08390
0420 00 C40001C6    SNDS1 LD   L  EDIT         GET AREA CODE        88D08400
0422 00 F50001CD          EOR  L1 MOD          SET MODIFIER         88D08410
0424 0  F011              EOR      SNS          SET SENSE FNC        88D08420
0425 0  D011              STO      SN3+1        SAVE                 88D08430
0426 00 67000002          LDX   L3 2                                88D08440
0428 0  080D        SNDS2 XIO      SNS          ISSUE SENSE          88D08450
0429 00 D7000437          STO  L3 SNSV-1       SAVE                 88D08460
042B 0  73FF              MDX   3  -1           DECR IX              88D08470
042C 0  70FB              MDX      SNDS2        LOOP                 88D08480
042D 0  C00A              LD       SNSV         GET SECOND           88D08490
042E 0  F00A              EOR      SNSV+1       COMPARE WITH FIRST   88D08500
042F 0  4820              BSC      Z            IS DR FULLY SEL      88D08510
0430 0  70EF              MDX      SNDS1        NO                   88D08520
0431 0  C006              LD       SNSV         GET SENSE WD         88D08530
0432 00 67000000    SNDS3 LDX   L3 0            RESTORE IX 3         88D08540
0434 00 4C80041E          BSC   I  SNDSW        EXIT             SX  88D08550
                    *                                                88D08560
                    *                    CONSTANTS                   88D08570
                    *                                                88D08580
0436    0000              BSS  E  0                                  88D08590
0436 0  0700        SNS   DC       /0700        SENSE IOCC           88D08600
0437 0  0000              DC       0                                 88D08610
0438 0  0000        SNSV  DC       0            TEMP STORAGE         88D08620
0439 0  0000              DC       0                                 88D08630
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D08640
                    *                                                88D08650
                    *               COMMON PRINT ROUTINE             88D08660
                    *                                                88D08670
                    *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D08680
043A 0  0000        PRINT DC       0                           SE   88D08690
043D 00 6E0004E1          STX   L2 FRMC8+1     SAVE IX 2            88D08700
043D 00 6D0004DF          STX   L1 FRMC7+1     SAVE IX 1            88D08710
043F 00 0C0001C2          XIO   L  RDBSW        READ DATA SWS       88D08720
0441 00 C40001CB          LD    L  SWO          GET DATA SWS        88D08730
0443 0  1802              SRA      2                                 88D08740
0444 00 4C0404CE          BSC   L  FRMC4,E      BRANCH = BYPASS PR  88D08750
0446 0  1010              SLA      16           CLEAR MSG WDS       88D08760
0447 00 D40004F5          STO   L  MSG2                            88D08770
0449 00 D40004F6          STO   L  MSG3                            88D08780
044B 00 D40004F4          STO   L  MSG1                            88D08790
044D 00 D40004F8          STO   L  MSG                             88D08800
044F 00 D40004F7          STO   L  MSG4                            88D08810
0451 00 668004F1          LDX   I2 RID          IX 2 = RTN NO       88D08820
```

```
0453 00 C60001D3          LD    L2 CMRTT       GET RTN ADRS         88D08830
0455 00 D40004F2          STO   L  RAD          SAVE               88D08840
0457 00 6680043A          LDX   I2 PRINT        IX 2 = ADRS OF CALL 88D08850
0459 0  C200              LD    2  0            GET MSG ID          88D08860
045A 00 D40004F0          STO   L  MID          SAVE               88D08870
045C 0  C201              LD    2  1            GET FORM NO         88D08880
045D 0  D003              STO      PR1+1                            88D08890
045E 00 6D0004F3          STX   L1 UNIT         SAVE DR NO         88D08900
0460 00 66000000    PR1   LDX   L2 0            IX 2 = FORM NO     88D08910
0462 00 C6000487          LD    L2 FRWC         GET 1443 WD CT     88D08920
0464 00 D4000616          STO   L  PRWDC        SET                88D08930
0466 00 94000684          S     L  ONE          SUB 1              88D08940
0468 00 D40004AE          STO   L  STWC+1       SAVE               88D08950
046A 00 C600048C          LD    L2 FRST         GET MSG WD CT      88D08960
046C 00 D40004B0          STO   L  STWC+3       SAVE               88D08970
046E 0  C010              LD       LOGX0                           88D08980
046F 0  D042              STO      FRMC2+1      RESTORE RTN        88D08990
0470 0  C0F0              LD       PR1+1        GET FORM NO        88D09000
0471 0  4810              BSC      -            IS IT NOT LINE 0   88D09010
0472 0  700A              MDX      PR05         NO                 88D09020
0473 0  1001              SLA      1            CLEAR BIT 0        88D09030
0474 0  1801              SRA      1                               88D09040
0475 0  D001              STO      PR04+1       SAVE               88D09050
0476 00 66000000    PR04  LDX   L2 0            IX 2 = FORM NO     88D09060
0478 0  C008              LD       LOGX2        SET FOR NOT LINE 0 88D09070
0479 00 D40004B0          STO   L  STWC+3                          88D09080
047B 0  C004              LD       LOGX1                           88D09090
047C 0  D035              STO      FRMC2+1                          88D09100
047D 00 4E800482    PR05  BSC   I2 FORM         GO TO FORM         88D09110
047F 0  04EE        LOGX0 DC       PID-1        LINE 0 CONSTANT    88D09120
0480 0  04F2        LOGX1 DC       UNIT-1       NOT LINE 0 CONSTANT 88D09130
0481 0  0005        LOGX2 DC       5            NOT LINE 0 WD CT   88D09140
                    *                                                88D09150
                    *                    FORM ADDRESSES              88D09160
                    *                                                88D09170
0482 0  0000        FORM  DC       0                               88D09180
0483 0  0491              DC       FORM1                           88D09190
0484 0  049E              DC       FORM2                           88D09200
0485 0  049F              DC       FORM3                           88D09210
0486 0  04A3              DC       FORM4                           88D09220
0487 0  0000        FRWC  DC       0                               88D09230
0488 0  001A              DC       26           WD CT FORM 1       88D09240
0489 0  000E              DC       14                    2         88D09250
048A 0  0011              DC       17                    3         88D09260
048B 0  0011              DC       17                    4         88D09270
048C 0  0000        FRST  DC       0                               88D09280
048D 0  0009              DC       9            MSG LNGTH FORM 1   88D09290
048E 0  0005              DC       5                       2       88D09300
048F 0  0006              DC       6                       3       88D09310
0490 0  0006              DC       6                       4       88D09320
                    *                                                88D09330
                    *                                                88D09340
0491 00 C40006E2    FORM1 LD    L  PRPAT        GET EXPECTED DATA  88D09350
0493 0  D060              STO      MSG1         SAVE               88D09360
0494 00 C7000941          LD    L3 IOAA+8      GET DATA RECEIVED   88D09370
0496 0  D05E              STO      MSG2         SAVE               88D09380
0497 00 C4000685          LD    L  WDCT        GET WD NO IN ERROR  88D09390
0499 0  D05C              STO      MSG3         SAVE               88D09400
049A 00 C4000686          LD    L  WDCT        GET TRK IN ERROR   88D09410
049C 00 D40004F7          STO   L  MSG4        SET                88D09420
049E 0  7007        FORM2 MDX      FORMC       GO TO COMMON RTN    88D09430
                    *                                                88D09440
049F 00 C4000438    FORM3 LD    L  SNSV        GET SENSE WORD     88D09450
04A1 0  D052              STO      MSG1        SAVE               88D09460
04A2 0  7003              MDX      FORMC       GO TO COMMON RTN   88D09470
                    *                                                88D09480
                    *                                                88D09490
                                                                     88D09500
```

```
04A3 00 C4000328  FORM4 LD   L  WRERR     GET NO OF RETRYS         8BD09510
04A5 0  D04E             STO    MSG1      SAVE                     8BD09520
                  *                                                8BD09530
                  *            COMMON ROUTINE                      8BD09540
                  *                                                8BD09550
04A6 00 6600001A  FORMC LDX  L2 26        IX 2 = LNGTH MSG         8BD09560
04A8 0  1010            SLA    16                                  8BD09570
04A9 00 D60004F8  FRMC1 STO  L2 MSGO-1    CLEAR MSG AREA           8BD09580
04AB 0  72FF            MDX    2 -1                                8BD09590
04AC 0  70FC            MDX    FRMC1                                8BD09600
                  *                                                8BD09610
04AD 00 65000000  STWC  LDX  L1 0         SET IXING                8BD09620
04AF 00 66000000        LDX  L2 0                                  8BD09630
04B1 00 C60004EE  FRMC2 LD   L2 PID-1     GET A WORD               8BD09640
04B3 00 D40005D6        STO  L  HEXWD     SET IN CONV RTN          8BD09650
04B5 00 440005B4        BSI  L  HEXCV     CONVERT TO HEX      SRC  8BD09660
04B7 00 CC0005DC        LDD  L  HEXCD     GET CONVERTED WD         8BD09670
04B9 00 D50004F8        STO  L1 MSGO-1    SET IN MSG               8BD09680
04BB 0  18D0            RTE    16         MOVE Q TO A              8BD09690
04BC 00 D50004F9        STO  L1 MSGO      SET IN MSG               8BD09700
04BE 0  71FD            MDX    1 -3       DECR IX 1                8BD09710
04BF 0  1000            NOP                                        8BD09720
04C0 0  72FF            MDX    2 -1       DECR IX 2                8BD09730
04C1 0  70EF            MDX    FRMC2      LOOP                     8BD09740
                  *                                                8BD09750
04C2 00 0C0001C2        XIO  L  RDBSW     READ DATA SWS            8BD09760
04C4 00 C40001CB        LD   L  SWO       GET SWS                  8BD09770
04C6 0  1009            SLA    9                                   8BD09780
04C7 0  4828            BSC    +Z         IS 1443 TO BE USED       8BD09790
04C8 0  7003            MDX    FRMC3      YES                      8BD09800
04C9 00 44000514        BSI  L  LOGC      GO TO TYPEWRITER    SRC  8BD09810
04CB 0  7002            MDX    FRMC4                               8BD09820
04CC 00 440005EE  FRMC3 BSI  L  PR43      GO TO 1443          SRC  8BD09830
04CE 00 0C0001C2  FRMC4 XIO  L  RDBSW     READ DATA SWS            8BD09840
04D0 00 C40001CB        LD   L  SWO       GET SWS                  8BD09850
04D2 0  1801            SRA    1                                   8BD09860
04D3 0  4804            BSC    E          IS HALT ON ERROR ON      8BD09870
04D4 0  700F            MDX    FRMC6      YES                      8BD09880
                  *                                                8BD09890
04D5 00 0C0001C2  FRMC5 XIO  L  RDBSW     READ DATA SWS            8BD09900
04D7 00 C40001CB        LD   L  SWO       GET SWS                  8BD09910
04D9 0  1803            SRA    3                                   8BD09920
04DA 0  4804            BSC    E          IS LOOP ON ERROR ON      8BD09930
04DB 0  700F            MDX    FRMC9      YES                      8BD09940
04DC 00 7402043A        MDX  L  PRINT,2   SET RETURN TO CONT       8BD09950
04DE 00 65000000  FRMC7 LDX  L1 0         RESTORE IX 1             8BD09960
04E0 00 66000000  FRMC8 LDX  L2 0         RESTORE IX 2             8BD09970
04E2 00 4C80043A        BSC  I  PRINT     EXIT                SX   8BD09980
                  *                                                8BD09990
                  *            HALT ON ERROR SW IS ON              8BD10000
                  *                                                8BD10010
04E4 0  C00B      FRMC6 LD     MID        GET MSG ID               8BD10020
04E5 0  180C            SRA    12                                  8BD10030
04E6 0  F007            EOR    ERRR                                8BD10040
04E7 0  4820            BSC    Z          IS THIS AN ERROR         8BD10050
04E8 0  70EC            MDX    FRMC5      NO                       8BD10060
04E9 0  300B      WAITB DC     /300B      ERROR WAIT               8BD10070
04EA 0  70EA            MDX    FRMC5                               8BD10080
                  *                                                8BD10090
                  *                                                8BD10100
                  *            LOOP ON ERROR SW IS ON              8BD10110
                  *                                                8BD10120
04EB 00 7403043A  FRMC9 MDX  L  PRINT,3   SET RETURN TO LOOP       8BD10130
04ED 0  70F0            MDX    FRMC7                               8BD10140
                  *                                                8BD10150
                  *            CONSTANTS                           8BD10160
                  *                                                8BD10170
04EE 0  000E      ERRR  DC     /000E      ERROR CK                 8BD10170
04EF 0  BD00      PID   DC     /BD00      PROGRAM ID               8BD10180
```

```
04F0 0  0000      MID   DC     0          MESSAGE ID               8BD10190
04F1 0  0000      RID   DC     0          ROUTINE NUMBER           8BD10200
04F2 0  0000      RAD   DC     0          ROUTINE ADDRESS          8BD10210
04F3 0  0000      UNIT  DC     0          UNIT NUMBER              8BD10220
04F4 0  0000      MSG1  DC     0          MODIFIER1                8BD10230
04F5 0  0000      MSG2  DC     0                  2                8BD10240
04F6 0  0000      MSG3  DC     0                  3                8BD10250
04F7 0  0000      MSG4  DC     0                  4                8BD10260
                  *                                                8BD10270
                  *                                                8BD10280
                  *            OUTPUT MSG AREA                     8BD10290
                  *                                                8BD10300
04F8 0  0000      MSG   DC     0          WD CT OR CAR RET         8BD10310
04F9 0  0000      MSGO  DC     0          OUTPUT MSG AREA          8BD10320
04FA    0019            BSS    25                                  8BD10330
0513 0  FFFF      TERM  DC     /FFFF      TERMINATOR               8BD10340
*XXXXXXXXXXXXXXXXXXXX XXXXXXXXXXXXXXXXXXXXXXXXXXXXX                 8BD10350
                  *                                                8BD10360
                  *            ROUTINE TO CONVERT PRINTER          8BD10370
                  *            PACKED CODE TO PACKED TYPE          8BD10380
                  *                                                8BD10390
*XXXXXXXXXXXXXXXXXXXX XXXXXXXXXXXXXXXXXXXXXXXXXXXXX                 8BD10400
0514 0  0000      LOGC  DC     0                            SE     8BD10410
0515 0  1010            SLA    16                                  8BD10420
0516 0  D039            STO    LOX00      CLEAR HALF WD SW         8BD10430
0517 0  C06B            LD     PRSP       SET CARRIAGE RETURN      8BD10440
0518 00 D40004F8        STO  L  MSG                               8BD10450
051A 0  692E            STX  1  LOGC7+1   SAVE IX 1                8BD10460
051B 0  6A2F            STX  2  LOGC8+1   SAVE IX 2                8BD10470
051C 0  6B30            STX  3  LOGC9+1   SAVE IX 3                8BD10480
051D 00 670004F9        LDX  L3 MSGO      IX 3 = ADRS OF MSG       8BD10490
051F 0  C300      LOGC1 LD     3 0        GET WD TO CONVERT        8BD10500
0520 0  D030            STO    LOX02      SAVE                     8BD10510
0521 00 F4000513        EOR  L  TERM                              8BD10520
0523 0  4818            BSC    +-         IS IT A TERM             8BD10530
0524 0  7021            MDX    LOGC0      YES                      8BD10540
0525 0  C02B      LOGC2 LD     LOX02      GET WD                   8BD10550
0526 0  180C            SRA    12         SAVE ZONE                8BD10560
0527 0  D001            STO    LOGC3+1                             8BD10570
0528 00 65000000  LOGC3 LDX  L1 0         IX 1 = ZONE              8BD10580
052A 00 C5000553        LD   L1 LOX04     GET ADRS OF ZONE         8BD10590
052C 0  D007            STO    LOGC5+1    SAVE                     8BD10600
052D 0  C023            LD     LOX02      GET WD TO CONVERT        8BD10610
052E 0  1004            SLA    4          SAVE POSITION            8BD10620
052F 0  180C            SRA    12                                 8BD10630
0530 0  D001            STO    LOGC4+1                             8BD10640
0531 00 66000000  LOGC4 LDX  L2 0         IX 2 = POSITION          8BD10650
0533 00 C6000000  LOGC5 LD   L2 0         GET TYPEWRITER CODE      8BD10660
0535 00 74000550        MDX  L  LOX00,0   IS THIS FIRST HALF       8BD10670
0537 0  7007            MDX    LOGC6      NO                       8BD10680
0538 0  D019            STO    LOX03      YES                      8BD10690
0539 00 74010550        MDX  L  LOX00,1   SET TO SECOND HALF       8BD10700
053B 0  C015            LD     LOX02      GET WD TO CONVERT        8BD10710
053C 0  1008            SLA    8          SET TO SECOND HALF       8BD10720
053D 0  D013            STO    LOX02      SAVE                     8BD10730
053E 0  70E6            MDX    LOGC2      GO CONVERT               8BD10740
                  *                                                8BD10750
                  *            SECOND HALF WORD                    8BD10760
                  *                                                8BD10770
053F 0  1808      LOGC6 SPA    8          MOVE TO SECOND HALF      8BD10780
0540 0  F011            EOR    LOX03      COMBINE WITH FIRST       8BD10790
0541 0  D300      LOGC8 STO    3 0        SET IN MSG               8BD10800
0542 0  1010            SLA    16                                  8BD10810
0543 0  D00C            STO    LOX00      SET TO FIRST HALF        8BD10820
0544 0  7301            MDX    3 1        IX 3 = NEXT WD           8BD10830
0545 0  70D9            MDX    LOGC1      CONVERT NEXT WD          8BD10840
                  *                                                8BD10850
                  *            FOUND A TERMINATOR                  8BD10860
```

```
0546 00 4C000584    LOGC0 BSC  L  LOG00      GO PRINT              88D10870
0548 00 65000000    LOGC7 LDX  L1 0          RESTORE IX 1          88D10880
054A 00 66000000    LOGC8 LDX  L2 0          RESTORE IX 2          88D10890
054C 00 67000000    LOGC9 LDX  L3 0          RESTORE IX 3          88D10900
054E 00 4C800514          BSC  I  LOGC       EXIT             SX   88D10910
                      *                                            88D10920
                      *                                            88D10930
                      *                CONSTANTS                   88D10940
                      *                                            88D10950
0550 0  0000        LOX00 DC   0            HALF WORD SW           88D10960
0551 0  0000        LOX02 DC   0            TEMP STORAGE FOR       88D10970
                      *                     WORD TO CONVERT        88D10980
0552 0  0000        LOX03 DC   0            TEMP STORAGE FOR       88D10990
                      *                     TYPEWRITER CODE        88D11000
0553 0  0559        LOX04 DC   PRO0         ADRS OF ZONE 0         88D11010
0554 0  0562              DC   PRO1-2       ADRS OF ZONE 1         88D11020
0555 0  056D              DC   PRO2         ADRS OF ZONE 2         88D11030
0556 0  0579              DC   PRO3-1       ADRS OF ZONE 3         88D11040
                      *                                            88D11050
                      *                                            88D11060
                      *                                            88D11070
0557 0  C028        LOGCA LD   PRSP         GET CARRIAGE RETURN    88D11080
0558 0  70E8              MDX  LOGCB                               88D11090
                      *                                            88D11100
                      *                     PRINTER CODE TO TYPEWRITER   88D11110
                      *                     CODE CONVERSION TABLE       88D11120
                      *                                            88D11130
0559 0  2100        PRO0  DC   /2100        BLANK                  88D11140
055A 0  FC00              DC   /FC00        1                      88D11150
055B 0  D800              DC   /D800        2                      88D11160
055C 0  DC00              DC   /DC00        3                      88D11170
055D 0  F000              DC   /F000        4                      88D11180
055E 0  F400              DC   /F400        5                      88D11190
055F 0  D000              DC   /D000        6                      88D11200
0560 0  D400              DC   /D400        7                      88D11210
0561 0  E400              DC   /E400        8                      88D11220
0562 0  E000              DC   /E000        9                      88D11230
0563 0  C400              DC   /C400        0                      88D11240
0564 0  9A00        PRO1  DC   /9A00        S                      88D11250
0565 0  9E00              DC   /9E00        T                      88D11260
0566 0  B200              DC   /B200        U                      88D11270
0567 0  B600              DC   /B600        V                      88D11280
0568 0  9200              DC   /9200        W                      88D11290
0569 0  9600              DC   /9600        X                      88D11300
056A 0  A600              DC   /A600        Y                      88D11310
056B 0  A200              DC   /A200        Z                      88D11320
056C 0  2100              DC   /2100        BLANK                  88D11330
056D 0  BE00        PRO2  DC   /BE00        -                      88D11340
056E 0  7E00              DC   /7E00        J                      88D11350
056F 0  5A00              DC   /5A00        K                      88D11360
0570 0  5E00              DC   /5E00        L                      88D11370
0571 0  7200              DC   /7200        M                      88D11380
0572 0  7600              DC   /7600        N                      88D11390
0573 0  5200              DC   /5200        O                      88D11400
0574 0  5600              DC   /5600        P                      88D11410
0575 0  6600              DC   /6600        Q                      88D11420
0576 0  6200              DC   /6200        R                      88D11430
0577 0  4200              DC   /4200                               88D11440
0578 0  4000              DC   /4000        $                      88D11450
0579 0  D600              DC   /D600        *                      88D11460
057A 0  3E00        PRO3  DC   /3E00        A                      88D11470
057B 0  1A00              DC   /1A00        B                      88D11480
057C 0  1E00              DC   /1E00        C                      88D11490
057D 0  3200              DC   /3200        D                      88D11500
057E 0  3600              DC   /3600        E                      88D11510
057F 0  1200              DC   /1200        F                      88D11520
0580 0  1600              DC   /1600        G                      88D11530
0581 0  2600              DC   /2600        H                      88D11540
```

```
0582 0  2200              DC   /2200        I                      88D11550
0583 0  8121        PRSP  DC   /8121        CARRIAGE RETURN        88D11560
                      *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX    88D11570
                      *                                            88D11580
                      *                TYPEWRITER ROUTINE          88D11590
                      *                                            88D11600
                      *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX    88D11610
0584 0  082B        LOG00 XIO  SENSE        SENSE FOR READY        88D11620
0585 0  180A              SRA  10                                  88D11630
0586 0  4804              BSC  E            IS TYPEWRITER READY    88D11640
                      *                                            88D11650
0587 0  300C        WAITC DC   /300C        NOT READY              88D11660
0588 00 0C00060C          XIO  L  MASK0     MASK ALL LVLS          88D11670
058A 00 0C00060E          XIO  L  MASK1                            88D11680
058C 0  1010              SLA  16                                  88D11690
058D 0  D025              STO  WRDSW        CLEAR HALF WD SW       88D11700
058E 0  6300              LDX  3  0                                88D11710
                      *                                            88D11720
058F 00 C70004F8    LOG01 LD   L3 MSG       GET PRINT WD           88D11730
0591 0  0020              STO  IOARA        SET IN OUTPUT AREA     88D11740
                      *                                            88D11750
0592 00 F4000513          EOR  L  TERM      CK FOR TERMINATOR      88D11760
0594 00 4C1805A8          BSC  L  LOG02,+-  EXIT                   88D11770
                      *                OUTPUT A CHARACTER          88D11780
                      *                                            88D11790
0596 0  0817        XIOWR XIO  WRITE        WRITE CHARACTER        88D11800
                      *                                            88D11810
0597 0  0818        XIOSN XIO  SENSE        CHECK BUSY             88D11820
                      *                                            88D11830
0598 0  180B              SRA  11                                  88D11840
0599 0  4804              BSC  E            IS TYPEWRITER BUSY     88D11850
059A 0  70FC              MDX  XIOSN        BUSY                   88D11860
                      *                                            88D11870
                      *                                            88D11880
                      *                CHECK FOR 1ST 1/2 WORD      88D11890
                      *                                            88D11900
059B 0  C017              LD   WRDSW        GET 1/2 WORD SWITCH    88D11910
059C 0  4804              BSC  E                                   88D11920
059D 0  7006              MDX  LOG03        GO SETUP FOR NEXT WD   88D11930
                      *                                            88D11940
                      *                SET UP FOR 2ND 1/2 WORD     88D11950
                      *                                            88D11960
059E 0  C013              LD   IOARA        GET WORD IN IO AREA    88D11970
059F 0  1008              SLA  8            POSITION 2ND 1/2 WD    88D11980
05A0 0  D011              STO  IOARA                               88D11990
05A1 00 740105B3          MDX  L  WRDSW,1   BUMP WORD SWITCH       88D12000
05A3 0  70F2              MDX  XIOWR        GO WRITE 2ND 1/2 WD    88D12010
                      *                SET UP FOR NEXT WORD        88D12020
                      *                                            88D12030
05A4 0  7301        LOG03 MDX  3 1          NEXT WORD INDEX        88D12040
05A5 00 740105B3          MDX  L  WRDSW,1   BUMP WORD SW           88D12050
05A7 0  70E7              MDX  LOG01        GO GET NEXT WORD       88D12060
                      *                                            88D12070
05A8 00 0C000610    LOG02 XIO  L  UNMK3     UNMASK ALL LVLS        88D12080
05AA 00 0C000612          XIO  L  UNMK4                            88D12090
05AC 00 4C000548          BSC  L  LOGC7     EXIT             SX    88D12100
                      *                                            88D12110
                      *                CONSTANTS                   88D12120
                      *                                            88D12130
05AE    0000              BSS  E  0                                88D12140
05AE 0  0582        WRITE DC   IOARA        WRITE IOCC             88D12150
05AF 0  0902              DC   /0902                               88D12160
05B0 0  0000        SENSE DC   /0000        SENSE IOCC             88D12170
05B1 0  0F03              DC   /0F03                               88D12180
                                                                   88D12190
                                                                   88D12200
                                                                   88D12210
                                                                   88D12220
```

```
05B2 0  0000     IOARA DC      0           OUTPUT AREA
05B3 0  0000     WRDSW DC      0           HALF WORD SW           88D12230
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D12240
                 *                                               88D12250
                 *                                               88D12260
                 *              HEXADECIMAL CONVERSION            88D12270
                 *                                               88D12280
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D12290
05B4 0  0000     HEXCV DC      0                            SE    88D12300
05B5 00 6E0005D1       STX  L2 HEXC2+1     SAVE IX 2              88D12310
05B7 00 6F0005D3       STX  L3 HEXC3+1     SAVE IX 3              88D12320
05B9 0  6204           LDX  2  4           CONVERSION INDEX       88D12330
05BA 0  C01B           LD      HEXWD       GET WORD TO CONVERT    88D12340
05BB 0  1890           SRT     16          SET IN Q               88D12350
05BC 0  1010           SLA     16          CLEAR A                88D12360
05BD 0  1084     HEXC1 SLT     4           GET CHARACTER          88D12370
05BE 0  D001           STO     HEXC1+3                            88D12380
05BF 00 67000000       LDX  L3 0           SET CODE TABLE INDEX   88D12390
                 *                                               88D12400
05C1 00 C70005DE       LD   L3 CODEH       GET CHARACTER          88D12400
05C3 00 D60005D6       STO  L2 HEX00-1     SAVE                   88D12410
05C5 0  1010           SLA     16                                 88D12420
                 *                                               88D12430
05C6 0  72FF           MDX  2  -1          CHECK IF DONE          88D12440
05C7 0  70F5           MDX     HEXC1                              88D12450
                 *                                               88D12460
05C8 0  C011           LD      HEX00+3     PACK CODED WORDS       88D12470
05C9 0  1008           SLA     8                                  88D12480
05CA 0  E80E           OR      HEX00+2                            88D12490
05CB 0  D010           STO     HEXCD                              88D12500
05CC 0  C00B           LD      HEX00+1                            88D12510
05CD 0  1008           SLA     8                                  88D12520
05CE 0  E808           OR      HEX00                              88D12530
05CF 0  D00D           STO     HEXCD+1                            88D12540
05D0 00 66000000 HEXC2 LDX  L2 0           RESTORE IX 2           88D12550
05D2 00 67000000 HEXC3 LDX  L3 0           RESTORE IX 3           88D12560
05D4 00 4C8005B4       BSC  I  HEXCV       RETURN TO USER    SX   88D12570
                 *                                               88D12580
                 *              CONSTANTS                         88D12590
                 *                                               88D12600
05D6 0  0000     HEXWD DC      0           WORD TO CONVERT        88D12610
05D7 0  0000     HEX00 DC      0           *                      88D12620
05D8 0  0000           DC      0           * UNPACKED CODED       88D12630
05D9 0  0000           DC      0           * WORD                 88D12640
05DA 0  0000           DC      0           *                      88D12650
                 *                                               88D12660
05DC    0000           BSS  E  0                                  88D12680
                 *                                               88D12690
05DC 0  0000     HEXCD DC      0           * PACKED CODED WORD     88D12700
05DD 0  0000           DC      0           *                      88D12710
                 *                                               88D12720
                 *                                               88D12730
                 *              CONVERSION TABLE                  88D12740
                 *                                               88D12750
05DE 0  000A     CODEH DC      /000A       0                      88D12760
05DF 0  0001           DC      /0001       1                      88D12770
05E0 0  0002           DC      /0002       2                      88D12780
05E1 0  0003           DC      /0003       3                      88D12790
05E2 0  0004           DC      /0004       4                      88D12800
05E3 0  0005           DC      /0005       5                      88D12810
05E4 0  0006           DC      /0006       6                      88D12820
05E5 0  0007           DC      /0007       7                      88D12830
05E6 0  0008           DC      /0008       8                      88D12840
05E7 0  0009           DC      /0009       9                      88D12850
05E8 0  0031           DC      /0031       A                      88D12860
05E9 0  0032           DC      /0032       B                      88D12870
05EA 0  0033           DC      /0033       C                      88D12880
05EB 0  0034           DC      /0034       D                      88D12890
05EC 0  0035           DC      /0035       E                      88D12900
05ED 0  0036           DC      /0036       F
```

```
                 *                                               88D12910
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D12920
                 *                                               88D12930
                 *              PRINT ON 1443 PRINTER             88D12940
                 *                                               88D12950
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D12960
05EE 0  0000     PR43  DC      0                            SE    88D12970
05EF 0  C01A           LD      SNSPR       GET SENSE IOCC         88D12980
05F0 0  D01A           STO     SNSPR+1     SET                    88D12990
05F1 0  C024           LD      PRWDC                              88D13000
05F2 00 D40004F8       STO  L  MSG         SET WD CT              88D13010
05F4 0  0817           XIO     MASK0       MASK ALL LEVELS        88D13020
05F5 0  0818           XIO     MASK1                              88D13030
                 *                                               88D13040
05F6 0  0813           XIO     SNSPR       CK FOR PRINTER READY   88D13050
05F7 0  4804           BSC  E                                     88D13060
05F8 0  300D     WAITD DC      /300D       PRINTER IS NOT READY   88D13070
05F9 0  081A           XIO     WRPR        WRITE                  88D13080
                 *                                               88D13090
05FA 0  080F     PR431 XIO     SNSPR       WAIT FOR NOT COMPLTE   88D13100
05FB 0  1002           SLA     2                                  88D13110
05FC 0  4810           BSC     -           IS PRINTER COMPLETE    88D13120
05FD 0  70FC           MDX     PR431       NO                     88D13130
                 *                                               88D13140
05FE 0  C00C           LD      SNSPR+1     GET IOCC               88D13150
05FF 00 F4000684       EOR  L  ONE         SET BIT 15             88D13160
0601 0  D009           STO     SNSPR+1     SAVE                   88D13170
                 *                                               88D13180
0602 0  0807     PR432 XIO     SNSPR       SENSE                  88D13190
0603 0  1801           SRA     1                                  88D13200
0604 0  4804           BSC  E              IS PRINTER BUSY        88D13210
0605 0  70FC           MDX     PR432       YES                    88D13220
                 *                                               88D13230
0606 0  0809           XIO     UNMK3       UNMASK ALL LEVELS      88D13230
0607 0  080A           XIO     UNMK4                              88D13240
                 *                                               88D13250
0608 00 4C8005EE       BSC  I  PR43        EXIT              SX   88D13260
                 *                                               88D13270
                 *              CONSTANTS                         88D13280
                 *                                               88D13290
060A    0000           BSS  E  0                                  88D13300
060A 0  3700     SNSPR DC      /3700       SENSE IOCC             88D13310
060B 0  0000           DC      0                                  88D13320
                 *                                               88D13330
060C 0  FFFF     MASK0 DC      /FFFF       MASK IOCCS             88D13340
060D 0  0480           DC      /0480                              88D13350
060E 0  FFFF     MASK1 DC      /FFFF                              88D13360
060F 0  0481           DC      /0481                              88D13370
                 *                                               88D13380
0610 0  0000     UNMK3 DC      0           UNMASK IOCCS           88D13390
0611 0  0480           DC      /0480                              88D13400
0612 0  0000     UNMK4 DC      0                                  88D13410
0613 0  0481           DC      /0481                              88D13420
                 *                                               88D13430
0614 0  04F8     WRPR  DC      MSG         WRITE IOCC             88D13440
0615 0  3500           DC      /3500                              88D13450
0616 0  0017     PRWDC DC      23          WORD COUNT             88D13460
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D13470
                 *                                               88D13480
                 *              DESELECT DRIVE ROUTINE            88D13490
                 *                                               88D13500
                 *                                               88D13510
                 *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX       88D13520
0617 0  0000     DSLT  DC      0                            SE    88D13530
0618 0  C009           LD      DSL         GET MOD                88D13540
0619 00 F5000188       EOR  L1 TAPE0       SET IOCC               88D13550
061B 0  D007           STO     DSL+1       SAVE                   88D13560
061C 0  0805           XIO     DSL         SENSE DRIVE            88D13570
061D 0  1000           NOP                                        88D13580
```

```
061E 0  1000              NOP                                          88D13590
061F 0  0802              XIO   DSL      SENSE DEVICE                   88D13600
0620 00 4C800617          BSC   I DSLT   EXIT                     SX    88D13610
                     *                                                  88D13620
                     *                 CONSTANTS                        88D13630
                     *                                                  88D13640
0622    0000              BSS   E 0                                     88D13650
0622 0  0720         DSL  DC    /0720    SENSE IOCC                     88D13660
0623 0  0000              DC    0                                       88D13670
                     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXYX     88D13680
                     *                                                  88D13690
                     *          TESTING ROUTINES 1 THROUGH 7            88D13700
                     *                                                  88D13710
                     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX        88D13720
0624 0  6B07         CMRT STX   3 CMRT3+1  SAVE IX 3                    88D13730
0625 0  1010              SLA   16         ZERO A REG                   88D13740
0626 0  D05C              STO   OECTR      CLEAR ODD EVEN CTR           88D13750
0627 00 6600FFF8          LDX   L2 -8      IX 2 = NO WDS                88D13760
0629 00 4400028E     CMRTO BSI  L SP7F     GO SET I/O AREA      SRC     88D13770
062B 00 67000000     CMRT3 LDX  L3 0       RESTORE IX 3                 88D13780
062D 0  C055              LD    OECTR      GET ODD EVEN CTR             88D13790
062E 00 84000684          A     L ONE      ADD ONE                      88D13800
0630 0  D052              STO   OECTR      SAVE                         88D13810
0631 0  4804              BSC   E          IS CTR EVEN                  88D13820
0632 0  702F              MDX   CMRT2      NO                           88D13830
0633 00 C7000679          LD    L3 TR1-1   GET BAD TRACK CONST          88D13840
0635 00 F6000008     CMRT1 EOR  L2 IOAA+8  SET                         88D13850
0637 00 D6000941          STO   L2 IOAA+8                              88D13860
0639 0  6B07              STX   3 CMRTF+1  SAVE IX 3                    88D13870
063A 00 440002D4          BSI   L WRT      GO WRITE             SRC     88D13880
                     *                                                  88D13890
063C 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D13900
063E 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D13910
0640 00 67000000     CMRTF LDX  L3 0       RESTORE IX 3                 88D13920
0642 00 4400032C          BSI   L RD       GO READ              SRC     88D13930
0644 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D13940
                     *                                                  88D13950
                     *                CHECK DATA                        88D13960
                     *                                                  88D13970
0646 00 C4000684     CMRT6 LD   L ONE      GET 1                        88D13980
0648 0  D03C              STO   WDCT       SET AS WD CT                 88D13990
0649 00 6F000686          STX   L3 MSG4T   SET TRK                      88D14000
064B 0  6B0E              STX   3 CMRT8+1  SAVE IX 3                    88D14010
064C 0  C03A              LD    LNEO       SET LINE 0                   88D14020
064D 0  D01F              STO   CMRT9                                   88D14030
064E 0  63F8              LDX   3 -8       IX 3 = NO WDS                88D14040
064F 00 C7000941     CMRTC LD   L3 IOAA+8  GET A DATA WD                88D14050
0651 00 F40002A3          EOR   L P7F                                   88D14060
0653 0  4820              BSC   Z          IS WD CORRECT                88D14070
0654 0  7011              MDX   CMRTB      NO                           88D14080
0655 00 74010685     CMRTD MDX  L WDCT,1   INCR WD CT                   88D14090
0657 0  7301              MDX   3 1        DECR IX 3                    88D14100
0658 0  70F6              MDX   CMRTC      LOOP                         88D14110
0659 00 67000000     CMRT8 LDX  L3 0       RESTORE IX 3                 88D14120
                     *                                                  88D14130
                     *          CHECK FOR ROUTINE COMPLETE              88D14140
                     *                                                  88D14150
065B 0  C027         CMRTE LD   OECTR      GET ODD EVEN CTR             88D14160
065C 0  4804              BSC   E          IS IT EVEN                   88D14170
065D 0  70CB              MDX   CMRTO      NO                           88D14180
065E 0  7201              MDX   2 1        DECR IX 2                    88D14190
065F 0  70C9              MDX   CMRTO      CONTINUE RTN                 88D14200
0660 00 4C0001EA     CMRT5 BSC  L RETRN    RTN EXIT                     88D14210
                     *                                                  88D14220
                     *          ODD EVEN CTR IS ODD                     88D14230
                     *                                                  88D14240
0662 00 C7000679     CMRT2 LD   L3 TR1-1   GET BAD TR CONSTANT          88D14250
0664 0  1008              SLA   8          MOVE TO FIRST CHAR           88D14260
```

```
0665 0  70CF              MDX   CMRT1                                   88D14270
                     *                                                  88D14280
                     *               DATA NOT CORRECT                   88D14290
                     *                                                  88D14300
0666 00 C40002A3     CMRTB LD   L P7F      GET EXPECTED                 88D14310
0668 00 D40006E2          STO   L PRPAT    SAVE                         88D14320
066A 00 4400043A          BSI   L PRINT    GO PRINT             SRC     88D14330
066C 0  E001              DC    /E001      ERROR 1                      88D14340
066D 0  0001         CMRT9 DC   /0001      FORM 1                       88D14350
066E 0  7001              MDX   CMRT7      CONTINUE                     88D14360
066F 0  70D0              MDX   CMRTF      LOOP ON ERROR                88D14370
0670 0  C017         CMRT7 LD   LNE1       SET NOT LINE 0               88D14380
0671 0  D0FB              STO   CMRT9                                   88D14390
0672 00 0C0001C2          XIO   L RDBSW    READ DATA SWS                88D14400
0674 00 C40001CB          LD    L SWO      GET SWS                      88D14410
0676 0  1007              SLA   7                                       88D14420
0677 0  4810              BSC   -          IS PRINT ONLY 1 ON           88D14430
0678 0  70DC              MDX   CMRTD      NO                           88D14440
0679 0  70DF              MDX   CMRT8      YES                          88D14450
                     *                                                  88D14460
                     *                CONSTANTS                         88D14470
                     *                                                  88D14480
067A 0  0040         TR1  DC    /0040      CHARACTER-TRACK 1            88D14490
067B 0  0020         TR2  DC    /0020                  2               88D14500
067C 0  0010         TR3  DC    /0010                  3               88D14510
067D 0  0008         TR4  DC    /0008                  4               88D14520
067E 0  0004         TR5  DC    /0004                  5               88D14530
067F 0  0002         TR6  DC    /0002                  6               88D14540
0680 0  0001         TR7  DC    /0001                  7               88D14550
0681 0  BCOF         DSWEX DC   /BCOF      ERROR EXPECTED               88D14560
0682 0  BF9F         DSWCR DC   /BF9F      CORRECTED EXPECTED           88D14570
0683 0  0000         OECTR DC   0          ODD-EVEN CTR                 88D14580
0684 0  0001         ONE  DC    1          CONSTANT 1                   88D14590
0685 0  0000         WDCT DC    0          WORD IN ERROR COUNT          88D14600
0686 0  0000         MSG4T DC   0          TRACK IN ERROR STORE         88D14610
0687 0  0001         LNEO DC    /0001                                   88D14620
0688 0  8001         LNE1 DC    /8001                                   88D14630
                     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX     88D14640
                     *                                                  88D14650
                     *               TESTING ROUTINE 8                  88D14660
                     *                                                  88D14670
                     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX     88D14680
0689 0  6808         RTN8 STX   3 RTN8B+1  SAVE IX 3                    88D14690
068A 0  1010              SLA   16         CLEAR ODD EVEN CTR           88D14700
068B 00 D40006B3          STO   L OECTR                                88D14710
068D 00 6600FFF8          LDX   L2 -8      IX 2 = NUMBER WORDS          88D14720
068F 00 440002A5     RTN8A BSI  L SP8F     GO SET I/O AREA      SRC     88D14730
0691 00 67000000     RTN8B LDX  L3 0       RESTORE IX 3                 88D14740
0693 00 C4000683          LD    L OECTR    GET ODD/EVEN CTR             88D14750
0695 00 84000684          A     L ONE      ADD 1                        88D14760
0697 00 D4000683          STO   L OECTR    SAVE                         88D14770
0699 0  4804              BSC   E          IS CTR EVEN                  88D14780
069A 0  702E              MDX   RTN8M      NO                           88D14790
069B 0  C044              LD    TRO        GET BAD TR CONSTANT          88D147.0
069C 00 F6000941     RTN8C EOR  L2 IOAA+8  SET BAD CHARACTER            88D14800
069E 00 D6000941          STO   L2 IOAA+8                              88D14810
                     *                                                  88D14820
06A0 00 440002D4          BSI   L WRT      GO WRITE             SRC     88D14830
                     *                                                  88D14840
06A2 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D14850
06A4 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D14860
                     *                                                  88D14870
06A6 00 4400032C     RTN8D BSI  L RD       GO READ              SRC     88D14880
06A8 00 440003C4          BSI   L BSP      GO BACKSPACE         SRC     88D14890
                     *                                                  88D14900
                     *                CHECK DATA                        88D14910
                     *                                                  88D14920
06AA 00 C4000684     RTN8E LD   L ONE      GET 1                        88D14930
                     *                                                  88D14940
```

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

```
06AC 00 D4000685       STO  L  WDCT       SET AS WD CT          8BD14950
06AE 0  1010           SLA     16         CLEAR A REG           8BD14960
06AF 00 D4000686       STO  L  MSG4T      SAVE                  8BD14970
06B1 00 C4000687       LD   L  LNEO       SET LINE 0            8BD14980
06B3 0  D01E           STO     RTN8Q                            8BD14990
06B4 0  6B0B           STX  3  RTN8J+1    SAVE IX 3             8BD15000
06B5 0  63F8           LDX  3  -8         IX 3 = NUMBER WORDS   8BD15010
06B6 00 C7000941  RTN8H LD  L3  IOAA+8     GET A DATA WD         8BD15020
06B8 0  F028           EOR     P8F        IS WD CORRECT         8BD15030
06B9 0  4820           BSC     Z                                8BD15040
06BA 0  7011           MDX     RTN8N      NO                    8BD15050
06BB 00 74010685  RTN8F MDX  L  WDCT,1    INCR WD CT            8BD15060
06BD 0  7301           MDX  3  1          DECR IX 3             8BD15070
06BE 0  70F7           MDX     RTN8H      LOOP                  8BD15080
06BF 00 67000000  RTN8J LDX L3  0         RESTORE IX 3          8BD15090
     *                                                          8BD15100
     *                CHECK FOR ROUTINE COMPLETE                8BD15110
     *                                                          8BD15120
06C1 00 C4000683  RTN8K LD   L  OECTR     GET ODD EVEN CTR      8BD15130
06C3 0  4804           BSC     E          IS IT EVEN            8BD15140
06C4 0  70CA           MDX     RTN8A      NO                    8BD15150
06C5 0  7201           MDX  2  1          DECR IX 2             8BD15160
06C6 0  70C8           MDX     RTN8A      CONTINUE RTN          8BD15170
06C7 00 4C0001EA  RTN8L BSC  L  RETRN     ROUTINE COMPLETE      8BD15180
     *                                                          8BD15190
     *                ODD-EVEN CTR IS ODD                       8BD15200
     *                                                          8BD15210
06C9 0  C016      RTN8M LD      TRO        GET BAD TR CONSTANT   8BD15220
06CA 0  1008           SLA     8          MOVE TO FIRST CHAR    8BD15230
06CB 0  70D0           MDX     RTN8C                            8BD15240
     *                                                          8BD15250
     *                DATA IS NOT CORRECT                       8BD15260
     *                                                          8BD15270
06CC 00 C40006E1  RTN8N LD   L  P8F       GET PATTERN           8BD15280
06CE 0  D013           STO     PRPAT      SET FOR PRINT         8BD15290
06CF 00 440043A        BSI  L  PRINT      PRINT BAD DATA        8BD15300
06D1 0  E001           DC      /E001      ERROR 1               8BD15310
06D2 0  0001      RTN8Q DC      /0001      FORM 1                8BD15320
06D3 0  7001           MDX     RTN8P      CONTINUE              8BD15330
06D4 0  70D1           MDX     RTN8D      LOOP ON ERROR         8BD15340
06D5 00 0C0001C2  RTN8P XIO  L  RDBSW     READ DATA SWS         8BD15350
06D7 00 C4000688       LD   L  LNE1       SET NOT LINE 0        8BD15360
06D9 0  D0F8           STO     RTN8Q                            8BD15370
06DA 00 C40001CB       LD   L  SWO        GET SWS               8BD15380
06DC 0  1007           SLA     7                                8BD15390
06DD 0  4810           BSC     -          PRINT ONLY FIRST      8BD15400
06DE 0  70DC           MDX     RTN8F      NO                    8BD15410
06DF 0  70DF           MDX     RTN8J      YES                   8BD15420
     *                                                          8BD15430
     *                CONSTANTS                                 8BD15440
     *                                                          8BD15450
06E0 0  0080      TRO   DC     /0080      BAD TR CONSTANT       8BD15460
06E1 0  8F8F      P8F   DC     /8F8F      PATTERN               8BD15470
06E2 0  0000      PRPAT DC     0          PATTERN TO PRINT      8BD15480
     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX              8BD15490
     *                                                          8BD15500
     *                TESTING ROUTINE 9                         8BD15510
     *                                                          8BD15520
     *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX              8BD15530
06E3 0  6208      RTN9  LDX  2  8          IX 2 = NO TRACKS      8BD15540
06E4 0  6308      RTN90 LDX  3  8                                8BD15550
06E5 0  C068      RTN9J LD      P8F70      GET PATTERN           8BD15560
06E6 00 D7000938       STO L3  IOAA-1     SET IN I/O AREA       8BD15570
06E8 0  73FF           MDX  3  -1         DECR IX 3             8BD15580
06E9 0  70FB           MDX     RTN9J                            8BD15590
06EA 00 67000131       LDX L3  305        IX 3 = 305 CHARACTER  8BD15600
06EC 0  1010           SLA     16         CLEAR A REG           8BD15610
06ED 00 D7000940  RTN9K STO L3  IOAA+7     SET IN I/O AREA       8BD15620
```

2400 CYCLIC REDUNDANCY CHECK FUNCTION TEST

```
06EF 0  73FF           MDX  3  -1         DECR IX 3             8BD15630
06F0 0  70FC           MDX     RTN9K      LOOP                  8BD15640
06F1 0  C05D           LD      CRCSP      GET 00D5              8BD15650
06F2 00 D4000942       STO  L  IOAA+9     SET AS CRC CHARACTER  8BD15660
06F4 00 D4000944       STO  L  IOAA+11    SET AS LRC CHARACTER  8BD15670
06F6 0  6308           LDX  3  8                                8BD15680
06F7 00 C7000938  RTN9A LD  L3  IOA        GET A DATA WD         8BD15690
06F9 00 F6000745       EOR L2  TRKA-1     SET DEAD TRACK        8BD15700
06FB 00 D7000938       STO L3  IOA        STORE                 8BD15710
06FD 0  73FF           MDX  3  -1         DECR IX 3             8BD15720
06FE 0  70F8           MDX     RTN9A      LOOP                  8BD15730
06FF 00 C4000942       LD   L  IOAA+9     GET CRC CHARACTER     8BD15740
0701 00 F600073D       EOR L2  CRCA-1     SET DEAD TRACK        8BD15750
0703 00 D4000942       STO  L  IOAA+9     SET AS CRC CHARACTER  8BD15760
0705 00 D4000944       STO  L  IOAA+11    SET AS LRC CHARACTER  8BD15770
     *                                                          8BD15780
0707 00 440002D4       BSI  L  WRT        GO WRITE         SRC  8BD15790
     *                                                          8BD15800
0709 00 440003C4       BSI  L  BSP        GO BACKSPACE     SRC  8BD15810
070B 00 440003C4       BSI  L  BSP        GO BACKSPACE     SRC  8BD15820
     *                                                          8BD15830
070D 00 4400032C  RTN9B BSI  L  RD         GO READ          SRC  8BD15840
070F 00 440003C4       BSI  L  BSP        GO BACKSPACE     SRC  8BD15850
     *                                                          8BD15860
     *                CHECK DATA                                8BD15870
     *                                                          8BD15880
0711 0  63F8           LDX  3  -8         IX 3 = NUMBER WDS     8BD15890
0712 00 C4000684       LD   L  ONE        SET WD CT = 1         8BD15900
0714 00 D4000685       STO  L  WDCT                             8BD15910
0716 00 C600074F       LD   L2 TRKMS-1    GET TRK IN ERROR      8BD15920
0718 00 D4000686       STO  L  MSG4T      SAVE                  8BD15930
071A 00 C4000687       LD   L  LNEO       SET LINE 0            8BD15940
071C 0  D013           STO     RTN9Q                            8BD15950
071D 00 C7000941  RTN9C LD  L3  IOAA+8     GET A DATA WD         8BD15960
071F 0  F02E           EOR     P8F70                            8BD15970
0720 0  4820           BSC     Z          IS IT CORRECT         8BD15980
0721 0  7008           MDX     RTN9F      NO                    8BD15990
0722 00 74010685  RTN9D MDX  L  WDCT,1    INCR WD CT            8BD16000
0724 0  7301           MDX  3  1          DECR IX 3             8BD16010
0725 0  70F7           MDX     RTN9C      LOOP                  8BD16020
0726 0  72FF      RTN9E MDX  2  -1         IS RTN COMPLETE       8BD16030
0727 0  70BC           MDX     RTN90      NO                    8BD16040
0728 00 4C0001EA       BSC  L  RETRN      YES                   8BD16050
     *                                                          8BD16060
     *                DATA IS INCORRECT                         8BD16070
     *                                                          8BD16080
072A 0  C023      RTN9F LD      P8F70      GET PATTERN           8BD16090
072B 00 D40006E2       STO  L  PRPAT      SET FOR PRINT         8BD16100
072D 00 4400043A       BSI  L  PRINT      PRINT BAD DATA        8BD16110
072F 0  E001           DC      /E001      ERROR 1               8BD16120
0730 0  0001      RTN9Q DC      /0001      FORM 1                8BD16130
0731 0  7001           MDX     RTN9H      CONTINUE              8BD16140
0732 0  70DA           MDX     RTN9B      LOOP ON ERROR         8BD16150
0733 00 0C0001C2  RTN9H XIO  L  RDBSW     READ DATA SWS         8BD16160
0735 00 C4000688       LD   L  LNE1       SET NOT LINE 0        8BD16170
0737 0  D0F8           STO     RTN9Q                            8BD16180
0738 00 C40001CB       LD   L  SWO        GET SWS               8BD16190
073A 0  1007           SLA     7                                8BD16200
073B 0  4810           BSC     -          PRINT ONLY FIRST      8BD16210
073C 0  70E5           MDX     RTN9D      NO                    8BD16220
073D 0  70E8           MDX     RTN9E      YES                   8BD16230
     *                                                          8BD16240
     *                CONSTANTS                                 8BD16250
     *                                                          8BD16260
073E 0  0001      CRCA  DC     /0001      CRC CNST-TRK 7        8BD16270
073F 0  0000            DC     /0000                 6          8BD16280
0740 0  0004            DC     /0004                 5          8BD16290
0741 0  0000            DC     /0000                 4          8BD16300
```

```
0742 0  0000         DC    /0000                3          88D16310
0743 0  0020         DC    /0020                2          88D16320
0744 0  0000         DC    /0000                1          88D16330
0745 0  0000         DC    /0000                0          88D16340
0746 0  0100   TRKA  DC    /0100   DEAD TR CNST-TR 7        88D16350
0747 0  0200         DC    /0200                6          88D16360
0748 0  0400         DC    /0400                5          88D16370
0749 0  0800         DC    /0800                4          88D16380
074A 0  0010         DC    /0010                3          88D16390
074B 0  0020         DC    /0020                2          88D16400
074C 0  0040         DC    /0040                1          88D16410
074D 0  8000         DC    /8000                0          88D16420
074E 0  8F70   P8F70 DC    /8F70   DATA PATTERN             88D16430
074F 0  0025   CRCSP DC    /0025   CRC/LRC CHARACTER        88D16440
0750 0  0007   TRKMS DC    7       TRACK IN ERROR-TRK 7     88D16450
0751 0  0006         DC    6                6               88D16460
0752 0  0005         DC    5                5               88D16470
0753 0  0004         DC    4                4               88D16480
0754 0  0003         DC    3                3               88D16490
0755 0  0002         DC    2                2               88D16500
0756 0  0001         DC    1                1               88D16510
0757 0  0000         DC    0                0               88D16520
               *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D16520
               *                                           88D16530
               *                                           88D16540
               *            TESTING ROUTINE 10             88D16550
               *                                           88D16560
               *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D16570
0758 0  6208   RTN10 LDX    2 8     IX 2 = NO TRACKS        88D16580
0759 0  6308   RT10L LDX    3 8                             88D16590
075A 0  C0F3   RT10J LD     P8F70   GET PATTERN             88D16600
075B 00 D70C0938       STO L3 IOAA-1 SET IN I/O AREA        88D16610
075D 0  73FF          MDX    3 -1    DECR IX 3              88D16620
075E 0  70FB          MDX    RT10J   LOOP                   88D16630
075F 00 67000131      LDX  L3 305    IX 3 = 610 CHARACTER S 88D16640
0761 0  1010          SLA    16      CLEAR A REG            88D16640
0762 00 D7000940 RT10K STO L3 IOAA+7 SET IN I/O             88D16650
0764 0  73FF          MDX    3 -1    DECR IX 3              88D16660
0765 0  70FC          MDX    RT10K   LOOP                   88D16670
0766 0  C0E8          LD     CRCSP   GET CRC/LRC            88D16680
0767 00 D4000942      STO  L IOAA+9  SET AS CRC             88D16690
0769 00 D4000944      STO  L IOAA+11 SET AS LRC             88D16700
076B 0  6308          LDX    3 8                            88D16710
076C 00 C7000938 RT10B LD  L3 IOA    GET A DATA WD          88D16720
076E 00 F60007AA      EOR  L2 TRKD-1 SET DEAD TRACK         88D16730
0770 00 D7000938      STO  L3 IOA    SET AS DATA            88D16740
0772 0  73FF          MDX    3 -1    DECR IX 3              88D16750
0773 0  70F8          MDX    RT10B   LOOP                   88D16760
               *                                           88D16770
0774 00 440002D4      BSI  L WRT     GO WRITE          SRC  88D16780
               *                                           88D16790
0776 00 440003C4      BSI  L BSP     GO BACKSPACE      SRC  88D16800
0778 00 440003C4      BSI  L BSP     GO BACKSPACE      SRC  88D16810
               *                                           88D16820
077A 00 440003C4 RT10G BSI L RD      GO READ           SRC  88D16830
077C 00 440003C4      BSI  L BSP     GO BACKSPACE      SRC  88D16840
               *                                           88D16850
               *                 CHECK DATA                88D16860
               *                                           88D16870
               *                                           88D16880
077E 0  63F8          LDX    3 -8    IX 3 = NUMBER WDS      88D16890
077F 00 C4000684      LD   L ONE     GET 1                 88D16900
0781 00 D4000685      STO  L WDCT    SET AS WD CT           88D16910
0783 00 C600074F      LD   L2 TRKMS-1 GET TRK IN ERROR      88D16920
0785 00 D4000686      STO  L MSG4T   SAVE                  88D16930
0787 00 C4000687      LD   L LNE0    SET LINE 0            88D16940
0789 0  D013          STO    RT1UQ                          88D16950
078A 00 C7000941 RT10C LD  L3 IOAA+8 GET A DATA WD          88D16960
078C 0  F0C1          EOR    P8F70                           88D16970
078D 0  4820          BSC    Z       IS IT CORRECT          88D16980
```

```
078E 0  7008          MDX    RT10F   NO                     88D16990
078F 00 74010685 RT10D MDX L WDCT,1 INCR WD CT              88D17000
0791 0  7301          MDX    3 1     DECR IX 3              88D17010
0792 0  70F7          MDX    RT10C   LOOP                   88D17020
0793 0  72FF   RT10E  MDX    2 -1    IS ROUTINE COMPLETE    88D17030
0794 0  70C4          MDX    RT10L   NO                     88D17040
0795 00 4C0001EA      BSC  L RETRN   EXIT                   88D17050
               *                                           88D17060
               *                                           88D17070
               *            DATA IS INCORRECT              88D17080
               *                                           88D17080
0797 0  C0B6   RT10F  LD     P8F70   GET PATTERN            88D17080
0798 00 D40006E2      STO  L PRPAT   SET FOR PRINT          88D17090
079A 00 4400043A      BSI  L PRINT   PRINT BAD DATA         88D17100
079C 0  E001          DC     /E001   ERROR 1               88D17110
079D 0  0001          DC     /0001   FORM 1                88D17120
079E 0  7001   RT10Q  DC     /0001   CONTINUE              88D17130
079F 0  70DA          MDX    RT10H   LOOP ON ERROR         88D17140
07A0 00 0C0001C2 RT10H XIO L RDBSW   READ DATA SWS         88D17150
07A2 00 C4000688      LD   L LNE1    SET NOT LINE 0        88D17160
07A4 0  D0F8          STO    RT10Q                          88D17170
07A5 00 C40001CB      LD   L SW0     GET SWS               88D17180
07A7 0  1007          SLA    7                             88D17190
07A8 0  4810          BSC    -       PRINT ONLY FIRST      88D17200
07A9 0  70E5          MDX    RT10D   NO                    88D17210
07AA 0  70E8          MDX    RT10E   YES                   88D17220
               *                                           88D17230
               *                 CONSTANTS                 88D17240
               *                                           88D17250
07AB 0  0101   TRKD   DC     /0101   BAD TRK CNST-TR 7     88D17260
07AC 0  0202          DC     /0202                6        88D17270
07AD 0  0404          DC     /0404                5        88D17280
07AE 0  0808          DC     /0808                4        88D17290
07AF 0  1010          DC     /1010                3        88D17300
07B0 0  2020          DC     /2020                2        88D17310
07B1 0  4040          DC     /4040                1        88D17320
07B2 0  8080          DC     /8080                0        88D17330
07B3 0  8080   TRKB   DC     /8080   BAD TR CONSTANT       88D17340
               *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D17350
               *                                           88D17360
               *            TESTING ROUTINE 11             88D17370
               *                                           88D17380
               *XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX   88D17390
07B4 00 440002BC RTN11 BSI L SP80    SET I/O AREA          88D17400
07B6 0  6307   RT11L  LDX    3 7                      SRC  88D17410
07B7 00 C7000938 RT11A LD  L3 IOA    GET A PATT WD         88D17420
07B9 00 E40007F6      AND  L R11X0   SET LOST CHARACTER    88D17430
07BB 00 D7000938      STO  L3 IOA    SET                   88D17440
07BD 0  73FF          MDX    3 -1    DECR IX 3             88D17450
07BE 0  70F8          MDX    RT11A   LOOP                  88D1746C
               *                                           88D17470
07BF 00 440002D4      BSI  L WRT     GO WRITE          SRC  88D17480
               *                                           88D17490
07C1 00 440003C.      BSI  L BSP     GO BACKSPACE      SRC  88D17500
07C3 00 440003C4      BSI  L BSP     GO BACKSPACE      SRC  88D17510
               *                                           89D17520
07C5 00 440002C RT11B BSI L RD       GO READ           SRC  88D17530
07C7 00 440003C4      BSI  L BSP     GO BACKSPACE      SRC  88D17540
               *                                           88D17550
               *                 CHECK DATA                88D17560
               *                                           88D17570
07C9 0  63F8          LDX    3 -8    IX 3 = NUMBER WDS     88D17580
07CA 00 C4000684      LD   L ONE     GET 1                 88D17590
07CC 00 D4000685      STO  L WDCT    SET AS WD CT          88D17600
07CE 00 C4000513      LD   L TERM    GET FFFF              88D17610
07D0 00 D4000686      STO  L MSG4T   SET AS TRK IN ERROR   88D17620
07D2 00 C4000687      LD   L LNE0    SET LINE 0            88D17630
07D4 0  D013          STO    RT11Q                          88D17640
07D5 00 C7000941 RT11C LD  L3 IOAA+8 GET A DATA WD         88D17650
                                                           88D17660
```

F
L

```
07D7 00 F40002D3          EOR  L P80                            88D17670
07D9 0  4820              BSC    Z       IS WD CORRECT          88D17680
07DA 0  7006              MDX    RT11F   NO                     88D17690
07DB 00 74010685  RT11D   MDX  L WDCT,1  INCR WD CT             88D17700
07DD 0  7301              MDX    3 1     DECR IX 3              88D17710
07DE 0  70F6              MDX    RT11C                          88D17720
07DF 00 4C0001EA  RT11E   BSC  L RETRN   ROUTINE EXIT           88D17730
*                                                               88D17740
*                                 DATA IS INCORRECT             88D17750
*                                                               88D17760
07E1 00 C40002D3  RT11F   LD   L P80     GET PATTERN            88D17770
07E3 00 D40006E2          STO  L PRPAT   SET FOR PRINT          88D17780
07E5 00 4400043A          BSI  L PRINT   PRINT BAD DATA         88D17790
07E7 0  E001              DC     /E001   ERROR 1                88D17800
07E8 0  0001      RT11Q   DC     /0001   FORM 1                 88D17810
07E9 0  7001              MDX    RT11H   CONTINUE               88D17820
07EA 0  70DA              MDX    RT11B   LOOP ON ERROR          88D17830
07EB 00 0C0001C2  RT11H   XIO  L RDBSW   READ DATA SWS          88D17840
07ED 00 C4000688          LD   L LNE1    SET NOT LINE 0         88D17850
07EF 0  D0F8              STO    RT11Q                          88D17860
07F0 00 C40001CB          LD   L SW0     GET SWS                88D17870
07F2 0  1007              SLA    7                              88D17880
07F3 0  4810              BSC    -       PRINT ONLY FIRST       88D17890
07F4 0  70E6              MDX    RT11D   NO                     88D17900
07F5 0  70E9              MDX    RT11E   YES                    88D17910
07F6 0  FF00      R11X0   DC     /FF00   SET LOST CHAR          88D17920
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX             88D17930
*                                                               88D17940
*                                 TESTING ROUTINES 12           88D17950
*                                 THROUGH 18                    88D17960
*                                                               88D17970
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX             88D17980
07F7 0  73F5      CM312   MDX    3 -11   SET IX 3               88D17990
07F8 0  6B08              STX    3 CM123+1 SAVE IX 3            88D18000
07F9 0  1010              SLA    16      ZERO A REG             88D18010
07FA 00 D4000683          STO  L OECTR   CLEAR ODD EVEN CTR     88D18020
07FC 00 6600FFF8          LDX  L2 -8     IX 2 = NO WDS          88D18030
07FE 00 440002BC  CM120   BSI  L SP80    SET I/O AREA     SRC   88D18040
0800 00 67000000  CM123   LDX  L3 0      RESTORE IX 3           88D18050
0802 00 C4000683          LD   L OECTR   GET ODD EVEN CTR       88D18060
0804 00 84000684          A    L ONE     ADD 1                  88D18070
0806 00 D4000683          STO  L OECTR   SAVE                   88D18080
0808 0  4804              BSC    E       IS CTR EVEN            88D18090
0809 0  7032              MDX    CM122   NO                     88D18100
080A 00 C7000679          LD   L3 TR1-1  GET BAD TRACK CONST    88D18110
080C 00 F6000941  CM121   EOR  L2 IOAA+8 SET                    88D18120
080E 00 D6000941          STO  L2 IOAA+8 SET                    88D18130
0810 0  6B07              STX    3 CM12F+1 SAVE IX 3            88D18140
0811 00 440002D4          BSI  L WRT     GO WRITE         SRC   88D18150
*                                                               88D18160
0813 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18170
0815 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18180
0817 00 67000000  CM12F   LDX  L3 0      RESTORE IX 3           88D18190
0819 00 4400032C          BSI  L RD      GO READ          SRC   88D18200
081B 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18210
*                                                               88D18220
*                                 CHECK DATA                    88D18230
*                                                               88D18240
081D 00 C4000684  CM126   LD   L ONE     GET 1                  88D18250
081F 00 D4000685          STO  L WDCT    SET AS WD CT           88D18260
0821 00 6F000686          STX  L3 MSG4T  SET TRK IN ERROR       88D18270
0823 00 C4000687          LD   L LNE0    SET LINE 0             88D18280
0825 0  D021              STO    CM12Q                          88D18290
0826 0  6B0C              STX    3 CM128+1 SAVE IX 3            88D18300
0827 0  63F8              LDX    3 -8     IX 3 = NO WDS          88D18310
0828 00 C7000941  CM12C   LD   L3 IOAA+8 GET A DATA WD          88D18320
082A 00 F40002D3          EOR  L P80                            88D18330
082C 0  4820              BSC    Z       IS WD CORRECT          88D18340
```

```
082D 0  7012              MDX    CM12B   NO                     88D18350
082E 00 74010685  CM12D   MDX  L WDCT,1  INCR WD CT             88D18360
0830 0  7301              MDX    3 1     DECR IX 3              88D18370
0831 0  70F6              MDX    CM12C   LOOP                   88D18380
0832 00 67000000  CM128   LDX  L3 0      RESTORE IX 3           88D18390
*                                                               88D18400
*                                 CHECK FOR ROUTINE COMPLETE    88D18410
*                                                               88D18420
0834 00 C4000683  CM12E   LD   L OECTR   GET ODD EVEN CTR       88D18430
0836 0  4804              BSC    E       IS IT EVEN             88D18440
0837 0  70C6              MDX    CM120   NO                     88D18450
0838 0  7201              MDX    2 1     DECR IX 2              88D18460
0839 0  70C4              MDX    CM120                          88D18470
083A 00 4C0001EA  CM125   BSC  L RETRN   RTN EXIT               88D18480
*                                                               88D18490
*                                 ODD EVEN CTR IS ODD           88D18500
*                                                               88D18510
083C 00 C7000679  CM122   LD   L3 TR1-1  GET BAD TR CONSTANT    88D18520
083E 0  1008              SLA    8       MOVE TO FIRST CHAR     88D18530
083F 0  70CC              MDX    CM121                          88D18540
*                                                               88D18550
*                                 DATA IS NOT CORRECT           88D18560
*                                                               88D18570
0840 00 C40002D3  CM12B   LD   L P80     GET EXPECTED           88D18580
0842 00 D40006E2          STO  L PRPAT   SAVE                   88D18590
0844 00 4400043A          BSI  L PRINT   GO PRINT         SRC   88D18600
0846 0  E001              DC     /E001   ERROR 1                88D18610
0847 0  0001      CM12Q   DC     /0001   FORM 1                 88D18620
0848 0  7001              MDX    CM127   CONTINUE               88D18630
0849 0  70CD              MDX    CM12F   LOOP ON ERROR          88D18640
084A 00 0C0001C2  CM127   XIO  L RDBSW   READ DATA SWS          88D18650
084C 00 C4000688          LD   L LNE1    SET NOT LINE 0         88D18660
084E 0  D0F8              STO    CM12Q                          88D18670
084F 00 C40001CB          LD   L SW0     GET SWS                88D18680
0851 0  1007              SLA    7                              88D18690
0852 0  4810              BSC    -       IS PRINT ONLY 1 ON     88D18700
0853 0  70DA              MDX    CM12D   NO                     88D18710
0854 0  70DD              MDX    CM128   YES                    88D18720
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX             88D18730
*                                                               88D18740
*                                 TESTING ROUTINE 19            88D18750
*                                                               88D18760
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX             88D18770
0855 0  1010      RTN19   SLA    16      CLEAR ODD EVEN CTR     88D18780
0856 00 D4000683          STO  L OECTR                          88D18790
0858 00 6600FFF8          LDX  L2 -8     IX 2 = NO WDS          88D18800
085A 00 4400028E  RT19A   BSI  L SP7F    GO SET I/O AREA  SRC   88D18810
085C 00 C4000683          LD   L OECTR   GET ODD/EVEN CTR       88D18820
085E 00 84000684          A    L ONE     ADD 1                  88D18830
0860 00 D4000683          STO  L OECTR   SAVE                   88D18840
0862 0  4804              BSC    E       IS CTR EVEN            88D18850
0863 0  7030              MDX    RT19M   NO                     88D18860
0864 00 C40006E0          LD   L TR0     GET BAD TR CONSTANT    88D18870
0866 00 F6000941  RT19C   EOR  L2 IOAA+8 SET BAD CHARACTER      88D18880
0868 00 D6000941          STO  L2 IOAA+8                        88D18890
*                                                               88D18900
086A 00 440002D4          BSI  L WRT     GO WRITE         SRC   88D18910
*                                                               88D18920
086C 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18930
086E 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18940
*                                                               88D18950
0870 00 4400032C  RT19D   BSI  L RD      GO READ          SRC   88D18960
0872 00 440003C4          BSI  L BSP     GO BACKSPACE     SRC   88D18970
*                                                               88D18980
*                                 CHECK DATA                    88D18990
*                                                               88D19000
0874 00 C4000684  RT19E   LD   L ONE     GET 1                  88D19010
0876 00 D4000685          STO  L WDCT    SET AS WD CT           88D19020
```

```
0878 0  1010              SLA   16         CLEAR A REG          88D19030
0879 00 D4000686          STO L MSG4T       SET TRK IN ERROR     88D19040
087B 00 C4000687          LD  L LNE0        SET LINE 0           88D19050
087D 0  D021              STC   RT19Q                            88D19060
087E 0  6B0C              STX 3 RT19J+1     SAVE IX 3            88D19070
087F 0  63F8              LDX   3 -8        IX 3 = NUMBER WORDS  88D19080
0880 00 C7000941  RT19H   LD  L3 IOAA+8     GET A DATA WD        88D19090
0882 00 F40002A3          EOR L P7F         IS WD CORRECT        88D19100
0884 0  4820              BSC   Z                                88D19110
0885 0  7012              MDX   RT19N       NO                   88D19120
0886 00 74010685  RT19F   MDX L WDCT,1      INCR WD CT           88D19130
0888 0  7301              MDX   3 1         DFCR IX 3            88D19140
0889 0  70F6              MDX   RT19H       LOOP                 88D19150
088A 00 67000000  RT19J   LDX L3 0         RESTORE IX 3         88D19160
*                                                               88D19170
*                         CHECK FOR ROUTINE COMPLETE            88D19180
*                                                               88D19190
088C 00 C4000683  RT19K   LD  L OECTR       GET ODD EVEN CTR     88D19200
088E 0  4804              BSC   E           IS IT EVEN           88D19210
088F 0  70CA              MDX   RT19A       NO                   88D19220
0890 0  7201              MDX   2 1         DECR IX 2            88D19230
0891 0  70C8              MDX   RT19A       CONTINUE RTN         88D19240
0892 00 4C0001EA  RT19L   BSC L RETRN       ROUTINE COMPLETE     88D19250
*                                                               88D19260
*                         ODD-EVEN CTR IS ODD                   88D19270
*                                                               88D19280
0894 00 C40006E0  RT19M   LD  L TRO         GET BAD TR CONSTANT  88D19290
0896 0  1008              SLA   8           MOVE TO FIRST CHAR   88D19300
0897 0  70CE              MDX   RT19C                            88D19310
*                                                               88D19320
*                         DATA IS NOT CORRECT                   88D19330
*                                                               88D19340
0898 00 C40002A3  RT19N   LD  L P7F         GET PATTERN          88D19350
089A 30 D40006E2          STO L PRPAT       SET FOR PRINT        88D19360
089C 00 440C043A          BSI L PRINT       PRINT BAD DATA  SRC  88D19370
089E 0  E001              DC    /E001       ERROR 1              88D19380
089F 0  0001     RT19Q    DC    /0001       FORM 1               88D19390
08A0 0  7001              MDX   RT19P       CONTINUE             88D19400
08A1 0  70CE              MDX   RT19D       LOOP ON ERROR        88D19410
08A2 00 0C0001C2  RT19P   XIO L RDBSW       READ DATA SWS        88D19420
08A4 00 C4000688          LD  L LNE1        SET NOT LINE 0       88D19430
08A6 0  D0F8              STO   RT19Q                            88D19440
08A7 00 C40001CB          LD  L SW0         GET SWS              88D19450
08A9 0  1007              SLA   7                                88D19460
08AA 0  4810              BSC   -           PRINT ONLY FIRST     88D19470
08AB 0  70DA              MDX   RT19F       NO                   88D19480
08AC 0  70DD              MDX   RT19J       YES                  88D19490
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D19500
*                                                               88D19510
*                         TESTING ROUTINE 20                    88D19520
*                                                               88D19530
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D19540
08AD 0  6207     RT20     LDX   2 7         IX 2 = NO TRACKS     88D19550
08AE 00 440002BC  RT200   BSI L SP80        SET I/O AREA    SRC  88D19560
08B0 0  6308              LDX   3 8                              88D19570
08B1 00 C7000938  RT20A   LD  L3 IOA        GET A DATA WD        88D19580
08B3 00 F60008FF          EOR L2 TRKC-1     SET BAD TRACK        88D19590
08B5 00 D7000938          STO L3 IOA        SET IN I/O AREA      88D19600
08B7 0  73FF              MDX   3 -1        DECR IX 3            88D19610
08B8 0  70F8              MDX   RT20A       LOOP                 88D19620
*                                                               88D19630
08B9 00 440002D4          BSI L WRT         GO WRITE        SRC  88D19640
*                                                               88D19650
08BB 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D19660
08BD 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D19670
*                                                               88D19680
08BF 00 4400032C  RT20B   BSI L RD          GO READ         SRC  88D19690
08C1 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D19700
```

```
*                                                               88D19710
*                         CHECK DATA                            88D19720
*                                                               88D19730
08C3 0  63F8              LDX   3 -8        IX 3 = NUMBER WDS    88D19740
08C4 00 C4000684          LD  L ONE         SET WD CT = 1        88D19750
08C6 00 D4000685          STO L WDCT                             88D19760
08C8 00 6E000686          STX L2 MSG4T      SET TRK IN ERROR     88D19770
08CA 00 C4000687          LD  L LNE0        SET LINE 0           88D19780
08CC 0  D015              STO   RT20Q                            88D19790
08CD 00 C7000941  RT20C   LD  L3 IOAA+8     GET A DATA WD        88D19800
08CF 00 F40002D3          EOR L P80                              88D19810
08D1 0  4820              BSC   Z           IS IT CORRECT        88D19820
08D2 0  7008              MDX   RT20F       NO                   88D19830
08D3 00 74010685  RT20D   MDX L WDCT,1      INCR WD CT           88D19840
08D5 0  7301              MDX   3 1         DECR IX 3            88D19850
08D6 0  70F6              MDX   RT20C       LOOP                 88D19860
08D7 0  72FF     RT20E    MDX   2 -1        IS RTN COMPLETE      88D19870
08D8 0  7005              MDX   RT200       NO                   88D19880
08D9 00 4C0001EA          BSC L RETRN       YES                  88D19890
*                                                               88D19900
*                         DATA IS INCORRECT                     88D19910
*                                                               88D19920
08DB 00 C40002D3  RT20F   LD  L P80         GET PATTERN          88D19930
08DD 00 D40006E2          STO L PRPAT       SET FOR PRINT        88D19940
08DF 00 440C043A          BSI L PRINT       PRINT BAD DATA  SRC  88D19950
08E1 0  E001              DC    /E001       ERROR 1              88D19960
08E2 0  0001     RT20Q    DC    /0001       FORM 1               88D19970
08E3 0  7001              MDX   RT20H       CONTINUE             88D19980
08E4 0  70DA              MDX   RT20B       LOOP ON ERROR        88D19990
08E5 00 0C0001C2  RT20H   XIO L RDBSW       READ DATA SWS        88D20000
08E7 00 C4000688          LD  L LNE1        SET NOT LINE 0       88D20010
08E9 0  D0F8              STO   RT20Q                            88D20020
08EA 00 C40001CB          LD  L SW0         GET SWS              88D20030
08EC 0  1007              SLA   7                                88D20040
08ED 0  4810              BSC   -           PRINT ONLY FIRST     88D20050
08EE 0  70E4              MDX   RT20D       NO                   88D20060
08EF 0  70E7              MDX   RT20E       YES                  88D20070
*                                                               88D20080
*                         CONSTANTS                             88D20090
*                                                               88D20100
08F0 0  4040     TRKC     DC    /4040       BAD TR CNST-TR 1     88D20110
08F1 0  2020              DC    /2020                    2       88D20120
08F2 0  1010              DC    /1010                    3       88D20130
08F3 0  0808              DC    /0808                    4       88D20140
08F4 0  0404              DC    /0404                    5       88D20150
08F5 0  0202              DC    /0202                    6       88D20160
08F6 0  0101              DC    /0101                    7       88D20170
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D20180
*                                                               88D20190
*                         TESTING ROUTINE 21                    88D20200
*                                                               88D20210
*XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX           88D20220
08F7 00 4400028E  RT21     BSI L SP7F        SET I/O AREA    SRC  88D20230
08F9 0  6308              LDX   3 8                              88D20240
08FA 00 C7000938  RT21B   LD  L3 IOA        GET A DATA WD        88D20250
08FC 00 F40007B3          EOR L TRKB        SET BAD TRACK        88D20260
08FE 00 D7000938          STO L3 IOA        SET AS DATA          88D20270
0900 0  73FF              MDX   3 -1        DECR IX 3            88D20280
0901 0  70F8              MDX   RT21B       LOOP                 88D20290
*                                                               88D20300
0902 00 440002D4          BSI L WRT         GO WRITE        SRC  88D20310
*                                                               88D20320
0904 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D20330
0906 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D20340
*                                                               88D20350
0908 00 4400032C  RT21G   BSI L RD          GO READ         SRC  88D20360
090A 00 440003C4          BSI L BSP         GO BACKSPACE    SRC  88D20370
*                                                               88D20380
```

```
                      *                    CHECK DATA                    88D20390
                      *                                                  88D20400
090C 0  63F8          LDX   3 -8       IX 3 = NUMBER WDS                 88D20410
090D 00 C4000684      LD    L ONE      GET 1                            88D20420
090F 00 D4000685      STO   L WDCT     SET AS WD CT                     88D20430
0911 0  1010          SLA   16         CLEAR A REG                      88D20440
0912 00 D4000686      STO   L MSG4T    SET TRK IN ERROR                 88D20450
0914 00 C4000687      LD    L LNE0     SET LINE 0                       88D20460
0916 0  D013          STO     RT21Q                                    88D20470
0917 00 C70C0941      RT21C LD   L3 IOAA+8   GET A DATA WD              88D20480
0919 00 F40002A3      EOR   L P7F                                      88D20490
091B 0  4820          BSC     Z         IS IT CORRECT                   88D20500
091C 0  7006          MDX     RT21F     NO                              88D20510
091D 00 74010685      RT21D MDX  L WDCT,1   INCR WD CT                  88D20520
091F 0  7301          MDX   3 1         DECR IX 3                       88D20530
0920 0  70F6          MDX     RT21C     LOOP                            88D20540
0921 00 4C0001EA      RT21E BSC  L RETRN    EXIT                        88D20550
                      *                                                  88D20560
                      *                                                  88D20570
                      *                    DATA IS INCORRECT             88D20580
0923 00 C40002A3      RT21F LD   L P7F      GET PATTERN                 88D20590
0925 00 D40006E2      STO   L PRPAT    SET FOR PRINT                    88D20600
0927 00 4400043A      BSI   L PRINT    PRINT BAD DATA        SRC        88D20610
0929 0  E001          DC      /E001     ERROR 1                         88D20620
092A 0  0001          RT21Q DC  /0001   FORM 1                          88D20630
092B 0  7001          MDX     RT21H     CONTINUE                        88D20640
092C 0  70DB          MDX     RT21G     LOOP ON ERROR                   88D20650
092D 00 0C0001C2      RT21H XIO  L RDBSW    READ DATA SWS               88D20660
092F 00 C4000688      LD    L LNE1     SET NOT LINE 0                   88D20670
0931 0  D0F8          STO     RT21Q                                    88D20680
0932 00 C4C001CB      LD    L SW0      GET SWS                          88D20690
0934 0  1007          SLA   7                                          88D20700
0935 0  4810          BSC     -         PRINT ONLY FIRST                88D20710
0936 0  70E6          MDX     RT21D     NO                              88D20720
0937 0  70E9          MDX     RT21E     YES                             88D20730
0938 0  4267          IOA   DC  /4267   WORD COUNT                      88D20740
0939 0  0000          IOAA  DC  0       I/O AREA                        88D20750
093A    0266          BSS     614                                      88D20760
0BA0    012D          END     START                         88D2076 88D20770
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BEGAN	0147	014A
BEGIN	0143	01AE,01B6,01D0,0217
BSP	03C4	030D,0345,037C,03B4,03CE,063C,063E,0644,06A2,06A4,
		06A8,0709,070B,070F,0776,0778,077C,07C1,07C3,07C7,
		0813,0815,081B,086C,086E,0872,08BB,08BD,08C1,0904,
		0906,090A
BSPI0	03F4	03D2,03D3,03D4
BSP01	03C5	03F0
BSP02	03CE	03CB,03DA
BSP03	03D0	03CD,03E4
BSP04	03DB	03D9
BSP05	03E5	03E3
BSP06	03E7	03C9
BSP07	03F1	03EF
CLN	0370	0368
CLN1	037A	
CLN2	037D	0386
CLN3	0383	037B,0394,0395,0396
CLN5	0388	0391,0392,0398
CLN6	038C	038A
CLN7	038E	0388
CLN8	0393	0382
CMRT	0624	01D4,01D5,01D6,01D7,01D8,01D9,01DA
CMRTB	0666	0654
CMRTC	064F	0658
CMRTD	0655	0678
CMRTE	065B	
CMRTF	0640	0639,066F
CMRTT	01D3	01A6,01EC,0453
CMRT0	0629	065D,065F
CMRT1	0635	0665
CMRT2	0662	0632
CMRT3	062B	0624
CMRT5	0660	
CMRT6	0646	
CMRT7	0670	066E
CMRT8	0659	064B,0679
CMRT9	066D	064D,0671
CMR12	07F7	01DF,01E0,01E1,01E2,01E3,01E4,01E5
CM12B	0840	0823
CM12C	0828	0831
CM12D	082E	0853
CM12E	0834	
CM12F	0817	0810,0849
CM12Q	0847	0825,084E
CM120	07FE	0837,0839
CM121	080C	083F
CM122	083C	0809
CM123	0800	07F8
CM125	083A	
CM126	081D	
CM127	084A	0848
CM128	0832	0826,0854
CODEH	05DE	05C1
CORDS	03C1	0360
CRCA	073E	0701
CRCSP	074F	06F1,0766
CRC7F	02A4	029C
CRC8F	02BB	02B4
CRC80	02D2	02C6
DSL	0622	0618,061B,061C,061F
DSLT	0617	0386,0620
DSW	023A	0231,02E3,02E8,0302,0340,0349,035E,0399,03D6,03DB,
		03E7,0410
DSWCR	0682	

F
L

```
CKWEX   0681
EDIT    01C6    0134,014F,C168,016C,0176,0181,0220,0269,0420
EDT     0132    012D
EDT1    0133    0137
EDT2    013D    0138
ELE     032A
END     020D    0205
ERA     0324    0311,0312,0313
ERRR    04EE    04E6
FORM    0482    047D
FORMC   04A6    049E,04A2
FORM1   0491    0483
FORM2   049E    0484
FORM3   049F    0485
FORM4   04A3    0486
FOUR    0329    02FF
FRMC1   04A9    04AC
FRMC2   04B1    046F,047C,04C1
FRMC3   04CC    04C8
FRMC4   04CE    0444,04CB
FRMC5   04D5    04E8,04EA
FRMC6   04E4    04D4
FRMC7   04DE    043D,04ED
FRMC8   04E0    043B
FRMC9   04EB    04DB
FRST    048C    046A
FRWC    0487    0462
HEXCD   05DC    04B7,05CB,05CF
HEXCV   05B4    04B5,05D4
HEXC1   05BD    05BE,05C7
HEXC2   05D0    05B5
HEXC3   05D2    05B7
HEXWD   05D6    04B3,05BA
HEX00   05D7    05C3,05C8,05CA,05CC,05CE
ILSW    0238    021C,0254
INTR    0219    0234,023F
INTR1   0227    0222
INTR2   023E    0145,024A,0251
INTR3   0232    0226
IOA     0938    02DA,0322,0335,03BC,06F7,06FB,076C,0770,07B7,07BB,
                08B1,08B5,06FA,08FE
IJAA    0939    0291,0298,029C,029F,02A9,02B0,02B5,02B7,02C0,02C7,
                02CC,02CE,0494,0635,0637,064F,069C,069E,06B6,06E6,
                06ED,06F2,06F4,06FF,0703,0705,071D,075B,0762,0767,
                0769,078A,07D5,080C,080E,0828,0866,086B,0880,08CD,
                0917
IOARA   05B2    0591,059E,05A0,05AE
K005    03A7    0393
K009    03A9    0366,0373
K010    03A8    0376
LNE0    0687    064C,06B1,071A,0787,07D2,0823,087B,08CA,0914
LNE1    0688    0670,06D7,0735,07A2,07ED,084C,08A4,08E7,092F
LOGC    0514    04C9,054E
LOGCA   0557
LOGCB   0541    0558
LOGCO   0546    0524
LOGC1   051F    0545
LOGC2   0525    053E
LOGC3   0528    0527
LOGC4   0531    0530
LOGC5   0533    052C
LOGC6   053F    0537
LOGC7   0548    051A,05AC
LOGC8   054A    051B
LOGC9   054C    051C
LOGX0   047F    046E
LOGX1   0480    0478
LOGX2   0481    0478
```

```
LOG00   0584    0546
LOG01   058F    05A7
LOG02   05A8    0594
LOG03   05A4    059D
LOX00   0550    0516,0535,0539,0543
LOX02   0551    0520,0525,052D,0538,053D
LOX03   0552    0538,0540
LOX04   0553    052A
MASK0   060C    0588,05F4
MASK1   060E    058A,05F5
MID     04F0    045A,04E4
MK0     01BE    0243
MK1     01C0    0245
MOD     01CD    0183,0422
MSG     04F8    044D,0518,058F,05F2,0614
MSG0    04F9    0449,0489,048C,051D
MSG1    04F4    044B,0493,04A1,04A5
MSG2    04F5    0447,0496
MSG3    04F6    0449,0499
MSG4    04F7    044F,049C
MSG4T   0686    049A,0649,06AF,0718,0785,07D0,0821,0879,08C8,0912
MTST    015A
OECTR   0683    0626,062D,0630,065B,068B,0693,0697,06C1,07FA,0802,
                0806,0834,0856,085C,0860,088C
ONE     0684    01A0,0220,02FC,036B,0466,05FF,062E,0646,0695,06AA,
                0712,077F,07CA,0804,081D,085E,0874,08C4,090D
PID     04EF    047F,04B1
PRINT   043A    01AA,01B2,01F1,02F2,0306,0316,0356,039D,03AB,03DF,
                03EB,0414,0457,04DC,04E2,04EB,066A,06CF,072D,079A,
                07E5,0844,089C,08DF,0927
PRPAT   06E2    0491,0668,06CE,072B,0798,07E3,0842,089A,08DD,0925
PRSP    0583    0517,0557
PRWDC   0616    0464,05F1
PRO0    0559    0553
PRO1    0564    0554
PRO2    056D    0555
PRO3    057A    0556
PRO4    0476    0475
PRO5    047D    0472
PR1     0460    045D,0470
PR43    05EE    04CC,0608
PR431   05FA    05FD
PR432   0602    0605
P7F     02A3    0290,0651,0666,0882,0898,0919,0923
P8F     06E1    02A7,06BB,06CC
P8F70   074E    06E5,071F,072A,075A,078C,0797
P80     02D3    02BE,07D7,07E1,082A,0840,08CF,08DB
RAD     04F2    0455
RD      032C    0354,0642,06A6,070D,077A,07C5,0819,0870,08BF,0908
RDBSW   01C2    0163,0195,020D,043F,04C2,04CE,04D5,0672,06D5,0733,
                07A0,07EB,084A,08A2,08E5,092D
RDE     0352    0337,03B3
RDFNC   03BE    032F
RDIOC   03BC    0331,033E,0347,038C
RDSSW   01C4    0199
RDTWC   03BA    0333
RDTX0   03AA    0365
RDO1    0339    0358,038B,03B8
RDO2    0356    033D
RDO3    035C    035A
RDO4    035E    0344,034D
RDO5    0399    0362,0374
RDO6    03A2
RDO7    03AB    0351
RDO8    03B0    03A1,03AF
RDO9    03B4    036F,03A5
RD1DS   03BF    0342
RD2DS   03C0    034B
```

RETRN	01EA	01E9,0660,06C7,0728,0795,07DF,083A,0892,08D9,0921
RETR1	01F1	0192,01ED
RETR2	01F6	01F5
RETR3	0203	01FB
RID	04F1	015D,019E,01A2,01A4,01EA,01FF,0209,0210,0451
RSRT	01D2	0155
RSTRT	01D0	J151
RTN10	0758	01DD
RTN11	07B4	01DE
RTN19	0855	01E6
RTN8	0689	01DB
RTN8A	068F	06C4,06C6
RTN8B	0691	0689
RTN8C	069C	06CB
RTN8D	06A6	06D4
RTN8E	06AA	
RTN8F	06BB	06DE
RTN8H	06B6	06BE
RTN8J	06BF	06B4,06DF
RTN8K	06C1	
RTN8L	06C7	
RTN8M	06C9	069A
RTN8N	06CC	06BA
RTN8P	06D5	06D3
RTN8Q	06D2	06B3,06D9
RTN9	06E3	01DC
RTN9A	06F7	06FE
RTN9B	070D	0732
RTN9C	071D	0725
RTN9D	0722	073C
RTN9E	0726	073D
RTN9F	072A	0721
RTN9H	0733	0731
RTN9J	06E5	06E9
RTN9K	06ED	06F0
RTN9Q	0730	071C,0737
RTN9O	06E4	0727
RT10B	076C	0773
RT10C	078A	0792
RT10D	078F	07A9
RT10E	0793	07AA
RT10F	0797	078E
RT10G	077A	079F
RT10H	07A0	079E
RT10J	075A	075E
RT10K	0762	0765
RT10L	0759	0794
RT10Q	079D	0789,07A4
RT11A	07B7	078E
RT11B	07C5	07EA
RT11C	07D5	07DE
RT11D	07DB	07F4
RT11E	07DF	07F5
RT11F	07E1	07DA
RT11H	07EB	07E9
RT11J	02C0	02C3
RT11K	02C7	02CA
RT11L	07B6	
RT11Q	07E8	07D4,07EF
RT19A	085A	088F,0891
RT19C	0866	0897
RT19D	0870	08A1
RT19E	0874	
RT19F	0886	08AB
RT19H	0880	0889
RT19J	088A	087E,08AC
RT19K	088C	
RT19L	0892	

RT19M	0894	0863
RT19N	0898	0885
RT19P	08A2	08A0
RT19Q	089F	087D,08A6
RT20	08AD	01E7
RT20A	08B1	08B8
RT20B	08BF	08E4
RT20C	08CD	08D6
RT20D	08D3	08EE
RT20E	08D7	08EF
RT20F	08DB	08D2
RT20H	08E5	08E3
RT20Q	08E2	08CC,08E9
RT20O	08AE	08D8
RT21	08F7	01E8
RT21B	08FA	0901
RT21C	0917	0920
RT21D	091D	0936
RT21E	0921	0937
RT21F	0923	091C
RT21G	0908	092C
RT21H	092D	092B
RT21Q	092A	0916,0931
RWD	03F6	0174,018A,031E,040E
RWDIO	041C	0401,0402,0403
RWD01	03F7	0419
RWD02	0405	0409,040D
RWD03	040E	03FE,040C
RWD04	0410	03FB
RWD05	041A	0418
R11X0	07F6	0789
SDSW	023C	0227,022A,022B,022C,022F,0230
SELDR	03C2	
SENSE	05B0	0584,0597
SNDSW	041E	0170,0186,02DC,0339,037E,03C5,03F7,0405,0434
SNDS1	0420	0430
SNDS2	0429	042C
SNDS3	0432	041F
SNS	0436	0424,0425,0428
SNSPR	060A	05EF,05F0,05F6,05FA,05FE,0601,0602
SNSV	0438	0304,039B,03DD,03E9,0412,0429,042D,042E,0431,049F
SP7F	028E	02A1,0629,085A,08F7
SP7F0	0291	0294
SP7F1	0298	029B
SP8F	02A5	02B9,068F
SP8F0	02A9	02AC
SP8F1	02B0	02B3
SP80	02BC	02D0,07B4,07FE,08AE
START	012D	08A0
STWC	04AD	0468,046C,0479
SUPR	0163	01AF,0215
SUPR0	0191	018D
SUPR1	0195	0190,01EF,0201,020B
SUPR2	01A2	019C
SUPR3	0176	0167,016B,01B7
SUPR4	01A8	0173
SUPR5	01AF	
SUPR6	01B0	0189
SUPR7	01B7	
SUPR8	018C	0179,017B,0180
SVEXT	027C	0276
SVINT	0242	0224,023E,0250,0281
SVIN0	025C	0272,0278
SVIN1	025E	0266
SVIN2	0267	026E
SVIN3	0254	024D
SVIO	028C	0247,0262,0263,027C
SVO	0283	0270

SV1	0284	025C
SV2	0285	025A
SV3	0286	0277
SV4	0287	0259,025E,0267,026C,026F,027A
SV5	0288	025D,0260,0264
SV6	0289	025B,0261,0278
SV7	028A	0256,0273
SW0	01CB	0164,017C,0196,01C2,0212,0441,04C4,04D0,04D7,0674,
		060A,0738,07A5,07F0,084F,08A7,08EA,0932
SW1	01CC	019A,01C4
TAAQ	0236	021B,0232
TAILS	023B	021D
TAPE0	01B8	015B,016E,018C,01A9,01F7,01F9,0228,02D5,030F,032D,
		03D0,03FF,0619
TAPE1	01B9	015C,0184,0191,01B1,0203
TASS	0233	021A
TERM	0513	013F,0521,0592,07CE
TERR	0240	021E
TPINT	023F	014D
TRKA	0746	06F9
TRKB	07B3	08FC
TRKC	08F0	08B3
TRKD	07AB	076E
TRKMS	0750	0716,0783
TR0	06E0	069B,06C9,0864,0894
TR1	067A	0633,0662,080A,083C
TR2	067B	
TR3	067C	
TR4	067D	
TR5	067E	
TR6	067F	
TR7	0680	
UNIT	04F3	045E,0480
UNMK0	01BA	0161,027D
UNMK1	01BC	0162,027F
UNMK3	0610	05A8,0606
UNMK4	0612	05AA,0607
WAITA	0404	300A
WAITB	04E9	300B
WAITC	0587	300C
WAITD	05F8	300D
WAITE	0241	300E
WAITF	038D	300F
WAIT1	0142	3001
WAIT2	0159	3002
WAIT3	0198	3003
WAIT4	02F2	3004
WAIT5	02FA	3005
WAIT6	0314	3006
WAIT7	033F	3007
WAIT8	0348	3008
WAIT9	03D5	3009
WDCT	0685	0497,0648,0655,06AC,06BB,0714,0722,0781,078F,07CC,
		07DB,081F,082E,0876,0886,08C6,08D3,090F,091D
WRDSW	05B3	058D,059B,05A1,05A5
WRERP	0328	015F,02ED,02F9,02FB,02FE,030C,031C,034E,0363,0369,
		036D,0370,0378,03A3,03B1,04A3
WRIOC	0322	02D8,02E1
WRITE	05AE	0596
WRPR	0614	05F9
WRT	02D4	02F0,063A,06A0,0707,0774,07BF,0811,086A,08B9,0902
WRTCC	0326	02D7
WRTSW	0327	02EA
WRTWC	032B	02D9
WRT01	02D5	0315,0320
WRT02	02DC	02F7
WRT03	02F0	031D
WRT04	02F2	02E0

WRT05	02F8	02F6,030A,035C,03E5,03F1,041A
WRT06	02FB	02EC
WRT07	030B	
WRT08	030D	0301
WRT09	0316	02EF
WRT10	031B	031A
WRT11	031E	02E7
XIOSN	0597	059A
XIOWR	0596	05A3

TABLE OF CONTENTS

---

1. PURPOSE

    TO ASSIST THE CE TO PUNCH THE NECESSARY EDIT CARDS AND/OR PAPER TAPE FOR
    THE 1800 DIAGNOSTIC FUNCTION TESTS.

2. REQUIREMENTS

    2.1 PROGRAM

        A. 4K EDIT UTILITY (PID 08C2) IF ONLY A 4K SYSTEM
        B. 8K EDIT UTILITY (PID 08C3) IF GREATER THAN 4K
        C. DP I/O EDIT SKELETONS (PID 08C4) FOR EDITING OF MONITOR AND
            DP I/O PROGRAMS
        D. P I/O AND NON-MONITOR EDIT SKELETONS (PID 08C5) FOR PROCESS
            I/O AND NON-MONITOR PROGRAMS REQUIRING EDIT

    2.2 EQUIPMENT

        A. 1442 OR 1054/55
        B. 1816
        C. 4K OR GREATER

3. USE PROCEDURE PROGRAM LOADING

    3.1 EITHER EDIT UTILITY PROGRAM (4K PID 08C2 OR 8K PID 08C3) FOLLOWED
         BY EITHER OR BOTH EDIT SKELETONS (DP I/O PID 08C4 OR P I/O NON-MONITOR
         PID 08C5) ARE LOADED BY THE RELOCATABLE LOADER PID 08B1 FOR CARDS
         OR PID 08B0 FOR PAPER TAPE. TO SAVE LOADING ALL SKELETONS SEE
         SECTION 3.2. IF CARDS ARE TO BE PUNCHED, PLACE
         BLANK CARDS BEHIND THE DECK.

    3.2 SKELETON IDENTIFICATION

         EACH DECK OF SKELETONS CONTAINS SEVERAL SMALLER GROUPS. EACH
         SMALL GROUP HAS THE FOLLOWING IDENTIFICATION.

             COLUMN   73-74   PID OF THE SKELETON GROUP,
                                C4 - DP I/O EDIT SKELETONS
                                C5 - P I/O NON-MONITOR EDIT SKELETONS
                        75-76   PID FOR THE PROGRAM TO BE EDITED.
                        77   SKELETON SEQUENCE NUMBER OF THE PID
                                IN COLUMN 75-76
                        78-80   CARD SEQUENCE WITHIN EACH SKELETON
                                COL. 77.

         NOTE - FOR EACH PID TO BE EDITED, THERE WILL BE A MINIMUM OF TWO
         SKELETONS AND A MAXIMUM OF TEN SKELETONS. ALL SKELETONS FOR ONE
         PID WILL BE REFERRED TO AS A SET OF SKELETONS.

         SINCE ONLY ONE PROGRAM MAY BE EDITED EACH PASS ONLY ONE SET OF
         SKELETONS IS REQUIRED TO BE LOADED WITH EITHER EDIT UTILITY CONTROL
         PROGRAM (PID 08C2 OR 08C3). HOWEVER ALL SKELETONS MAY BE PLACED
         AFTER EITHER EDIT CONTROL AND THE PROGRAM WILL OPERATE PROPERLY.

         IF LOADING FROM PAPER TAPE EACH SET OF SKELETONS IS SEPARATED BY
         AN IDENTIFICATION LEADER. THE TAPE MUST BE MANUALLY POSITIONED
         TO THE DELETE FIELD AHEAD OF THE PROPER SET OF SKELETONS BEFORE
         ENTERING THE PID TO BE EDITED.

         EACH SET OF SKELETONS WILL BE PRECEEDED BY THE FOLLOWING IDENTI-
         FICATION.

         *R   PID   08CX-Z   SKELTONS FOR YY

                     Z = VERSION
                     X = 4 OR 5
                     YY = PID FOR THE PROGRAM TO BE EDITED.

3.3 PROGRAM OPERATION

SET IN THE DATA ENTRY SWITCHES TO SELECT THE DESIRED EDIT OUTPUT
AS FOLLOWS,

CARDS ONLY   - /0000
PAPER TAPE ONLY- /8000
CARDS AND TAPE - /4000

A MESSAGE WILL BE PRINTED ON THE 1816 AFTER CORRECT LOADING
REQUESTING THE PID OF THE PROGRAM TO BE EDITED. THE PROGRAM WILL
THEN READ CARDS LOOKING FOR A SKELETON WITH THE PID OF THE PROGRAM
TO BE EDITED. WHEN THIS IS FOUND THE PROGRAM WILL ASK A SERIES
OF QUESTIONS VIA THE 1816 AND THE CE MUST RESPOND TO EACH.

AFTER EACH RESPONSE THE END OF FIELD (EOF) KEY MUST BE DEPRESSED.
WHEN MAKING MULTIPLE ENTRIES A COMMA MUST BE TYPED AFTER EACH
GROUP AND EOF AFTER THE LAST ENTRY. IN CASE OF AN ERROR OR CORRECTIONS
SEE SECTION 3.7.

3.4 PROGRAM TERMINATION

A MESSAGE WILL BE PRINTED TO INDICATE ALL NECESSARY DATA HAS
BEEN RECEIVED AND THE EDIT INFORMATION WILL BE PUNCHED VIA THE METHOD
SELECTED IN SECTION 3.3. THE PROGRAM THEN LISTS ALL THE EDIT
INFORMATION SO A RECORD MAY BE MAINTAINED. A MESSAGE AND A
PROGRAM WAIT TERMINATES THE PROGRAM.

3.5 RERUN OR RESTART PROCEDURE

FOR EITHER RERUN OR RESTART PLACE THE DESIRED SKELETON (TO SELECT
A SKELETON SEE 3.2) IN THE READER AND PUSH START. A REQUEST FOR
PID MESSAGE WILL INDICATE A SUCCESSFUL RETRY. IF THIS PROCEDURE
FAILS, SEE SECTION 3.1 PROGRAM LOADING.

A.   RERUN
     AFTER THE READER IS READY PRESS START.

B.   RESTART
     AFTER THE READER IS READY PRESS STOP, RESET, AND START.

3.6 PROGRAM WAITS

PROGRAM WAITS ARE IDENTIFIED BY THE B AND I REGISTER AND ARE FOUND
AT THE BEGINNING OF THE LISTING. THE FOLLOWING IS AN EXAMPLE.

```
*****************************************************************
B-REG  I-REG              WAITS         COMMENTS
*****************************************************************
300F   01ED       DC      WAITF+1       IN THIS AREA IS A
                     *                  DESCRIPTION OF THE
                     *                  ABOVE WAIT.
                     *
                     *
```

3.7 ERROR PROCEDURE

ERRORS WILL FALL INTO TWO TYPES.

A.   REPEAT FIELD

     AN ERROR MESSAGE INDICATES A PROGRAM FOUND ERROR BECAUSE OF
     INCORRECT FORMAT OR THE ERASE FIELD KEY (ER FLD) HAS BEEN
     DEPRESSED. ALL THE DATA ENTERED SINCE THE LAST COMMA HAS BEEN
     ERASED. THE LINE WITH THE ERROR WILL CONTAIN THREE ASTERISKS.

B.   REPEAT CHARACTER

     IF THE CE WISHES TO CORRECT THE LAST CHARACTER TYPED HE WILL
     PRESS ERASE CHARACTER KEY (ER CHR). THE TYPEWRITER WILL
     BACKSPACE AND THE CORRECT CHARACTER WILL BE TYPED OVER
     THE ERROR CHARACTER. IF AN OVERPRINT IS NOT DESIRABLE,
     MANUALLY LINE FEED BEFORE TYPING THE CORRECT CHARACTER.

4. PRINTOUTS

4.1 STATUS MESSAGES BEGIN WITH AN A AND WILL TELL OF SOME CONDITION.

MID   PROG   MESSAGE

A001   CNTRL   EDIT CARD LIST

                  ALL NECESSARY DATA HAS BEEN ENTERED AND THE
                  INFORMATION WILL BE PUNCHED AND LISTED.

A002   CNTRL   END OF PRG

                  THE PROGRAM IS FINISHED FOR THE PID SELECTED.
                  IF ANOTHER PID IS TO BE SELECTED SEE SECTION 3.5.

4.2 COMMAND MESSAGES BEGIN WITH A C AND REQUESTS ACTION BY THE CE FOR
THE CONTINUATION OF THE PROGRAM.

THE LIST OF CHARACTER AND MEANING THAT WILL BE FOUND IN COMMAND
MESSAGES.

     VVVV - A DEVICE, SUCH AS 1442, CONSOLE INTERRUPT, OR MONITOR
            OUTPUT. IT WOULD INCLUDE FIRST OR SECOND DEVICE.
     W   - MAG TAPE DRIVE 0 OR 1.
     XX   - PID OF PROGRAM BEING EDITED.
     ZZ   - CARD NUMBER

MID   PROGRAM   MESSAGE

C000   CNTRL   ENTER 2 DIGIT PID TO BE EDITED.

       ENTER THE PID OF THE PROGRAM THAT IS TO BE EDITED.

C001   PID XX-CD ZZ ENTER 2 DIGIT DECIMAL INTERPT LVL FOR VVVV.

C002   PID XX-CD 00 ENTER 2 DIGIT DECIMAL ILSW BIT FOR VVVV.

C003   PID XX-CD 00 ENTER 1 DIGIT DECIMAL CH FOR VVVV.

C004   PID XX-CD 00 ENTER NUMBER OF VVVV ON SYSTEM, 1 DIGIT.

C005   PID XX-CD 00 DOES THIS SYSTEM HAVE 2 VVVV-TYPE Y OR N.

C006 PID XX-CD 00 ARE ADKS REFERENCE CHANGES DESIRED-TYPE Y OR N.

IF THE ADDRESSES NORMALLY USED BY THE PROGRAM,
ARE KNOWN TO BE BAD, ANSWER Y.

C007 PID XX-CD 00 ENTER 1 DIGIT DECIMAL FLD NUMBER TO BE CHANGED
FOLLOWED BY 3 DIGIT DECIMAL ADRS DESIRED-1-8
ENTRIES IN FOLLOWING FORMAT
D DDD,.

C008 PID XX-CD 00 ENTER 4 DIGIT HEX TIMER BASE FOR INT TIMER A.

TIME BASE OF TIMER A IN MILLISEC.	CONSTANT ENTERED IN HEX
128.000	
64.000	0001
32.000	0002
16.000	0004
8.000	0007
4.000	000E
2.000	001B
1.000	0036
.500	006B
.250	00D6
.125	01AB
	0356

C009 PID XX-CD 00 ENTER AI MODEL-TYPE 1 OR 2.

C00A PID XX-CD 01 ENTER 5 DIGIT DECIMAL CYCLE COUNT.

THIS COUNT DETERMINES THE NUMBER OF TIMES EACH
SPECIFIED MULTIPLEX ADDRESS IS READ AND CONVERTED.
THE COUNT MAY BE ANY NUMBER FROM 00001 TO 32000.

C00B PID XX-CD ZZ SHOULD FIRST RDING BE PREC VOLT-TYPE Y, OR N.

IF IT IS DESIRED TO ENTER PRECISION VOLTAGES
TYPE N. IF Y IS TYPED THE AI PROGRAM WILL
USE THE FIRST ENTRY RECEIVED AS THE PRECISION
VOLTAGE.

C00C PID XX-CD ZZ RELOAD TO CORRECT THIS ERROR OR PRESS
START TO IGNORE.

THIS MESSAGE OCCURS ONLY ON A 4K SYSTEM. IF
IGNORED THE ERROR WILL BE PUNCHED AND LISTED AT
THE COMPLETION OF THE PROGRAM. THE ERRORS THEN
MAY BE MANUALLY CORRECTED.

C00D PID XX-CD ZZ IS EXT SYNC DESIRED-TYPE Y OR N.

C00E PID XX-CD 00 IS IT DESIRED TO CHANGE THE DLY CONSTANT
- TYPE Y OR N.

IF A DELAY OF OTHER THAN THE STANDARD
IS DESIRED, TYPE Y.

C00F PID XX-CD 00 ENTER 2 DIGIT HEX DELAY CONSTANT.

C010 PID XX-CD 00 IS MEMORY SPEED FOR THIS SYS 2 MICRSEC-
TYPE Y OR N.

C011 PID XX-CD 00 ENTER 2 DIGIT DECIMAL AREA CODE FOR VVVV.

C012 PID XX-CD 00 DOES THIS SYSTEM HAVE A VVVV-TYPE Y OR N.

C013 PID XX-CD 00 IS DRIVE W A 9 TRK DRIVE-TYPE Y OR N.

C014 PID 01-CD 02 ENTER DEVICE INFO IN THE FOLLOWING FORMAT.
1-40 DEVICES - SPACE BETWEEN ENTRIES,
IL ILSW CH AC MOD.

DD DD H DD HH,

D - DECIMAL CHARACTER.
H - HEXADECIMAL CHARACTER-ENTER 0-8 OR F FOR
CHANNEL.

ONE LINE OF INFORMATION IS ENTERED FOR EACH
DEVICE ON THE SYSTEM.

C015 PID 08-CD 01 IS IT DESIRED TO CHANGE WD CTS-TYPE Y OR N.

IF WORD COUNTS OTHER THAN THOSE NORMALLY USED
BY THE 2400 IS PROGRAM ARE DESIRED, TYPE Y.

C016 PID 08-CD 01 ENTER REC TO CHANGE AND WD CT DESIRED IN
FOLLOWING FORMAT
D DDDD,

1 TO 8 LINES OF ENTRIES MAY BE MADE. THE FIRST
DIGIT IS THE RECORD NUMBER TO CHANGE (1-8) AND
THE FOUR DIGIT ENTRY IS THE DESIRED DECIMAL
WORD COUNT (0001-1000).

C017 PID 21-CD 00 IS COMPARATOR FEATURE INSTALLED-TYPE Y OR N.

C018 PID 21-CD 0A IS OVERLAP CHECK DESIRED-TYPE Y OR N.

C019 PID 21-CD 1B ENTER 3 DIGIT DECIMAL WD CT 1-100.

THIS VALUE (001-100) WILL SPECIFY THE NUMBER OF
MULTIPLEX ADDRESSES TO BE USED FROM THE AIIAT
TABLE. A COUNT OF ONE MUST BE ADDED TO THE WORD
COUNT FOR EACH TIME CHAINING IS SPECIFIED.

C01A PID 21-CD 1C IS OVERLAP CARD INSTALLED-TYPE Y OR N.

C01B PID 21-CD 1D SHOULD LIMIT WDS BE HONORED-TYPE Y OR N.

C01C PID XX-CD 04 ENTER 2 DIGIT DECIMAL RESOLUTION.

TYPE EITHER, 08,11, OR 14.

C01D   NOT USED

C01E   NOT USED

CO1F PID XX-CD 06 ENTER DECIMAL ADDRESSES.

THE INPUT MUST FOLLOW THIS FORMAT. FROM 1-100
LINES MAY BE ENTERED. IF AN ADDRESS HAS A
LIMIT WORD, TYPE 'L' IN THE SPACE INDICATED.
(SEE LINE 1) IF THERE IS NO LIMIT WORD,
TYPE THE COMMA AFTER THE ADDRESS (SEE LINE 3)
IF CHAINING IS DESIRED, TYPE 'C' ON THE NEXT
LINE AFTER THE ADDRESS. (SEE LINE 2) A 1 IN
THE HIGH ORDER POSITION OF THE MPX ADDRESS
INDICATES A SOLID STATE POINT. PRESS THE EOF
KEY AFTER THE LAST LINE.

```
MPX
ADDR
10XXX L,          ( SOLID STATE ADDR.  THAT
                    HAS LIMIT WORD)
C,                ( CHAIN TO NEXT ADDRESS)
10XXX,            ( SOLID STATE ADDR. WITH NO
                    LIMIT WORD)
C,                ( CHAIN TO NEXT ADDRESS )
10XXX (PRESS EOF  ( SOLID STATE ADDR. WITH NO
      KEY )         LIMIT WORD AND NO CHAINING)
```

CO20 PID 21-CD 10 ARE LMT CK WDS DESIRED-TYPE Y OR N.

CO21 PID 21-CD 10 ENTER LMT WD DATA FOR ADR.

THE INPUT MUST FOLLOW THIS FORMAT. THERE
WILL BE ONE CO21 MESSAGE FOR EACH MPX ADDRESS
THAT IS TO BE LIMIT CHECKED.

RANGE PREC VOLT LIMIT WORD
XXX YXXX.XXXXX +XXX -XXX (PRESS EOF KEY)
              NOTE
'Y' IS THE SIGN OF THE PREC VOLT VALUE, IT
MUST BE EITHER '+' OR '-'.

CO22 PID XX-CD ZZ ENTER DECIMAL ADDRESS AND RANGE.

THE INPUT MUST FOLLOW THIS FORMAT. FROM 1-5
LINES MAY BE ENTERED. A 1 IN THE HIGH ORDER
POSITION OF THE MPX ADDRESS INDICATES A SOLID
STATE POINT. PRESS THE EOF KEY AFTER THE
LAST LINE.

MPX			RANGE TABLE
ADDR	RANGE CONSTANT	RANGE	CONSTANT TO ENTER
XXXXX XXX,		500 MV	500
XXXXX XXX,		200 MV	200
XXXXX XXX,		100 MV	100
XXXXX XXX,		50 MV	050
XXXXX XXX		20 MV	020
(PRESS EOF KEY)		10 MV	010
		5 VOLTS	005

CO23 PID XX-CD ZZ ENTER DECIMAL ADDRESS, RANGE AND PREC VOLT.

THE INPUT MUST FOLLOW THIS FORMAT. FROM 1-5
LINES MAY BE ENTERED. SEE MESSAGE CO22 FOR
RANGE TABLE. A 1 IN THE HIGH ORDER POSITION OF
THE MPX ADDRESS INDICATES A SOLID STATE POINT.
PRESS THE EOF KEY AFTER THE LAST LINE.

ADDR RANGE PREC VOLT VALUE	NOTE
XXXXX XXX YXXX.XXXXX,	'Y' IS THE SIGN OF
XXXXX XXX YXXX.XXXXX,	THE PREC VOLT VALUE.
XXXXX XXX YXXX.XXXXX.	IT MUST BE EITHER
XXXXX XXX YXXX.XXXXX,	'+' OR '-'.
XXXXX YXX YXXX.XXXXX, (PRESS EOF KEY)	

CO24 PID 22-CD 06 ENTER DECIMAL ADDRESS AND WD CTS FOR THE AIIAT TBL.

EACH MPX ADDRESS IS FOLLOWED BY A WORD COUNT TO
DETERMINE THE LENGTH OF THE SEQUENTIAL TABLE. A
MAXIMUM OF FIVE SEQUENTIAL TABLES MAY BE CHAINED
TOGETHER TO A TOTAL WORD COUNT OF 150.

THE INPUT MUST FOLLOW THIS FORMAT. FROM 1-5
LINES MAY BE ENTERED. A 1 IN THE HIGH ORDER
POSITION OF THE MPX ADDRESS INDICATES A SOLID
STATE POINT. PRESS THE EOF KEY AFTER THE LAST
LINE.

```
ADDR  WD CT
XXXXX XXX,
XXXXX XXX,
XXXXX XXX,
XXXXX XXX,
XXXXX XXX ( PRESS EOF KEY)
```

CO25 PID 23-CDS 2,4,5 ENTER DECIMAL ADR, RESOL AND RANGE.

THE INPUT MUST FOLLOW THIS FORMAT. FROM 1-5
LINES MAY BE ENTERED. SEE MESSAGE CO22 FOR
RANGE TABLE A 1 IN THE HIGH ORDER POSITION OF
MPX ADDRESS INDICATES A SOLID STATE POINT.
PRESS THE EOF KEY AFTER THE LAST LINE.
A 1 IN THE HIGH ORDER POSITION OF THE MPX ADDR
INDICATES A SOLID STATE POINT. PRESS THE EOF
AFTER THE LAST LINE.

```
ADDR  RES RANGE
XXXXX XX XXX,
XXXXX XX XXX,
XXXXX XX XXX,
XXXXX XX XXX,
XXXXX XX XXX  (PRESS EOF KEY )
```

CO26 PID 23-CDS 2-5 ENTER DECIMAL ADR, RESOL, RANGE, PREC VOLT.

THE INPUT MUST FOLLOW THIS FORMAT. FROM
1-5 LINES MAY BE ENTERED. SEE MESSAGE
CO22 FOR RANGE TABLE. A 1 IN THE HIGH
ORDER POSITION OF THE MPX ADDRESS INDICATES
A SOLID STATE POINT. PRESS THE EOF KEY
AFTER THE LAST LINE.

ADDR RES RANGE PREC VOLT VALUE	NOTE
XXXXX XX XXX YXXX.XXXXX,	'Y' IS THE SIGN
XXXXX XX XXX YXXX.XXXXX,	OF THE PREC VOLT
XXXXX XX XXX YXXX.XXXXX,	VALUE. IT MUST
XXXXX XX XXX YXXX.XXXXX,	BE EITHER '+'
XXXXX XX XXX YXXX.XXXXX (PRESS EOF KEY)	OR '-'

CO27 PID 23-CD 06 IS RANDOM MODE DESIRED-TYPE Y OR N.

CO28 PID 23-CD 08 ENTER 1 DIGIT WD COUNT FROM 1 TO 5.

A NUMBER FROM 1-5 IS ENTERED TO
INDICATE THE NUMBER OF MULTIPLEX
ADDRESSES IN THE AIMPX TABLE TO BE USED.

CO29 PID 24-CD 00   ENTER 2 DIGIT DECIMAL NUMBER OF DIGITAL INPUT
                     GROUPS ON THE SYSTEM.

                     (01-24)

CO2A PID 25-CD 00   ENTER 3 DIGIT DECIMAL NUMBER OF HIGHEST DIGITAL
                     INPUT ADRS AVAILABLE ON THIS SYSTEM.

                     (064-127)

CO2B PID 25-CD 00   ARE PISW ENTRIES DESIRED-TYPE Y OR N.

CO2C PID 25-CD 00   ENTER DESIRED IL ILSW FOR PISWS-1 TO 24 ENTRIES
                     IN FOLLOWING FORMAT
                     DD DD,.

CO2D PID B6-CD 00   ENTER 2 DIGIT HEX MODIFIER FOR 2ND 1442.

CO2E PID B6-CD 00   IS MAG TAPE DR A 2402-TYPE Y OR N.

CO2F PID B9-CD 00   ENTER 1 DIGIT DECIMAL MODEL OF DRIVE W-TYPE
                     1, 2 OR 3.

CO30 PID BD-CD 00   NO DR HAS BEEN EDITED AS A 9 TRK DRIVE-
                     THIS PROG THEREFORE IS ILLEGAL TO RUN ON
                     THIS SYSTEM-DO YOU DESIRE TO CHANGE ENTRIES-
                     TYPE Y OR N.

CO31 PID BE-CD 00   IS A WORD COUNT OTHER THAN 321 DESIRED-TYPE
                     Y OR N.

CO32 PID BE-CD 00   ENTER 4 DIGIT DECIMAL WORD COUNT.

CO33 PID BE-CD 00   THE WORD COUNT ENTERED WILL FORCE DSW ERRORS
                     DURING THE PROGRAM RUN-IS THIS DESIRED-TYPE
                     Y OR N.

CO34 PID BE-CD 00   IS A PATTERN OTHER THAN FFFF DESIRED-TYPE Y OR N.

CO35 PID BE-CD 00   ENTER 4 DIGIT HEX PATTERN DESIRED.

CO36 PID 06-CD 00   IS THE ABOVE ID NUMBER FOR VVVV-TYPE Y OR N.

CO37 PID 06-CD 00   ENTER 1 DIGIT TYPEWRITER ID NUMBER 1-8.

CO38 PID 0A-CD 00   DOES 1443 HAVE 120 PRINT POSITIONS-TYPE Y OR N.

4.3 ERROR MESSAGES WILL BEGIN WITH AN E AND INDICATE A FAILURE OR AN
     INCORRECT ENTRY. FOR ERROR CORRECTION SEE SECTION 3.7.

MID   PROG   MESSAGE

E001   LINE CANCELLED.

     ALL THE DATA ENTERED HAS BEEN ERASED FOR THE LAST ENTRY UNLESS
     MULTIPLE ENTRIES AND THEN IT WILL BE ERASED TO THE LAST COMMA.
     THE LINE WITH THE ERROR WILL CONTAIN THREE ASTERISKS.

E002 CNTRL   ENTRY TOO LARGE.

     THE DATA ENTERED WAS LARGER THAN THE LIMITS FOR A GIVEN
     CONDITION. THE QUESTION WILL BE REPEATED.

E003 CNTRL   ILLEGAL ENTRY.

     THE DATA ENTERED WAS NOT REQUESTED. SOMETHING OTHER THAN
     Y OR N ON TYPE Y OR N, OTHER THAN 0-9 ON DECIMAL ENTRY, OR
     OTHER THAN 0-9 A-F ON HEX ENTRY.

E004 CNTRL   FORMAT ERROR.

     THE DATA ENTERED WAS NOT IN THE PROPER FORMAT. THE QUESTION
     WILL BE REPEATED.

E005 CNTRL   1442 ERROR.

     THE 1442 WAS NOT READY OR AN ERROR WAS DETECTED.

E006 PID XX-CD ZZ 2 OR MORE ENTRIES ARE IDENTICAL.

E007 PID XX-CD ZZ ENTRY TOO LARGE OR 0000.

E008 PID XX-CD 00 ADRS WAS BETWEEN 90 AND 110.

E009 PID XX-CD 00 NUMBER OF DEVICES WAS GREATER THAN 3.

E00A PID XX-CD ZZ ADRS IS TOO GREAT.

E00B PID XX-CD 00 NUMBER OF DEVICES WAS 0000.

E00C PID XX-CD 00 ILLEGAL TIMER CONSTANT.

E00D PID XX-CD 00 ILLEGAL MODEL.

E00E PID XX-CD ZZ CYCLE COUNT OF 0000.

E00F PID XX-CD ZZ AREA CODE WAS TOO LARGE.

E010 PID XX-CD ZZ IMPROPER NUMBER OF WDS.

                    TOO MANY LINES OF DATA OR TOO MANY OR
                    TOO FEW CHARACTERS PER LINE WERE ENTERED.

E011 PID XX-CD ZZ TOO MANY WORDS ON ONE CARD.

                    THIS PRINTOUT WILL OCCUR ONLY IF A
                    COMPARE INSTRUCTION IS FAILING TO SKIP.

E012 PID 0B-CD 00 TOO LARGE A WD CT-MAX IS 1000.

E013   NOT USED

E014   NOT USED

E015   NOT USED

E016 PID 21-CD 00 HIGH VALUE LESS THAN LOW.

                    THE HIGH PRIORITY CHANNEL ENTERED IS
                    GREATER THAN THE LOW.

E017 PID 21-CD 18 ILLEGAL WD CT.

                    WORD COUNT ENTERED WAS ZERO OR GREATER THAN 100

E018 PID 21-CD 06   MORE THAN 2 RLY PTS.

                    MORE THAN 2 RELAY POINTS WERE ENTERED.

E019 PID 21-CD 06   MOD 2 AND MORE THAN 1 RLY PT.

E01A PID 21-CD 06   RLY PT IN LAST ADRS-AIIAT TBL.

E01B PID 21-CD 06   LESS THAN 95 SS PTS BETWEEN RLY PT.

E01C PID 21-CD 06   WD CT IS GREATER THAN NUMBER OF AIIAT ENTRIES.
E01D PID 21-CD 10   ENTRIES DO NOT MATCH.

                    SCANNED THE AIIAT TABLE WITHOUT FINDING AN
                    ADDRESS THAT WAS SPECIFIED IN THE AIMPX TABLE.
                    EITHER THE ADDRESS IS MISSING OR THE ADDRESSES
                    ARE NOT IN THE SAME SEQUENCE.

E01E PID 21-CD 10   LMT CK REQ WRONG.

              1.   LIMIT WORDS WERE ENTERED BUT COMPARATOR
                    WAS NOT INSTALLED.

              2.   LIMIT WORDS WERE ENTERED BUT OPERATOR
                    TYPED N IN REPLY TO MESSAGE C020.

                    IN BOTH CASES THE PROGRAM PUTS ZEROS IN
                    THE LIMIT WORD TABLE AND CONTINUES.

E01F PID 21-CD 10   ATTEMPTED TO LMT CK RLY ADR IN OVERLAP.

E020   NOT USED

E021 PID 22-CD 2-6 FOUND NO MATCH OF ADR AND AIIAT ENTRIES.
C027 PID 23-CD 06   IS RANDOM MODE DESIRED-TYPE Y OR N.

C028 PID 23-CD 08   ENTER 1 DIGIT WD COUNT FROM 1 TO 5.

                    THE WORD COUNT (AIWC) WENT TO ZERO BEFORE ALL
                    OF THE AIMPX ADDRESS WERE FOUND IN THE
                    AIIAT TABLE.

E022   NOT USED

E023 PID 22-CD 06   WD CT GREATER THAN 150.

E024 PID 22-CD 06   WD CTS IN AIIAT TBL ARE ALL 0000.

E025 PID 23-CD 08   ENTRY WAS 0000 OR GREATER THAN 5.

E026 PID 23-CD 2-8 WD CT IS GREATER THAN NUMBER OF AIMPX ENTRIES.

E027 PID 24-CD 00   NUMBER OF GROUPS ENTERED WAS TOO GREAT.

                    CANNOT BE MORE THAN 64 GROUPS.

E028 PID 25-CD 00   ADRS ENTERED WAS GREATER THAN 127.

E029   NOT USED

E02A PID 25-CD 00   ADRS ENTERED WAS LESS THAN 64.

E02B PID B6-CD 00   ILLEGAL MODIFIER.

E02C PID B9-CD 00   ENTRY WAS GREATER THAN 3.

5. COMMENTS

    THE SKELETONS FOR THE PID REQUESTED MUST BE LOADED BEHIND THE PROGRAM.
    (SEE SECTION 3.2 FOR SKELETON SELECTION) IF THE SELECTED SKELETON
    IS NOT FOUND THE PROGRAM WILL HANG UP IN THE LOADER AFTER SEARCHING ALL
    AVAILABLE SKELETONS. WHEN THE FIRST SKELETON OF THE SELECTED PID
    IS FOUND IT IS LOADED INTO MEMORY. IF THIS IS THE 4K EDIT CONTROL
    PROGRAM (PID 08C2) THE SKELETONS WILL BE BROUGHT INTO MEMORY ONE AT A
    TIME, EACH ASKING ITS QUESTIONS. THE 8K EDIT CONTROL PROGRAM (PID 08C3)
    WILL BRING IN ALL SKELETONS BELONGING TO THE SELECTED PID.

    AFTER ALL THE NECESSARY DATA FOR THE SELECTED PID HAS BEEN RECEIVED
    THE CARD READER WILL PASS ANY PUNCHED CARDS AND WHEN BLANK CARDS ARE
    FOUND BEGIN PUNCHING THE EDIT CARDS. IF THE PAPER TAPE VERSION IS
    USED THE PUNCH WILL START AS SOON AS THE NECESSARY DATA HAS BEEN
    RECEIVED. AFTER PUNCHING HAS BEEN COMPLETED THE PROGRAM LISTS THE
    EDIT INFORMATION FOR A RECORD.

    MOST ERRORS THAT ARE FOUND BY THE PROGRAM WILL BE CORRECTED AT THE
    TIME THE DATA IS REQUESTED. IN THE 4K EDIT CONTROL PROGRAM IF THE
    CORRECTION CAN NOT BE ACCOMPLISHED AT THE TIME OF ENTRY, A MESSAGE OCCURS
    INDICATING THE PROGRAM AND SKELETONS MUST BE RELOADED OR PRESS START TO
    IGNORE THE ERROR AND MAKE THE CORRECTION MANUALLY AFTER THE EDIT INFORMATION
    HAS BEEN PUNCHED AND PRINTED. IN THE 8K EDIT CONTROL PROGRAM IT
    REINITIALIZES ALL SKELETONS AND CONTINUES FROM THE POINT OF ERROR.

    ONLY ONE PID MAY BE EDITED AT A TIME AND IF A SECOND EDITING IS
    REQUIRED SEE SECTION 3.5 FOR RERUN OR RESTART.

6. PROGRAMMERS GUIDE TO EDIT CONTROL USAGE

    6.1 PURPOSE

         IT IS THE INTENT OF THIS DOCUMENTATION TO SPECIFY HOW THE PROGRAMMER
         CAN TAKE ADVANTAGE OF COMMON ROUTINES WHEN WRITING SKELETONS TO RUN WIT
         EDIT CONTROL PROGRAM. EDIT CONTROL PROVIDES,

         1.   SHARING OF PREDEBUGGED COMMON ROUTINES.
         2.   INTERFACE BETWEEN SKELETON AND I/O DEVICES.
         3.   SEQUENCING OF SKELETON OPERATION WHEN SEVERAL SKELETONS ARE
              REQUIRED.
         4.   COMMON BLOCKS OF STORAGE FOR MULTIPLE USE.

    6.2 RESERVED AREAS OF STORAGE

         A.   'KEYIN'

              THIS IS A BLOCK OF 600 WORDS USED TO STORE KEYBOARD ENTRIES AS
              THEY ARE RECEIVED. AT LOCATION 'KEYIN-1' IS A COUNT OF THE WORDS
              STORED IN 'KEYIN'. THIS BLOCK OF DATA AND THE WORD COUNT IS
              CLEARED BY CALL ON THE ROUTINE 'KEY.' A TERMINATOR WORD OF /FFFF
              IS SET AS THE LAST WORD IN 'KEYIN' WHENEVER THE EOF KEY IS
              DEPRESSED FOLLOWING ANY KEYBOARD CODE. THIS AREA MAY BE USED AS
              TEMPORARY STORAGE BY SKELETONS BETWEEN CALLS ON THE ROUTINE 'KEY'

         B.   'BINARY'

              A BLOCK OF 160 WORDS USED TO STORE CONVERTED DATA. THIS DATA
              WILL BE EITHER DECIMAL OR HEXADECIMAL DEPENDING ON THE CONVERSION
              ROUTINE LAST USED BY THE SKELETON. A COUNT OF THE NUMBER OF
              WORDS CURRENTLY STORED IS CONTAINED IN LOCATION 'BINARY-1.'

C. 'ZERO'

THIS LOCATION CONTAINS A CONSTANT OF ZERO.

D. 'TERM'

THIS LOCATION CONTAINS A CONSTANT OF /FFFF.

E. 'STBF'

THIS STORAGE LOCATION CONTAINS THE DISPLACEMENT OF THE NEXT
LOCATION AVAILABLE IN THE BLOCK OF CORE LABELED 'SEIB.' 'STBF'
WILL BE PROPERLY UPDATED BY CONTROL IF EDIT CARDS ARE STORED IN
CARD ORDER. IF IT IS DESIRED TO BUILD EDIT CARDS OUT OF SEQUENCE,
THEN 'STBF' MUST BE MAINTAINED BY THE SKELETON USER.

F. 'SEIB'

A BLOCK OF 322 WORDS USED FOR SAVING EDIT CARDS. THIS BLOCK MAY
NOT BE REFERENCED DIRECTLY BY THE SKELETON. HOWEVER, IT MAY
BE REFERENCED THRU LABEL 'SRTRY+1' TO +323. THE NEXT AVAILABLE
LOCATION MAY BE FOUND BY REFERENCE TO THE DISPLACEMENT CONSTANT
CONTAINED IN LOCATION 'STBF.'

G. 'SRTRY'

THIS LOCATION SHOULD ALWAYS CONTAIN THE RETURN ADDRESS TO BE
REFERENCED BY ROUTINE 'SER' IN CASE OF AN ERROR. THIS LOCATION
MAY BE SET EITHER BY A DIRECT STORE OR BY A CALL ON ROUTINE
'SSUER.'

6.3 ROUTINES AVAILABLE IN EDIT CONTROL

THE FOLLOWING IS A DESCRIPTION OF THE ROUTINES AVAILABLE AND THE CALL
NECESSARY TO USE THE ROUTINE.

A. 'CKYN' - CHECK KEYBOARD ENTRY FOR Y OR N.

```
BSI  I  CKYN
RETURN 1.
RETURN 2.
```

THE ROUTINE WILL CHECK THE KEYBOARD ENTRY STORED AT LOCATION
'KEYIN' FOR Y OR N. IF THE ENTRY IS Y, THE ROUTINE WILL RETURN
TO RETURN 1. IF THE ENTRY IS N, THE ROUTINE WILL RETURN TO
RETURN 2. THE ROUTINE WILL ACCEPT EITHER THE UPPER OR LOWER CASE
ENTRY FOR THE Y AND N KEYS. IF THE ENTRY IS NEITHER Y OR N
A CALL IS MADE ON ROUTINE 'SER' TO PRINT 'ILLEGAL ENTRY.'

B. 'ENDO' - END STATEMENT RETURN

```
END1  BSC  L  ENDO
      END     END1
```

IN ORDER TO PREVENT RELOCATION ERRORS DURING ASSEMBLY, EACH
SKELETON MUST END WITH THE ABOVE TWO STATEMENTS. THE END
STATEMENT WILL THEN GO TO LABEL 'END1' WHICH WILL BRANCH TO THE
EDIT CONTROL PROGRAM AFTER LOADING OF EACH SKELETON.

C. 'HLT' - RELOAD WAIT

```
BSI  I  HLT
```

BRANCH TO A WAIT WITHIN THE EDIT CONTROL PROGRAM. THIS WAIT MUST
BE USED WHEN AN ERROR REQUIRING RELOAD IS ENCOUNTERED.

D. 'KTYPS' - PRINT WITH NO CONVERSION

```
BSI  I  KTYPS
```

TILT CODE. THE MESSAGE ADDRESS MUST BE CONTAINED IN INDEX
REGISTER 1. PRINTING IS TERMINATED WHEN /FFFF IS FOUND.

E. 'KEY' - PRINT EBCDIC AND READ KEYBOARD

```
BSI  I  KEY
DC      MESSAGE ADDRESS
DC      CONTROL WORD
```

ADDRESS PRINTING CONTINUES UNTIL /FFFF IS FOUND. IF MESSAGE
ADDRESS POINTS TO A /FFFF, NO PRINTING WILL TAKE PLACE.

AFTER PRINTING, BIT 0 OF THE CONTROL WORD IS CHECKED FOR
THE FOLLOWING.

```
BO - 0 -   RETURN WITHOUT READING KEYBOARD
   - 1 -   READ THE KEYBOARD UNTIL EOF IS DEPRESSED.
```

BITS 6 AND 7 OF CONTROL WORD.

```
00 -   STORE KEYBOARD ENTRIES IN 'KEYIN' AREA WITH NO
       CONVERSION.

01 -   CONVERT KEYBOARD CHARACTERS RECEIVED (AS
       SPECIFIED BY BITS 8-11) TO DECIMAL AND STORE IN
       'BINRY' AREA.

10 -   CONVERT KEYBOARD CHARACTERS RECEIVED (AS
       SPECIFIED BY BITS 8-11) TO HEXADECIMAL AND STORE
       IN 'BINRY' AREA.
```

BITS 8-11 OF CONTROL WORD

WITH NO CONVERSION THIS IS THE MINIMUM NUMBER OF CHARACTERS
TO ACCEPT.

WITH COVERSION, THIS IS THE NUMBER OF KEYBOARD CHARACTERS TO
CONVERT TO ONE DECIMAL OR HEXADECIMAL WORD.

F. 'SSUER' - SET ERROR RETURN

```
BSI  I  SSUER
```

STORE THE ADDRESS OF THE CALL IN LOCATION 'SRTRY' FOR POSSIBLE
LATER USE BY ROUTINE 'SER.'

G. 'SER' - PRINT ERROR MESSAGE

```
BSI  I  SER
DC      MESSAGE ADDRESS
```

PRINT THE MESSAGE SPECIFIED BY MESSAGE ADDRESS AND RETURN TO THE
ADDRESS CONTAINED IN LOCATION 'SRTRY.' MESSAGE IS TERMINATED BY
/FFFF.

H.   'SIL' - CHECK FOR VALID INTERRUPT LEVEL

          BSI I SIL

     CHECKS THE DECIMAL ENTRY STORED AT LOCATION 'BINRY' FOR A VALID
     INTERRUPT LEVEL. IF THE ENTRY IS VALID, THE ROUTINE RETURNS
     WITH THE ENTRY IN THE A REGISTER IN BITS 0 THROUGH 7. IF THE
     ENTRY IS GREATER THAN 23, THIS ROUTINE WILL CALL ON ROUTINE
     'SER' TO PRINT 'ENTRY TOO LARGE'.

I.   'SILSW' - CHECK FOR VALID ILSW BIT

          BSI I SILSW

     CHECKS THE DECIMAL ENTRY STORED AT LOCATION 'BINRY' FOR A VALID
     ILSW BIT. IF THE ENTRY IS VALID, THE ROUTINE RETURNS WITH THE
     ENTRY IN THE A REGISTER IN BITS 8 THROUGH 11. IF THE ENTRY IS
     GREATER THAN 15, A CALL IS MADE ON ROUTINE 'SER' TO PRINT
     'ENTRY TOO LARGE'.

J.   'SCH' - CHECK FOR VALID CHANNEL

          BSI I SCH

     CHECKS THE HEXADECIMAL ENTRY STORED AT LOCATION 'BINRY' FOR A
     VALID CHANNEL. IF THE ENTRY IS VALID, THE ROUTINE RETURNS WITH
     THE ENTRY IN THE A REGISTER IN BITS 12 THROUGH 15. IF THE ENTRY
     IS GREATER THAN 8 AND IS NOT F, A CALL IS MADE ON ROUTINE 'SER'
     TO PRINT 'ENTRY TOO LARGE'.

K.   'SKINO' - CLEAR KEYIN AREA

          BSI I SKINO

     CLEARS THE BLOCK OF CORE LABELED 'KEYIN' TO ALL ZEROS.

L.   'SKINI' - SET KEYIN AREA

          BSI I SKINI

     SETS THE BLOCK OF CORE LABELED 'KEYIN' TO /FFFF.

M.   'PDKYB' - CONVERT KEYBOARD TO DECIMAL

          BSI I PDKYB
          DC   CHARACTERS PER WORD
          DC   ADDRESS OF DISPLACEMENT

     STARTING AT LOCATION 'KEYIN' + THE CONTENTS OF DISPLACEMENT
     ADDRESS, THIS ROUTINE WILL CONVERT TO ONE DECIMAL WORD THE NUMBER
     OF KEYBOARD CHARACTERS SPECIFIED BY CHARACTERS PER WORD. CONVER-
     SION WILL CONTINUE UNTIL A TERMINATOR OF /FFFF IS FOUND.

N.   PHKYB' - CONVERT KEYBOARD TO HEXADECIMAL

          BSI I PHKYB
          DC   CHARACTERS PER WORD
          DC   ADDRESS OF DISPLACEMENT

     THIS ROUTINE IS IDENTICAL TO ROUTINE 'PDKYB' EXCEPT THAT THE
     CONVERSION IS TO HEXADECIMAL.

O.   'SECSU' - SET EDIT CARD

          BSI I SECSU
          DC   ADDRESS OF DATA

     INDEX REGISTER 1 MUST CONTAIN PID.
     INDEX REGISTER 2 MUST CONTAIN CARD NUMBER.
     INDEX REGISTER 3 MUST CONTAIN NUMBER OF ENTRIES.

     THIS ROUTINE WILL SET ONE COMPLETE EDIT CARD INTO LOCATION
     'SEIB + STBF.' THE CONTENTS OF 'STBF' WILL BE UPDATED BY THE
     ROUTINE TO THE NEXT AVAILABLE LOCATION AFTER THE EDIT CARD JUST
     STORED. 'STBF' MAY BE SET BY THE SKELETON IF IT IS DESIRED TO
     SET EDIT CARDS OUT OF SEQUENCE.

P.   'S2' - SKELETON EXIT

          BSC L S2

     THIS IS THE FINAL EXIT POINT, TO CONTROL, FOR EACH SKELETON. THE
     CONTROL SECTION WILL CHECK THE NEXT SKELETON FOR A TERM SKELETON,
     AND IF FOUND IT WILL PUNCH AND LIST THE EDIT CARDS. IF NOT FOUND
     THE NEXT SKELETON WILL BE ENTERED.

6.4 SKELETON REQUIREMENTS

     EACH SKELETON MUST BE PRECEEDED BY A SERIES OF EQUATE STATEMENTS. (SEE
     SECTION 6.6). THE SKELETONS MUST BE RELOCATABLE AND THE ORIGIN
     STATEMENT MUST BE TO *+3095. NO SKELETON MAY EXCEED 1000 WORDS AND
     TOTAL SKELETONS FOR ANY ONE PID MUST NOT EXCEED 5000 WORDS.
     THE FIRST THREE WORDS OF EACH SKELETON ARE RESERVED FOR PID,
     CARD NUMBER AND NUMBER OF ENTRIES. THE FOURTH WORD MUST
     BE THE ENTRY POINT OF THE SKELETON . THESE FIRST FOUR
     WORDS MUST BE LABELED SKI1, SKI2, SKI3, AND SKI4. (SEE SECTION 6.7).
     EACH SKELETON MUST END AS EXPLAINED UNDER 'ENDO'. SECTIONS 6.6, 6.7,
     AND 6.8 CONTAIN A SAMPLE PROGRAM WHICH CAN BE USED FOR REFERENCE.
     MESSAGES AS SHOWN IN THE SAMPLE PROGRAM ARE IN STANDARD FORMAT AND THIS
     FORM SHOULD BE FOLLOWED. STANDARD MESSAGES PRESENTLY IN THE DOCUMENTA-
     TION SHOULD BE USED WHENEVER POSSIBLE TO PREVENT DOCUMENTATION CHANGES.

6.5 COMMENTS

     ANY LABELS CONTAINED IN THE EQUATE STATEMENTS NOT EXPLAINED ABOVE ARE
     SPECIALIZED ROUTINES USED EXCLUSIVELY BY THE AI EDIT SKELETONS AND NEED
     NOT CONCERN THE USER.

DATE   04NOV66
EC NO. 415233

PROG ID 08C2-*
PAGE   8

DATE   04NOV66
EC NO. 415233

PROG ID 08C2-*
PAGE   8A

6.6 EQUATE STATEMENTS

```
                ORG     *+3095
        KEY     EQU     300
        CKYN    EQU     KEY+1
        SSUER   EQU     CKYN+1
        SIL     EQU     SSUER+1
        SILSW   EQU     SIL+1
        SCH     EQU     SILSW+1
        SER     EQU     SCH+1
        SECSU   EQU     SER+1
        SKIN1   EQU     SECSU+1
        SKINO   EQU     SKIN1+1
        PDKYB   EQU     SKINO+1
        PHKYB   EQU     PDKYB+1
        ENDO    EQU     PHKYB+1
        S2      EQU     ENDO+2
        BINRY   EQU     S2+4
        KEYIN   EQU     BINRY+161
        ZERO    EQU     KEYIN+600
        BGNR    EQU     ZERO+1
        ERR     EQU     BGNR+1
        WCC     EQU     ERR+1
        MTRM    EQU     WCC+1 -
        TRFX    EQU     MTRM+1
        TERM    EQU     TRFX+1
        LWC     EQU     TERM+1
        LGROP   EQU     LWC+1
        STBF    EQU     LGROP+1
        SRTRY   EQU     STBF+1
        KYTPS   EQU     SRTRY+323
        HLT     EQU     KYTPS+1
        CODE    EQU     HLT+1
```

6.7 PROGRAM SECTION

```
        SKI1    DC      /000B           PID
        SKI2    DC      /0000           CD NO
        SKI3    DC      /0002           NO OF ENTRIES
        SKI4    BSI  I  SSUER           SET ERROR RETURN      SRC
                BSI  I  KEY             ENTER IL              SRC
                DC      SM1
                DC      /8120
    *
                BSI  I  SIL             CK IL
                STO  L  SWB1            SAVE                  SRC
    *
                BSI  I  SSUER           SET ERROR RETURN      SRC
                BSI  I  KEY             ENTER ILSW            SRC
                DC      SM2
                DC      /8120
    *
                BSI  I  SILSW           CK ILSW BIT           SRC
                EOR  L  SWB1            BUILD DDEF
                STO  L  SWB1            SAVE
    *
                BSI  I  SSUER           SET ERROR RETURN      SRC
                BSI  I  KEY             ENTER CH              SRC
                DC      SM3
                DC      /8210
    *
                BSI  I  SCH             CK CHANNEL            SRC
                EOR     SWB1            BUILD DDEF
                STO     SWB1            SAVE
    *
                BSI  I  SSUER           SET ERROR RETURN      SRC
                BSI  I  KEY             2 DRS ON SYS          SRC
```

```
                DC      SM4
                DC      /8000
    *
                BSI  I  CKYN            CK FOR Y OR N         SRC
                MDX     SK1             ENTRY WAS Y
    *
                LD      K0001           GET 1
                STO     SWB2            SET NOT AVAIL
                MDX     SK2
    *
        SK1     SLA     16              SET AVAIL
                STO     SWB2
    *
        SK2     LDX  I1 SKI1            SET IXING
                LDX  I2 SKI2
                LDX  I3 SKI3
    *
                BSI  I  SECSU           SET CARD             SRC
                DC      SWB1
    *
                BSI  I  SSUER           SET ERROR RETURN     SRC
                BSI  I  KEY             ARE WD CT CHGS DES    SRC
                DC      SM5
                DC      /8000
    *
                BSI  I  CKYN            CK FOR Y OR N         SRC
                MDX     SK3             ENTRY WAS Y
                MDX     SK4             ENTRY WAS N
    *
        SK3     LDX  I1 SKI1            SET IXING
                LDX  I2 SKI5
                LDX  I3 SKI6
    *
                BSI  I  SECSU           SET CARD             SRC
                DC      SWB3
    *
                BSC  L  S2              EXIT
    *
        SK4     BSI  I  SSUER           SET ERROR RETURN     SRC
                BSI  I  KEY             ENTER REC WD CT,      SRC
                DC      SM6
                DC      /8040
    *
                LD   L  KEYIN-1         GET WD CT
                CMP     K0056           CK FOR MAX
                MDX     SKE01           ERROR-TOO MANY
                NOP     0
                LDX  L1 KEYIN           SET IX
        SK5     LD   L  0               GET ENTRY
                STO  L  KEYIN           SET
                LD   L  TERM            GET FFFF
                STO  L  KEYIN+1         SET
                BSI  I  PDKYB           CONVERT              SRC
                DC      1
                DC      ZERO
                LD   L  BINRY           GET REC NO
                BSC  L  SKE05,+-        ERROR
                CMP     K0008           CK FOR MAX
                MPX     SKE04           TOO GREAT
                NOP     0
                STO     SK6+1           SET
        SK6     LDX  L3 0               IX 3 = ENTRY
                MDX     1 2             INCR IX 1
                MDX  L  KEYIN-1,-2      DECR WD CT
                MDX     SK7
                BSI  I  SER             TOO FEW ENTRIES      SRC
                DC      SE001
```

```
        *
        SK7     LD    1 0              SET ENTRIES
                STO L KEYIN
                LD    1 1
                STO L KEYIN+1
                LD    1 2
                STO L KEYIN+2
                LD    1 3
                STO L KEYIN+3
                LD   L TERM
                STO L KEYIN+4
        *
                BSI I PDKYB            CONVERT            SRC
                DC    4
                DC    ZERO
                LD   L BINRY           CK NUMBER
                CMP   K1000
                MDX   SKE03            ERROR TOO GREAT
                NOP   0
                STO L3 SWB2            SAVE ENTRY
                MDX   1 5              INCR IX 1
                MDX  L KEYIN-1,-5      DECR WD CT
                MDX   S5               GET NEXT
                MDX   SK3              COMPLETE
        *
        K0001   DC    1                CONSTANTS
        K0056   DC    56
        K1000   DC    1000
        K0008   DC    8
        *
        SWB1    DC    0                DATA STORAGE
        SWB2    DC    0
        SWB3    DC    0
                DC    0
                DC    0
                DC    0
                DC    0
                DC    0
                DC    0
                DC    0
        *
        SKI5    DC    /0001            CD ONE
        SKI6    DC    /0008            NO OF ENTRIES
        *
        SKE01   BSI I SER              TOO MANY WD CTS    SRC
                DC    SE001
        *
        SKE03   BSI I SER              WD CT TOO GREAT    SRC
                DC    SE003
        *
        SKE04   BSI I SER              REC TOO GREAT      SRC
                DC    SE004
        *
        SKE05   BSI I SER              FLD WAS ZERO       SRC
                DC    SE004
        *
        SE001   EBC   .E010  PID OB-CD 00.
                EBC   . IMPROPER NUMBER .
                EBC   .OF WDS.
                DC    /FFFF
        *
        SE003   EBC   .E012  PID OB-CD 00.
                EBC   . TOO LARGE A WD C.
                EBC   .T-MAX IS 1000.
                DC    /FFFF
        *
        SE004   EBC   .E007  PID OB-CD 00.
                EBC   . ENTRY TOO LARGE .
```

```
                EBC   .OR 0000.
                DC    /FFFF
        *
        SM1     EBC   .C001  PID OB-CD 00.
                EBC   . ENTER 2 DIGIT DE.
                EBC   .CIMAL INTR LVL FOR.
                EBC   . MAG TAPE.
                DC    /FFFF
        *
        SM2     EBC   .C002  PID OB-CD 00.
                EBC   . ENTER 2 DIGIT DE.
                EBC   .CIMAL ILSW BIT FOR.
                EBC   . MAG TAPE.
                DC    /FFFF
        *
        SM3     EBC   .C003  PID OB-CD 00.
                EBC   . ENTER 1 DIGIT DE.
                EBC   .CIMAL CH FOR MAG T.
                EBC   .APE.
                DC    /FFFF
        *
        SM4     EBC   .C005  PID OB-CD 00.
                EBC   . DOES THIS SYSTEM.
                EBC   . HAVE 2 TAPE DRS-T.
                EBC   .YPE Y OR N.
                DC    /FFFF
        *
        SM5     EBC   .C015  PID OB-CD 01.
                EBC   . IS IT DESIRED TO.
                EBC   . CHANGE WD CTS-TYP.
                EBC   .E Y OR N.
                DC    /FFFF
        *
        SM6     EBC   .C016  PID OB-CD 01.
                EBC   . ENTER REC TO CHA.
                EBC   .NGE AND WD CT DESI.
                EBC   .RED, 1-8 ENTRIES I.
                EBC   .N FOLLOWING FORMAT.
                EDC   .$D DDDD,.
                DC    /FFFF
        END1    BSC  L ENDO
                END   END1
```

6.8 TERM SKELETON

```
                ORG      *+3095
        KEY     EQU      300
        CKYN    EQU      KEY+1
        SSUER   EQU      CKYN+1
        SIL     EQU      SSUER+1
        SILSW   EQU      SIL+1
        SCH     EQU      SILSW+1
        SER     EQU      SCH+1
        SECSU   EQU      SER+1
        SKIN1   EQU      SECSU+1
        SKINO   EQU      SKIN1+1
        PDKYB   EQU      SKINO+1
        PHKYB   EQU      PDKYB+1
        ENDO    EQU      PHKYB+1
        S2      EQU      ENDO+2
        BINRY   EQU      S2+4
        KEYIN   EQU      BINRY+161
        ZERO    EQU      KEYIN+600
        BGNR    EQU      ZERO+1
        ERR     EQU      BGNR+1
        WCC     EQU      ERR+1
        MTRM    EQU      WCC+1
        TRFX    EQU      MTRM+1
        TERM    EQU      TRFX+1
        LWC     EQU      TERM+1
        LGROP   EQU      LWC+1
        STBF    EQU      LGROP+1
        SRTRY   EQU      STBF+1
        KYTPS   EQU      SRTRY+323
        HLT     EQU      KYTPS+1
        CODE    EQU      HLT+1
        SKI1    DC       /000B
        SKI2    DC       /FFFF
        SKI3    DC       0
        SKI4    DC       0
        END1    BSC   L  ENDO
                END      END1
```

-- LAST PAGE --

```
028C                    ABS
                        ORG    /3001
                        *
                        *******************************************
3001 0 0772             DC     WAIT1+1    1816 IS OUT OF FORMS.      8C200010
                        *                 MAKE READY AND PRESS       8C200020
                        *                 START.                     8C200030
                        *******************************************  8C200040
3002 0 075C             DC     WAIT2+1    1816 IS HUNG IN BUSY.      8C200050
                        *                 RESTART IS REQUIRED.       8C200060
                        *******************************************  8C200070
3003 0 0983             DC     WAIT3+1    1442 IS NOT READY          8C200080
                        *                 BEFORE A READ.             8C200090
                        *                 MAKE READY AND PUSH        8C200100
                        *                 START.                     8C200110
                        *******************************************  8C200120
3004 0 098A             DC     WAIT4+1    1442 READ ERROR.           8C200130
                        *                 RELOAD CARDS AND           8C200140
                        *                 PUSH START TO RETRY.       8C200150
                        *******************************************  8C200160
3005 0 0BE7             DC     WAIT5+1    RELOAD REQUIRED TO         8C200170
                        *                 CORRECT ERROR-PRESS        8C200180
                        *                 START TO IGNORE.           8C200190
                        *******************************************  8C200210
3006 0 09D7             DC     WAIT6+1    1442 IS NOT READY          8C200220
                        *                 BEFORE A READ.  MAKE       8C200230
                        *                 READY AND PRESS START.     8C200240
                        *******************************************  8C200250
3007 0 09DE             DC     WAIT7+1    1442 PUNCH ERROR.          8C200260
                        *                 PRESS START TO RETRY.      8C200270
                        *******************************************  8C200280
3008 0 05E0             DC     WAIT8+1    END OF PROGRAM.            8C200290
                        *                 LOAD SKELTONS AND          8C200300
                        *                 PRESS START TO RERUN.      8C200310
                        *******************************************  8C200320
3009                    ORG    300                                   8C200330
0C17         SKI1  EQU  3095                                         8C200340
0C18         SKI2  EQU  SKI1+1                                       8C200350
0C19         SKI3  EQU  SKI2+1                                       8C200360
0C1A         SKI4  EQU  SKI3+1                                       8C200370
012C 0 05E7  KEY   DC   KEYE                                         8C200380
012D 0 077A  CKYN  DC   CKYNE                                        8C200390
012E 0 079A  SSUER DC   SSUEE                                        8C200400
012F 0 07A1  SIL   DC   SILE                                         8C200410
0130 0 07AF  SILSW DC   SILSE                                        8C200420
0131 0 07BA  SCH   DC   SCHE                                         8C200430
0132 0 07CB  SER   DC   SERE                                         8C200440
0133 0 07D5  SECSU DC   SECSE                                        8C200450
0134 0 0803  SKIN1 DC   KINI                                         8C200460
0135 0 080E  SKINO DC   KINO                                         8C200470
0136 0 0818  PDKYB DC   DKYB                                         8C200480
0137 0 0821  PHKYB DC   HKYB                                         8C200490
0138 00 4C800A94  ENDO  BSC  I  RDSK                                 8C200500
013A 00 4C0005B9  S2    BSC  L  END1                                 8C200510
013C 0 0000             DC   0                                       8C200520
                                                                     8C200530
                                                                     8C200540
                                                                     8C200550
                                                                     8C200560
                                                                     8C200570
                                                                     8C200580
                                                                     8C200590
                                                                     8C200600
                                                                     8C200610
                                                                     8C200620
                                                                     8C200630
                                                                     8C200640
                                                                     8C200650
                                                                     8C200660
                                                                     8C200670
                                                                     8C200680
```

```
013D 0 0000  BWC   DC   0        BINARY WORD COUNT               8C200690
013E   00A0  BINRY BSS  160                                      8C200700
             *******************************************         8C200710
01DE 0 0000  KIWC  DC                                            8C200720
01DF   0258  KEYIN BSS  600                                      8C200730
             *******************************************         8C200740
0437 0 0000  ZERO  DC   /0000                                    8C200750
0438 0 0AB4  BGNR  DC   LBGNR                                    8C200760
0439 0 0AC1  ERR   DC   LERR                                     8C200770
043A 0 0AC5  WCC   DC   LWCC                                     8C200780
043B 0 0ACD  MTRM  DC   LMTRM                                    8C200790
043C 0 0AE5  TRFX  DC   LTRFX                                    8C200800
043D 0 FFFF  TERM  DC   /FFFF                                    8C200810
043E 0 0000  LWC   DC            WC STORAGE                      8C200820
043F 0 0000  LGROP DC            GROUP COUNTER                   8C200830
0440 0 0000  STBF  DC   0        DISPLACEMENT                    8C200840
0441 0 0000  SRTRY DC   /0000                                    8C200850
             *                                                   8C200860
             *                                                   8C200870
             *********  EDIT IMAGE BUFFER *********               8C200880
0442 0 0000  SEIB  DC   /0000                                    8C200890
0443   0141        BSS  321                                      8C200900
0584 0 0768  KTYPS DC   KTYP                                     8C200910
0585 0 0BE5  HLT   DC   HLTE                                     8C200920
0586 0 0A69  CODE  DC   KTILT                                    8C200930
0588   0000        BSS  E  0                                     8C200940
0588 00 4C00058B  SRST  BSC  L  START      RESTART               8C200950
                   *                       CONTROL SECTION       8C200960
058A 0 1000  STARI NOP  0                                        8C200980
058B 00 C40005E2  START LD   L  K3095      SET LDR CONSTANTS     8C201000
058D 00 D400006F        STO  L  /006F      *                     8C201010
058F 00 D4000125        STO  L  /0125      *                     8C201020
0591 0 1010             SLA  16            *                     8C201030
0592 00 D4000127        STO  L  /0127      *                     8C201040
0594 00 D4000440        STO  L  STBF                             8C201050
             *                                                   8C201060
0596 0 C8F1             LDD     SRST       SET RESTART           8C201070
0597 00 DC000000        STD  L  /0000      *                     8C201080
0599 00 4480012E  S1    BSI  I  SSUER      SET ERROR RETURN  SRC 8C201090
059B 00 4480012C        BSI  I  KEY        REQ PID           SRC 8C201100
059D 0 0BBB             DC      SM2                               8C201120
059E 0 8220             DC      /8220                             8C201130
             *                                                   8C201140
059F 00 C400013E        LD   L  BINRY      GET PID REQUESTED     8C201150
05A1 00 B40005E6        CMP  L  K00FF                            8C201160
05A3 0 703F             MDX     ERRO4                             8C201170
05A4 0 1000             NOP  0                                    8C201180
05A5 0 D03B             STO     XPID       SAVE                   8C201190
             *                                                   8C201200
05A6 00 44000A94  S2E   BSI  L  RDSK       READ A SKELETON   SRC 8C201210
             *                                                   8C201220
05A8 0 C8DF             LDD     SRST       SET RESTART           8C201230
05A9 00 DC000000        STD  L  /0000      *                     8C201240
             *                                                   8C201250
05AB 00 C4000C17        LD   L  SKI1       GET PID READ          8C201260
05AD 00 F40005E1        EOR  L  XPID       IS IT DESIRED         8C201270
05AF 00 4C2005B9        BSC  L  END1,Z     NO                    8C201280
05B1 00 C4000C18        LD   L  SKI2       GET CD NO             8C201290
05B3 00 F400043D        EOR  L  TERM       IS IT TERM            8C201300
05B5 00 4C1805C3        BSC  L  STTRM,+-   YES                   8C201310
05B7 00 4C000C1A        BSC  L  SKI4       GO TO SKELTON         8C201320
             *                                                   8C201330
05B9 00 C40005E2  END1  LD   L  K3095      RESET LOADER CNSTS    8C201340
05BB 00 D400006F        STO  L  /006F      *                     8C201350
05BD 00 D4000125        STO  L  /0125      *                     8C201360
```

```
05BF 0  1010        SLA    16      •                        8C201370
05C0 00 D4000127    STO  L /0127    •                        8C201380
05C2 0  70E3        MDX    S2E      READ NEXT SKELTON        8C201390

05C3 00 C4000440  STTRM LD  L STBF   COMPUTE ADRS            8C201400
05C5 00 84000801    A    L STBF1     •                       8C201410
05C7 0  D001        STO    •+1       SAVE                    8C201420
05C8 00 65000000    LDX  L1 0                                8C201430
05CA 00 C4000C17    LD   L SKI1      GET PID                 8C201440
05CC 0  D100        STO  1  0                                8C201450
05CD 00 C400043D    LD   L TEPM      GET TERMINATION         8C201460
05CF 0  D101        STO  1  1        SET                     8C201470
05D0 00 44000907    BSI  L PECOR     PUNCH EDIT        SRC   8C201480
05D2 0  1010        SLA    16        CLEAR DISPL             8C201490
05D3 00 D4000440    STO  L STBF      •                       8C201500
                                                             8C201510
05D5 00 65000142    LDX  L1 322      CLEAR EDIT BFR          8C201520
05D7 00 D4000441  STTR STO L SEIB-1  •                       8C201530
05D9 0  71FF        MDX  1  -1                               8C201540
05DA 0  70FC        MDX    STTR                              8C201550
05DB 00 4480012C    BSI  I KEY       PROG END          SRC   8C201560
05DD 0  0BD1        DC     SM33                              8C201570
05DE 0  0000        DC     0                                 8C201580
                                                             8C201590
05DF 0  3008      WAIT8 WAIT 8       PROGRAM END             8C201600
05E0 0  70AA        MDX    START     RESTART PROG            8C201610
                                                             8C201620
05E1 0  0000      XPID  DC  0        CONSTANTS               8C201630
05E2 0  CC17      K3095 DC  3095                             8C201640
05E3 00 44800132  ERR04 BSI I SER                            8C201650
05E5 0  0BAD        DC     SE002                             8C201660
05E6 0  00FF      K00FF DC  /00FF                            8C201670
                                                             8C201680
                                                             8C201690
                                                             8C201700
                                   PRINTER I/O ROUTINE       8C201710
                                                             8C201720
                                   CALL  BSI   KEY           8C201730
                                         DC    MSGAD         8C201740
                                         DC    ID            8C201750
                                                             8C201760
                                   ID  BIT 0  KEYBOARD       8C201770
                                       X0XX   NO CONV        8C201780
                                       X1XX   DEC CONV       8C201790
                                       X2XX   HEX CONV       8C201800
                                                             8C201810
                                                             8C201820
05E7 0  0000      KEYE  DC  /0000                            8C201830
05E8 0  6941        STX  1 KEY96+1   SAVE STATUS             8C201840
05E9 0  6A42        STX  2 KEY97+1                           8C201850
05EA 0  6B43        STX  3 KEY98+1                           8C201860
05EB 00 DC000A22    STD  L KAQ                               8C201870
05ED 0  2843        STS    KEY99                             8C201880
                                                             8C201890
05EE 00 C48005E7    LD   I KEYE      FETCH MESS ADRS         8C201900
05F0 00 D4000A1C    STO  L KMSG                              8C201910
05F2 00 740105E7    MDX  L KEYE,1    POINT TO ID             8C201920
                                                             8C201930
05F4 00 65000A1D    LDX  L1 KOUT     SET CARRIER RETURN      8C201940
05F6 00 C4000A79    LD   L KCR                               8C201950
                                                             8C201960
05F8 0  1808        SRA    8         CLEAR EBDIC CODE        8C201970
05F9 0  1008        SLA    8                                 8C201980
05FA 0  D100        STO  1  0        STORE IN OUTPUT AREA    8C201990
                                                             8C20200C
05FB 00 C4800A1C  KEBC2 LD I KMSG    CHECK TERMINATOR        8C202010
05FD 00 84000A2C    A    L KONE                              8C202020
05FF 00 4C180621    BSC  L KCHK,+-   BR IF NO MORE MESS      8C202030
                                                             8C202040
```

```
                                   **********************************    8C202050
0601 0  6208        LDX  2  8                                8C202060
0602 00 67000A50  KEBC3 LDX L3 KTGLT  CONVERT-CHARS TO RTT   8C202070
0604 0  7101        MDX  1  1                                8C202080
0605 0  C4800A1C  KEBC4 LD  I KMSG    FETCH EBDIC CHARS      8C202090
0607 0  1A00        SRA  2  0                                8C202100
0608 0  1008        SLA    8                                 8C202110
0609 0  1808        SRA    8                                 8C202120
060A 0  F300        EOR  3  0                                8C202130
060B 0  D100        STO  1  0                                8C202140
060C 0  1008        SLA    8                                 8C202150
060D 0  7301        MDX  3  1                                8C202160
060E 00 4C200605    BSC  L KEBC4,Z   BR IF NOT THE CHAR      8C202170
                                                             8C202180
0610 0  7200        MDX  2  0        SKIP IF 2 CHARS CNVT    8C202190
0611 0  700D        MDX    KEBC6                             8C202200
                                                             8C202210
0612 00 C4000A2C    LD   L KONE      SET TERMINATOR          8C202220
0614 0  8100        A    1  0                                8C202230
0615 0  D100        STO  1  0                                8C202240
0616 00 65000A1D    LDX  L1 KOUT     GO PRINT CHARS          8C202250
0618 00 44000768    BSI  L KTYP                              8C202260
                                                             8C202270
061A 00 65000A1C    LDX  L1 KOUT-1                           8C202280
061C 00 74010A1C    MDX  L KMSG,1    POINT TO NEXT WORD      8C202290
061E 0  700C        MDX    KEBC2                             8C202300
                                                             8C202310
061F 0  6200      KEBC6 LDX 2 0      CONVERT SECOND CHAR     8C202320
0620 0  70E1        MDX    KEBC3                             8C202330
                                   **********************************    8C202340
                                                             8C202350
                                                             8C202360
0621 00 65000A79  KCHK  LDX L1 KCR                           8C202370
0623 00 44000768    BSI  L KTYP                              8C202380
0625 00 C48005E7    LD   I KEYE      DO CAR RET         SRC  8C202390
0627 00 4C280636    BSC  L KFRM,+Z   BR IF KBD ENTRY         8C202400
                                   **********************************    8C202410
                                                             8C202420
0629 00 65000000  KEY96 LDX L1 /0000   RESTORE STATUS        8C202430
062B 00 66000000  KEY97 LDX L2 /0000                         8C202440
062D 00 67000000  KEY98 LDX L3 /0000                         8C202450
062F 00 CC000A22    LDD  L KAQ                               8C202460
0631 0  2000      KEY99 LDS 0                                8C202470
                                                             8C202480
0632 00 740105E7    MDX  L KEYE,1                            8C202490
0634 00 4C8005E7    BSC  I KEYE      RETURN EXIT             8C202500
                                   **********************************    8C202510
                                                             8C202520
                                                             8C202530
0636 0  1090      KFRM  SLT 16       FETCH FORM NUMBER       8C202550
0637 00 C48005E7    LD   I KEYE                              8C202560
0639 0  1004        SLA    4                                 8C202570
063A 0  18CC        RTE    12                                8C202580
063B 00 D4000729    STO  L KEYFM     SAVE FORM NO            8C202600
063D 0  1804        SRA    4                                 8C202610
063E 0  1084        SLT    4                                 8C202620
063F 00 D400072A    STO  L KEYNO     SAVE CHAR/WD COUNT      8C202630
                                                             8C202640
0641 00 44800134  KEYOG BSI I SKIN1  SET KEYIN TO FFFF  SRC  8C202650
                                                             8C202660
0643 00 6F0001DE    STX  L3 KIWC     RESET WD CT             8C202670
                                                             8C202680
0645 00 670001DF    LDX  L3 KEYIN    RESET READ AREA         8C202690
                                                             8C202700
0647 00 6F000A2A  KEYO  STX L3 KRED                          8C202710
                                                             8C202720
```

```
0649 00 44000745        BSI  L  KNBY      WAIT FOR NOT BUSY        8C202730
                     *                                             8C202740
064B 00 0C000A28  KEY1  XIO  L  KPCD      SET KEYBOARD PROCEED     8C202750
                     *                                             8C202760
064D 00 0C000A1A  KEY2  XIO  L  KSNS      SENSE STATUS             8C202760
064F 0  1001           SLA     1                                  8C202770
0650 00 4C280656       BSC  L  KEY3,+Z    GO READ KEYBOARD         8C202790
                     *                                             8C202800
0652 0  1005           SLA     5                                  8C202810
0653 00 4C10064B       BSC  L  KEY1,-     BR IF NOT PROCEED        8C202820
0655 0  70F7           MDX     KEY2                                8C202830
                     *                                             8C202840
0656 00 0C000A2A  KEY3  XIO  L  KRED      READ KEYBOARD            8C202850
                                                                  8C202860
0658 0  610B     KFMS  LDX  1 11          CHECK FOR DEC OR SPC     8C202870
0659 0  C300     KFMS1 LD      3 KRED-KRED FETCH CHAR READ         8C202880
065A 00 F5000A33       FOR  L1 KECOD-1                            8C202890
065C 00 4C1806B3       BSC  L  KDEC,+-    BR IF DEC OR SPACE       8C202900
                     *                                             8C202910
065E 0  71FF           MDX     1 -1                                8C202920
065F 0  70F9           MDX     KFMS1                               8C202930
                                                                  8C202940
0660 00 C4000729       LD   L  KEYFM      CHECK FOR FORM           8C202950
0662 00 F4000A2C       EOR  L  KONE                                8C202960
0664 00 4C18067D       BSC  L  KFM0,+-    BRANCH IF FORM 1         8C202970
                 ****************************************          8C202980
0666 0  6106     KFM2  LDX  1 6           CHECK FOR HEX            8C202990
0667 0  C300     KFM21 LD      3 KRED-KRED FETCH CHAR READ         8C203000
0668 00 F5000A3E       EOR  L1 KECAD-1                            8C203010
066A 00 4C1806B6       BSC  L  KHEX,+-.   BR IF ALPHA              8C203020
                     *                                             8C203030
066C 0  71FF           MDX     1 -1                                8C203040
066D 0  70F9           MDX     KFM21                               8C203050
066E 0  C300           LD      3 KRED-KRED FETCH CHAR READ         8C203060
066F 00 F4000A31       EOR  L  KECPD                               8C203070
0671 00 4C20067D       BSC  L  KFM0,Z     BR IF NOT PERIOD         8C203080
0673 0  C3FC           LD      3 -4       A PLUS OR MINUS          8C203090
0674 0  6201           LDX  2 1                                    8C203100
0675 0  1240           SLCA 2 0                                    8C203110
0676 00 F4000B7F       EOR  L  K8000                               8C203120
0678 00 4420072D       BSI  L  KERR,Z     BR IF NOT + OR -         8C203130
067A 00 C4000A65       LD   L  KTPLT                               8C203140
067C 0  7022           MDX     KPNE                                8C203150
                     *                                             8C203160
                 ****************************************          8C203170
067D 0  6108     KFM0  LDX  1 8           CHECK UC SP CHRS         8C203180
067E 0  C300     KFM01 LD      3 0        GET CHR READ             8C203190
067F 00 F5000A2C       EOR  L1 KN-1       CK AGAINST TBL           8C203200
0681 00 4C1806A8       BSC  L  KMDX,+-    CHAR FOUND               8C203210
0683 0  71FF           MDX     1 -1       DECR IX 1                8C203220
0684 0  70F9           MDX     KFM01      LOOP                     8C203230
                     *                                             8C203240
0685 0  6107           LDX  1 7           CK LC SP CHRS            8C203250
0686 0  C300     KFM02 LD      3 0        GET CHR READ             8C203260
0687 00 F5000A47       EOR  L1 KAL-1      CK AGAINST TBL           8C203270
0689 00 4C1806B1       BSC  L  KMPX,+-    CHARACTER FOUND          8C203280
068B 0  71FF           MDX     1 -1       DECR IX 1                8C203290
068C 0  70F9           MDX     KFM02      LOOP                     8C203300
068D 0  C300           LD      3 0        GET CHR READ             8C203310
068E 00 F4000A21       EOR  L  KL                                  8C203320
0690 00 442006CC       BSI  L  KSPC,Z                              8C203330
                     *                                             8C203340
0692 0  6201           LDX  2 1                                    8C203350
0693 0  C3FA           LD      3 -6                                8C203360
0694 0  1002           SLA     2                                   8C203370
0695 0  1240           SLCA 2 0                                    8C203380
0696 00 F4000B7F       EOR  L  K8000                               8C203390
0698 00 4420072D       BSI  L  KERR,Z     BR IF NOT 1 OR ZERO      8C203400
```

```
                     *                                             8C203410
069A 0  C3FA           LD      3 -6                                8C203410
069B 0  1802           SRA     2                                   8C203420
069C 0  D3FA           STO     3 -6                                8C203430
069D 00 C4000A55       LD   L  KLRT                                8C203440
069F 00 EC000A2C  KPNE  OR   L  KONE                               8C203450
06A1 00 65000A1D       LDX  L1 KOUT                                8C203460
06A3 0  D100           STO  1 0                                    8C203470
06A4 00 44000768       BSI  L  KTYP                                8C203480
06A6 00 4C000647       BSC  L  KEYO       BRANCH                   8C203490
                     *                                             8C203500
06A8 0  C300     KMDX  LD      3 0        FETCH CHAR               8C203510
06A9 00 F4000A32       EOR  L  KECPD+1                             8C203520
06AB 00 4C2006B1       BSC  L  KMPX,7     BR IF NOT + SIGN         8C203530
06AD 0  C300           LD      3 0        MAKE + = /9000           8C203540
06AE 0  180C           SRA     12                                  8C203550
06AF 0  100C           SLA     12                                  8C203560
06B0 0  D300           STO     3 0                                 8C203570
06B1 0  7111     KMPX  MDX     1 KN-KECGD ADJ IX 1                 8C203580
06B2 0  7001           MDX     KDEC1                               8C203590
                     *                                             8C203600
                 ****************************************          8C203610
                     *                                             8C203620
06B3 0  7118     KDEC  MDX     1 KECOD-KECGD CORCT XR1             8C203630
                     *                                             8C203640
06B4 0  4003     KDEC1 BSI     KSTO       GO STORE + PRT    SRC    8C203650
                     *                                             8C203660
06B5 0  7091           MDX     KEYO       RETURN FOR NEXT          8C203670
                     *                                             8C203680
                     *                                             8C203690
06B6 0  7123     KHEX  MDX     1 KECAD-KECGD GO PRINT A - F        8C203700
06B7 0  70FC           MDX     KDEC1                               8C203710
                 ****************************************          8C203720
                     *                                             8C203730
                     *                    STORE AND PRINT RTN      8C203740
06B8 0  0000     KSTO  DC      /0000                               8C203750
06B9 0  C300           LD      3 0                                 8C203760
06BA 0  EBFF           OR      3 -1                                8C203770
06BB 0  1804           SRA     4                                   8C203780
06BC 00 4C9806B8       BSC  I  KSTO,+-    BR IF SECOND SPACE       8C203790
                     *                                             8C203800
06BE 00 C5000A4F       LD   L1 KTGLT-1    FETCH TYPR CHAR          8C203810
06C0 00 EC000A2C       OR   L  KONE                               8C203820
06C2 00 65000A1D       LDX  L1 KOUT                                8C203830
06C4 0  D100           STO  1 0                                    8C203840
06C5 00 44000768       BSI  L  KTYP       TYPE CHARACTER           8C203850
                     *                                             8C203860
06C7 00 740101DE       MDX  L  KIWC,1     UPDATE KEYBOARD BUF      8C203870
06C9 0  7301           MDX     3 1                                 8C203880
                     *                                             8C203890
06CA 00 4C8006B8       BSC  I  KSTO       RETURN TO USER           8C203900
                 ****************************************          8C203910
                     *                    SPECIAL CHAR CHECK       8C203920
06CC 0  0000     KSPC  DC      /0000                               8C203930
                     *                                             8C203940
06CD 0  C300           LD      3 0        FETCH KEY CHARACTER      8C203950
06CE 00 F4000A4F       EOR  L  KCMA                                8C203960
06D0 00 4C2006E8       BSC  L  KSPC5,Z    BR IF NOT A  COMMA       8C203970
                     *                                             8C203980
06D2 00 C40001DE       LD   L  KIWC                                8C203990
06D4 00 94000789       S    L  K0002                               8C204000
06D6 00 4428072D       BSI  L  KERR,+Z    BR IF COMMA TOO SOON     8C204010
                     *                                             8C204020
06D8 0  C3FF           LD      3 -1       FETCH LAST ENTRY         8C204030
06D9 0  1804           SRA     4                                   8C204040
06DA 00 4C1806DF       BSC  L  KSPC2,+-   BR IF SPACE LAST         8C204050
06DC 00 740101DE       MDX  L  KIWC,+1                             8C204060
                                                                  8C204070
                                                                  8C204080
```

```
06DE 0  7301            MDX     3 +1                              8C204090
06DF 00 C4000A2C  KSPC2 LD   L  KONE                             8C204100
06E1 0  D3FF            STO     3 -1      SET FIELD PROTECT MK    8C204110
                  *                                              8C204120
06E2 00 65000700        LDX  L1 KCOMA                            8C204130
06E4 00 44000768        BSI  L  KTYP      GO PRINT + OR-         8C204140
                  *                                              8C204150
06E6 00 64000647        LDX  L  KEYO      RETURN FOR MORE CHR    8C204160
                  *                                              8C204170
                  *******************************************    8C204180
06E8 0  C300      KSPC5 LD      3 0       FETCH KEY CHARACTER    8C204190
06E9 00 F4000A46        EOR  L  KERSE                            8C204200
06EB 00 4C200703        BSC  L  KSPC9,Z   BR IF NOT ERASE CHAR   8C204210
                  *                                              8C204220
06ED 00 C40001DE        LD   L  KIWC                             8C204230
06EF 00 4C080647        BSC  L  KEYO,+    BR IF WORD COUNT ZERO  8C204240
                  *                                              8C204250
06F1 0  C3FF            LD      3 -1      CHECK PROTECT BIT      8C204260
06F2 00 4C040647        BSC  L  KEYO,E    BR IF LAST WORD PROTD  8C204270
06F4 0  1801            SRA     1                                8C204280
06F5 00 4C0406FB        BSC  L  KSPC6,E   DO BKSP OVER PERIOD    8C204290
06F7 0  73FF            MDX     3 -1      DECREASE WORD COUNT    8C204300
06F8 00 74FF01DE        MDX  L  KIWC,-1                          8C204310
06FA 0  1000            NOP                                      8C204320
06FB 00 65000702  KSPC6 LDX  L1 KBKSP                            8C204330
06FD 0  406A            BSI     KTYP      DO A BACKSPACE    SRC  8C204340
                  *                                              8C204350
06FE 00 4C000647        BSC  L  KEYO      RETURN°                8C204360
                  *******************************************    8C204370
0700 0  8000      KCOMA DC      /8000     COMMA RESPONSE         8C204380
0701 0  8101            DC      /8101                            8C204390
0702 0  1101      KBKSP DC      /1101                            8C204400
                  *                                              8C204410
0703 0  C300      KSPC9 LD      3 0       FETCH KEY CHAR         8C204420
0704 00 F4000A45        EOR  L  KRENT                            8C204430
0706 00 4418072D        BSI  L  KERR,+-   BR IF ERASE FIELD      8C204440
                  *                                              8C204450
0708 0  C300            LD      3 KRED-KRED  FETCH CHAR PEAD     8C204460
0709 00 F4000A47        EOR  L  KENDK                            8C204470
070B 00 4C200647        BSC  L  KEYO,Z    BR IF NOT EOF KEY      8C204480
                  *                                              8C204490
070D 00 C40001DE        LD   L  KIWC      FETCH WORD COUNT       8C204500
070F 0  901A            S       KEYNO                            8C204510
0710 00 4428072D        BSI  L  KERR,+Z   TOO FEW ENTRIES        8C204520
0712 00 658001DE        LDX  I1 KIWC      CLEAR FIELD PROT BIT   8C204530
0714 00 C50001DE  KSPCA LD   L1 KIWC                             8C204540
0716 0  1804            SRA     4                                8C204550
0717 0  1004            SLA     4                                8C204560
0718 00 D50001DE        STO  L1 KIWC                             8C204570
071A 0  71FF            MDX     1 -1                             8C204580
071B 0  70F8            MDX     KSPCA                            8C204590
                  *                                              8C204600
                  *                                              8C204610
071C 0  C3FF            LD      3 -1      REMOVE SP BEFORE       8C204620
                  *                        TERMINATE             8C204630
071D 0  1804            SRA     4                                8C204640
071E 00 4C200725        BSC  L  KSPCE,Z   BR IF NO SPACE THERE   8C204650
0720 0  73FF            MDX     3 -1      DECREMENT WORD COUNT   8C204660
0721 00 74FF01DE        MDX  L  KIWC,-1                          8C204670
0723 0  7001            MDX     KSPCE                            8C204680
0724 0  4008            BSI     KERR                             8C204690
0725 0  C01E      KSPCE LD      KNEG      SET TERMINATION        8C204700
0726 0  D300            STO     3 0                              8C204710
0727 00 44000AA0        BSI  L  LDOIT     LET LLOYD DO IT        8C204720
0729 0  0000      KEYFM DC      /0000     FORM NUMBER            8C204730
072A 0  0000      KEYNO DC      /0000     CHARS / WORD           8C204740
072B 00 4C000629  EXIT  BSC  L  KEY96                            8C204750
                  *******************************************    8C204760
```

```
                  *                                              8C204770
072D 0  0000      KERR  DC      /0000                            8C204780
072E C0 65000A7A        LDX  L1 KFELD     PRINT FIELD CANCELLD   8C204790
0730 0  4037            BSI     KTYP      TYPE             SRC   8C204800
                  *                                              8C204810
0731 0  7301            MDX     3 1                              8C204820
0732 00 740101DF        MDX  L  KIWC,1                           8C204830
0734 0  61FF            LDX     1 -1                             8C204840
0735 0  C3FF      KERR1 LD      3 -1      ERASE TO FIELD MARK    8C204850
0736 00 4C040647        BSC  L  KEYO,E    BR IF FIELD MARK       8C204860
                  *                                              8C204870
0738 0  C00B            LD      KNEG                             8C204880
0739 0  D300            STO     3 0                              8C204890
073A 0  73FF            MDX     3 -1      DECREMENT WORD COUNT   8C204900
073B 00 74FF01DE        MDX  L  KIWC,-1                          8C204910
073D 0  70F7            MDX     KERR1                            8C204920
                  *                                              8C204930
073E 00 C40001DE        LD   L  KIWC                             8C204940
0740 00 4C100647        BSC  L  KEYO,-                           8C204950
0742 00 4C000641        BSC  L  KEYOG                            8C204960
0744 0  FFFF      KNEG  DC      -1        CONSTANT MINUS ONE     8C204970
                  *******************************************    8C204980
                  *                                              8C204990
                  *                                              8C205000
                  *                         TYPR NOT BUSY RTN    8C205010
0745 0  0000      KNBY  DC      /0000                            8C205020
0746 0  6A1B            STX     2 KNBY5+1                        8C205030
0747 00 6600000A        LDX  L2 10        SET TIME COUNTER       8C205040
0749 00 6E000767        STX  L2 KTIME                            8C205050
074B 00 66007FFF  KNBY0 LDX  L2 /7FFF                            8C205060
074D 00 0C000A1A  KNBY1 XIO  L  KSNS      CHECK BUSY             8C205070
074F 0  1004            SLA     4                                8C205080
0750 00 4C100761        BSC  L  KNBY5,-   BR IF NOT BUSY         8C205090
0752 0  72FF            MDX     2 -1                             8C205100
0753 0  70F9            MDX     KNBY1     CHECK AGAIN            8C205110
0754 00 74FF0767        MDX  L  KTIME,-1  DECREMENT TIMER       8C205120
0756 0  70F4            MDX     KNBY0                            8C205130
                  *                                              8C205140
0757 00 6600075D        LDX  L2 KNBY4     TYPR HUNG UP BUSY      8C205150
0759 00 6E000003        STX  L2 3                                8C205160
075B 0  3002      WAIT2 WAIT    2         1816 HUNG UP BUSY      8C205170
075C 0  70EA            MDX     KNBY+2                           8C205180
                  *                                              8C205190
075D 00 6600012C  KNBY4 LDX  L2 300       RESTORE RESTART        8C205200
075F 00 6E000003        STX  L2 3                                8C205210
                  *                                              8C205220
0761 00 66000000  KNBY5 LDX  L2 /0000     EXIT                   8C205230
0763 00 0C000A24        XIO  L  KRDY      RESET                  8C205240
0765 00 4C800745        BSC  I  KNBY                             8C205250
0767 0  0000      KTIME DC      /0000     TIME COUNTER           8C205260
                  *******************************************    8C205270
                  *                                              8C205280
                  *                                              8C205290
                  *                        PRINTER OUTPUT RTN    8C205300
                  *                        XR1 = ADRS OF MESS    8C205310
                  *                                              8C205320
                  *                                              8C205330
0768 0  0000      KTYP  DC      /0000                            8C205340
0769 00 6D000A26  KTYP1 STX  L1 KPRT      SAVE PRINTING ADDR     8C205350
                  *                                              8C205360
076B 0  40D9            BSI     KNBY      WAIT OFR NOT BUSY      8C205370
                  *                                              8C205380
076C 00 0C000A24  KTYP5 XIO  L  KRDY      CHECK READY            8C205390
076E 0  1005            SLA     5                                8C205400
076F 00 4C100773        BSC  L  KTYP6,-   BR IF READY            8C205410
0771 0  3001      WAIT1 WAIT    1         PRINTER OUT OF FORMS   8C205420
                                                                 8C205430
                                                                 8C205440
```

```
0772 0  70F9           MDX   KTYP5                         8C205450
                *                                          8C205460
0773 00 0C000A26 KTYP6 XIO L KPRT     OUTPUT ONE CHAR      8C205470
0775 0  C100           LD   1 0                            8C205480
0776 00 4C840768       BSC  I KTYP,E  EXIT IF MSG PRIM     8C205490
                *                                          8C205500
0778 0  7101           MDX  I 1                            8C205510
0779 0  70EF           MDX    KTYP1                         8C205520
077A 0  0000    CKYNE  DC     0                      SE    8C205530
077B 00 C40001DF       LD   L KEYIN   GET ENTRY            8C205540
077D 0  F018           EOR    YES     IS IT Y LC           8C205550
077E 00 4C180794       BSC  L CKYNO,+- YES                 8C205560
0780 00 C40001DF       LD   L KEYIN   GET ENTRY            8C205570
0782 0  F014           EOR    YES1    IS IT Y UC           8C205580
0783 00 4C180794       BSC  L CKYNO,+- YES                 8C205590
0785 00 C40001DF       LD   L KEYIN   GET ENTRY            8C205600
0787 0  F010           EOR    NO      IS IT N LC           8C205610
0788 00 4C180792       BSC  L CKYN1,+- YES                 8C205620
078A 00 C40001DF       LD   L KEYIN   GET ENTRY            8C205630
078C 0  F00C           EOR    NO1     IS IT N UC           8C205640
078D 00 4C180792       BSC  L CKYN1,+- YES                 8C205650
                *                                          8C205660
078F 00 44800132       BSI  I SER     NOT Y OR N     SRC   8C205670
0791 0  0B88           DC     PCKBE                         8C205680
                *                                          8C205690
0792 00 7401077A CKYN1 MDX    CKYNE,1 INCR RETURN          8C205700
0794 00 4C80077A CKYNO BSC  I CKYNE   EXIT            SX    8C205710
                *                                          8C205720
0796 0  2020    YES    DC     /2020   LOWER CASE Y         8C205730
0797 0  8060    YES1   DC     /8060   UPPER CASE Y         8C205740
0798 0  4100    NO     DC     /4100   LOWER CASE N         8C205750
0799 0  8120    NO1    DC     /8120   UPPER CASE N         8C205760
                *                                          8C205770
                *                                          8C205780
                * SET UP RETURN ON ERROR                   8C205790
                *                                          8C205800
079A 0  0000    SSUEE  DC     /0000                         8C205810
079B 0  COFE           LD     SSUEE                         8C205820
079C 0  901C           S      K0002                         8C205830
079D 00 D4000441       STO  L SRTRY                         8C205840
079F 00 4C80079A       BSC  I SSUEE                         8C205850
079A            SSEUR  EQU    SSUEE                         8C205860
                * CHECK IF INTERRUPT LEVEL                 8C205870
                *    IS TO GREAT                            8C205880
                *                                          8C205890
07A1 0  0000    SILE   DC     0                             8C205900
07A2 00 C400013E       LD   L BINRY                         8C205910
07A4 0  1008           SLA    8                             8C205920
07A5 0  B008           CMP    S1700                         8C205930
07A6 0  7002           MDX    SILER   GREATER.ERROR         8C205940
07A7 0  7004           MDX    SIL1                          8C205950
07A8 0  7003           MDX    SIL1                          8C205960
                *                                          8C205970
07A9 00 44800132 SILER BSI  I SER                           8C205980
07AB 0  0BAD           DC     SE002                         8C205990
                *                                          8C206000
07AC 00 4C8007A1 SIL1  BSC  I SILE                          8C206010
                *                                          8C206020
07AE 0  1700    S1700  DC     /1700                         8C206030
                *                                          8C206040
                *         CHECK IF ILSW IS VALID            8C206050
                *                                          8C206060
07AF 0  0000    SILSE  DC     /0000                         8C206070
07B0 00 C400013E       LD   L BINRY                         8C206080
07B2 0  1004           SLA    4                             8C206090
07B3 0  B004           CMP    S00F0                         8C206100
07B4 0  70F4           MDX    SILER   ERROR                 8C206110
07B5 0  1000           NOP    0                             8C206120
```

```
07B6 00 4C8007AF SIA   BSC  I SILSE                         8C206130
                *                                          8C206140
07B8 0  00F0    S00F0  DC     /00F0                         8C206150
07B9 0  0002    K0002  DC     2                             8C206160
                *                                          8C206170
                *          CHECK CHANNEL VALUE              8C206180
                *                                          8C206190
07BA 0  0000    SCHE   DC     /0000                         8C206200
07BB 00 C400013E       LD   L BINRY                         8C206210
07BD 0  B00C           CMP    S0008                         8C206220
07BE 0  7002           MDX    SCHER                         8C206230
07BF 0  7005           MDX    SCH1                          8C206240
07C0 0  7004           MDX    SCH1                          8C206250
                *                                          8C206260
07C1 0  F007    SCHER  EOR    S000F                         8C206270
07C2 00 4C1807C5       BSC  L SCH1,+-                        8C206280
07C4 0  70E4           MDX    SILER   ERROR                 8C206290
                *                                          8C206300
07C5 00 C400013E SCH1  LD   L BINRY                         8C206310
07C7 00 4C8007BA       BSC  I SCHE                          8C206320
07C9 0  000F    S000F  DC     /000F                         8C206330
                *                                          8C206340
07CA 0  0008    S0008  DC     /0008                         8C206350
07CB 0  0000    SERE   DC     0                             8C206360
07CC 00 C48007CB       LD   I SERE    FETCH ERROR ADDRESS   8C206370
07CE 0  D002           STO    SER1                          8C206380
                *                                          8C206390
07CF 00 4480012C       BSI  I KEY                           8C206400
07D1 0  0000    SER1   DC     /0000   ADDRESS               8C206410
07D2 0  0000           DC     /0000   ID                    8C206420
                *                                          8C206430
07D3 00 4C800441       BSC  I SRTRY                         8C206440
                *                                          8C206450
                *          SET UP ROUTINE                   8C206460
                *             X2= CARD NUMBER               8C206470
                *                                          8C206480
07D5 0  0000    SECSE  DC     0                      SE    8C206490
07D6 00 C48007D5       LD   I SECSE   GET MSG ADRS          8C206500
07D8 0  D024           STO    SIMB    SAVE                  8C206510
07D9 0  6A24    SE1    STX  2 SECB    SET CD NO             8C206520
07DA 0  6924           STX  1 CPID    SET PID               8C206530
07DB 0  6B24           STX  3 NOEN    SET NO OF ENTRIES     8C206540
07DC 0  C024           LD     STBF1   GET EDIT IMAGE ADRS   8C206550
07DD 00 84000440       A    L STBF                          8C206560
07DF 0  D003           STO    SE2+1   SET                   8C206570
07E0 00 658007FD       LDX I1 SIMB    IX 1 = MSG ADRS       8C206580
07E2 00 67000000 SE2   LDX L3 0       IX 3 = STARTING ADRS  8C206590
07E4 00 66800800       LDX I2 NOEN    IX 2 = NO ENTRIES     8C206600
07E6 0  C018           LD     CPID    GET PID               8C206610
07E7 0  D300           STO  3 0       SET                   8C206620
07E8 0  C015           LD     SECB    GET CD NO             8C206630
07E9 0  D301           STO  3 1       SET                   8C206640
07EA 0  C015           LD     NOEN    GET NO ENTRIES        8C206650
07EB 0  D302           STO  3 2       SET                   8C206660
07EC 0  7303           MDX  3 3       INCR IX 3             8C206670
07ED 0  C100    SE3    LD   1 0       GET AN ENTRY          8C206680
07EE 0  D300           STO  3 0       SET                   8C206690
07EF 0  7101           MDX  1 1       INCR MSG ADRS         8C206700
07F0 0  7301           MDX  3 1       INCR BFR ADRS         8C206710
07F1 0  72FF           MDX  2 -1      DECR NO ENTRIES       8C206720
07F2 0  70FA           MDX    SE3     LOOP                  8C206730
07F3 00 C4000440       LD   L STBF                          8C206740
07F5 0  800C           A      K0003   ADD 3                 8C206750
07F6 0  8009           A      NOEN    ADD NO ENTRIES        8C206760
07F7 00 D4000440       STO  L STBF                          8C206770
07F9 00 740107D5       MDX  L SECSE,1 INCR RETURN           8C206780
07FB 00 4C8007D5       BSC  I SECSE   EXIT            SX    8C206790
                *                                          8C206800
```

```
07FD 0  0000      SIMB  DC    0           MSG ADRS                    8C206810
07FE 0  0000      SECB  DC    0           CARD NO                     8C206820
07FF 0  0000      CPID  DC    0           PID                         8C206830
0800 0  0000      NOEN  DC    0           NO ENTRIES                  8C206840
0801 0  0442      STRF1 DC    SEIB        CD BFR ADRS                 8C206850
0802 0  0003      K0003 DC    3           CONSTANT 3                  9C206860
****************************************                              8C206870
0803 0  0000      KIN1  DC    0                                  SE  8C206880
0804 00 67000258        LDX   L3 600      SET IXING                   8C206890
0806 00 C400043D        LD    L  TERM     GET FFFF                    8C206900
0808 00 D70001DE  SKINA STO   L3 KIWC     SET KEYIN AREA              8C206910
080A 0  73FF            MDX   3  -1        DECR IX 3                   8C206920
080B 0  70FC            MDX      SKINA     LOOP                        8C206930
080C 00 4C800803        BSC   I  KIN1      EXIT                   SX  8C206940
****************************************                              8C206950
                                                                     8C206955
080E 0  0000      KINO  DC    0                                  SE  8C206960
080F 00 67000258        LDX   L3 600      SET IXING                   8C206970
0811 0  1010            SLA      16        CLEAR ACCUM                 8C206980
0812 00 D70001DE  SKINB STO   L3 KIWC     CLEAR KEYIN AREA            8C206990
0814 0  73FF            MDX   3  -1        DECR IX 3                   8C207000
0815 0  70FC            MDX      SKINB     LOOP                        8C207010
0816 00 4C80080E        BSC   I  KINO      EXIT                   SX  8C207020
                                                                     8C207030
                                DEC KEYBOARD TO BINARY RT            8C207040
0818 0  0000      DKYB  DC    0                                       8C207050
0819 0  D862            STO      PHKX1     SAVE A + Q                  8C207060
081A 0  C0FD            LD       DKYB                                  8C207070
081B 0  D005            STO      HKYB                                  8C207080
081C 00 D4000885        STO   L  PHDSW     SET HEX-DEC SW = DEC        8C207090
081E 00 C40008CD        LD    L  PDKX1     CONSTANT 10                 8C207100
0820 0  7005            MDX      PHKYD     ENTER COMMON SECTION        8C207110
                                                                     8C207120
                                                                     8C207130
                                                                     8C207140
                                HEX KEYBOARD TO BINARY RT            8C207150
0821 0  0000      HKYB  DC    0                                       8C207160
0822 0  D859            STO      PHKX1     SAVE A + Q                  8C207170
0823 0  C05F            LD       PHKX7     CONSTANT ZERO               8C207180
0824 0  D060            STO      PHDSW     SET HEX-DEC SW = HEX        8C207190
0825 0  C05E            LD       PHKX8                                 8C207200
0826 0  D01F      PHKYD STO      PHKYC     SET CONV CK                 8C207210
0827 0  284F            STS      PHKYS     SAVE STATUS                 8C207220
0828 0  6949            STX   1  PHKY6+1   SAVE X1                     8C207230
0829 0  6A4A            STX   2  PHKY7+1   SAVE X2                     8C207240
082A 0  6B4B            STX   3  PHKYB+1   SAVE X3                     8C207250
082B 00 67800821        LDX   I3 HKYB                                 8C207260
082D 00 C7000000        LD    L3 0                                    8C207270
082F 0  D04E            STO      PHKX2     SAVE CHAR/WORD              8C207280
0830 00 C7800001        LD    I3 1         GET ADDR OF DISP            8C207290
0832 0  804C            A        PHKX3     COMPUTE START ADDR          8C207300
0833 0  D04C            STO      PHKX4                                 8C207310
                                                                     8C207320
                                INITIALIZE BINRY BUFFER             8C207330
                                                                     8C207340
0834 0  1810            SRA      16                                   8C207350
0835 00 D400013D        STO   L  BWC       RESET WORD COUNT           8C207360
                                                                     8C207370
                                CONVERT NUMBER TO HEX               8C207380
                              * AND STORE IN BINARY BUF             8C207390
                                                                     8C207400
0837 00 6680013D  PHKY5 LDX   I2 BWC       SET X2 TO NEXT              8C207410
0839 00 7600013D        MDX   L2 BINRY-1   * AVAILABLE SPACE -1        8C207420
083B 0  6A0C            STX   2  PHKY1+1                              8C207430
083C 0  6A16            STX   2  PHKY3+1                              8C207440
083D 00 6580087E        LDX   I1 PHKX2     SET X1 TO STARTING         8C207450
083F 00 75800880        MDX   I1 PHKX4     * ADDR + NUM CHAR/WD       8C207460
0841 00 6780087E        LDX   I3 PHKX2     SET X3 TO CHAR/WD          8C207480
```

```
0843 0  C100      PHKY2 LD    1  0         GET NUMBER                  8C207490
0844 00 440008D6        BSI   L  PCKB      CONVERT TO BINARY           8C207500
0846 0  0010      PHKYC DC    16           LIM CK = 16 OR 10           8C207510
0847 00 D7000000  PHKY1 STO   L3 0         PLACE IN BINRY BUFF         8C207520
0849 0  71FF            MDX   1  -1                                    8C207530
084A 0  73FF            MDX   3  -1         SKIP WHEN DONE              8C207540
084B 0  70F7            MDX      PHKY2                                 8C207550
084C 00 74000885        MDX   L  PHDSW,0   CK HEX-DEC SW               8C207560
084E 0  7037            MDX      PDKY1     BRANCH TO DEC RT            8C207570
                                                                     8C207580
                                PACK BINARY                         8C207590
                                                                     8C207600
084F 00 6780087E        LDX   I3 PHKX2     SET X3 TO CHAR/WD          8C207600
0851 0  10A0            SLT      32                                   8C207610
0852 00 C7000000  PHKY3 LD    L3 0                                    8C207620
0854 0  1884            SRT      4                                    8C207630
0855 0  73FF            MDX   3  -1                                   8C207640
0856 0  70FB            MDX      PHKY3                                8C207650
0857 0  63FC            LDX   3  -4                                   8C207660
0858 00 7780087E        MDX   I3 PHKX2     RIGHT JUSTIFY              8C207670
085A 0  1884      PHKY4 SRT      4                                   8C207680
085B 0  7300            MDX   3  0                                    8C207690
085C 0  7001            MDX      PHKY9                                8C207700
085D 0  7002            MDX      PHKY9+2                              8C207710
085E 0  7301      PHKY9 MDX   3  1                                    8C207720
085F 0  70FA            MDX      PHKY4                                8C207730
0860 0  18D0            RTE      16                                   8C207740
0861 00 D6000001  PHKYF STO   L2 1         PLACE IN BINRY BUFF         8C207750
0863 00 7401013D        MDX   L  BWC,1     BUMP WORD COUNT            8C207760
                                                                     8C207770
                                BUMP TO NEXT KEYIN FIELD            8C207780
                                                                     8C207790
0865 0  C018      PHKYH LD       PHKX2     GET CHAR/WD                8C207800
0866 0  801A            A        PHKX5     ADD ONE FOR SPACE          8C207810
0867 0  8018            A        PHKX4                                8C207820
0868 0  D017            STO      PHKX4                                8C207830
0869 00 67800880        LDX   I3 PHKX4                               8C207840
086B 0  C300            LD    3  0                                    8C207850
086C 0  F015            EOR      PHKX6     CK FOR TERMINATOR          8C207860
086D 0  4820            BSC   Z            SKIP IF FOUND              8C207870
086E 0  70C8            MDX      PHKY5     GET NEXT NUMBER            8C207880
                                                                     8C207890
                                EXIT FROM RT                        8C207900
                                                                     8C207910
086F 00 74020821        MDX   L  HKYB,2                              8C207910
0871 00 65000000  PHKY6 LDX   L1 0         RESTORE REGS               8C207920
0873 00 66000000  PHKY7 LDX   L2 0                                   8C207930
0875 00 67000000  PHKY8 LDX   L3 0                                   8C207940
0877 0  2000      PHKYS LDS      0                                   8C207950
0878 0  C803            LDD      PHKX1                               8C207960
0879 00 4C800821        BSC   I  HKYB      EXIT FROM SUBRT            8C207980
                                                                     8C207990
087C    0000            BSS   E  0                                   8C208010
087C    0002      PHKX1 BSS      2         SAVE A + Q                 8C208020
087E 0  0002      PHKX2 DC    0            CHAR PER WORD              8C208030
087F 0  01DE      PHKX3 DC    KEYIN-1                                8C208040
0880 0  0000      PHKX4 DC    0            STARTING ADDR             8C208050
0881 0  0001      PHKX5 DC    1            CONSTANT 1                8C208060
0882 0  FFFF      PHKX6 DC    /FFFF        CONSTANT FFFF             8C208070
0883 0  0000      PHKX7 DC    0            CONSTANT 0                8C208080
0884 0  0010      PHKX8 DC    16           CONSTANT 16               8C208090
0885 0  0000      PHDSW DC    0            HEX-DEC SWITCH            8C208100
                                                                     8C208110
                                CONV NUM TO DEC AND STORE           8C208120
                              * IN BINARY BUF                       8C208130
                                                                     8C208140
0886 0  10A0      PDKY1 SLT      32                                  8C208150
                                                                     8C208160
```

```
0887 0 D840          STD    PDKWA    ZERO OUT WORK AREA      8C208170
                 *                                           8C208180
                 *        CK FOR 9 CH/WD                     8C208190
                 *                                           8C208200
0888 0 C0F5          LD     PHKX2    GET CH/WD               8C208200
0889 00 B4000904     CMP L  PCKX1    COMPARE TO 9            8C208210
088B 0 7039          MDX    PDKYE    ERROR TOO GREAT         8C208220
088C 0 7001          MDX    *+1                              8C208230
088D 0 90F3          S      PHKX5    SUB ONE                 8C208240
088E 0 D001          STO    PDKY2+1                          8C208250
088F 00 67000000 PDKY2 LDX L3 0     LDX MODIFIED CH/WD       8C208260
0891 00 66800848     LDX 12 PHKY1+1                          8C208270
0893 00 7680087E     MDX 12 PHKX2   SET UP 1ST POWER         8C208280
0895 0 6100          LDX 1 0                                 8C208290
0896 0 C200     PDKY3 LD    2 0     GET BIN NUMBER           8C208300
0897 00 A50008CC     M   L1 PDKX2   MULT BY POWER            8C208310
0899 0 71FC          MDX   1 -4     CK FOR CH/WD GRT 4       8C208320
089A 0 7009          MDX   PDKYH    CH/WD GRT 4              8C208330
089B 0 7104     PDKYJ MDX  1 4                               8C208340
089C 0 1000          SLA   0                                 8C208350
089D 0 882A          AD    PDKWA                             8C208360
089E 0 D829          STD   PDKWA                             8C208370
089F 0 7101          MDX   1 1                               8C208380
08A0 0 72FF          MDX   2 -1                              8C208390
08A1 0 73FF          MDX   3 -1                              8C208400
08A2 0 70F3          MDX   PDKY3                             8C208410
08A3 0 7003          MDX   PDKY6                             8C208420
08A4 0 18D0     PDKYH RTE  16       CH/WD GRT 4              8C208430
08A5 0 A02A          M     PDKX1+3  MULTIPY BY 10,000        8C208440
08A6 0 70F4          MDX   PDKYJ                             8C208450
                 *        CK FOR SIGNED NUMBER               8C208460
08A7 0 C0D6     PDKY6 LD   PHKX2                             8C208470
08A8 00 B4000904     CMP L  PCKX1   CONS 9                   8C208480
08AA 0 701A          MDX   PDKYE    ERROR TOO GREAT          8C208490
08AB 0 7001          MDX   *+1                               8C208500
08AC 0 7009          MDX   PDKY7    CK SIGN                  8C208510
                 *        CK FOR CH/WD GREATER               8C208520
                 *        * THAN 5                           8C208530
08AD 0 C0D0          LD    PHKX2                             8C208540
08AE 0 B026          CMP   PDKX3    CONS 5                   8C208550
08AF 0 700F          MDX   PDKY8                             8C208560
08B0 0 7001          MDX   *+1                               8C208570
08B1 0 700F          MDX   PDKYA    GO TO CK FOR /7FFF       8C208580
                 *                                           8C208590
                 *        SINGLE PRECISION NUMBER            8C208600
08B2 00 66800848 PDKYF LDX 12 PHKY1+1                        8C208610
08B4 0 C014          LD    PDKWA+1  GET CONV NUMBER          8C208640
08B5 0 70AB          MDX   PHKYF                             8C208650
                 *        CORRECT SIGN                       8C208660
08B6 0 C200     PDKY7 LD   2 0                               8C208670
08B7 00 4C1808BF     BSC L  PDKY8,+-  BRANCH IF POS NUMB     8C208680
08B9 0 10A0          SLT   32       CHANGE SIGN              8C208690
08BA 0 980D          SD    PDKWA                             8C208700
08BB 0 DA00     PDKY9 STD  2 0                               8C208710
08BC 00 7402013D     MDX L  BWC,2                            8C208720
08BE 0 70A6          MDX   PHKYH                             8C208730
08BF 0 C808     PDKY8 LDD  PDKWA    DOUBLE PREC POS NUMB     8C208740
08C0 0 70FA          MDX   PDKY9                             8C208750
                 *                                           8C208760
08C1 0 C806     PDKYA LDD  PDKWA    CK LESS THAN OR EQ /7FFF 8C208770
08C2 0 9807          SD    PDKX4    CONS 000008000           8C208780
08C3 00 4C2808B2     BSC L  PDKYF,+Z BRANCH TO SINGLE PREC   8C208790
08C5 00 44800132 PDKYE BSI I  SER                            8C208800
08C7 0 0888          DC    PCKBE                             8C208810
08C8 0 0000          BSS E 0                                 8C208820
08C8 0 0002     PDKWA BSS  2        WORK AREA                8C208830
                                                             8C208840
```

```
08CA 0 0000     PDKX4 DC   0        CONS /00008000           8C208850
08CB 0 8000          DC    /8000                             8C208860
08CC 0 0001     PDKX2 DC   1        CONV TABLE               8C208870
08CD 0 000A     PDKX1 DC   10                                8C208880
08CE 0 0064          DC    100                               8C208890
08CF 0 03E8          DC    1000                              8C208900
08D0 0 2710          DC    10000                             8C208910
08D1 0 000A          DC    10                                8C208920
08D2 0 0064          DC    100                               8C208930
08D3 0 03E8          DC    1000                              8C208940
08D4 0 2710          DC    10000                             8C208950
08D5 0 0005     PDKX3 DC   5        CONS 5                   8C208960
                 *                                           8C208970
                 *                                           8C208980
                 *                                           RC208990
                 *                                           8C209000
                 *        KEYBOARD TO BINARY RT              8C209010
                 *                                           8C209020
08D6 0 0000     PCKB DC   0                                  8C209030
08D7 0 6827          STX   3 PCKBX+1  SAVE X3                8C209040
08D8 0 D029          STO   PCKBA    SAVE NUMBER              8C209050
08D9 00 C48008D6     LD I  PCKB     GET LIMIT CK             8C209060
08DB 0 D001          STO   PCKB1+1                           8C209070
08DC 00 67000000 PCKB1 LDX L3 0     SET X3 TO LIM CK         8C209080
08DE 00 C7000A34     LD  L3 KECOD   LK UP CODE               8C209090
08E0 0 F021          EOR   PCKBA                             8C209100
08E1 00 4C1808F8     BSC L  PCKB3,+-  BRANCH IF FOUND        8C209110
08E3 0 73FF          MDX   3 -1     SKIP IF ILLEGAL          8C209120
08E4 0 70F9          MDX   PCKB1+2                           8C209130
08E5 00 C400087E     LD  L  PHKX2   CK FOR 9 CHAR FIELD      8C209140
08E7 0 901C          S     PCKX1                             8C209150
08E8 00 4C2008F5     BSC L  PCKB4,Z  GO TO ERROR IF NOT 9    8C209160
08EA 0 C017          LD    PCKBA    CK FOR +                 8C209170
08CB 0 F019          EOR   PCKX2                             8C209180
08EC 00 4C1808FC     BSC L  PCKBX-2,+-                       8C209190
08EE 0 C013          LD    PCKBA    CK FOR -                 8C209200
08EF 0 F016          EOR   PCKX3                             8C209210
08F0 00 4C2008F5     BSC L  PCKB4,Z  GO TO ERROR, NO + -     8C209220
08F2 00 C4000894     LD  L  PCKX4                            8C209230
08F4 0 7007          MDX   PCKBX-2                           8C209240
08F5 00 44800132 PCKB4 BSI I  SER    IMPROPER KEY CODE       8C209250
08F7 0 0B88          DC    PCKBE    * I.E NOT 0-9 OR 0-F     8C209260
08F8 0 73FF     PCKB3 MDX  3 -1                              8C209270
08F9 0 1000          SLA   0                                 8C209280
08FA 0 6808          STX   3 PCKBB                           8C209290
08FB 0 C007          LD    PCKBB    GET CONVERTED NUM        8C209300
08FC 00 740108D6     MDX L  PCKB,1                           8C209310
08FE 00 67000000 PCKBX LDX L3 0     RESTORE X3               8C209320
0900 00 4C8008D6     BSC I  PCKB                             8C209330
                 *                                           8C209340
0902 0 0000     PCKBA DC   0        ORIGINAL NUMBER          8C209350
0903 0 0000     PCKBB DC   0        CONVERTED NUMBER         8C209360
0904 0 0009     PCKX1 DC   9                                 8C209370
0905 0 8000     PCKX2 DC   /8000    +                        8C209380
0906 0 4000     PCKX3 DC   /4000    -                        8C209390
                 *                                           8C209400
                 *                                           8C209410
                 *                                           8C209420
                 *        PUNCH EDIT CARD OUTPUT ROUTINE      8C209430
                 *                                           8C209440
0907 0 0000     PECOR DC   0                                 8C209450
0908 00 DC00098C     STD L  PECX1    SAVE REGISTERS          8C209460
090A 0 285C          STS   PECOS                             8C209470
090B 0 1810          SRA   16                                8C209480
090C 0 6955     PECYF STX  1 PECY1+1                         8C209490
090D 0 6A56          STX   2 PECY2+1                         8C209500
090E 0 6B57          STX   3 PECY3+1                         8C209510
                                                             8C209520
```

```
090F 00 4480012C          BSI  I  KEY        PRINT EDIT CARD LIST      8C209530
0911 0  0B9F              DC      PECXF       * MESSAGE                 8C209540
0912 0  0000              DC      0                                     8C209550
                     *                                                  8C209560
                     *                                                  8C209570
                     *                 READ A CARD AND VERIFY           8C209580
                     *                 * THAT IT IS BLANK               8C209590
                     *                                                  8C209600
0913 00 66000442          LDX  L2 SEIB        SET X2 = ED IMAG BUF      8C209610
0915 00 650001E0          LDX  L1 KEYIN+1     X1 = OPT REG              8C209620
0917 00 0C000B0E  PECY7   XIO  L  RDSW        READ DATA SWS             8C209630
0919 00 C4000B10          LD   L  DTSW        GET SWS                   8C209640
091B 00 4C280921          BSC  L  PT,+Z       BRANCH IF P T             8C209650
091D 0  1001              SLA     1                                     8C209660
091E 00 4C280921          BSC  L  PT,+Z       BRANCH IF BOTH            8C209670
0920 0  7007              MDX     NTPT        NOT PAPER TAPE            8C209680
0921 00 44000AED  PT      BSI  L  PPT         PUNCH LEADER          SRC 8C209690
0923 00 C4000B10          LD   L  DTSW        GET SWS                   8C209700
0925 0  1001              SLA     1                                     8C209710
0926 00 4C10093C          BSC  L  PECYE,-     BRANCH IF NOT BOTH        8C209720
0928 0  086B      NTPT    XIO     PECX5       SENSE DSW                 8C209730
0929 00 4C04097E          BSC  L  PECY6,E     XFER IF NOT READY         8C209740
092B 0  0866              XIO     PECX4       READ A CARD               8C209750
092C 0  0867      PECY4   XIO     PECX5       SENSE DSW                 8C209760
092D 0  1801              SRA     1           CK BUSY                   8C209770
092E 00 4C04092C          BSC  L  PECY4,E     XFER IF BUSY              8C209780
0930 0  180C              SRA     12                                    8C209790
0931 00 4C040984          BSC  L  PECY8,E     XFER IF ERROR ON          8C209800
0933 0  0862              XIO     PECX6       RESET DSW                 8C209810
                     *                                                  8C209820
                     *                 CK FOR BLANK CARD                8C209830
                     *                                                  8C209840
0934 0  1810              SRA     16                                    8C209850
0935 0  6350              LDX   3 80                                    8C209860
0936 00 EF0001DF  PECY5   OR   L3 KEYIN                                 8C209870
0938 0  73FF              MDX   3 -1                                   .8C209880
0939 0  70FC              MDX     PECY5                                 8C209890
093A 00 4C200928          BSC  L  NTPT,Z                                8C209900
                     *                                                  8C209910
                     *                 BLANK OUT OUTPUT BUFF            8C209920
                     *                                                  8C209930
093C 0  1810      PECYE   SRA     16                                    8C209940
093D 0  6380              LDX   3 -80                                   8C209950
093E 00 D7000230  PECYA   STO  L3 KEYIN+81                              8C209960
0940 0  7301              MDX   3 1                                     8C209970
0941 0  70FC              MDX     PECYA                                 8C209980
                     *                                                  8C209990
0942 00 6700FFB0          LDX  L3 -80        SET X3 = COL CONTROL       8C210000
                     *                                                  8C210010
                     *                 SET E INTO OUTPUT AREA           8C210020
                     *                                                  8C210030
0944 00 C4000A43          LD   L  PBIX2                                 8C210030
0946 0  D100              STO   1 0                                     8C210040
0947 0  7301              MDX   3 1                                     8C210050
                     *                                                  8C210060
                     *                 SET PID INTO OUTPUT AREA         8C210070
                     *                                                  8C210080
0948 0  C200              LD    2 0                                     8C210090
0949 0  1008              SLA     8                                     8C210100
094A 0  4051              BSI     PBIHX       CONV TO HEX AND       SRC 8C210110
                     *                         * STORE IN OUTPUT        8C210120
                     *                                                  8C210130
                     *                 CK FOR END OF ED CD DIR          8C210140
                     *                                                  8C210150
094B 0  C201              LD    2 1                                     8C210160
094C 00 F40009E          EOR  L  PECXD                                  8C210170
094E 00 4C20096B          BSC  L  PECYB,Z     BRANCH IF NOT END CD      8C210180
0950 00 C40009E          LD   L  PECXD        SET FFFF EDIT END         8C210190
0952 0  4049              BSI     PBIHX       CONV AND STORE        SRC 8C210200
```

```
0953 0  4061              BSI     PED         PUNCH CARD            SRC 8C210210
0954 00 440009E0          BSI  L  PPECD       PRINT THE EDIT CARD   SRC 8C210220
0956 00 C4000B10          LD   L  DTSW        GET SWS                   8C210230
0958 00 4C280961          BSC  L  PECY1,+Z    BRANCH IF NOT CARDS       8C210240
095A 0  0835              XIO     PECXC       STACKER SELECT            8C210250
095B 0  083C              XIO     PECX7       FEED A CARD               8C210260
095C 0  0837      PECYC   XIO     PECX5       SENSE DSW                 8C210270
095D 0  1801              SRA     1                                     8C210280
095E 00 4C04095C          BSC  L  PECYC,E                               8C210290
0960 0  0835              XIO     PECX6       RESET DSW                 8C210300
                     *                                                  8C210310
0961 00 65000000  PECY1   LDX  L1 0          RESTORE REGS               8C210320
0963 00 66000000  PECY2   LDX  L2 0                                     CC210330
0965 00 67000000  PECY3   LDX  L3 0                                     8C210340
0967 0  2000      PECDS   LDS     0                                     8C210350
0968 0  C823              LDD     PECX1                                 8C210360
0969 00 4C800907          BSC  I  PECOR       EXIT FROM ROUTINE         8C210370
                     *                 SET CARD NUMB IN OUTPUT          8C210380
096B 0  C201      PECYB   LD    2 1                                     8C210390
096C 0  E821              OR      PECX3       ADD IN ED                 8C210400
096D 0  402E              BSI     PBIHX       CONV AND STORE        SRC 8C210410
                     *                                                  8C210420
                     *                 SET NUMB ENTRIES PER CARD        8C210430
                     *                                                  8C210440
096E 0  C202              LD    2 2                                     8C210450
096F 0  1888              SRT     8                                     8C210460
0970 0  1810              SRA     16                                    8C210470
0971 0  1088              SLT     8                                     8C210480
0972 0  D01C              STO     PECXE       SAVE                      8C210490
0973 0  4028              BSI     PBIHX       CONV AND STORE        SRC 8C210500
                     *                 MOVE DATA TO OUTPUT BUFF         8C210510
0974 0  C203      PECYD   LD    2 3                                     8C210520
0975 0  4026              BSI     PBIHX       CNV AND STORE         SRC 8C210530
0976 0  7201              MDX   2 1           BUMP IMAG BUF ADDR        8C210540
0977 00 74FF098F          MDX  L  PECXE,-1    DECREMENT ENTRIES/CD      8C210550
0979 0  70FA              MDX     PECYD                                 8C210560
097A 0  403A              BSI     PED         PUNCH A CARD          SRC 8C210570
097B 0  4064              BSI     PPECD       PRINT CARD            SRC 8C210580
097C 0  7203              MDX   2 3                                     8C210590
097D 0  70A5              MDX     PT+2        BRANCH                    8C210610
                     *                                                  8C210610
097E 00 4480012C  PECY6   BSI  I  KEY                                   8C210620
0980 0  0895              DC      PECX9                                 8C210630
0981 0  0000              DC      0                                     8C210640
0982 0  3003      WAIT3   WAIT    3           1442 NOT READY =RD1       8C210650
                                             *PUSH START TO RETRY       8C210660
0983 0  7093              MDX     PECY7       BRANCH                    8C210670
                     *                                                  8C210680
0984 00 4480012C  PECY8   BSI  I  KEY                                   8C210690
0986 0  0895              DC      PECX9                                 8C210700
0987 0  0000     $        DC      0           1442 READ ERROR          8C210710
0988 0  080D              XIO     PECX6       RESET DSW                 8C210720
0989 0  3004      WAIT4   WAIT    4           PUSH START TO REREAD      8C210730
098A 0  70AC              MDX     PECY7       BRANCH                    8C210740
                     *                                                  8C210750
098C  0000              BSS  E  0                                     8C210760
096C  0002      PECX1   BSS     2           SAVE A + Q                8C210770
098E  0  E000      PECX3   DC      /ED00                                8C210780
098F  0  0000      PECXE   DC      0           ENTRIES PER CARD         8C210790
0990  0  0000      PECXC   DC      0           STACKER SELECT IOCC      8C210800
0991  0  1480              DC      /1480                                8C210810
0992  0  01E0      PECX4   DC      KEYIN+1     READ A CARD IOCC         8C210820
0993  0  1600              DC      /1600                                8C210830
0994  0  0000      PECX5   DC      0           SENSE 1442 DSW           8C210840
0995  0  1700              DC      /1700                                8C210850
0996  0  0000      PECX6   DC      0           SENSE AND RESET DSW      8C210860
0997  0  1703              DC      /1703                                8C210870
0998  0  0000      PECX7   DC      0           FEED A CARD IOCC         8C210880
```

```
0999 0 1402         DC      /1402                              8C210890
099A 0 01E0   PECX8 DC      KEYIN+1    PUNCH A CARD IOCC       8C210900
099B 0 1500         DC      /1500                              8C210910
                                                               8C210920
                                                               8C210930
                            BINARY TO HEX  CARD IMAGE RT       8C210940
                                                               8C210950
099C 0 0000   PBIHX DC      0                                  8C210960
099D 0 1800         RTE  16            PUT BIN WORD TO BE      8C210970
                                       * CONVERTED IN Q REG    8C210980
099E 0 6911         STX  1 PBIY1+1     SAVE X1                 8C210990
099F 0 6A12         STX  2 PBIY2+1     SAVE X2                 8C211000
09A0 0 6104         LDX  1 4           SET LOOP CONTROL        8C211010
09A1 0 1810   PBIY3 SRA  16            CONV CHAR TO HEX        8C211020
09A2 0 1084         SLT  4                                     8C211030
09A3 0 D001         STO  *+1                                   8C211040
09A4 00 66000000    LDX  L2 0                                  8C211050
09A6 00 C6000135    LD   L2 KECOD+1    GET HEX EQUIV           8C211060
09A8 00 D7000230    STO  L3 KEYIN+81                           8C211070
09AA 0 7301         MDX  3 1           BUMP TO NEXT OUTPUT     8C211080
09AB 0 1000         SLA  0             NOP                     8C211090
09AC 0 71FF         MDX  1 -1                                  8C211100
09AD 0 70F3         MDX    PBIY3                                8C211110
09AE 0 7301         MDX  3 1           PUT BLANK IN OUTPUT     8C211120
09AF 00 65000000 PBIY1 LDX L1 0        RESTORE X1              8C211130
09B1 00 66000000 PBIY2 LDX L2 0        RESTORE X2              8C211140
09B3 00 4C80099C    BSC  I PBIHX                               8C211150
                                                               8C211160
                            PUNCH A CARD ROUTINE               8C211170
09B5 0 0000   PED   DC      0                            SE    8C211180
09B6 00 C4000B10    LD   L DTSW        GET SWS                 8C211190
09B8 00 4C2808B11   BSC  L HB05,+Z     BRANCH IF P T           8C211200
09BA 0 1001         SLA  1                                     8C211210
09BB 00 4C2808B11   BSC  L HB05,+Z     BRANCH IF BOTH          8C211220
09BD 00 C400022F PEDEN LD L KEYIN+80                           8C211230
09BF 0 E81F         OR   PEDX1         * AT END OF OUTPUT      8C211240
09C0 00 D400022F    STO  L KEYIN+80                            8C211250
09C2 0 08D1   PEDY4 XIO  PECX5         SENSE DSW               8C211260
09C3 00 4C0409D1    BSC  L PEDY1,E     XFER IF NOT RDY         8C211270
09C5 0 08CA         XIO  PECXC         STACKER SELECT          8C211280
09C6 0 08D3         XIO  PECX8         PUNCH CARD              8C211290
09C7 0 08CC   PEDY2 XIO  PECX5         SENSE DSW               8C211300
09C8 0 1801         SRA  1             CK BUSY                 8C211310
09C9 00 4C0409C7    BSC  L PEDY2,E     XFER IF BUSY            8C211320
09CB 0 180C         SRA  12                                    8C211330
09CC 00 4C0409D8    BSC  L PEDY3,E     XFER IF ERROR ON        8C211340
09CE 0 08C7         XIO  PECX6         RESET DSW               8C211350
09CF 00 4C8009B5 PEDEX BSC I PED       EXIT                SX  8C211360
                                                               8C211370
09D1 0 08C2   PEDY1 XIO  PECX5         SENSE DSW               8C211380
09D2 00 4480012C    BSI  I KEY                                 8C211390
09D4 0 0B95         DC   PECX9                                 8C211400
09D5 0 0000         DC   0                                     8C211410
09D6 0 3006   WAIT6 WAIT 6             1442 NOT RDY=PUNCH)     8C211420
09D7 0 70EA         MDX    PEDY4                                8C211430
                                                               8C211440
09D8 0 08BD   PEDY3 XIO  PECX6         RESET DSW               8C211450
09D9 00 4480012C    BSI  I KEY                                 8C211460
09DB 0 0B95         DC   PECX9                                 8C211470
09DC 0 0000         DC   0                                     8C211480
09DD 0 3007   WAIT7 WAIT 7             1442 ERROR AFTER        8C211490
                                       * PUNCHING              8C211500
09DE 0 70E3         MDX    PEDY4                                8C211510
                                                               8C211520
09DF 0 0008   PEDX1 DC      /0008      END OF PUNCH BIT        8C211530
                                                               8C211540
                                                               8C211550
                                                               8C211560
```

```
                                                               8C211570
                            CONVERT CCD TO EBDIC + KEY         8C211580
                                                               8C211590
09E0 0 0000   PPECD DC      /0000                              8C211600
09E1 0 692B         STX  1 PPEY5+1     SAVE XRS + A + Q        8C211610
09E2 0 6A2C         STX  2 PPEY6+1                             8C211620
09E3 0 682D         STX  3 PPEY7+1                             8C211630
09E4 0 D833         STD    PPEX3                                8C211640
                                                               8C211650
09E5 00 650001DF    LDX  L1 KEYIN      INITIALIZE ROUTINE      8C211660
09E7 00 6D0001DE    STX  L1 KIWC                               8C211670
09E9 0 6380         LDX  3 -80                                 8C211680
09EA 0 6202         LDX  2 2                                   8C211690
09EB 0 61EF   PPEY4 LDX  1 -17         RESTORE KECOD POINTR    8C211700
09EC 00 C7000230 PPEY2 LD L3 KEYIN+81  FETCH KEYBD CHAR        8C211710
09EE 00 F5000A45    EOR  L1 KECOD+17                           8C211720
09F0 0 1804         SRA  4                                     8C211730
09F1 00 4C1809F5    BSC  L PPEY1,+-    BR IF COMPARE           8C211740
09F3 0 7101         MDX  1 1                                   8C211750
09F4 0 70F7         MDX    PPEY2       TRY NEXT CHAR           8C211760
                                                               8C211770
09F5 00 C5000A79 PPEY1 LD L1 KTILT+16  PACK 2 EBDIC CHARS      8C211780
09F7 0 1008         SLA  8                                     8C211790
09F8 0 18D8         RTE  24                                    8C211800
09F9 0 72FF         MDX  2 -1          SKIP IF DONE TWO CHA RS 8C211810
09FA 0 7019         MDX    PPEY3       FETCH NEXT CHAR         8C211820
09FB 0 6202         LDX  2 2                                   8C211830
09FC 0 1800         RTE  16                                    8C211840
09FD 00 D48001DE    STO  I KIWC        PLACE IN OUTPUT AREA    8C211850
09FF 00 740101DE    MDX  L KIWC,1      NEXT STORAGE AREA       8C211860
0A01 0 F015         EOR    PPEX2                                8C211870
0A02 00 4C200A14    BSC  L PPEY3,Z     BR - NOT DBLE BLANK     8C211880
0A04 0 61FF   PPEY8 LDX  1 -1          SET TERM                8C211890
0A05 00 6D8001DE    STX  L1 KIWC                               8C211900
0A07 00 4480012C    BSI  I KEY         GO PRINT WHOLE EDIT     8C211910
0A09 0 01DF         DC     KEYIN       MSG AREA                8C211920
0A0A 0 0000         DC     0                                   8C211930
0A0B 0 C80C         LDD    PPEX3       RESTORE XRS, A AND Q    8C211940
0A0C 00 65000000 PPEY5 LDX L1 /0000                            8C211950
0A0E 00 66000000 PPEY6 LDX L2 /0000                            8C211960
0A10 00 67000000 PPEY7 LDX L3 /0000                            8C211970
0A12 00 4C8009E0    BSC  I PPECD       EXIT TO USER            8C211980
                                                               8C211990
0A14 0 7301   PPEY3 MDX  3 1           SKIP IF DONE            8C212000
0A15 0 70D5         MDX    PPEY4                                8C212010
0A16 0 70ED         MDX    PPEY8                                8C212020
                                                               8C212030
0A17 0 4040   PPEX2 DC     /4040       DOUBLE SPACE EBDIC      8C212040
0A18   0002   PPEX3 BSS  E 2           SAVED A AND Q           8C212050
                                                               8C212060
                                                               8C212070
                                                               8C212080
                            KEYBOARD CODES              *      8C212090
0A1A   0000         BSS  E                                     8C212100
0A1A 0 0000   KSNS  DC     /0000       SENSE-NO RESET          8C212110
0A1B 0 0F02         DC     /0F02                               8C212120
0A1C 0 0000   KMSG  DC     /0000       MESS ADRS               8C212130
0A1C          KECGD EQU    KMSG                                8C212140
0A1D 0 0000   KOUT  DC     /0000       ROT-TLT OUTPUT TABLE    8C212150
0A1E 0 0000         DC     /0000                               8C212160
0A1F 0 0000         DC     /0000                               8C212170
0A20 0 0004   K0004 DC     4                 CONSTANT          8C212180
                                                               8C212190
0A21 0 4400   KL    DC     /4400                               8C212200
0A22 0 0000   KAQ   DC     0           ACC                     8C212210
0A23 0 0000         DC     0           Q REG                   8C212220
                                                               8C212230
                                                               8C212240
```

```
0A24 0 0000   KRDY  DC  /0000    SENSE - RESET CMND   8C212250
0A25 0 0F03         DC  /0F03                         8C212260
0A26 0 0A24   KPRT  DC  KRDY      PRINT COMMAND        8C212270
0A27 0 0902         DC  /0902                          8C212280
0A28 0 0000   KPCD  DC  /0000     KBD PROCEED COMMAND   8C212290
0A29 0 0C02         DC  /0C02                          8C212300
0A2A 0 01DF   KRED  DC  KEYIN      READ KBD COMMAND      8C212310
0A2B 0 0A02         DC  /0A02                          8C212320
022C 0 0001   KONE  DC  1          CONSTANT 1           8C212330
0A2D 0 8120   KN    DC  /8120      UPPER CASE N         8C212340
0A2E 0 8060   KY    DC  /8060               Y           8C212350
0A2F 0 4420         DC  /4420               *           8C212360
0A30 0 FFFF         DC  /FFFF                           8C212370
0A31 0 8420   KECPD DC  /8420                           8C212380
0A32 0 80A0         DC  /80A0               .           8C212390
0A33 0 4C00         DC  /4000               -           8C212400
0A34 0 0000   KECOD DC  /0000      SPACE                8C212410
0A35 0 2000         DC  /2000      0                    8C212420
0A36 0 1000         DC  /1000      1                    8C212430
0A37 0 0800         DC  /0800      2                    8C212440
0A38 0 0400         DC  /0400      3                    8C212450
0A39 0 0200         DC  /0200      4                    8C212460
0A3A 0 0100         DC  /0100      5                    8C212470
0A3B 0 0080         DC  /0080      6                    8C212480
0A3C 0 0040         DC  /0040      7                    8C212490
0A3D 0 0040         DC  /0040      8                    8C212500
0A3E 0 0010         DC  /0020      9                    8C212510
0A3F 0 9000   KECAD DC  /9000      A                    8C212520
0A40 0 8800         DC  /8800      B                    8C212530
0A41 0 8400   KC    DC  /8400      C                    8C212540
0A42 0 8200         DC  /8200      D                    8C212550
0A43 0 8100   PBIX2 DC  /8100      E                    8C212560
0A44 0 8080         DC  /8080      F                    8C212570
0A45 0 0002   KRENT DC  /0002    ERASE FIELD            8C212580
0A46 0 0004   KERSE DC  /0004    ERASE CHAR             8C212590
0A47 0 0008   KENDK DC  /0008    END OF MESSAGE         8C212600
0A48 0 4100   KAL   DC  /4100    LOWER CASE N           8C212610
0A49 0 2020         DC  /2020               N           8C212620
0A4A 0 4220         DC  /4220               Y           8C212630
0A4B 0 FFFF         DC  /FFFF               *           8C212640
0A4C 0 8220         DC  /8220                           8C212650
0A4D 0 FFFF         DC  /FFFF               .           8C212660
0A4E 0 FFFF         DC  /FFFF                           8C212670
0A4F 0 2420   KCMA  DC  /2420               .           8C212680
*********************************************
                                  TYPEWRITER CODES
                                  AND EBDIC CODES
0A50 0 16C7   KTGLT DC  /16C7      G                    8C212760
0A51 0 26C8         DC  /26C8      H                    8C212770
0A52 0 22C9         DC  /22C9      I                    8C212780
0A53 0 7ED1         DC  /7ED1      J                    8C212790
0A54 0 5AD2         DC  /5AD2      K                    8C212800
0A55 0 5ED3   KLRT  DC  /5ED3      L                    8C212810
0A56 0 72D4         DC  /72D4      M                    8C212820
0A57 0 96E7         DC  /96E7      X                    8C212850
0A58 0 52D6         DC  /52D6      O                    8C212860
0A59 0 56D7         DC  /56D7      P                    8C212870
0A5A 0 66D8         DC  /66D8      Q                    8C212880
0A5B 0 62D9         DC  /62D9      R                    8C212890
0A5C 0 9AE2         DC  /9AE2      S                    8C212900
0A5D 0 9EE3         DC  /9EE3      T                    8C212910
                                                        8C212920
```

```
0A5E 0 B2E4         DC  /B2E4    U                      8C212930
0A5F 0 B6E5         DC  /B6E5    V                      8C212940
0A60 0 92E6         DC  /92E6    W                      8C212950
0A61 0 76D5         DC  /76D5    N                      8C212960
*
0A62 0 A6E8         DC  /A6E8    Y                      8C212970
0A63 0 D65C         DC  /D65C    *                      8C212980
0A64 0 806B         DC  /806B    .                      8C212990
0A65 0 0048   KTPLT DC  /0048    .                      8C213000
0A66 0 DA4E         DC  /DA4E    +                      8C213010
0A67 0 8460         DC  /8460    -                      8C213020
0A68 0 2140   KTDLT DC  /2140    SPACE                  8C213040
0A69 0 C4F0   KTILT DC  /C4F0    0                      8C213050
0A6A 0 FCF1         DC  /FCF1    1                      8C213060
0A6B 0 D8F2         DC  /D8F2    2                      8C213070
0A6C 0 DCF3         DC  /DCF3    3                      8C213080
0A6D 0 F0F4         DC  /F0F4    4                      8C213090
0A6E 0 F4F5         DC  /F4F5    5                      8C213100
0A6F 0 D0F6         DC  /D0F6    6                      8C213110
0A70 0 D4F7         DC  /D4F7    7                      8C213120
0A71 0 E4F8         DC  /E4F8    8                      8C213130
0A72 0 E0F9         DC  /E0F9    9                      8C213140
0A73 0 3EC1   KTALT DC  /3EC1    A                      8C213160
0A74 0 1AC2         DC  /1AC2    B                      8C213170
0A75 0 1EC3         DC  /1EC3    C                      8C213180
0A76 0 32C4         DC  /32C4    D                      8C213190
0A77 0 36C5         DC  /36C5    E                      8C213200
0A78 0 12C6         DC  /12C6    F                      8C213210
0A79 0 815B   KCR   DC  /815B    CARRIER RETURN         8C213230
                                 KEYBOARD ERROR MSG
0A7A 0 D600   KFELD DC  /D600    *                      8C213260
0A7B 0 D600         DC  /D600    *                      8C213270
0A7C 0 D600         DC  /D600    *                      8C213280
0A7D 0 8100         DC  /8100    CR                     8C213290
0A7E 0 3600         DC  /3600    E                      8C213300
0A7F 0 C400         DC  /C400    0                      8C213310
0A80 0 C400         DC  /C400    0                      8C213320
0A81 0 FC00         DC  /FC00    1                      8C213330
0A82 0 2100         DC  /2100                           8C213340
0A83 0 2100         DC  /2100                           8C213350
0A84 0 5E00         DC  /5E00    SP                     8C213360
0A85 0 2200         DC  /2200    L                      8C213370
0A86 0 7600         DC  /7600    I                      8C213380
0A87 0 3600         DC  /3600    N                      8C213390
0A88 0 2100         DC  /2100    E                      8C213400
0A89 0 1E00         DC  /1E00    SP                     8C213410
0A8A 0 3E00         DC  /3E00    C                      8C213420
0A8B 0 7600         DC  /7600    A                      8C213430
0A8C 0 1E00         DC  /1E00    N                      8C213440
0A8D 0 3600         DC  /3600    C                      8C213450
0A8E 0 5E00         DC  /5E00    E                      8C213460
0A8F 0 5E00         DC  /5E00    L                      8C213470
0A90 0 3600         DC  /3600    L                      8C213480
0A91 0 3200         DC  /3200    E                      8C213490
0A92 0 8120   K8120 DC  /8120    D                      8C213500
0A93 0 8101         DC  /8101    CR                     8C213510
                                 ROUTINE TO READ ONE
                                 SKELTON SECTION
0A94 0 0000   RDSK  DC  0                               8C213560
0A95 0 C005         LD   RDSX0   GET LDR RETURN   SE    8C213570
0A96 00 D4000124    STO L /0124  SET                    8C213580
0A98 0 6050         LDX X /0050  BRANCH TO LDR          8C213590
                                                        8C213600
```

```
OA99 C0 4C800A94   RDSK1 BSC  I   RDSK       EXIT                SX   8C213610
OA9B 0  0A99       RDSX0 DC       RDSK1      RETURN                   8C213620
                   *********************************************      8C213630
                   *                                                  8C213640
                   *                                                  8C213650
                   *                                                  8C213660
                   *              XFER VECTOR TBLS BY FORM NO.         8C213670
OA9C 0  0AB1       LRAIT DC       DONT       FORM 0                   8C213680
OA9D 0  0ADC             DC       LRTF1      1                        8C213690
OA9E 0  0AD4             DC       LRTF2      2                        8C213700
                   *                                                  8C213710
                   *                                                  8C213720
                   *                                                  8C213730
                   *                                                  8C213740
                   *                                                  8C213750
                   *                                                  8C213760
                   *                                                  8C213770
                   *                                                  8C213780
                   *                                                  8C213790
OA9F 0  0000       LWKA  DC                  WORK STORAGE AREA        8C213800
                   *                                                  8C213810
OAA0 0  0000       LDOIT DC                                      SE   8C213820
OAA1 0  6200             LDX   2  0                                   8C213830
OAA2 00 6E00043F         STX L2   LGROP      RESET GROUP CNTR         8C213840
OAA4 00 65800AA0         LDX I1   LDOIT                               8C213850
OAA6 0  C101             LD    1  1          LD CHR / WORD CNT        8C213860
OAA7 0  D0F7             STO      LWKA       SAVE IT                  8C213870
OAA8 0  6901             STX   1  LWCLD+1                             8C213880
OAA9 00 65800000   LWCLD LDX I1              LD FORM NUMBER           8C213890
OAAB 00 45800A9C         BSI I1   LRAIT      BRANCH TO RTN            8C213900
OAAD 00 74020AA0   DONT1 MDX L    LDOIT,2    INCR RETURN              8C213910
OAAF 00 4C800AA0         BSC I    LDOIT      EXIT                SX   8C213920
                   *                                                  8C213930
OAB1 0  0000       DONT  DC       0                                   8C213940
OAB2 00 4C000AAD         BSC L    DONT1                               8C213950
                   *                                                  8C213960
                   *                                                  8C213970
                   *                                                  8C213980
                   *              DATA WRONG ERROR                    8C213990
                   *                                                  8C214000
OAC1 0  0000       LERR  DC       0                                   8C214010
OAC2 00 44800132         BSI I    SER        DATA WRONG         SRC   8C214020
OAC4 0  0B88             DC       PCKBE                               8C214030
                   *                                                  8C214040
                   *                                                  8C214050
OAC5 0  0000       LWCC  DC                                      SE   8C214060
OAC6 0  6B01             STX   3  LD01+1                              8C214070
OAC7 00 C5000000   LD01  LD  L1              LD SPACE                 8C214080
OAC9 00 44200ACD         BSI L    LMTRM,Z    BR IF NOT SPACE          8C214090
OACB 00 4C800AC5         BSC I    LWCC       EXIT                SX   8C214100
                   *                                                  8C214110
                   *                                                  8C214120
                   *                                                  8C214130
                   *                                                  8C214140
OACD 0  0000       LMTRM DC                                      SE   8C214150
OACE 0  F004             EOR      LTERM                               8C214160
OACF 00 44200AC1         BSI L    LERR,Z     BR IF ERROR        SRC   8C214170
OAD1 00 4C800ACD         BSC I    LMTRM                          SX   8C214180
```

```
OAD3 0  FFFF       LTERM DC       /FFFF      ALL BITS                 8C214290
                   *                                                  8C214300
                   *                                                  8C214310
                   *                                                  8C214320
                   *                                                  8C214330
                   *                                                  8C214340
OAD4 0  0000       LRTF2 DC                                      SE   8C214350
OAD5 0  D002             STO      LCHBW      SET CHR / WD             8C214360
OAD6 00 44800137         BSI I    PHKYB      GO CONVERT TO HEX   SRC  8C214370
OAD8 0  0000       LCHBW DC                  CHR / BINARY WORD        8C214380
OAD9 0  0437             DC       ZERO       DISPLACEMENT ADDR        8C214390
OADA 00 4C800AD4         BSC I    LRTF2      EXIT                SX   8C214400
                   *                                                  8C214410
                   *                                                  8C214420
                   *                                                  8C214430
                   *                                                  8C214440
                   *                                                  8C214450
                   *                                                  8C214460
OADC 0  0000       LRTF1 DC                                      SE   8C214470
OADD 0  D003             STO      LCHBD      SET CHR / WD             8C214480
OADE 0  4006             BSI      LTRFX      GO TO SETUP AND CK       8C214490
OADF 00 44800136         BSI I    PDKYB      GO CONVERT TO DEC   SRC  8C214500
OAE1 0  0000       LCHBD DC                  CHR / BINARY WORD        8C214510
OAE2 0  0437             DC       ZERO       DISPLACEMENT ADDR        8C214520
OAE3 0  4C800ADC         BSC I    LRTF1      EXIT                SX   8C214530
                   *                                                  8C214540
                   *                                                  8C214550
                   *                                                  8C214560
                   *                                                  8C214570
OAE5 0  0000       LTRFX DC                                      SE   8C214580
OAE6 0  40CD             BSI      LBGNR      GO SET UP FOR FORM       8C214590
OAE7 00 67800A9F         LDX I3   LWKA       LD CHAR / WC CNT         8C214600
OAE9 0  7301             MDX   3  1                                   8C214610
OAEA 0  40DA             BSI      LWCC       GO TO CHECK FORM         8C214620
OAEB 00 4C800AE5         BSC I    LTRFX      EXIT                SX   8C214630
                   *                                                  8C214640
                   *                                                  8C214650
                   *                                                  8C214660
                   *                                                  8C214670
                   *                                                  8C214680
                   *              PUNCH LEADER                        8C214690
                   *                                                  8C214700
OAED 0  0000       PPT   DC       0                              SE   8C214710
OAEE 0  6303       PPT1  LDX   3  3          SET IXING                8C214720
OAEF 0  C009       PPT1A LD       WDCT       SET WD CT                8C214730
OAF0 0  D018             STO      CHOUT                               8C214740
OAF1 00 C7000AF9         LD  L3   LEADE-1    GET PATTERN              8C214750
OAF3 0  D014             STO      XIOUT      SET                      8C214760
OAF4 0  4008             BSI      PUTAP      PUNCH TAPE          SRC  8C214770
OAF5 0  73FF             MDX   3  -1         DECR IX 3                8C214780
OAF6 0  70F8             MDX      PPT1A      LOOP                     8C214790
OAF7 00 4C800AED         BSC I    PPT        EXIT                SX   8C214800
                   *                                                  8C214810
OAF9 0  0019       WDCT  DC       25         WD CT                    8C214820
OAFA 0  7F00       LEADE DC       /7F00      PATTERNS                 8C214830
OAFB 0  0000             DC       /0000                               8C214840
OAFC 0  7F00             DC       /7F00                               8C214850
                   *                                                  8C214860
                   *              PUNCH TAPE                          8C214870
                   *                                                  8C214880
OAFD 0  0000       PUTAP DC       0                              SE   8C214890
OAFE 0  080B       BCK   XIO      SEN55      SENSE                    8C214900
OAFF 0  1808             SRA      8                                   8C214910
OB00 00 4C040AFE         BSC L    BCK,E      BRANCH = NOT READY       8C214920
OB02 0  0809             XIO      PUNK       PUNCH A CHR              8C214930
OB03 00 74FF0B09         MDX L    CHOUT,-1   DECR WD CT               8C214940
OB05 0  70F8             MDX      BCK        LOOP                     8C214950
                                                                      8C214960
```

```
0806 00 4C800AFD          BSC  I  PUTAP     EXIT              SX   8C214970
0808    0000              BSS  E  0                                8C214980
0808 0  0000      XIOUT   DC     0                                 8C214990
0809 0  0000      CHOUT   DC     0          OUTPUT AREA             8C215000
080A 0  0000      SEN55   DC     0          WD CT                   8C215010
080B 0  1F01              DC     /1F01      SENSE IOCC              8C215020
080C 0  0806      PUNK    DC     XIOUT      PUNCH IOCC              8C215030
080D 0  1900              DC     /1900                              8C215040
080E 0  0810      RDSW    DC     DTSW       RD SWS IOCC             8C215050
080F 0  0240              DC     /0240                              8C215060
0810 0  0000      DTSW    DC     0          SW STORAGE              8C215070
                                                                    8C215080
                  .                 CONVERT AND PUNCH               8C215090
                  .                                                 8C215100
0811 0  6909      HB05    STX  1  EXT+1     SAVE IXING              8C215110
0812 0  6A0A              STX  2  EXT1+1                            8C215120
0813 0  6B11              STX  3  EXT2+1                            8C215130
0814 00 6500FFB0          LDX  L1 -80       SET IXING               8C215140
0816 00 C5000230          LD   L1 KEYIN+81  GET A WD                8C215150
0818 00 4C200B2C          BSC  L  HB05A,Z   BRANCH IF NOT 0         8C215160
081A 00 65000000  EXT     LDX  L1 0         RESTORE IXING           8C215170
081C 00 66000000  EXT1    LDX  L2 0                                 8C215180
081E 00 C4000141          LD   L  BINRY+3   GET CD NO               8C215190
0820 00 F400043D          EOR  L  TERM      CK FOR END CD           8C215200
0822 00 44180AED          BSI  L  PPT,+-    PUNCH TRAILER IF END    8C215210
0824 00 67000000  EXT2    LDX  L3 0                                 8C215220
0826 0  C0E9              LD     DTSW       GET SWS                 8C215230
0827 0  1001              SLA    1                                  8C215240
0828 00 4C1009CF          BSC  L  PEDEX,-   BRANCH IF NOT BOTH      8C215250
082A 00 4C0009BD          BSC  L  PEDEN     PUNCH CARD              8C215260
082C 0  1810      HB05A   SRA    16         CLEAR WD CT             8C215270
082D 0  D022              STO    PCAM                               8C215280
082E 0  7101      HB06    MDX  1  1         DECR IX 1               8C215290
082F 0  7001              MDX     HB07      CONTINUE                8C215300
0830 0  7022              MDX     LB06      PUNCH CARD              8C215310
0831 0  6204      HB07    LDX  2  4         SET 4 CHRS              8C215320
0832 0  1004      HB10    SLA    4          MOVE CHR                8C215330
0833 0  D01E              STO    TEMP1      SAVE                    8C215340
0834 00 C5000230          LD   L1 KEYIN+81  GET WD                  8C215350
0836 00 4C180B53          BSC  L  LB06,+-   BRANCH IF 0             8C215360
0838 0  6300      HTJB    LDX  3  0         SET COUNTER             8C215370
0839 0  4828              BSC     +Z        IS IT NEG               8C215380
083A 0  6203              MDX  3  3         YES                     8C215390
083B 0  1003              SLA    3          REMOVE ZONE             8C215400
083C 00 4C180B45          BSC  L  HTBZ,+-   BRANCH IF 0             8C215410
083E 0  7301              MDX  3  1         INCR CTR                8C215420
083F 00 4C280B43  HTJB1   BSC  L  HTBX,+Z   BRANCH IF NEG           8C215430
0841 0  1001              SLA    1          MOVE BIT                8C215440
0842 0  70FB              MDX     HTJB1-1   BRANCH                  8C215450
0843 0  6800      HTBX    STX  3  TEMP      SAVE CT                 8C215460
0844 0  C00C              LD     TEMP       GET CT                  8C215470
0845 0  E80C      HTBZ    OR     TEMP1      ADD TO SAVED            8C215480
0846 0  7101              MDX  1  1         DECR IX 1               8C215490
0847 0  72FF              MDX  2  -1        DECR IX 2               8C215500
0848 0  70E9              MDX     HB10       LOOP                    8C215510
0849 00 67800B50          LDX  I3 PCAM      SET IX 3                8C215520
084B 00 D7000140          STO  L3 BINRY+2   SAVE                    8C215530
084D 00 74010B50          MDX  L  PCAM,1    INCR LOC                8C215540
084F 0  700E              MDX     HB06       LOOP                    8C215550
                  .                                                 8C215560
0850 0  0000      PCAM    DC     0          STORAGE                 8C215570
0851 0  0000      TEMP    DC     0                                  8C215580
0852 0  0000      TEMP1   DC     0                                  8C215590
                  .                                                 8C215600
                  .                 PUNCH EDIT                      8C215610
                  .                                                 8C215620
0853 0  C02C      LB06    LD     H8100      GET E                   8C215630
                                                                    8C215640
```

```
0B54 00 D400013F          STO  L  BINRY+1   SAVE                    8C215650
0B56 00 C4000141          LD   L  BINRY+3   GET CD NO               8C215660
0B58 00 F400043D          EOR  L  TERM      CK FOR TERM             8C215670
0B5A 00 4C180B83          BSC  L  LB08,+-   BRANCH IF TERM          8C215680
0B5C 00 C4000142          LD   L  BINRY+4   GET NO ENTRIES          8C215690
0B5E 0  8022              A      FOUR       ADD 4                   8C215700
0B5F 0  D004              STO    LB0A+1     SAVE                    8C215710
0B60 0  1008              SLA    8          MOVE                    8C215720
0B61 00 D400013E          STO  L  BINRY     SAVE                    8C215730
0B63 00 66000000  LB0A    LDX  L2 0         SET IXING               8C215740
0B65 00 6500013E  LB09    LDX  L1 BINRY                             8C215750
0B67 0  C100              LD   1  0         GET WD                  8C215760
0B68 0  D09F              STO    XIOUT      SET                     8C215770
0B69 0  C014              LD     ONE        GET 1                   8C215780
0B6A 00 D4000809          STO  L  CHOUT     SET                     8C215790
0B6C 0  4090              BSI     PUTAP     PUNCH TAPE      SRC     8C215800
0B6D 0  7101              MDX  1  1         INCR IX 1               8C215810
0B6E 0  C100      LB07    LD   1  0         GET WD                  8C215820
0B6F 0  D098              STO    XIOUT      SET                     8C215830
0B70 0  C00D              LD     ONE        SET WD CT               8C215840
0B71 0  D097              STO    CHOUT      SET                     8C215850
0B72 0  408A              BSI     PUTAP     PUNCH TAPE      SRC     8C215860
0B73 0  C100              LD   1  0         GET WD                  8C215870
0B74 0  1008              SLA    8          SET 2ND HALF            8C215880
0B75 0  D092              STO    XIOUT      SET                     8C215890
0B76 0  C007              LD     ONE        GET 1                   8C215900
0B77 0  D091              STO    CHOUT      SET WD CT               8C215910
0B78 00 44800AFD          BSI  L  PUTAP     PUNCH TAPE      SRC     8C215920
0B7A 0  7101              MDX  1  1         INCR IX 1               8C215930
0B7B 0  72FF              MDX  2  -1        DECR IX 2               8C215940
0B7C 0  70F1              MDX     LB07      LOOP                    8C215950
0B7D 0  709C              MDX     EXT       EXIT                    8C215960
                  .                                                 8C215970
0B7E 0  0001      ONE     DC     1          CONSTANTS               8C215980
0B7F 0  8000      K8000   DC     /8000                              8C215990
0B80 0  8100      H8100   DC     /8100                              8C216000
0B81 0  0004      FOUR    DC     4                                  8C216010
0B82 0  0300      TREE    DC     /0300                              8C216020
                  .                                                 8C216030
0B83 0  C0FE      LB08    LD     TREE      GET 0300                8C216040
0B84 00 D400013E          STO  L  BINRY     SET                     8C216050
0B86 0  6203              LDX  2  3         SET IX 2                8C216060
0B87 0  70DD              MDX     LB09      BRANCH                  8C216070
0B88    0012      PCKBE   EBC    .E003 CNTRL-ILLEGAL.              8C216080
0B91    0006              EBC    . ENTRY.                          8C216090
0B94 0  FFFF      PCKX4   DC     /FFFF                              8C216100
0B95    0012      PECX9   EBC    .E005 CNTRL-1442 ER.              8C216110
0B9E 0  FFFF      PECXD   DC     /FFFF                              8C216120
0B9F    0012      PECXF   EBC    .$$A001 CNTRL-EDIT .              8C216130
0BA8    0007              EBC    .CD LIST.                          8C216140
0BAC 0  FFFF              DC     /FFFF                              8C216150
0BAD    0012      SE002   EBC    .E002 CNTRL-ENTRY T.              8C216160
0BB6    0008              EBC    .OO LARGE.                         8C216170
0BBA 0  FFFF              DC     /FFFF                              8C216180
0BBB    0012      SM2     EBC    .C000 CNTRL-ENTER 2.              8C216190
0BC4    0012              EBC    . DIGIT PID TO BE E.              8C216200
0BCD    0005              EBC    .DITED.                            8C216210
0BD0 0  FFFF              DC     /FFFF                              8C216220
0BD1    000F      SM33    EBC    .A002 END OF PRG.                 8C216230
0BD9 0  FFFF              DC     /FFFF                              8C216240
0BDA    0012      LEM01   EBC    .E004 CNTRL-FORMAT .              8C216250
0BE3    0002              EBC    .ER.                               8C216260
0BE4 0  FFFF              DC     /FFFF                              8C216270
0BE5 0  0000      HLTE    DC     0                                  8C216280
0BE6 0  3005      WAIT5   WAIT   5          RELOAD REQUIRED  SRC    8C216290
0BE7 00 4C800BE5          BSC  I  HLTE                       SX     8C216300
0BEA    058A              END    STARI            8C21630     8C216310
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BCK	0AFE	0B00,0B05
BGNR	0438	
BINRY	013E	059F,07A2,0780,07BB,07C5,0839,0B1E,084B,0B54,0B56, 0B5C,0B61,0B65,0884
BWC	013D	0835,0837,0863,088C
CHOUT	0B09	0AF0,0B03,086A,0B71,0B77
CKYN	012D	
CKYNE	077A	012D,0792,0794
CKYN0	0794	077E,0783
CKYN1	0792	078B,078D
CODE	0586	
CPID	07FF	07DA,07E6
DKYB	0818	0136,081A
DONT	0AB1	0A9C
DONT1	0AAD	0AB2
DTSW	0B10	0919,0923,0956,0986,080E,0B26
END0	0136	
END1	0589	013A,05AF
ERR	0439	
ERR04	05E3	05A3
EXIT	072B	
EXT	0B1A	0B11,0B7D
EXT1	0B1C	0B12
EXT2	0B24	0B13
FOUR	0B81	085E
HB05	0B11	0988,0988
HB05A	0B2C	0818
HB06	0B2E	0B4F
HB07	0B31	0B2F
HB10	0B32	0848
HKYB	0821	0137,081B,0828,086F,0879
HLT	0585	
HLTE	0BE5	0585,08E7
HTBX	0B43	0B3F
HTBZ	0B45	0B3C
HTOB	0B38	
HTOB1	0B3F	0842
HB100	0B80	0853
KAL	0A48	0687
KAQ	0A22	05E8,062F
KBKSP	0702	06FB
KC	0A41	
KCHK	0621	05FF
KCMA	0A4F	06CE
KCOMA	0700	06E2
KCR	0A79	05F6,0621
KDEC	06B3	065C
KDEC1	06B4	06B2,06B7
KEBC2	05FB	061E
KEBC3	0602	0620
KEBC4	0605	060D
KEBC6	061F	0611
KECAD	0A73	0668,0686
KECGD	0A1C	06B1,06B3,0686
KECOD	0A34	065A,06B3,08DE,09A6,09EE
KECPD	0A31	066F,06A9
KENDK	0A47	0709
KERR	072D	0678,0698,06D6,0706,0710,0724
KERR1	0735	073D
KERSE	0A46	06E9
KEY	012C	0598,05DB,07CF,090F,097E,0984,09D2,09D9,0A07
KEYE	05E7	012C,05EE,05F2,0625,0632,0634,0637
KEYFM	0729	063B,0660
KEYIN	01DF	0645,0778,0780,0785,078A,087F,0915,0936,093E,0992, 099A,09A8,09BD,09C0,09E5,09EC,0A09,0A2A,0B16,0B34

SYMBOL	VALUE	REFERENCES
KEYNO	072A	063F,070F
KEYOG	0641	0742
KEYO	0647	06A6,06B5,06E6,06EF,06F2,06FE,070B,0736,0740
KEY1	064B	0653
KEY2	064D	C655
KEY3	0656	0650
KEY96	0629	05E8,072B
KEY97	062B	05E9
KEY98	062D	05EA
KEY99	0631	05ED
KFELD	0A7A	072E
KFMO	067D	0664,0671
KFMO1	067E	0684
KFMO2	0686	068C
KFMS	0658	
KFMS1	0659	065F
KFM2	0666	
KFM21	0667	066D
KFRM	0636	0627
KHEX	0686	066A
KINO	080E	0135,0816
KIN1	0803	0134,080C
KIWC	01DE	0643,06C7,06D2,06DC,06ED,06F8,070D,0712,0714,0718, 0721,0732,0738,073E,0808,0812,09E7,09FD,09FF,0A05, 0AB5
KL	0A21	068E
KLRT	0A55	069D
KMDX	06A8	0681
KMPX	06B1	0689,06AB
KMSG	0A1C	05F0,05FB,0605,061C,0A1D
KN	0A2D	067F,06B1
KNBY	0745	0649,075C,0765,076B
KNBY0	074B	0756
KNBY1	074D	0753
KNBY4	075D	0757
KNBY5	0761	0746,0750
KNEG	0744	0725,0738
KONE	0A2C	05FD,0612,0662,069F,06C0,06DF
KOUT	0A1D	05F4,0616,061A,06A1,06C2
KPCD	0A28	0648
KPNE	069F	067C
KPRT	0A22	0769,0773
KRDY	0A24	0763,076C,0A26
KRED	0A2A	0647,0656,0659,0659,0667,0667,066E,066E,0708,0708
KRENT	0A45	0704
KSNS	0A1A	064D,0740
KSPC	06CC	0690
KSPCA	0714	071B
KSPCE	0725	071E,0723
KSPC2	06DF	06DA
KSPC5	06E8	06D0
KSPC6	06FB	06F5
KSPC9	0703	06E8
KSTO	06B8	0684,06BC,06CA
KTALT	0A73	
KTGLT	0A50	0602,06BE
KTILT	0A69	0586,09F5
KTIME	0767	0749,0754
KTOLT	0A68	
KTPLT	0A65	C67A
KTYP	0768	0584,0618,0623,06A4,06C5,06E4,06FD,0730,0776
KTYPS	0584	
KTYP1	0769	0779
KTYP5	076C	0772
KTYP6	0773	076F
KY	0A2E	
KOOFF	05E6	05A1
KO002	0789	06D4,079C

K0003	0802	07F5
K0004	0A20	
K3095	05E2	058B,05B9
K8000	0B7F	0676,0696
K8120	0A92	
LBGNR	0AB4	0438,0ABF,0AE6
LB0A	0B63	0B5F
LB06	0B53	0B30,0B36
LB07	0B6E	0B7C
LB08	0B83	0B5A
LB09	0B65	0B87
LCHBD	0AE1	0ADD
LCHBW	0AD8	0AD5
LDDIT	0AA0	0727,0AA4,0AAD,0AAF
LDD1	0AC7	0AC6
LEADE	0AFA	0AF1
LEMO1	0BDA	
LERR	0AC1	0439,0ACF
LGROP	043F	0AA2
LMTRM	0ACD	043B,0AC9,0AD1
LRAIT	0A9C	0AA8
LRTF1	0ADC	0A9D,0AE3
LRTF2	0AD4	0A9E,0ADA
LTFRM	0AD3	0ACE
LTRFX	0AE5	043C,0ADE,0AE8
LWC	043E	0AB8,0ABA,0ABD
LWCC	0AC5	043A,0ACB,0AEA
LWCLD	0AA9	0AA8
LWKA	0A9F	0AA7,0AE7
MIRM	043B	
NO	0798	0787
NOEN	0800	07DB,07E4,07EA,07F6
NO1	0799	078C
NTPT	0928	0920,093A
ONE	0B7E	0B69,0B70,0B76
PHIHX	099C	094A,0952,096D,0973,0975,0983
P4IX2	0A43	0944
P8IY1	09AF	099E
P8IY2	09B1	099F
P8IY3	09A1	09AD
PCAM	0885	081D,0B49,084D
PCKB	08D6	0844,08D9,08FC,0900
PCKBA	0902	08D8,08E0,08EA,08EE
PCKBB	0903	08FA,08FB
PCKBE	0888	0791,08C7,08F7,0AC4
PCKBX	08FE	08D7,08CC,08F4
PCKB1	08DC	08DB,08E4
PCKB3	08F8	08E1
PCKB4	08F5	08E8,08F0
PCKX1	0904	0889,08A8,08E7
PCKX2	0905	08EB
PCKX3	0906	08EF
PCKX4	0894	08F2
PDKWA	08C8	0887,089D,089E,08B4,088A,088F,08C1
PDKX1	08CD	081E,08A5
PDKX2	08CC	0897
PDKX3	08D5	08AE
PDKX4	08CA	08C2
PDKYA	08C1	08B1
PDKYB	0136	0ADF
PDKYE	08C5	088B,08AA
PDKYF	0882	08C3
PDKYM	08A4	089A
PDKYJ	089B	08A6
PDKY1	0886	084E
PDKY2	088F	088E
PDKY3	0896	08A2
PDKY6	08A7	08A3

PDKY7	08B6	08AC
PDKY8	08BF	08AF,08B7
PDKY9	08BB	08C0
PECOR	0907	05D0,0969
PECOS	0967	090A
PECXC	0990	095A,09C5
PECXD	0B9E	094C,0950
PECXE	098F	0972,0977
PECXF	0B9F	0911
PECX1	098C	0908,0968
PECX3	098E	096C
PECX4	0992	092B
PECX5	0994	0928,092C,095C,09C2,09C7,09D1
PECX6	0996	0933,0960,0988,09CE,09DB
PECX7	0998	095B
PECX8	099A	09C6
PECX9	0B95	0980,0986,09D4,09DB
PECYA	093E	0941
PECYB	096B	094E
PECYC	095C	095E
PECYD	0974	0979
PECYE	093C	0926
PECYF	090C	
PECY1	0961	090C,0958
PECY2	0963	090D
PECY3	0965	090E
PECY4	092C	092E
PECY5	0936	0939
PECY6	097E	0929
PECY7	0917	0983,0984
PECY8	0984	0931
PED	0985	0953,097A,09CF
PEDEN	09BD	082A
PEDEX	09CF	0828
PEDX1	090F	098F
PEDY1	09D1	09C3
PEDY2	09C7	09C9
PEDY3	09DB	09CC
PEDY4	09C2	09D7,09DE
PHDSW	09BD	081C,0824,084C
PHKX1	087C	0819,0822,0878
PHKX2	087E	082D,0830,0841,084F,0858,0865,0888,0893,08A7,08AD,08E5
PHKX3	087F	0832
PHKX4	0880	0833,083F,0867,0868,0869
PHKX5	0881	0866,088D
PHKX6	0882	086C
PHKX7	0883	0823
PHKX8	0884	0825
PHKYB	0137	0AD6
PHKYC	0846	0826
PHKYD	0826	0820
PHKYF	0861	0885
PHKYH	0865	088E
PHKYS	0877	0827
PHKY1	0847	083B,0891,08B2
PHKY2	0843	084B
PHKY3	0852	083C,0856
PHKY4	085A	085F
PHKY5	0837	086E
PHKY6	0871	0828
PHKY7	0873	0829
PHKY8	0875	082A
PHKY9	085E	085C,085D
PPECD	09E0	0954,0978,0A12
PPEX2	0A17	0A01
PPEX3	0A18	09E4,0A0B
PPEY1	09F5	09F1

PPEY2	09EC	09F4
PPEY3	0A14	09FA,0A02
PPEY4	09EB	0A15
PPEY5	0A0C	09E1
PPEY6	0A0E	09E2
PPEY7	0A10	09E3
PPEY8	0A04	0A16
PPT	0AED	0921,0AF7,0822
PPT1	0AEE	
PPT1A	0AEF	0AF6
PT	0921	091B,091E,097D
PUNK	0B0C	0B02
PUTAP	0AFD	0AF4,CB06,0B6C,0B72,0B78
RDSK	0A94	0138,05A6,0A99
RDSK1	0A99	0A9B
RDSW	0B0E	0917
RDSX0	0A9B	0A95
SCH	0131	
SCHE	078A	0131,07C7
SCHER	07C1	07BE
SCH1	07C5	07BF,07C0,07C2
SECB	07FE	07D9,07E8
SECSE	07D5	0133,07D6,07F9,07FB
SECSU	0133	
SEIB	0442	05D7,0801,0913
SFN55	0B0A	0AFE
SER	0132	05E3,078F,07A9,08C5,08F5,0AC2
SERE	07CB	0132,07CC
SER1	07D1	07CE
SE002	0BAD	05E5,07AB
SE1	07D9	
SE2	07E2	07DF
SE3	07ED	07F2
SIA	07B6	
SIL	012F	
SILE	07A1	012F,07AC
SILER	07A9	07A6,07B4,07C4
SILSE	07AF	0130,07B6
SILSW	0130	
SIL1	07AC	07A7,07A8
SIWB	07FD	07D8,07E0
SKINA	0808	0808
SKINB	0812	0815
SKINO	0135	
SKIN1	0134	0641
SKI1	0C17	012C,05AB,05C4
SKI2	0C18	012C,05B1
SKI3	0C19	012C
SKI4	0C1A	05B7
SM2	0BBB	059D
SM33	0BD1	05DD
SRST	0588	0596,05A8
SRTRY	0441	079D,07D3
SSEUR	079A	
SSUEE	079A	012E,079B,079F,07A1
SSUER	012E	0599
STARI	058A	0BE9
START	058B	0588,05E0
STBF	0440	0594,05C3,05D3,07DD,07F3,07F7
STBF1	0801	05C5,07DC
STTR	05D7	05DA
STTRM	05C3	05B5
S00F0	07BB	07B3
S000F	07C9	07C1
S0008	07CA	07BD
S1	0599	
S1700	07AE	07A5
S2	013A	

S2E	05A6	05C2
TEMP	0B51	0B43,0B44
TEMP1	0B52	0B33,0B45
TERM	043D	0583,05CD,0806,0B20,0858
TREE	0B82	0B83
TRFX	043C	
WAIT1	0771	3001
WAIT2	075B	3002
WAIT3	0982	3003
WAIT4	0989	3004
WAIT5	0BF6	3005
WAIT6	09D6	3006
WAIT7	09DD	3007
WAIT8	05DF	3008
WCC	043A	
WDCT	0AF9	0AEF
XIOUT	0808	0AF3,0B0C,0B68,086F,0875
XPID	05E1	05A5,05AD
YES	0796	077D
YES1	0797	0782
ZERO	0437	0AD9,0AE2

```
02BC                    ABS
                        ORG      /3001
                  *
                  ************************************************
3001 0  079C            DC       WAIT1+1    1816 IS OUT OF FORMS.
                  *                          MAKE READY AND PRESS
                  *                          START.
                  ************************************************
3002 0  07B6            DC       WAIT2+1    1816 IS HUNG IN BUSY.
                  *                          RESTART IS REQUIRED.
                  ************************************************
3003 0  09AD            DC       WAIT3+1    1442 IS NOT READY
                  *                          BEFORE A READ.
                  *                          MAKE READY AND PUSH
                  *                          START.
                  ************************************************
3004 0  09B4            DC       WAIT4+1    1442 READ ERROR.
                  *                          RELOAD CARDS AND
                  *                          PUSH START TO RETRY.
                  ************************************************
3005 0  0C11            DC       WAIT5+1    RELOAD REQUIRED TO
                  *                          CORRECT ERROR-PRESS
                  *                          START TO IGNORE.
                  ************************************************
3006 0  0A01            DC       WAIT6+1    1442 IS NOT READY
                  *                          BEFORE PUNCH.  MAKE
                  *                          READY AND PRESS START.
                  ************************************************
3007 0  0A08            DC       WAIT7+1    1442 PUNCH ERROR.
                  *                          PRESS START TO RETRY.
                  ************************************************
3008 0  05E6            DC       WAIT8+1    END OF PROGRAM.
                  *                          LOAD SKELETONS AND
                  *                          PRESS START TO RERUN.
                  ************************************************
3009                    ORG      300
0C17              SKI1   EQU      3095
0C18              SKI2   EQU      SKI1+1
0C19              SKI3   EQU      SKI2+1
0C1A              SKI4   EQU      SKI3+1
012C 0  0611      KEY    DC       KEYE
012D 0  07A4      CKYN   DC       CKYNE
012E 0  07C4      SSUER  DC       SSUEE
012F 0  07CB      SIL    DC       SILE
0130 0  07D9      SILSW  DC       SILSE
0131 0  07E4      SCH    DC       SCHE
0132 0  07F5      SER    DC       SERE
0133 0  07FF      SECSU  DC       SECSE
0134 0  082D      SKIN1  DC       KIN1
0135 0  0838      SKINO  DC       KINO
0136 0  0842      PDKYB  DC       DKYB
0137 0  084B      PHKYB  DC       HKYB
0138 00 4C800ABE  ENDO   BSC  I   RDSK
013A 00 4C0005CD  S2     BSC  L   END1
013C 0  0000             DC       0
```

```
8C300001
8C300002
8C300003
8C300007
8C300008
8C300009
8C300010
8C300011
8C300012
8C300013
8C300014
8C300016
8C300017
8C300018
8C300019
8C300020
8C300021
8C300022
8C300023
8C300024
8C300025
8C300026
8C300027
8C300028
8C300029
8C300030
8C300031
8C300032
8C300033
8C300034
8C300035
8C300036
8C300037
8C300038
8C300039
8C300040
8C300041
8C300042
8C300043
8C300044
8C300045
8C300046
8C300047
8C300048
8C300049
8C300050
8C300051
8C300052
8C300053
8C300054
8C300055
8C300060
8C300070
8C300080
8C30009C
8C300100
8C300110
8C300120
8C300130
8C300140
8C300150
8C300160
8C300170
8C300180
8C300190
8C300200
8C300210
```

```
013D 0  0000      BWC    DC       0          BINARY WORD COUNT
013E    00A0      BINRY  BSS      160
                  ************************************************
01DE 0  0000      KIWC   DC
01DF    0258      KEYIN  BSS      600
                  ************************************************
0437 0  0000      ZERO   DC       /0000
0438 0  0ADE      BGNR   DC       LBGNR
0439 0  0AEB      ERR    DC       LERR
043A 0  0AEF      WCC    DC       LWCC
043B 0  0AF7      MTRM   DC       LMTRM
043C 0  0B0F      TRFX   DC       LTRFX
043D 0  FFFF      TERM   DC       /FFFF
043E 0  0000      LWC    DC                  WC STORAGE
043F 0  0000      LGROP  DC                  GROUP COUNTER
0440 0  0000      STBF   DC       0          DISPLACEMENT
0441 0  0000      SRTRY  DC       /0000
                  *
                  *
                  ********* EDIT IMAGE BUFFER ***********
0442 0  0000      SEIB   DC       /0000
0443    0141             BSS      321
0584 0  0792      KTYPS  DC       KTYP
0585 0  0C0F      HLT    DC       HLTE
0586 0  0A93      CODE   DC       KTILT
0588    0000             BSS  E   0
0588 00 4C000590  SRST   BSC  L   START      RESTART
                  *
                  *                           CONTROL SECTION
058A 00 C400006F  START1 LD   L   /006F      CHANGE LDR BASE ADR
058C 00 84000602         A    L   K1048
058E 00 D400006F         STO  L   /006F
                  *
0590 0  1010      START  SLA      16          CLEAR ADDRESSES
0591 00 D4000127         STO  L   /0127
0593 0  D029            STO       SVIX3+1
0594 0  0039            STO       END1+1
0595 00 D4000440         STO  L   STBF
0597 0  C023            LD        BSAD1
0598 00 D4000125         STO  L   /0125       RESET BSE ADRS
                  *
059A 0  C8ED            LDD       SRST        SET RESTART
059B 00 DC000000         STD  L   /0000
                  *
059D 00 4480012E         BSI  I   SSUER       SET ERROR RETURN    SRC
059F 00 4480012C         BSI  I   KEY         ENTER PID           SRC
05A1 0  0BE5            DC        SM2
05A2 0  8220            DC        /8220
                  *
05A3 00 C400013E         LD   L   BINRY       GET ENTRY
05A5 00 B4000610         CMP  L   KOOFF
05A7 0  7065            MDX       ERRO4
05A8 0  1000            NOP
05A9 0  D056            STO       XPID         SAVE
                  *
05AA 00 44000ABE  S2E    BSI  L   RDSK        RD A SKELTON        SRC
                  *
05AC 0  C8DB            LDD       SRST        RESET RESTART
05AD 00 DC000000         STD  L   /0000
                  *
05AF 00 C4000C17         LD   L   SKI1        GET PID READ
05B1 0  F04E            EOR       XPID        IS IT PID DESIRED
05B2 00 4C1805BC         BSC  L   SVIX3,+-     YES
                  *
05B4 0  1010            SLA       16          CLEAR LDR RELOCAT
05B5 00 D4000127         STO  L   /0127
```

```
8C300220
8C300230
8C300240
8C300250
8C300260
8C300270
8C300280
8C300290
8C300300
8C300310
8C300320
8C300330
8C300340
8C300350
8C300360
8C300370
8C300380
8C300390
8C300400
8C300410
8C300420
8C300430
8C300440
8C300442
8C300443
8C300444
8C300445
8C300450
8C300460
8C300470
8C300480
8C300490
8C300500
8C300510
8C300520
8C300530
8C300540
8C300550
8C300560
8C300570
8C300572
8C300580
8C300590
8C300600
8C300610
8C300620
8C300630
8C300640
8C300650
8C300660
8C300670
8C300680
8C300690
8C300692
8C300694
8C300696
8C300700
8C300710
8C300720
8C300730
8C300740
8C300750
8C300760
8C300770
8C300780
8C300790
8C300800
8C300810
8C300820
```

```
05B7 0  C003               LD      BSAD1                           8C300830
05B8 00 D4000125           STO  L  /0125      RESET BSE ADRS       8C300840
05BA 0  70EF               MDX     S2E        READ NEXT            8C300850
05BB 0  0C17      BSAD1 DC         /0C17      BASE ADRS            8C300860
                                                                   8C300860
05BC 00 6700000G   SVIX3 LDX  L3  0           IX 3 = TBL LOC       8C300870
05BE 00 C4000127          LD   L  /0127       GET RFL FACTOR       8C300880
05C0 0  8040              A       BSADR        COMPUTE ADRS        8C300890
05C1 00 D7000603          STO  L3 RLTBL        SAVE                8C300900
05C3 0  D003              STO     RLFT+1                           8C300910
05C4 0  7301              MDX     3 1          INCR IX 3           8C300920
05C5 0  6BF7              STX     3 SVIX3+1    SAVE                8C300930
05C6 00 C4000000   RLFT   LD   L  0           GET CD NO           8C300940
05C8 00 F400043D          EOR  L  TERM        IS IT A TERM        8C300950
05CA 00 4C180C1A          BSC  L  SKI4,+-     START PROG          8C300960
05CC 0  70DD              MDX     S2E         READ MORE           8C300970
                                                                  8C300980
05CD 00 67000000   END1  LDX  L3  0           IX 3 = TBL ADRS     8C300990
05CF 00 C7000604         LD   L3  RLTBL+1     GET ADRS            8C301000
05D1 0  D001             STO      RLFT1+1     SAVE                8C301010
05D2 00 C4000000   RLFT1 LD   L   0           GET CD NO           8C301020
05D4 00 F400043D         EOR  L   TERM        IS IT A TERM        8C301030
05D6 00 4C1805E7         BSC  L   STTRM,+-    YES                 8C301040
05D8 00 C7000604         LD   L3  RLTBL+1     GET ADRS            8C301050
05DA 00 840007E3         A    L   K0002       ADD 2               8C301060
05DC 0  D003             STO      RLFT2+1     SAVE                8C301070
05DD 00 740105CE         MDX  L   END1+1,1    SET FOR NEXT        8C301080
05DF 00 4C000000   RLFT2 BSC  L   0           GO TO NEXT          8C301090
05E1 00 44800i2C   END   BSI  I   KEY         END OF PROGRAM  SRC 8C301100
05E3 0  0BFB             DC       SM33                            8C301110
05E4 0  0000             DC       /00G0                           8C301120
05E5 0  3008      WAIT8  WAIT     8                               8C301130
05E6 0  70A9             MDX      START                           8C301140
05E7 00 C4000440  STTRM  LD   L   STBF        GET DISPLACEMENT    8C301150
05E9 00 8400082B         A    L   STBFI       COMPUTE ADRS        8C301160
05EB 0  D001             STO      *+1         SAVE                8C301170
05EC 00 65000000         LDX  L1  0           IX 1 = ADRS         8C301180
05EE 00 C4000C17         LD   L   SKI1        GET PID             8C301190
05F0 0  D100             STO  I   0           SET                 8C301200
05F1 00 C400043D         LD   L   TERM                            8C301210
05F3 0  D101             STO  I   1           SET                 8C301220
05F4 00 44000931         BSI  L   PECOR       PUNCH CARDS    SRC  8C301230
05F6 0  1010             SLA      16          ZERO ACCUM          8C301240
05F7 00 D4000440         STO  L   STBF        CLEAR DISPL         8C301250
05F9 00 65000142         LDX  L1  322                             8C301260
05FB 00 D4000441  STTR   STO  L   SEIB-1      CLEAR CD BFR        8C301270
05FD 0  71FF             MDX      1 -1        DECR IX 1           8C301280
05FE 0  70FC             MDX      STTR        LOOP                8C301290
05FF 0  70E1             MDX      END         GO TO END           8C301300
0600 0  0000      XPID   DC       0           PID STORAGE         8C301310
0601 0  0C18      BSADR  DC       3096        CONSTANTS           8C301320
0602 0  0418      K1048  DC       1048                            8C301330
0603 0  0000      RLTBL  DC       0                               8C301340
0604                     BSS      9           TBL OF RFL FACTORS  8C301350
060D 00 44800132  ERR04  BSI  I   SER                             8C301360
060F 0  0BD7             DC       SE002                           8C301362
0610 0  00FF      KOOFF  DC       /00FF                           8C301364
                                                                  8C301366
      •                                                           8C301370
      •                                                           8C301380
      •                                                           8C301390
      •                          PRINTER I/O ROUTINE              8C301400
      •                                                           8C301410
      •                          CALL  BSI   KEY                  8C301420
      •                                DC    MSGAD                8C301430
      •                                DC    ID                   8C301440
      •                                                           8C301450
      •                          ID  BIT 0  KEYBOARD              8C301460
      •                              XOXX   NO CONV               8C301480
```

```
      •                          X1XX  DEC CONV                   8C301482
      •                          X2XX  HEX CONV                   8C301484
      •                                                           8C301500
0611 0  0000      KEYE  DC       /0000                            8C301500
0612 0  6941            STX   1  KEY96+1      SAVE STATUS         8C301510
0613 0  6A42            STX   2  KEY97+1                          8C301520
0614 0  6B43            STX   3  KEY98+1                          8C301530
0615 00 DC000A4C        STD   L  KAQ                              8C301540
0617 0  2843            STS      KEY99                            8C301550
                                                                  8C301560
0618 00 C4800611        LD    I  KEYE         FETCH MESS ADRS     8C301570
061A 00 D4000611        STO   L  KMSG                             8C301580
061C 00 74010611        MDX   L  KEYE,1       POINT TO ID         8C301590
                                                                  8C301600
061E 00 65000047        LDX  L1  KOUT         SET CARRIER RETURN  8C301610
0620 00 C4000AA3        LD    L  KCR                              8C301620
                                                                  8C301630
0622 0  1808            SRA      8            CLEAR EBDIC CODE    8C301640
0623 0  1008            SLA      8                                8C301650
0624 0  D100            STO   I  0            STORE IN OUTPUT AREA 8C301660
                                                                  8C301670
0625 00 C4800A46 KEBC2  LD    I  KMSG         CHECK TERMINATOR    8C301680
0627 00 84000A56        A     L  KONE                             8C301690
0629 00 4C180648        BSC   L  KCHK,+-      BR IF NO MORE MESS  8C301700
*************************************************                 8C301710
                                                                  8C301720
062B 0  6208            LDX   2  8                                8C301730
062C 00 67000A7A KE3C3  LDX  L3  KTGLT        CONVERT CHARS TO RTT 8C301740
062E 0  7101            MDX   1  1                                8C301750
062F 00 C4800A46 KEBC4  LD    I  KMSG         FETCH EBDIC CHARS   8C301760
0631 0  1A00            SRA   2  0                                8C301770
0632 0  1008            SLA      8                                8C301780
0633 0  1808            SRA      8                                8C301790
0634 0  F300            EOR   3  0                                8C301800
0635 0  D100            STO   I  0                                8C301810
0636 0  1008            SLA      8                                8C301820
0637 0  7301            MDX   3  1                                8C301830
0638 00 4C20062F        BSC   L  KEBC4,Z      BR IF NOT THE CHAR  8C301840
                                                                  8C301850
063A 0  7200            MDX   2  0            SKIP IF 2 CHARS CNVT 8C301860
063B 0  700D            MDX      KEBC6                            8C301870
                                                                  8C301880
063C 00 C4000A56        LD    L  KONE         SET TERMINATOR      8C301890
063E 0  8100            A     1  0                                8C301900
063F 0  D100            STO   I  0                                8C301910
0640 00 65000047        LDX  L1  KOUT         GO PRINT CHARS      8C301920
0642 00 44000792        BSI   L  KTYP                             8C301930
                                                                  8C301940
0644 00 65000A46        LDX  L1  KOUT-1                           8C301950
0646 00 74010A46        MDX   L  KMSG,1       POINT TO NEXT WORD  8C301960
0648 0  70DC            MDX      KEBC2                            8C301970
                                                                  8C301980
0649 0  6200      KEBC6 LDX   2  0            CONVERT SECOND CHAR 8C301990
064A 0  70E1            MDX      KEBC3                            8C302000
*************************************************                 8C302010
                                                                  8C302020
                                                                  8C302030
064B 00 65000AA3 KCHK   LDX  L1  KCR                              8C302040
064D 00 44000792        BSI   L  KTYP         DO CAR RET     SRC  8C302050
064F 00 C4800611        LD    I  KEYE                             8C302060
0651 00 4C280660        BSC   L  KFRM,+Z      BR IF KBD ENTRY     8C302070
*************************************************                 8C302080
                                                                  8C302090
0653 00 65000000 KEY96  LDX  L1  /0000        RESTORE STATUS      8C302100
0655 00 66000000 KEY97  LDX  L2  /0000                            8C302110
0657 00 67000000 KEY98  LDX  L3  /0000                            8C302120
0659 00 CC000A4C        LDD   L  KAQ                              8C302130
                                                                  8C302140
```

```
065B 0  2000      KEY99 LDS     0                            8C302150
                  *                                          8C302160
065C 00 74010611        MDX  L  KEYE,1                       8C302170
065E 00 4C800611        BSC  I  KEYE      RETURN EXIT        8C302180
                 ***************************************     8C302190
                 ***************************************     8C302200
                  *                                          8C302210
                  *                                          8C302220
0660 0  1090      KFRM  SLT     16        FETCH FORM NUMBER  8C302230
0661 00 C4800611        LD   I  KEYE                         8C302240
0663 0  1004            SLA     4                            8C302250
0664 0  18CC            RTE     12                           8C302260
0665 00 D4000753        STO  L  KEYFM     SAVE FORM NO       8C302270
0667 0  1804            SRA     4                            8C302280
0668 0  1084            SLT     4                            8C302290
0669 00 D4000754        STO  L  KEYNO     SAVE CHAR/WD COUNT 8C302300
                  *                                          8C302310
                  *                                          8C302320
066B 00 44800134  KEYOG BSI  I  SKIN1     SET KEYIN TO FFFF  SRC 8C302330
                  *                                          8C302340
066D 00 6F0001DE        STX  L3 KIWC      RESET WD CT        8C302350
                  *                                          8C302360
066F 00 670001DF        LDX  L3 KEYIN     RESET READ AREA    8C302370
                 ***************************************     8C302380
0671 00 6F000A54  KEYO  STX  L3 KRED                         8C302390
0673 C0 4400076F        BSI  L  KNBY      WAIT FOR NOT BUSY  9C302400
                  *                                          8C302410
0675 00 0C000A52  KEY1  XIO  L  KPCD      SET KEYBOARD PROCEED 8C302420
                                                             8C302430
0677 00 0C000A44  KEY2  XIO  L  KSNS      SENSE STATUS       8C302440
0679 0  1001            SLA     1                            8C302450
067A 00 4C280680        BSC  L  KEY3,+Z   GO READ KEYBOARD   8C302460
                  *                                          8C302470
067C 0  1005            SLA     5                            8C302480
067D 00 4C100675        BSC  L  KEY1,-    BR IF NOT PROCEED  8C302490
067F 0  70F7            MDX     KEY2                         8C302500
                  *                                          8C302510
0680 00 0C000A54  KEY3  XIO  L  KRED      READ KEYBOARD      8C302520
                  *                                          8C302530
0682 0  610B      KFMS  LDX  1 11         CHECK FOR DEC OR SPC 8C302540
0683 0  C300      KFMS1 LD    3 KRED-KRED FETCH CHAR READ    8C30255C
0684 00 F5000A5D        EOR  L1 KECOD-1                      8C302560
0686 00 4C1806DD        BSC  L  KDEC,+-   BR IF DEC CR SPACE 8C302570
                  *                                          8C302580
0688 0  71FF            MDX    1 -1                          8C302590
0689 0  70F9            MDX     KFMS1                        8C302600
                  *                                          8C302610
068A 00 C4000753        LD   L  KEYFM     CHECK FOR FORM     8C302620
068C 00 F4000A56        EOR  L  KONE                         8C302630
068E 00 4C1806A7        BSC  L  KFMO,+-   BRANCH IF FORM 1   8C302640
                 ***************************************     8C302650
0690 0  6106      KFM2  LDX  1 6          CHECK FOR HEX      8C302660
0691 0  C300      KFM21 LD    3 KRED-KRED FETCH CHAR READ    8C302670
0692 00 F5000A68        EOR  L1 KECAD-1                      8C302680
0694 00 4C1806E0        BSC  L  KHEX,←    BR IF ALPHA        8C302690
                  *                                          8C302700
0696 0  71FF            MDX    1 -1                          8C302710
0697 0  70F9            MDY     KFM21                        8C302720
0698 0  C300            LD    3 KRED-KRED FETCH CHAR READ    8C302730
0699 00 F4000A5B        EOR  L  KECPD          ,             8C302731
069B 00 4C2006A7        BSC  L  KFMO,Z    BR IF NOT PERIOD   8C302732
069D 0  C3FC            LD    3 -4        A PLUS OR MINUS    8C302733
069E 0  6201            LDX   2 1                            8C302734
069F 0  1240            SLCA  2 0                            8C302735
06A0 00 F4000BA9        EOR  L  K8000                        8C302736
06A2 00 44200757        BSI  L  KERR,Z    BR IF NOT + OR -   8C302737
06A4 00 C4000A8F        LD   L  KTPLT                        8C302738
06A6 0  7022            MDX     KPNE                         8C302739
```

```
                  *                                          8C302740
                 ***************************************     8C302750
06A7 0  6108      KFMO  LDX  1 8          CHECK UC SP CHRS   8C302760
06A8 0  C300      KFMO1 LD    3 0         GET CHR READ       RC302770
06A9 00 F5000A56        EOR  L1 KN-1      CK AGAINST TBL     8C302780
06AB 00 4C1806D2        BSC  L  KMDX,+-   CHAR FOUND         RC302790
06AD 0  71FF            MDX    1 -1       DECR IX 1          8C302800
06AE 0  70F9            MDX     KFMO1     LOOP               8C302810
                  *                                          8C302820
06AF 0  6107            LDX  1 7          CK LC SP CHRS      9C302830
06B0 0  C300      KFMO2 LD    3 0         GET CHR READ       8C302840
06B1 00 F5000A71        EOR  L1 KAL-1     CK AGAINST TBL     8C302850
06B3 00 4C1806DB        BSC  L  KMPX,+-   CHARACTER FOUND    8C302860
06B5 0  71FF            MDX    1 -1       DECR IX 1          8C302870
06B6 0  70F9            MDX     KFMO2     LOOP               8C302880
06B7 C  C300            LD    3 0         GET CHR READ       8C302890
06B8 00 F4000A4B        EOR  L  KL                           8C302900
06BA 00 442006F6        BSI  L  KSPC,Z                       8C302910
                  *                                          8C302920
06BC 0  6201            LDX  2 1                             8C302930
06BD 0  C3FA            LD    3 -6                           8C302940
06BE 0  1002            SLA     2                            8C302950
06BF 0  1240            SLCA  2 0                            8C302960
06C0 00 F4000BA9        EOR  L  K8000                        9C302970
06C2 00 44200757        BSI  L  KERR,Z    BR IF NOT 1 OR ZERO 8C302980
                  *                                          8C302990
06C4 0  C3FA            LD    3 -6                           8C303000
06C5 0  1802            SRA     2                            8C303010
06C6 0  D3FA            STO   3 -6                           8C303020
06C7 00 C4000A7F        LD   L  KLRT                         8C303030
06C9 00 EC000A56  KPNE  OR   L  KONE                         8C303040
06CB 00 65000A47        LDX  L1 KOUT                         8C303050
06CD 0  D100            STO   1 0                             8C303060
06CE 00 44000792        BSI  L  KTYP                         8C303070
06D0 00 4C000671        BSC  L  KEYO      BRANCH             8C303080
                  *                                          8C303090
06D2 0  C30C      KMDX  LD    3 0         FETCH CHAR         8C30(091
06D3 00 F4000A5C        EOR  L  KECPD+1                       8C303092
06D5 00 4C2006DB        BSC  L  KMPX,Z    BR IF NOT + SIGN   8C303093
06D7 0  C300            LD    3 0         MAKE + = /8000     9C303094
06D8 0  180C            SRA     12                           8C303095
06D9 0  100C            SLA     12                           8C303096
06DA 0  D300            STO   3 0                             8C303097
06DB 0  7111      KMPX  MDX    1 KN-KECGD ADJ IX 1           8C303100
06DC 0  7001            MDX     KDEC1                         8C303110
                  *                                          8C303120
                  *                                          8C303130
06DD 0  7118      KDEC  MDX    1 KECOD-KECGD  CORCT XR1      8C303140
                  *                                          8C303150
06DE 0  4003      KDEC1 BSI     KSTO      GO STORE + PRT   SRC 8C303160
                  *                                          8C303170
06DF 0  7091            MDX     KEYO      RETURN FOR NEXT    8C303180
                  *                                          8C303190
                  *                                          8C303200
                  *                                          8C303210
06E0 0  7123      KHEX  MDX    1 KECAD-KECGD  GO PRINT A - F 8C303220
06E1 0  70FC            MDX     KDEC1                         8C303230
                 ***************************************     8C303240
                  *                                          8C303250
                  *                        STORE AND PRINT RTN 8C303260
06E2 0  0000      KSTO  DC     /0000                         8C303270
06E3 0  C300            LD    3 0                             8C303280
06E4 0  EBFF            OR    3 -1                            8C303290
06E5 0  1804            SRA     4                             8C303300
06E6 00 4C9806E2        BSC  I  KSTO,+-   BR IF SECOND SPACE 8C303310
                  *                                          8C303320
06E8 00 C5000A79        LD   L1 KTGLT-1   FETCH TYPR CHAR    8C303330
06EA 00 EC000A56        OR   L  KONE                          8C303340
```

```
06EC 00 65000A47        LDX  L1 KOUT
06EE 0  D100            STO  1 0
06EF 00 44000792        BSI  L KTYP       TYPE CHARACTER
                   *
                   *                      UPDATE KEYBOARD BUF
06F1 00 740101DE        MDX  L KIWC,1
06F3 0  7301            MDX  3 1
                   *
06F4 00 4C8006E2        BSC  I KSTO       RETURN TO USER
                   *************************************************
                   *                      SPECIAL CHAR CHECK
06F6 0  0000      KSPC  DC     /0000
                   *
06F7 0  C300            LD   3 0          FETCH KEY CHARACTER
06F8 00 F4000A79        EOR  L KCMA
06FA 00 4C200712        BSC  L KSPC5,Z    BR IF NOT A  COMMA
                   *
06FC 00 C40001DE        LD   L KIWC
06FE 00 940007E3        S    L K0002
0700 00 44280757        BSI  L KERR,+Z    BR IF COMMA TOO SOON
                   *
0702 0  C3FF            LD   3 -1         FETCH LAST ENTRY
0703 0  1804            SRA  4
0704 00 4C180709        BSC  L KSPC2,+-   BR IF SPACE LAST
0706 00 740101DE        MDX  L KIWC,+1
0708 0  7301            MDX  3 +1
0709 00 C4000A56  KSPC2 LD   L KONE
070B 0  D3FF            STO  3 -1         SET FIELD PROTECT MK
                   *
070C 00 6500072A        LDX  L1 KCOMA
070E 00 44000792        BSI  L KTYP       GO PRINT + OR-
                   *
0710 00 64000671        LDX  L KEYO       RETURN FOR MORE CHR
                   *
                   *************************************************
0712 0  C300      KSPC5 LD   3 0          FETCH KEY CHARACTER
0713 00 F4000A70        EOR  L KERSE
0715 00 4C20072D        BSC  L KSPC9,Z    BR IF NOT ERASE CHAR
                   *
0717 00 C40001DE        LD   L KIWC
0719 00 4C080671        BSC  L KEYO,+     BR IF WORD COUNT ZERO
                   *
071B 0  C3FF            LD   3 -1         CHECK PROTECT BIT
071C 00 4C040671        BSC  L KEYO,E     BR IF LAST WORD PROTD
071E 0  1801            SRA  1
071F 00 4C040725        BSC  L KSPC6,E    DO BKSP OVER PERIOD
0721 0  73FF            MDX  3 -1         DECREASE WORD COUNT
0722 00 74FF01DE        MDX  L KIWC,-1
0724 0  1000            NOP
0725 00 6500072C  KSPC6 LDX  L1 KBKSP     DO A BACKSPACE
0727 0  406A            BSI    KTYP       DO BACKSPACE        SRC
                   *
0728 00 4C000671        BSC  L KEYO       RETURN
                   *************************************************
072A 0  8000      KCOMA DC     /8000      COMMA RESPONSE
072B 0  8101            DC     /8101
072C 0  1101      KBKSP DC     /1101
                   *
072D 0  C300      KSPC9 LD   3 0          FETCH KEY CHAR
072E 00 F4000A6F        EOR  L KRENT
0730 00 44180757        BSI  L KERR,+-    BR IF ERASE FIELD
                   *
0732 0  C300            LD   3 KRED-KRED  FETCH CHAR READ
0733 00 F4000A71        EOR  L KENDK
0735 00 4C200671        BSC  L KEYO,Z     BR IF NOT EOF KEY
                   *
0737 00 C40001DE        LD   L KIWC       FETCH WORD COUNT
0739 0  901A            S      KEYND
```

```
8C303350
8C303360
8C303370
8C303380
8C303390
8C303400
8C303410
8C303420
8C303430
8C303440
8C303450
8C303460
8C303470
8C303480
8C303490
8C303500
8C303510
8C303520
8C303530
8C303540
8C303550
8C303560
8C303570
8C303580
8C303590
8C303600
8C303610
8C303620
8C303630
8C303640
8C303650
8C303660
8C303670
8C303680
8C303690
8C303700
8C303710
8C303720
8C303730
8C303740
8C303750
8C303760
8C303770
8C303780
8C303790
8C303800
8C303810
8C303820
8C303830
8C303840
8C303850
8C303860
8C303870
8C303880
8C303890
8C303900
8C303910
8C303920
8C303930
8C303940
8C303950
8C303960
8C303970
8C303980
8C303990
8C304000
8C304010
8C304020
```

```
073A 00 44280757        BSI  L KERR,+Z    TOO FEW ENTRIES
073C 00 658001DE        LDX  I1 KIWC      CLEAR FIELD PROT BIT
073E 00 C50001DE  KSPCA LD   L1 KIWC
0740 0  1804            SRA  4
0741 0  1004            SLA  4
0742 00 D50001DE        STO  L1 KIWC
0744 0  71FF            MDX  1 -1
0745 0  70F8            MDX    KSPCA
                   *
                   *
0746 0  C3FF            LD   3 -1         REMOVE SP BEFORE
                   *                      TERMINATE
0747 0  1804            SRA  4
0748 00 4C20074F        BSC  L KSPCE,Z    BR IF NO SPACE THERE
074A 0  73FF            MDX  3 -1         DECREMENT WORD COUNT
074B 00 74FF01DE        MDX  L KIWC,-1
074D 0  7001            MDX    KSPCE
074E 0  4008            BSI    KERR
074F 0  C01E      KSPCE LD     KNEG       SET TERMINATION
0750 0  D300            STO  3 0
0751 00 44000ACA        BSI  L LDOIT      LET LLOYD DO IT
0753 0  0000      KEYFM DC     /0000      FORM NUMBER
0754 0  0000      KEYND DC     /0000      CHARS / WORD
0755 00 4C000653  EXIT  BSC  L KEY96
                   *************************************************
                   *
                   *
0757 0  0000      KERR  DC     /0000
0758 00 65000AA4        LDX  L1 KFELD     PRINT FIELD CANCELLD
075A 0  4037            BSI    KTYP       TYPE                SRC
                   *
075B 0  7301            MDX  3 1
075C 00 740101DE        MDX  L KIWC,1
075E 0  61FF            LDX  1 -1
075F 0  C3FF      KERR1 LD   3 -1         ERASE TO FIELD MARK
0760 00 4C040671        BSC  L KEYO,E     BR IF FIELD MARK
                   *
0762 0  C00B            LD     KNEG
0763 0  D300            STO  3 0
0764 0  73FF            MDX  3 -1         DECREMENT WORD COUNT
0765 00 74FF01DE        MDX  L KIWC,-1
0767 0  70F7            MDX    KERR1
                   *
0768 00 C40001DE        LD   L KIWC
076A 00 4C100671        BSC  L KEYO,-
076C 00 4C00066B        BSC  L KEYOG
076E 0  FFFF      KNEG  DC     -1          CONSTANT MINUS ONE
                   *************************************************
                   *
                   *
                   *                       TYPR NOT BUSY RTN
076F 0  0000      KNBY  DC     /0000
0770 0  6A1B            STX  2 KNBY5+1
0771 00 6600000A        LDX  L2 10
0773 00 6E000791        STX  L2 KTIME     SET TIME COUNTER
0775 00 66007FFF  KNBYO LDX  L2 /7FFF
0777 00 0C000A44  KNBY1 XIO  L KSNS       CHECK BUSY
0779 0  1004            SLA  4
077A 00 4C10078B        BSC  L KNBY5,-    BR IF NOT BUSY
077C 0  72FF            MDX  2 -1
077D 0  70F9            MDX    KNBY1      CHECK AGAIN
077E 00 74FF0791        MDX  L KTIME,-1  DECREMENT TIMER
0780 0  70F4            MDX    KNBYO
                   *
0781 00 66000787        LDX  L2 KNBY4     TYPR HUNG UP BUSY
0783 00 6E000003        STX  L2 3
0785 0  3002      WAIT2 WAIT   2          1816 HUNG UP BUSY
0786 0  70EA            MDX    KNBY+2
```

```
8C304030
8C304040
8C304050
8C304060
8C304070
8C304080
8C304090
8C304100
8C304110
8C304120
8C304130
8C304140
8C304150
8C304160
8C304170
8C304180
8C304190
8C304200
8C304210
8C304220
8C304230
8C304240
8C304250
8C304260
8C304270
8C304280
8C304290
8C304300
8C304310
8C304320
8C304330
8C304340
8C304350
8C304360
8C304370
8C304380
8C304390
8C304400
8C304410
8C304420
8C304430
8C304440
8C304450
8C304460
8C304462
8C304464
8C304470
8C304480
8C304490
8C304500
8C304510
8C304520
8C304530
8C304540
8C304550
8C304560
8C304570
8C304580
8C304590
8C304600
8C304610
8C304620
8C304630
8C304640
8C304650
8C304660
8C304670
8C304680
```

```
0787 00 6600012C   KNBY4 LDX  L2 300     RESTORE RESTART      8C304690
0789 00 6E000003         STX  L2 3                            8C304700
                   *                                          8C304710
078B 00 66000000   KNBY5 LDX  L2 /0000   EXIT                 8C304720
078D 00 0C000A4E         XID  L  KRDY    RESET                8C304730
078F 00 4C80076F         BSC  I  KNBY                         8C304740
0791 0  0000       KTIME DC     /0000    TIME COUNTER         8C304750
                   ***************************************************  8C304760
                   *                                          8C304770
                   *                                          8C304780
                   *                                          8C304790
                   *                        PRINTER OUTPUT RTN 8C304800
                   *                        XR1 = ADRS OF MESS 8C304810
                   *                                          8C304820
                   *                                          8C304830
0792 0  0000       KTYP  DC     /0000                         8C304840
0793 00 6D000A50   KTYP1 STX  L1 KPRT    SAVE PRINTING ADDR   8C304850
                   *                                          8C304860
0795 0  40D9             BSI     KNBY    WAIT OFR NUT BUSY    8C304870
                   *                                          8C304880
0796 00 0C000A4E   KTYP5 XID  L  KRDY    CHECK READY          8C304890
0798 0  1005             SLA     5                            8C304900
0799 00 4C10079D         BSC  L  KTYP6.- BR IF READY          8C304910
079B 0  3001       WAIT1 WAIT    1       PRINTER OUT OF FORMS 8C304920
                   *                                          8C304930
079C 0  70F9             MDX     KTYP5                        8C304940
                   *                                          8C304950
079D 00 0C000A50   KTYP6 XID  L  KPRT    OUTPUT ONE CHAR      8C304960
079F 0  C100             LD   1  0                            8C304970
07A0 00 4C840792         BSC  I  KTYP,E  EXIT IF MSG PRIM     8C304980
                   *                                          8C304990
07A2 0  7101             MDX  1  1                            8C305000
07A3 0  70EF             MDX     KTYP1                        8C305010
07A4 0  0000       CKYNE DC      0                       SE   8C305020
07A5 00 C40001DF         LD   L  KEYIN   GET ENTRY            8C305030
07A7 0  F018             EOR     YES     IS IT Y LC           8C305040
07A8 00 4C1807BE         BSC  L  CKYND,+- YES                 8C305050
07AA 00 C40001DF         LD   L  KEYIN   GET ENTRY            8C305060
07AC 0  F014             EOR     YES1    IS IT Y UC           8C305070
07AD 00 4C1807BE         BSC  L  CKYND,+- YES                 8C305080
07AF 00 C40001DF         LD   L  KEYIN   GET ENTRY            8C305090
07B1 0  F010             EOR     NO      IS IT N LC           8C305100
07B2 00 4C1807BC         BSC  L  CKYN1,+- YES                 8C305110
07B4 00 C40001DF         LD   L  KEYIN   GET ENTRY            8C305120
07B6 0  F00C             EOR     NO1     IS IT N UC           8C305130
07B7 00 4C1807BC         BSC  L  CKYN1,+- YES                 8C305140
                   *                                          8C305150
07B9 00 4480012C         BSI  I  SER     NOT Y OR N      SRC  8C305160
07BB 0  0BB2             DC      PCKBE                        8C305170
                   *                                          8C305180
07BC 00 740107A4   CKYN1 MDX  L  CKYNE,1 INCR RETURN          8C305190
07BE 00 4C8007A4   CKYND BSC  I  CKYNE   EXIT             SX  8C305200
                   *                                          8C305210
07C0 0  2020       YES   DC      /2020   LOWER CASE Y         8C305220
07C1 0  8060       YES1  DC      /6060   UPPER CASE Y         8C305230
07C2 0  4100       NO    DC      /4100   LOWER CASE N         8C305240
07C3 0  8120       NO1   DC      /8120   UPPER CASE N         8C305250
                   *                                          8C305260
                   *                                          8C305270
                   *  SET UP RETURN ON ERROR                  8C305280
                   *                                          8C305290
07C4 0  0000       SSUEE DC      /0000                        8C305300
07C5 0  C0FE             LD      SSUEE                        8C305310
07C6 0  901C             S       K0002                        8C305320
07C7 00 D4000441         STO  L  SRTRY                        8C305330
07C9 00 4C8007C4         BSC  I  SSUEE                        8C305340
07C4               SSEUR EQU     SSUEE                        8C305350
                   *                        CHECK IF INTERRUPT LEVEL  8C305360
                   *                        IS TO GREAT
```

```
07CB 0  0000       SILE  DC      /0000                        8C305370
07CC 00 C400013E         LD   L  BINRY                        8C305380
07CE 0  1008             SLA     8                            8C305390
07CF 0  B008             CMP     S1700                        8C305400
07D0 0  7002             MDX     SILER   GREATER ERROR        8C305410
07D1 0  7004             MDX     SIL1                         8C305420
07D2 0  7003             MDX     SIL1                         8C305430
                   *                                          8C305440
07D3 00 4480132         SILER BSI  I  SER                     8C305450
07D5 0  0BD7             DC      SE002                        8C305460
                   *                                          8C305470
07D6 00 4C8007CB   SIL1  BSC  I  SILE                         8C305480
                   *                                          8C305490
07D8 0  1700       S1700 DC      /1700                        8C305500
                   *                                          8C305510
                   *                        CHECK IF ILSW IS VALID  8C305520
                   *                                          8C305530
07D9 0  0000       SILSE DC      /0000                        8C305540
07DA 00 C400013E         LD   L  BINRY                        8C305550
07DC 0  1004             SLA     4                            8C305560
07DD 0  B004             CMP     S00F0                        8C305570
07DE 0  70F4             MDX     SILER   ERROR                8C305580
07DF 0  1000             NOP     0                            8C305590
                   *                                          8C305600
                   *                                          8C305610
07E0 00 4C8007D9   SIA   BSC  I  SILSE                        8C305620
                   *                                          8C305630
07E2 0  00F0       S00F0 DC      /00F0                        8C305640
07E3 0  0002       K0002 DC      2                            8C305650
                   *                                          8C305660
                   *                        CHECK CHANNEL VALUE  8C305670
                   *                                          8C305680
07E4 0  0000       SCHE  DC      /0000                        8C305690
07E5 00 C400013E         LD   L  BINRY                        8C305700
07E7 0  B00C             CMP     S000B                        8C305710
07E8 0  7002             MDX     SCHER                        8C305720
07E9 0  7005             MDX     SCH1                         8C305730
07EA 0  7004             MDX     SCH1                         8C305740
                   *                                          8C305750
07EB 0  F007       SCHER EOR     S000F                        8C305760
07EC 00 4C1807EF         BSC  L  SCH1,+-                      8C305770
07EE 0  70E4             MDX     SILER   ERROR                8C305780
                   *                                          8C305790
07EF 00 C400013E   SCH1  LD   L  BINRY                        8C305800
07F1 00 4C8007E4         BSC  I  SCHE                         8C305810
07F3 0  000F       S000F DC      /000F                        8C305820
                   *                                          8C305830
07F4 0  0008       S0008 DC      /0008                        8C305840
07F5 0  0000       SERE  DC      /0000                        8C305850
07F6 00 C48007F5         LD   I  SERE    FETCH ERROR ADDRESS  8C305860
07F8 0  D002             STO     SER1                         8C305870
                   *                                          8C305880
07F9 00 4480012C         BSI  I  KEY                          8C305890
07FB 0  0000       SER1  DC      /0000   ADDRESS              8C305900
07FC 0  0000             DC      /0000   ID                   8C305910
                   *                                          8C305920
07FD 00 4C800441         BSC  I  SRTRY                        8C305930
                   *                                          8C305940
                   *                        SET UP ROUTINE     8C305950
                   *                        X2= CARD NUMBER    8C305960
                   *                                          8C305970
07FF 0  0000       SECSE DC      0                       SE   8C305980
0800 00 C48007FF         LD   I  SECSE   GET MSG ADRS         8C305990
0802 0  D024             STO     SIWB    SAVE                 8C306000
0803 0  6A24       SE1   STX  2  SECB    SET CD NO            8C306010
0804 0  6924             STX  1  CPID    SET PID              8C306020
0805 0  6B24             STX  3  NOEN    SET NO OF ENTRIES    8C306030
0806 0  C024             LD      STBF1   GET EDIT IMAGE ADRS  8C306040
```

```
0807 00 84000440          A    L  STBF                              8C306050
0809 0  D003              STO     SE2+1      SET                     8C306060
080A 00 65800827    SE2   LDX  I1 SIWB       IX 1 = MSG ADRS         8C306070
080C 00 67000000          LDX  L3 0          IX 3 = STARTING ADRS    8C306080
080E 00 6680082A          LDX  I2 NOEN       IX 2 = NO ENTRIES       8C306090
0810 0  C018              LD      CPID       GET PID                 8C306100
0811 0  D300              STO  3  0          SET                     8C306110
0812 0  C015              LD      SECB       GET CD NO               8C306120
0813 0  D301              STO  3  1          SET                     8C306130
0814 0  C015              LD      NOEN       GET NO ENTRIES          8C306140
0815 0  D302              STO  3  2          SET                     8C306150
0816 0  7303              MDX  3  3          INCR IX 3               8C306160
0817 0  C100        SE3   LD   1  0          GET AN ENTRY            8C306170
0818 0  D300              STO  3  0          SET                     8C306180
0819 0  7101              MDX  1  1          INCR MSG ADRS           8C306190
081A 0  7301              MDX  3  1          INCR BFR ADRS           8C306200
081B 0  72FF              MDX  2 -1          DECR NO ENTRIES         8C306210
081C 0  70FA              MDX     SE3        LOOP                    8C306220
081D 00 C4000440          LD   L  STBF                               8C306230
081F 0  800C              A       K0003      ADD 3                   8C306240
0820 0  8009              A       NOEN       ADD NO ENTRIES          8C306250
0821 00 D4000440          STO  L  STBF                               8C306260
0823 00 74010FFF          MDX  L  SECSE,1    INCR RETURN             8C306270
0825 00 4C8007FF          BSC  I  SECSE      EXIT              SX    8C306280
          *                                                          8C306290
0827 0  0000        SIWB  DC      0          MSG ADRS                8C306300
0828 0  0000        SECB  DC      0          CARD NO                 8C306310
0829 0  0000        CPID  DC      0          PID                     8C306320
082A 0  0000        NOEN  DC      0          NO ENTRIES              8C306330
082B 0  0442        STBF1 DC      SEIB       CD BFR ADRS             8C306340
082C 0  0003        K0003 DC      3          CONSTANT 3              8C306350
          *************************************************          8C306360
082D 0  0000        KIN1  DC      0                            SE    8C306370
082E C0 67000000          LDX  L3 600        SET IXING              8C306380
0830 00 C400043D          LD   L  TERM       GET FFFF               8C306390
0832 00 D70001DE   SKINA  STO  L3 KIWC       SET KEYIN AREA         8C306400
0834 0  73FF              MDX  3 -1          DECR IX 3               8C306410
0835 0  70FC              MDX     SKINA      LOOP                    8C306420
0836 00 4C80082D          BSC  I  KIN1       EXIT              SX    8C306430
          *************************************************          8C306440
          *                                                          8C306450
0838 0  0000        KINO  DC      0                            SE    8C306460
0839 0  67000258          LDX  L3 600        SET IXING              8C306470
083B 0  1010              SLA     16         CLEAR ACCUM            8C306480
083C 00 D70001DE          STO  L3 KIWC       CLEAR KEYIN AREA       8C306490
083E 0  73FF       SKINB  MDX  3 -1          DECR IX 3              8C306500
083F 0  70FC              MDX     SKINB      LOOP                   8C306510
0840 00 4C800838          BSC  I  KINO       EXIT              SX    8C306520
          *                                                          8C306530
          *              DEC KEYBOARD TO BINARY RT                   8C306540
          *                                                          8C306550
0842 0  0000        DKYB  DC      0                            SE    8C306560
0843 0  D862              STO     PHKX1      SAVE A + Q             8C306570
0844 0  C0FD              LD      DKYB                             8C306580
0845 0  D005              STO     HKYB                             8C306590
0846 00 D40008AF          STO  L  PHDSW      SET HEX-DEC SW = DEC   8C306600
0848 00 C40008F7          LD   L  PDKX1      CONSTANT 10           8C306610
084A 0  7005              MDX     PHKYD      ENTER COMMON SECTION  8C306620
          *                                                          8C306630
          *                                                          8C306640
          *              HEX KEYBOARD TO BINARY RT                   8C306650
          *                                                          8C306660
0848 0  0000        HKYB  DC      0                            SE    8C306670
084C 0  D859              STO     PHKX1      SAVE A + Q             8C306680
084D 0  C05F              LD      PHKX7      CONSTANT ZERO         8C306690
084E 0  D060              STO     PHDSW      SET HEX-DEC SW = HEX  8C306700
084F 0  C05E              LD      PHKX8                            8C306710
0850 0  D01F       PHKYD  STO     PHKYC      SET CONV CK           8C306720
0851 0  284F              STS     PHKYS      SAVE STATUS
```

```
0852 0  6949              STX  1  PHKY6+1    SAVE X1                 8C306730
0853 0  6A4A              STX  2  PHKY7+1    SAVE X2                 8C306740
0854 0  6B4B              STX  3  PHKY8+1    SAVE X3                 8C306750
0855 00 6780084B          LDX  I3 HKYB                               8C306760
0857 00 C7000000          LD   L3 0                                  8C306770
0859 0  D04E              STO     PHKX2      SAVE CHAR/WORD          8C306780
085A 00 C7800001          LD   I3 1          GET ADDR OF DISP        8C306790
085C 0  804C              A       PHKX3      COMPUTE START ADDR      8C306800
085D 0  D04C              STO     PHKX4                              8C306810
          *                                                          8C306820
          *                    INITIALIZE BINRY BUFFER               8C306830
          *                                                          8C306840
085E 0  1810              SRA     16                                 8C306850
085F 00 D400013D          STO  L  BWC        RESET WORD COUNT        8C306860
          *                                                          8C306870
          *              CONVERT NUMBER TO HEX                       8C306880
          *              * AND STORE IN BINARY BUF                   8C306890
          *                                                          8C306900
0861 00 6680013D   PHKY5  LDX  I2 BWC        SET X2 TO NEXT          8C306910
0863 00 76000013D         MDX  L2 BINRY-1    * AVAILABLE SPACE -1    8C306920
0865 0  6A0C              STX  2  PHKY1+1                            8C306930
0866 0  6A16              STX  2  PHKY3+1                            8C306940
0867 00 653008A8          LDX  I1 PHKX2      SET X1 TO STARTING      8C306950
0869 00 758008AA          MDX  I1 PHKX4      * ADDR + NUM CHAR/WD    8C306960
086B 00 678008A8          LDX  I3 PHKX2      SET X3 TO CHAR/WD       8C306970
086D 0  C100       PHKY2  LD   1  0          GET NUMBER              8C306980
086E 00 44000900          BSI  L  PCKB       CONVERT TO BINARY       8C306990
0870 0  0010       PHKYC  DC      16         LIM CK = 16 OR 10       8C307000
0871 00 D7000000   PHKY1  STO  L3 0          PLACE IN BINRY BUFF     8C307010
0873 0  71FF              MDX  3 -1                                  8C307020
0874 0  73FF              MDX  1 -1                                  8C307030
0875 0  70F7              MDX     PHKY2      SKIP WHEN DONE          8C307040
0876 00 740008AF          MDX  L  PHDSW,0    CK HEX-DEC SW           8C307050
0878 0  7037              MDX     PDKY1      BRANCH TO DEC RT        8C307060
          *                                                          8C307070
          *                    PACK BINARY                           8C307080
          *                                                          8C307090
0879 00 678008A8          LDX  I3 PHKX2      SET X3 TO CHAR/WD       8C307100
087B 0  10A0              SLT     32                                 8C307110
087C 00 C7000000   PHKY3  LD   L3 0                                  8C307120
087E 0  1884              SRT     4                                  8C307130
087F 0  73FF              MDX  3 -1                                  8C307140
0880 0  70FB              MDX     PHKY3                              8C307150
0881 0  63FC              LDX  3 -4          RIGHT JUSTIFY           8C307160
0882 00 778008A8          MDX  I3 PHKX2                              8C307170
0884 0  1884       PHKY4  SRT     4                                  8C307180
0885 0  7300              MDX  3  0                                  8C307190
0886 0  7001              MDX     PHKY9                              8C307200
0887 0  7002              MDX     PHKY9+2                            8C307210
0888 0  7301       PHKY9  MDX  3  1                                  8C307220
0889 0  70FA              MDX     PHKY4                              8C307230
088A 0  18D0              RTE     16                                 8C307240
088B 00 D6000001   PHKYF  STO  L2 1          PLACE IN BINRY BUFF     8C307250
088D 00 74010130          MDX  L  BWC,1      BUMP WORD COUNT         8C307260
          *                                                          8C307270
          *                    BUMP TO NEXT KEYIN FIELD              8C307280
          *                                                          8C307290
088F 0  C018       PHKYH  LD      PHKX2      GET CHAR/WD             8C307300
0890 0  801A              A       PHKX5      ADD ONE FOR SPACE       8C307310
0891 0  801B              A       PHKX4                              8C307320
0892 0  D017              STO     PHKX4                              8C307330
0893 00 678008AA          LDX  I3 PHKX4                              8C307340
0895 0  C300              LD   3  0                                  8C307350
0896 0  F015              EOR     PHKX6      CK FOR TERMINATOR       8C307360
0897 0  4820              BSC     Z          SKIP IF FOUND           8C307370
0898 0  70C8              MDX     PHKY5      GET NEXT NUMBER          8C307380
          *                                                          8C307390
          *                    EXIT FROM RT                          8C307400
          *
```

```
0899 00 7402084B          MDX   L  HKYB,2
089B 00 65000000  PHKY6   LDX   L1 0              RESTORE REGS
089D 00 66000000  PHKY7   LDX   L2 0
089F 00 67000900  PHKY8   LDX   L3 0
08A1 0  2000      PHKYS   LDS      0
08A2 0  C803              LDD      PHKX1
08A3 00 4C80084B          BSC   I  HKYB           EXIT FROM SUBRT
*
*
08A6    0000      PHKX1   BSS   E  0
08A6    0002      PHKX1   BSS      2              SAVE A + Q
08A8 0  0000      PHKX2   DC       0              CHAR PER WORD
08A9 0  01DE      PHKX3   DC       KEYIN-1
08AA 0  0000      PHKX4   DC       0              STARTING ADDR
08AB 0  0001      PHKX5   DC       1              CONSTANT 1
08AC 0  FFFF      PHKX6   DC       /FFFF          CONSTANT FFFF
08AD 0  0000      PHKX7   DC       0              CONSTANT 0
08AE 0  0010      PHKX8   DC       16             CONSTANT 16
08AF 0  0000      PHDSW DC         0              HEX-DEC SWITCH
*
*
*                          CONV NUM TO DEC AND STORE
*                          IN BINARY BUF
*
08B0 0  10A0      PDKY1   SLT      32
08B1 0  D840              STD      PDKWA          ZERO OUT WORK AREA
*
*                          CK FOR 9 CH/WD
*
08B2 0  C0F5              LD       PHKX2          GET CH/WD
08B3 00 B400092E          CMP   L  PCKX1          COMPARE TO 9
08B5 0  7039              MDX      PDKYE          ERROR TOO GREAT
08B6 0  7001              MDX      *+1
08B7 0  90F3              S        PHKX5          SUB ONE
08B8 0  D001              STO      PDKY2+1
08B9 00 67000000  PDKY2   LDX   L3 0              LDX MODIFIED CH/WD
08BB 00 66800872          LDX   I2 PHKY1+1
08BD 00 76800A8          MDX   I2 PHKX2           SET UP 1ST POWER
08BF 0  6100              LDX   1  0
08C0 0  C200      PDKY3   LD    2  0              GET BIN NUMBER
08C1 00 A50008F6          M     L1 PDKX2          MULT BY POWER
08C3 0  71FC              MDX   1  -4             CK FOR CH/WD GRT 4
08C4 0  7009              MDX      PDKYH          CH/WD GRT 4
08C5 0  7104      PDKYJ   MDX   1  4
08C6 0  1000              SLA      0
08C7 0  882A              AD       PDKWA
08C8 0  D829              STD      PDKWA
08C9 0  7101              MDX   1  1
08CA 0  72FF              MDX   2  -1
08CB 0  73FF              MDX   3  -1
08CC 0  70F3              MDX      PDKY3
08CD 0  7003              MDX      PDKY6
08CE 0  18D0      PDKYH   RTE      16             CH/WD GRT 4
08CF 0  A02A              M        PDKX1+3        MULTIPY BY 10,000
08D0 0  70F4              MDX      PDKYJ
*                          CK FOR SIGNED NUMBER
*
08D1 0  C006      PDKY6   LD       PHKX2
08D2 00 B400092E          CMP   L  PCKX1          CONS 9
08D4 0  701A              MDX      PDKYE          ERROR TOO GREAT
08D5 0  7001              MDX      *+1
08D6 0  7009              MDX      PDKY7          CK SIGN
*                          CK FOR CH/WD GREATER
*                          THAN 5
08D7 0  C0D0              LD       PHKX2
08D8 0  B026              CMP      PDKX3          CONS 5
08D9 0  700F              MDX      PDKY6
08DA 0  7001              MDX      *+1
```

```
8C307410
8C307420
8C307430
8C307440
8C307450
8C307460
8C307470
8C307480
8C307490
8C307500
8C307510
8C307520
8C307530
8C307540
8C307550
8C307560
8C307570
8C307580
8C307590
8C307600
8C307610
8C307620
8C307630
8C307640
8C307650
8C307660
8C307670
8C307680
8C307690
8C307700
8C307710
8C307720
8C307730
8C307740
8C307750
8C307760
8C307770
8C307780
8C307790
8C307800
8C307810
8C307820
8C307830
8C307840
8C307850
8C307860
8C307870
8C307880
8C307890
8C307900
8C307910
8C307920
8C307930
8C307940
8C307950
8C307960
8C307970
8C307980
8C307990
8C308000
8C308010
8C308020
8C308030
8C308040
8C308050
8C308060
8C308070
8C308080
```

```
08DB 0  700F              MDX      PDKYA         GO TO CK FOR /7FFF
*                          SINGLE PRECISION NUMBER
*
08DC 00 66800872  PDKYF   LDX   I2 PHKY1+1
08DE 0  C014              LD       PDKWA+1       GET CONV NUMBER
08DF 0  70AB              MDX      PHKYF
*                          CORRECT SIGN
08E0 0  C200      PDKY7   LD    2  0
08E1 00 4C1808E9          BSC   L  PDKY8,+-      BRANCH IF POS NUMB
08E3 0  10A0              SLT      32            CHANGE SIGN
08E4 0  980D              SD       PDKWA
08E5 0  DA00      PDKY9   STD   2  0
08E6 00 7402013D          MDX   L  BWC,2
08E8 0  70A6              MDX      PHKYH
08E9 0  C808      PDKY8   LDD      PDKWA         DOUBLE PREC POS NUMB
08EA 0  70FA              MDX      PDKY9
*                          CK LESS THAN OR EQ /7FFF
08EB 0  C806      PDKYA   LDD      PDKWA
08EC 0  9807              SD       PDKX4         CONS 000000R000
08ED 00 4C2808DC          BSC   L  PDKYF,+Z      BRANCH TO SINGLE PREC
08EF 00 44800132  PDKYE   BSI   I  SER
08F1 0  0BB2              DC       PCKBE
08F2 0  0000              BSS   E  0
08F2 0  0002      PDKWA   BSS      2             WORK AREA
08F4 0  0000      PDKX4   DC       0             CONS /00000R000
08F5 0  8000              DC       /8000
08F6 0  0001      PDKX2   DC       1             CONV TABLE
08F7 0  000A      PDKX1   DC       10
08F8 0  0064              DC       100
08F9 0  03E8              DC       1000
08FA 0  2710              DC       10000
08FB 0  000A              DC       10
08FC 0  0064              DC       100
08FD 0  03E8              DC       1000
08FE 0  2710              DC       10000
08FF 0  0005      PDKX3   DC       5             CONS 5
*
*
*
*
*
*                          KEYBOARD TO BINARY RT
*
0900 0  0000      PCKB    DC       0
0901 0  6B27              STX   3  PCKBX+1       SAVE X3
0902 0  D029              STD      PCKBA         SAVE NUMBER
0903 00 C4800900          LD    I  PCKB          GET LIMIT CK
0905 0  D001              STO      PCKB1+1
0906 00 67000000  PCKB1   LDX   L3 0             SET X3 TO LIM CK
0908 00 C7000A5E          LD    L3 KECOD         LK UP CODE
090A 00 F021              EOR      PCKBA
090B 00 4C180922          BSC   L  PCKB3,+-      BRANCH IF FOUND
090D 0  73FF              MDX   3  -1            SKIP IF ILLEGAL
090E 0  70F9              MDX      PCKB1+2
090F 00 C40008A8          LD    L  PHKX2         CK FOR 9 CHAR FIELD
0911 0  901C              S        PCKX1
0912 00 4C20091F          BSC   L  PCKB4,+       GO TO ERROR IF NOT 9
0914 0  C017              LD       PCKBA         CK FOR +
0915 0  F019              EOR      PCKX2
0916 00 4C180926          BSC   L  PCKBX-2,+-    CK FOR -
0918 0  C013              LD       PCKBA
0919 0  F016              EOR      PCKX3
091A 00 4C20091F          BSC   L  PCKB4,Z       GO TO ERROR, NO + -
091C 00 C4000BBE          LD    L  PCKX4
091E 0  7007              MDX      PCKBX-2
091F 00 44800132  PCKB4   BSI   I  SER           IMPROPER KEY CODE
0921 0  0BB2              DC       PCKBE         * I.E NOT 0-9 OR 0-F
```

```
8C308090
8C308100
8C308110
8C308120
8C308130
8C308140
8C308150
8C308160
8C308170
8C308180
8C308190
8C308200
8C308210
8C308220
8C308230
8C308240
8C308250
8C308260
8C308270
8C308280
8C308290
8C308300
8C308310
8C308320
8C308330
8C308340
8C308350
8C308360
8C308370
8C308380
8C308390
8C308400
8C308410
8C308420
8C308430
8C308440
8C308450
8C308460
8C308470
8C308480
8C308490
8C308500
8C308510
8C308520
8C308530
8C308540
8C308550
8C308560
8C308570
8C308580
8C308590
8C308600
8C308610
8C308620
8C308630
8C308640
8C308650
8C308660
8C308670
8C308680
8C308690
8C308700
8C308710
8C308720
8C308730
8C308740
8C308750
8C308760
```

```
0922 0   73FF       PCKB3 MDX   3 -1                              8C308770
0923 0   1000             SLA   0                                 8C308780
0924 0   6B08             STX   3 PCKBB                           8C308790
0925 0   C007             LD    PCKBB       GET CONVERTED NUM     8C308800
0926 00  74010900         MDX L PCKB,1                            8C308810
0928 00  67000000   PCKBX LDX  L3 0         RESTORE X3            8C308820
092A 00  4C800900         BSC I PCKB                              8C308830
      *                                                           8C308840
092C 0   0000       PCKBA DC    0           ORIGINAL NUMBER       8C308850
092D 0   0000       PCKBB DC    0           CONVERTED NUMBER      8C308860
092E 0   0009       PCKX1 DC    9                                 8C308870
092F 0   8000       PCKX2 DC    /8000       +                     8C308880
0930 0   4000       PCKX3 DC    /4000       -                     8C308890
      *                                                           8C308900
      *                                                           8C308910
      *             PUNCH EDIT CARD OUTPUT ROUTINE                8C308920
      *                                                           8C308930
0931 0   0000       PECOR DC    0                                 8C308940
0932 00  DC0009B6         STD L PECX1       SAVE REGISTERS        8C308950
0934 0   285C             STS   PECOS                             8C308960
0935 0   1810             SRA   16                                8C308970
0936 0   6955       PECYF STX   1 PECY1+1                         8C308980
0937 0   6A56             STX   2 PECY2+1                         8C308990
0938 0   6857             STX   3 PECY3+1                         8C309000
0939 00  4480012C         BSI I KEY         PRINT EDIT CARD LIST  8C309010
093B 0   08C9             DC    PECXF       * MESSAGE             8C309020
093C 0   0000             DC    0                                 8C309030
      *                                                           8C309040
      *                                                           8C309050
      *             READ A CARD AND VERIFY                        8C309060
      *             * THAT IT IS BLANK                            8C309070
      *                                                           8C309080
093D 00  66000442         LDX  L2 SEIB      SET X2 = ED IMAG BUF  8C309090
093F 00  650001E0         LDX  L1 KEYIN+1   X1 = OPT REG          8C309100
0941 00  0C000B38   PECY7 XIO L RDSW        READ DATA SWS         8C309110
0943 00  C4000B3A         LD  L DTSW        GET SWS               8C309120
0945 00  4C28094B         BSC L PT,+Z       BRANCH IF P T         8C309130
0947 0   1001             SLA   1                                 8C309140
0948 00  4C28094B         BSC L PT,+Z       BRANCH IF BOTH        8C309150
094A 0   7007             MDX   NTPT        NOT PAPER TAPE        8C309160
094B 00  44000B17   PT    BSI L PPT         PUNCH LEADER     SRC  8C309170
094D 00  C4000B3A         LD  L DTSW        GET SWS               8C309180
094F 0   1001             SLA   1                                 8C309190
0950 00  4C100966         BSC L PECYE,-     BRANCH IF NOT BOTH    8C309200
0952 0   086B       NTPT  XIO   PECX5       SENSE DSW             8C309210
0953 00  4C0409A8         BSC L PECY6,E     XFER IF NOT READY     8C309220
0955 0   0866             XIO   PECX4       READ A CARD           8C309230
0956 0   0867       PECY4 XIO   PECX5       SENSE DSW             8C309240
0957 0   1801             SRA   1           CK BUSY               8C309250
0958 00  4C040956         BSC L PECY4,E     XFER IF BUSY          8C309260
095A 0   180C             SRA   12                                8C309270
095B 00  4C0409AE         BSC L PECY8,E     XFER IF ERROR ON      8C309280
095D 0   0862             XIO   PECX6       RESET DSW             8C309290
      *                                                           8C309300
      *                                                           8C309310
      *             CK FOR BLANK CARD                             8C309320
      *                                                           8C309330
095E 0   1810             SRA   16                                8C309340
095F 0   6350             LDX   3 80                              8C309350
0960 00  EF0001DF   PECY5 OR   L3 KEYIN                           8C309360
0962 0   73FF             MDX   3 -1                              8C309370
0963 0   70FC             MDX   PECY5                             8C309380
0964 00  4C200952         BSC L NTPT,Z                            8C309390
      *                                                           8C309400
      *             BLANK OUT OUTPUT BUFF                         8C309410
      *                                                           8C309420
0966 0   1810       PECYE SRA   16                                8C309430
0967 0   63B0             LDX   3 -80                             8C309440
```

```
0968 00  D7000230   PECYA STD  L3 KEYIN+81                        8C309450
096A 0   7301             MDX   3 1                                8C309460
096B 0   70FC             MDX   PECYA                              8C309470
      *                                                            8C309480
096C 00  6700FF80         LDX  L3 -80       SET X3 = COL CONTROL   8C309490
      *                                                            8C309500
      *                   SET E INTO OUTPUT AREA                   8C309510
096E 00  C4000A6D         LD   L PC1X2                             8C309520
0970 0   D100             STO   1 0                                8C309530
0971 0   7301             MDX   3 1                                8C309540
      *                                                            8C309550
      *                   SET PID INTO OUTPUT AREA                 8C309560
0972 0   C200             LD    2 0                                8C309570
0973 0   1008             SLA   8                                  8C309580
0974 0   4051             BSI   PBIHX       CONV TO HEX AND   SRC  8C309590
      *                               * STORE IN OUTPUT            8C309600
      *                                                            8C309610
      *                   CK FOR END OF ED CD DIR                  8C309620
      *                                                            8C309630
0975 0   C201             LD    2 1                                8C309640
0976 00  F4000BC8         EOR  L PECXD                             8C309650
0978 00  4C200995         BSC  L PECYB,Z    BRANCH IF NOT END CD   8C309660
097A 00  C4000BC8         LD   L PECXD      SET FFFF EDIT END      8C309670
097C 0   4049             BSI   PBIHX       CONV AND STORE    SRC  8C309680
097D 0   4061             BSI   PED         PUNCH CARD        SRC  8C309690
097E 00  44000A0A         BSI  L PPECD      PRINT THE EDIT CARD    8C309700
0980 00  C4000B3A         LD   L DTSW       GET SWS                8C309710
0982 00  4C28098B         BSC  L PECY1,+Z   BRANCH IF NOT CARDS    8C309720
0984 0   0835             XIO   PECXC       STACKER SELECT         8C309730
0985 0   083C             XIO   PECX7       FEED A CARD            8C309740
0986 0   0837       PECYC XIO   PECX5       SENSE DSW              8C309750
0987 0   1801             SRA   1                                  8C309760
0988 00  4C040986         BSC  L PECYC,E                           8C309770
098A 0   0835             XIO   PECX6       RESET DSW              8C309780
      *                                                            8C309790
098B 00  65000000   PECY1 LDX  L1 0                                8C309800
098D 00  66000000   PECY2 LDX  L2 0         RESTORE REGS           8C309810
098F 00  67000000   PECY3 LDX  L3 0                                8C309820
0991 0   2000       PECOS LDS   0                                  8C309830
0992 0   C823             LDD   PECX1                              8C309840
0993 00  4C800931         BSC I PECOR       EXIT FROM ROUTINE      8C309850
      *                               SET CARD NUMB IN OUTPUT      8C309860
0995 0   C201       PECYB LD    2 1                                8C309870
0996 0   E821             OR    PECX3       ADD IN ED              8C309880
0997 0   402E             BSI   PBIHX       CONV AND STORE    SRC  8C309890
      *                                                            8C309900
      *                   SET NUMB ENTRIES PER CARD                8C309910
      *                                                            8C309920
0998 0   C202             LD    2 2                                8C309930
0999 0   1888             SRT   8                                  8C309940
099A 0   1810             SRA   16                                 8C309950
099B 0   1088             SLT   8                                  8C309960
099C 0   D01C             STD   PECXE       SAVE                   8C309970
099D 0   4028             BSI   PBIHX       CONV AND STORE    SRC  8C309980
      *                               MOVE DATA TO OUTPUT BUFF     8C309990
099E 0   C203       PECYD LD    2 3                                8C310000
099F 0   4026             BSI   PBIHX       CNV AND STORE     SRC  8C310010
09A0 0   7201             MDX   2 1         BUMP IMAG BUF ADDR     8C310020
09A1 00  74FF09B9         MDX L PECXE,-1    DECREMENT ENTRIES/CD   8C310030
09A3 0   70FA             MDX   PECYD                              8C310040
09A4 0   403A             BSI   PED         PUNCH A CARD      SRC  8C310050
09A5 0   4064             BSI   PPECD       PRINT CARD        SRC  8C310060
09A6 0   72C3             MDX   2 3                                8C310070
09A7 0   70A5             MDX   PT+2        BRANCH                 8C310080
      *                                                            8C310090
09A8 00  4480012C   PECY6 BSI I KEY                                8C310100
09AA 0   0BBF             DC    PECX9                              8C310110
                                                                   8C310120
```

8K EDIT CONTROL

```
09AB 0  0000          DC    0                                         8C310130
09AC 0  3003   WAIT3  WAIT  3          1442 NOT READY =RD)            8C310140
               *                       *PUSH START TO RETRY           8C310150
09AD 0  7093          MDX   PECY7       BRANCH                        8C310160
               *                                                      8C310170
09AE 00 4480012C PECY8 BSI  I  KEY                                    8C310180
09B0 0  0BBF          DC    PECX9                                     8C310190
09B1 0  0000          DC    0          1442 READ ERROR               8C310200
09B2 0  080D          XIO   PECX6      RESET DSW                     8C310210
09B3 0  3004   WAIT4  WAIT  4          PUSH START TO REREAD          8C310220
09B4 0  708C          MDX   PFCY7      BRANCH                        8C310230
               *                                                      8C310240
09B6    0000          BSS  E  0                                       8C310250
09B6    0002   PECX1  BSS   2          SAVE A + Q                    8C310260
09B8 0  ED00   PFCX3  DC   /ED00                                     8C310270
09B9 0  0000   PECXE  DC    0          ENTRIES PER CARD             8C310280
09BA 0  0000   PECXC  DC    0          STACKER SELECT IOCC          8C310290
09BB 0  1480          DC   /1480                                     8C31030C
09BC 0  01E0   PECX4  DC    KEYIN+1    READ A CARD IOCC             8C310310
09BD 0  1600          DC   /1600                                     8C310320
09BE 0  0000   PECX5  DC    0          SENSE 1442 DSW               8C310330
09BF 0  1700          DC   /1700                                     8C310340
09C0 0  0000   PECX6  DC    0          SENSE AND PESET DSW          8C310350
09C1 0  1703          DC   /1703                                     8C310360
09C2 0  0000   PECX7  DC    0          FEED A CARD IOCC             8C310370
09C3 0  1402          DC   /1402                                     8C310380
09C4 0  01E0   PECX8  DC    KEYIN+1    PUNCH A CARD IOCC            8C310390
09C5 0  1500          DC   /1500                                     8C310400
               *                                                      8C310410
               *                                                      8C310420
               *              BINARY TO HEX  CARD IMAGE RT          8C310430
               *                                                      8C310440
09C6 0  0000   PBIHX  DC    0                                        8C310450
09C7 0  1800          RTE   16         PUT BIN WORD TO BE           8C310460
               *                       * CONVERTED IN Q REG         8C310470
09C8 0  6911          STX   1 PBIY1+1  SAVE X1                      8C310480
09C9 0  6A12          STX   2 PBIY2+1  SAVE X2                      8C310490
09CA 0  6104          LDX   1 4        SET LOOP CONTROL            8C310500
09CB 0  1810   PBIY3  SRA   16         CONV CHAR TO HEX            8C310510
09CC 0  1084          SLT   4                                       8C310520
09CD 0  D001          STO   *+1                                     8C310530
09CE 00 66000000      LDX   L2 0                                    8C310540
09D0 00 C6000A5F      LD    L2 KECOD+1 GET HEX EQUIV               8C310550
09D2 00 D7000230      STO   L3 KEYIN+81                            8C310560
09D4 0  7301          MDX   3 1        BUMP TO NEXT OUTPUT         8C310570
09D5 0  1000          SLA   0          NOP                         8C310580
09D6 0  71FF          MDX   1 -1                                   8C310590
09D7 0  70F3          MDX   PBIY3                                  8C310600
09D8 0  7301          MDX   3 1        PUT BLANK IN OUTPUT         8C310610
09D9 00 65000000 PBIY1 LDX  L1 0       RESTORE X1                 8C310620
09DB 00 66000000 PBIY2 LDX  L2 0       RESTORE X2                 8C310630
09DD 00 4C8009C6      BSC   I PBIHX                               8C310640
               *                                                      8C310650
               *              PUNCH A CARD ROUTINE                8C310660
09DF 0  0000   PED    DC    0                              SE     8C310670
09E0 00 C4000B3A      LD    L DTSW      GET SWS                   8C310680
09E2 00 4C280B3B      BSC   L HB05,+Z   BRANCH IF P T            8C310690
09E4 0  1001          SLA   1                                     8C310700
09E5 00 4C280B3B      BSC   L HB05,+Z   BRANCH IF BOTH           8C310710
09E7 00 C400022F PEDEN LD   L KEYIN+80                           8C310720
09E9 0  E81F          OR    PEDX1       * AT END OF OUTPUT       8C310730
09EA 00 D400022F      STO   L KEYIN+80                           8C310740
09EC 0  08D1   PEDY4  XIO   PECX5       SENSE DSW                8C310750
09ED 00 4C0409FB      BSC   L PEDY1,E   XFER IF NOT RDY          8C310760
09EF 0  08CA          XIO   PECXC       STACKER SELECT           8C310770
09F0 0  08D3          XIO   PECX8       PUNCH C..RD              8C310780
09F1 0  08CC   PEDY2  XIO   PECX5       SENSE DSW                8C310790
09F2 0  1801          SRA   1           CK BUSY                  8C310800
```

8K EDIT CONTROL

```
09F3 00 4C0409F1      BSC   L PEDY2,E   XFER IF BUSY             8C310810
09F5 0  180C          SRA   12                                   8C310820
09F6 00 4C040A02      BSC   L PEDY3,E   XFER IF ERROR ON         8C310830
09F8 0  08C7          XIO   PECX6       RESET DSW                8C310840
09F9 00 4C8009DF PEDEX BSC  I PED       EXIT             SX      8C310850
               *                                                      8C310860
09FB 0  08C2   PEDY1  XIO   PECX5       SENSE DSW                8C310870
09FC 00 4480012C      BSI   I KEY                                8C310880
09FE 0  0BBF          DC    PECX9                                8C310890
09FF 0  0000          DC    0                                    8C310900
0A00 0  3006   WAIT6  WAIT  6           1442 NOT RDY=PUNCH)      8C310910
0A01 0  70EA          MDX   PEDY4                                8C310920
               *                                                      8C310930
0A02 0  08BD   PEDY3  XIO   PECX6       RESET DSW                8C310940
0A03 00 4480012C      BSI   I KEY                                8C310950
0A05 0  0BBF          DC    PECX9                                8C310960
0A06 0  0000          DC    0                                    8C310970
0A07 0  3007   WAIT7  WAIT  7           1442 ERROR AFTER         8C310980
               *                        * PUNCHING              8C310990
0A08 0  70E3          MDX   PEDY4                                8C311000
               *                                                      8C311010
0A09 0  0008   PEDX1  DC   /0008        END OF PUNCH BIT         8C311020
               *                                                      8C311030
               *                                                      8C311040
               *                                                      8C311050
               *                                                      8C311060
               *              CONVERT CCD TO EBDIC + KEY         8C311070
               *                                                      8C311080
0A0A 0  0000   PPECD  DC   /0000                                 8C311090
0A0B 0  692B          STX   1 PPEY5+1                            8C311100
0A0C 0  6A2C          STX   2 PPEY6+1   SAVE XRS + A + Q         8C311110
0A0D 0  6B2D          STX   3 PPEY7+1                            8C311120
0A0E 0  D833          STD   PPEX3                                8C311130
               *                                                      8C311140
               *                                                      8C311150
0A0F 00 650001DF      LDX   L1 KEYIN    INITIALIZE ROUTINE       8C311160
0A11 00 6D0001DE      STX   L1 KIWC                              8C311170
0A13 0  6380          LDX   3 -80                                8C311180
0A14 0  6202          LDX   2 2                                  8C311190
0A15 0  61EF   PPEY4  LDX   1 -17       RESTORE KECOD POINTR     8C311200
0A16 00 C7000230 PPEY2 LD   L3 KEYIN+81 FETCH KEYBD CHAR        8C311210
0A18 00 F5000A6F      EOR   L1 KECOD+17                         8C311220
0A1A 0  1804          SRA   4                                    8C311230
0A1B 00 4C180A1F      BSC   L PPEY1,+-  BR IF COMPARE           8C311240
0A1D 0  7101          MDX   1 1                                  8C311250
0A1E 0  70F7          MDX   PPEY2       TRY NEXT CHAR           8C311260
               *                                                      8C311270
               *                                                      8C311280
0A1F 00 C5000AA3 PPEY1 LD   L1 KTILT+16 PACK 2 EBDIC CHARS       8C311290
0A21 0  1008          SLA   8                                    8C311300
0A22 0  18D8          RTE   24                                   8C311310
0A23 0  72FF          MDX   2 -1        SKIP IF DONE TWO CHARS   8C311320
0A24 0  7019          MDX   PPEY3       FETCH NEXT CHAR          8C311330
0A25 0  6202          LDX   2 2                                  8C311340
0A26 0  18D0          RTE   16                                   8C311350
0A27 00 D48001DE      STO   I KIWC      PLACE IN OUTPUT AREA     8C311360
0A29 00 740101DE      MDX   L KIWC,1    NEXT STORAGE AREA        8C311370
0A2B 0  F015          EOR   PPEX2                                8C311380
0A2C 00 4C200A3E      BSC   L PPEY3,Z   BR - NOT DBLE BLANK      8C311390
0A2E 0  61FF   PPEY8  LDX   1 -1        SET TERM                8C311400
0A2F 00 6D8001DE      STX   L1 KIWC                             8C311410
0A31 00 4480012C      BSI   I KEY       GO PRINT WHOLE EDIT     8C311420
0A33 0  01DF          DC    KEYIN       MSG AREA                8C311430
0A34 0  0000          DC    0                                   8C311440
0A35 0  C80C          LDD   PPEX3       RESTORE XRS, A AND Q    8C311450
0A36 00 65000000 PPEY5 LDX  L1 /0000                           8C311460
0A38 00 66000000 PPEY6 LDX  L2 /0000                           8C311470
0A3A 00 67000000 PPEY7 LDX  L3 /0000                           8C311480
```

```
0A3C 00 4C800A0A        BSC  I PPECD    FXIT TO USER              8C311490
                   *                                              8C311500
0A3E 0 7301    PPEY3 MDX    3 1         SKIP IF DONE              8C311510
0A3F 0 70D5          MDX    PPEY4                                 8C311520
0A40 0 70ED          MDX    PPEY8                                 8C311530
                   *                                              8C311540
0A41 0 4040    PPEX2 DC     /4040       DOUBLE SPACE EBDIC        8C311550
0A42   0002    PPEX3 BSS E  2           SAVED A AND Q             8C311560
                   *                                              8C311570
                   *                                              8C311580
                   *                                              8C311590
                   *                    KEYBOARD CODES      *     8C311600
0A44   0000          BSS E                                        8C311610
0A44 0 0000    KSVS  DC     /0000       SENSE-NO RESET            8C311620
0A45 0 0F02          DC     /0F02                                 8C311630
0A46 0 0000    KMSG  DC     /0000       MESS ADRS                 8C311640
0A46           KECSD EQU    KMSG                                  8C311650
0A47 0 0000    KOUT  DC     /0000       ROT-TLT OUTPUT TABLE      8C311660
0A48 0 0000          DC     /0000                                 8C311670
0A49 0 0000          DC     /0000                                 8C311680
0A4A 0 0004    K0004 DC     4               CONSTANT              8C311690
                   *                                              8C311700
0A4B 0 4400    KL    DC     /4400                                 8C311710
0A4C 0 0000    KAQ   DC     0           ACC                       8C311720
0A4D 0 0000          DC     0           Q REG                     8C311730
0A4E 0 0000    KRDY  DC     /0000       SENSE - RESET CMND        8C311740
0A4F 0 0F03          DC     /0F03                                 8C311750
0A50 0 0A4E    KPRT  DC     KRDY        PRINT COMMAND             8C311760
0A51 0 0902          DC     /0902                                 8C311770
0A52 0 0000    KPCD  DC     /0000       KBD PROCEED COMMAND       8C311780
0A53 0 0C02          DC     /0C02                                 8C311790
0A54 0 019F    KRED  DC     KEYIN       READ KBD COMMAND          8C311800
0A55 0 0A02          DC     /0A02                                 8C311810
0A56 0 0001    KONE  DC     1           CONSTANT 1                8C311820
0A57 0 8120    KN    DC     /8120       UPPER CASE N              8C311840
0A58 0 8060    KY    DC     /8060            Y                    8C311850
0A59 0 4420          DC     /4420            *                    8C311860
0A5A 0 FFFF          DC     /FFFF                                 8C311870
0A5B 0 8420    KECPD DC     /8420                                 8C311880
0A5C 0 80A0          DC     /80A0            +                    8C311890
0A5D 0 4000          DC     /4000            -                    8C311900
                   *                                              8C311910
0A5E 0 0000    KECOD DC     /0000       SPACE                     8C311920
0A5F 0 2000          DC     /2000       0                         8C311930
0A60 0 1000          DC     /1000       1                         8C311940
0A61 0 0800          DC     /0800       2                         8C311950
0A62 0 0400          DC     /0400       3                         8C311960
0A63 0 0200          DC     /0200       4                         8C311970
0A64 0 0100          DC     /0100       5                         8C311980
0A65 0 0080          DC     /0080       6                         8C311990
0A66 0 0040          DC     /0040       7                         8C312000
0A67 0 0020          DC     /0020       8                         8C312010
0A68 0 0010          DC     /0010       9                         8C312020
                   *                                              8C312030
0A69 0 9000    KECAD DC     /9000       A                         8C312040
0A6A 0 8800          DC     /8800       B                         8C312050
0A6B 0 8400    KC    DC     /8400       C                         8C312060
0A6C 0 8200          DC     /8200       D                         8C312070
0A6D 0 8100    PBIX2 DC     /8100       E                         8C312080
0A6E 0 8080          DC     /8080       F                         8C312090
                   *                                              8C312100
0A6F 0 0002    KRENT DC     /0002       ERASE FIELD               8C312110
0A70 0 0004    KERSE DC     /0004       ERASE CHAR                8C312120
0A71 0 0008    KENDK DC     /0008       END OF MESSAGE            8C312130
0A72 0 4100    KAL   DC     /4100       LOWER CASE N              8C312140
0A73 0 2020          DC     /2020            Y                    8C312150
0A74 0 4220          DC     /4220            *                    8C312160
0A75 0 FFFF          DC     /FFFF                                 8C312170
```

```
0A76 0 8220          DC     /8220            .                    8C312180
0A77 0 FFFF          DC     /FFFF                                 8C312190
0A78 0 FFFF          DC     /FFFF                                 8C312200
0A79 0 2420    KCMA  DC     /2420                                 8C312210
          *****************************************************   8C312220
                   *                                              8C312230
                   *                    TYPEWRITER CODES          8C312240
                   *                      AND EBDIC CODES         8C312250
                   *                                        *     8C312260
0A7A 0 16C7    KTGLT DC     /16C7       G                         8C312270
0A7B 0 26C8          DC     /26C8       H                         8C312280
0A7C 0 22C9          DC     /22C9       I                         8C312290
0A7D 0 7ED1          DC     /7ED1       J                         8C312300
0A7E 0 5AD2          DC     /5AD2       K                         8C312310
                   *                                              8C312320
0A7F 0 5ED3    KLRT  DC     /5ED3       L                         8C312330
0A80 0 72D4          DC     /72D4       M                         8C312340
                   *                                              8C312350
0A81 0 96E7          DC     /96E7       X                         8C312360
0A82 0 52D6          DC     /52D6       O                         8C312370
0A83 0 56D7          DC     /56D7       P                         8C312380
0A84 0 66D8          DC     /66D8       Q                         8C312390
0A85 0 62D9          DC     /62D9       R                         8C312400
0A86 0 9AE2          DC     /9AE2       S                         8C312410
0A87 0 9EE3          DC     /9EE3       T                         8C312420
0A88 0 B2E4          DC     /B2E4       U                         8C312430
0A89 0 B6E5          DC     /B6E5       V                         8C312440
0A8A 0 92E6          DC     /92E6       W                         8C312450
0A8B 0 76D5          DC     /76D5       N                         8C312460
                   *                                              8C312470
0A8C 0 A6E8          DC     /A6E8       Y                         8C312480
0A8D 0 D65C          DC     /D65C       *                         8C312490
0A8E 0 806B          DC     /806B       ,                         8C312500
0A8F 0 004B    KTPLT DC     /004B       .                         8C312510
0A90 0 DA4E          DC     /DA4E       +                         8C312520
0A91 0 8460          DC     /8460       -                         8C312530
                   *                                              8C312540
0A92 0 2140    KTDLT DC     /2140       SPACE                     8C312550
0A93 0 C4F0    KTILT DC     /C4F0       0                         8C312560
0A94 0 FCF1          DC     /FCF1       1                         8C312570
0A95 0 D8F2          DC     /D8F2       2                         8C312580
0A96 0 DCF3          DC     /DCF3       3                         8C312590
0A97 0 F0F4          DC     /F0F4       4                         8C312600
0A98 0 F4F5          DC     /F4F5       5                         8C312610
0A99 0 D0F6          DC     /D0F6       6                         8C312620
0A9A 0 D4F7          DC     /D4F7       7                         8C312630
0A9B 0 E4F8          DC     /E4F8       8                         8C312640
0A9C 0 E0F9          DC     /E0F9       9                         8C312650
                   *                                              8C312660
0A9D 0 3EC1    KTALT DC     /3EC1       A                         8C312670
0A9E 0 1AC2          DC     /1AC2       B                         8C312680
0A9F 0 1EC3          DC     /1EC3       C                         8C312690
0AA0 0 32C4          DC     /32C4       D                         8C312700
0AA1 0 36C5          DC     /36C5       E                         8C312710
0AA2 0 12C6          DC     /12C6       F                         8C312720
                   *                                              8C312730
0AA3 0 815B    KCR   DC     /815B       CARRIER RETURN            8C312740
                   *                                              8C312750
                   *                    KEYBOARD ERROR MSG        8C312760
0AA4 0 D600    KFELD DC     /D600       *                         8C312770
0AA5 0 D600          DC     /D600       *                         8C312780
0AA6 0 D600          DC     /D600       *                         8C312790
0AA7 0 8100          DC     /8100       CR                        8C312800
0AA8 0 3600          DC     /3600       E                         8C312810
0AA9 0 C400          DC     /C400       O                         8C312820
0AAA 0 C400          DC     /C400       O                         8C312830
0AAB 0 FC00          DC     /FC00       1                         8C312840
0AAC 0 2100          DC     /2100                                 8C312850
```

```
0AAD 0  2100              DC    /2100      SP              8C312860
0AAE 0  5E00              DC    /5E00      L               8C312870
0AAF 0  2200              DC    /2200      I               8C312680
0AB0 0  7600              DC    /7600      N               8C312890
0AB1 0  3600              DC    /3600      E               8C312900
0AB2 0  2100              DC    /2100      SP              8C312910
0AB3 0  1E00              DC    /1E00      C               8C312920
0AB4 0  3E00              DC    /3E00      A               8C312930
0AB5 0  7600              DC    /7600      N               8C312940
0AB6 0  1E00              DC    /1E00      C               8C312950
0AB7 0  3600              DC    /3600      E               8C312960
0AB8 0  5E00              DC    /5E00      L               8C312970
0AB9 0  5E00              DC    /5E00      L               8C312980
0ABA 0  3600              DC    /3600      E               8C312990
0ABB 0  3200              DC    /3200      D               8C313000
0ABC 0  8120       K8120  DC    '/8120                     8C313010
0ABD 0  8101              DC    /8101      CR              8C313020
*                                                          8C313030
*                                                          8C313040
*                    ROUTINE TO READ ONE                   8C313050
*                    SKELTON SECTION                       8C313060
*                                                          8C313070
0ABE 0  0000       RDSK   DC    0                    SE    8C313070
0ABF 0  C005              LD    RDSX0   GET LDR RETURN     8C313080
0AC0 00 D4000124          STO   L /0124  SET              8C313090
0AC2 0  6050              LDX   X /0050  BRANCH TO LDR      8C313100
0AC3 00 4C800ABE   RDSK1  BSC   I RDSK   EXIT          SX  8C313110
0AC5 0  0AC3       RDSX0  DC    RDSK1  RETURN              8C313120
************************************************           8C313130
*                                                          8C313140
*                                                          8C313150
*                                                          8C313160
*                    XFER VECTOR TBLS BY FORM NO.          8C313170
0AC6 0  C4D4       LRAIT  DC    DONT    FORM 0             8C313180
0AC7 0  CE06              DC    LRTF1   1                  8C313190
0AC8 0  0AFE              DC    LRTF2   2                  8C313200
*                                                          8C313210
*                                                          8C313220
*                                                          8C313230
*                                                          8C313240
*                                                          8C313250
*                                                          8C313260
*                                                          8C313270
*                                                          8C313280
0AC9 0  0000       LWKA   DC    -       WORK STORAGE AREA  8C313290
*                                                          8C313300
0ACA 0  0000       LDOIT  DC                        SE     8C313310
0ACB 0  6200              LDX   2  0                       8C313320
0ACC 00 6E00043F          STX   L2 LGROP  RESET GROUP CNTR 8C313330
0ACE 00 65800ACA          LDX   I1 LDOIT                   8C313340
0AD0 0  C101              LD    I 1     LD CHR / WORD CNT   8C313350
0AD1 0  D0F7              STO   LWKA    SAVE IT            8C313360
0AD2 0  6901              STX   1 LWCLD+1                   8C313370
0AD3 00 65800000   LWCLD  LDX   I1      LD FORM NUMBER      8C313380
0AD5 00 45800AC6          BSI   I1 LRAIT  BRANCH TO RTN    8C313390
0AD7 00 74020ACA   DONT1  MDX   L LDOIT,2 INCR RETURN      8C313400
0AD9 00 4C800ACA          BSC   I LDOIT  EXIT          SX  8C313410
*                                                          8C313420
0ADB 0  0000       DONT   DC    C                          8C313430
0ADC 00 4C000AD7          BSC   L DONT1                     8C313440
*                                                          8C313450
*                                                          8C313460
*                                                          8C313470
0ADE 0  0000       LBGNR  DC                        SE     8C313480
0ADF 00 650001DE          LDX   L1 KIWC   LD INPUT TBL ADDR 8C313490
0AE1 0  C100              LD    I 0     LD INPUT WC         8C313500
0AE2 00 D400043E          STO   L LWC   SAVE WC            8C313510
0AE4 00 6680043E          LDX   I2 LWC                     8C313520
0AE6 0  7201              MDX   2 1                         8C313530
```

```
0AE7 00 7402043E          MDX   L LWC,2  ADD 2 TO WC    SX 8C313540
0AE9 00 4C800ADE          BSC   I LBGNR  EXIT           SX 8C313550
*                                                          8C313560
*                                                          8C313570
*                                                          8C313580
*                    DATA WRONG ERROR                      8C313590
0AEB 0  0000       LERR   DC    0                          8C313600
0AEC 00 44800132          BSI   I SER    DATA WRONG    SRC 8C313610
0AEE 0  0BB2              DC    PCKBE                       8C313620
*                                                          8C313630
*                                                          8C313640
*                                                          8C313650
0AEF 0  0000       LWCC   DC                        SE     8C313660
0AF0 0  6B01              STX   3 LD01+1                    8C313670
0AF1 00 C5000000   LD01   LD    L1      LD SPACE           8C313680
0AF3 00 44200AF7          BSI   L LMTRM,Z  BR IF NOT SPACE 8C313690
0AF5 00 4C800AEF          BSC   I LWCC   EXIT          SX  8C313700
*                                                          8C313710
*                                                          8C313720
*                                                          8C313730
*                                                          8C313740
0AF7 0  0000       LMTRM  DC                        SE     8C313750
0AF8 0  F004              EOR   LTERM                       8C313760
0AF9 00 44200AEB          BSI   L LERR,Z  BR IF ERROR   SRC 8C313770
0AFB 00 4C800AF7          BSC   I LMTRM                 SX  8C313780
0AFD 0  FFFF       LTERM  DC    /FFFF   ALL BITS            8C313790
*                                                          8C313800
*                                                          8C313810
*                                                          8C313820
*                                                          8C313830
*                                                          8C313840
*                                                          8C313850
*                                                          8C313860
0AFE 0  0000       LRTF2  DC                        SE     8C313870
0AFF 0  D002              STO   LCHBW   SET CHR / WD        8C313880
0B00 00 44800137          BSI   I PHKYB  GO CONVERT TO HEX SRC 8C313890
0B02 0  0000       LCHBW  DC            CHR / BINARY WORD   8C313900
0B03 0  0437              DC    ZERO    DISPLACEMENT ADDR   8C313910
0B04 00 4C800AFE          BSC   I LRTF2  EXIT          SX   8C313920
*                                                          8C313930
*                                                          8C313940
*                                                          8C313950
*                                                          8C313960
0B06 0  0000       LRTF1  DC                        SE     8C313970
0B07 0  D003              STO   LCHBD   SET CHR / WD        8C313980
0B08 0  4006              BSI   LTRFX   GO TO SETUP AND CK  8C313990
0B09 00 44800136          BSI   I PDKYB  GO CONVERT TO DEC SRC 8C314010
0B0B 0  0000       LCHBD  DC            CHR / BINARY WORD   8C314020
0B0C 0  0437              DC    ZERO    DISPLACEMENT ADDR   8C314030
0B0D 00 4C800B06          BSC   I LRTF1  EXIT          SX   8C314040
*                                                          8C314050
*                                                          8C314060
*                                                          8C314070
*                                                          8C314080
0B0F 0  0000       LTRFX  DC                        SE     8C314090
0B10 0  40CD              BSI   LBGNR   GO SET UP FOR FORM  8C314100
0B11 00 67800AC9          LDX   I3 LWKA  LD CHAR / WC CNT   8C314110
0B13 0  7301              MDX   3 1                         8C314120
0B14 0  40DA              BSI   LWCC    GO TO CHECK FORM    8C314130
0B15 00 4C800B0F          BSC   I LTRFX  EXIT          SX   8C314140
*                                                          8C314150
*                                                          8C314160
*                                                          8C314170
*                                                          8C314180
*                                                          8C314190
*                    PUNCH LEADER                          8C314200
*                                                          8C314210
```

```
0B17 0  0000      PPT    DC    0                              SE   8C314220
0B18 0  6303      PPT1   LDX   3 3          SET IXING              8C314230
0B19 0  C009      PPT1A  LD    WDCT         SET WD CT              8C314240
0B1A 0  D018             STO   CHOUT                               8C314250
0B1B 00 C7000B23         LD    L3 LEADE-1   GET PATTERN            8C314260
0B1D 0  D014             STO   XIOUT        SET                    8C314270
0B1E 0  4008             BSI   PUTAP        PUNCH TAPE        SRC  8C314280
0B1F 0  73FF             MDX   3 -1         DECR IX 3              8C314290
0B20 0  70F8             MDX   PPT1A        LOOP                   8C314300
0B21 00 4C800B17         BSC   I PPT        EXIT             SX   8C314310
 *                                                                8C314320
0B23 0  0019      WDCT   DC    25           WD CT                 8C314330
0B24 0  7F00      LEADE  DC    /7F00        PATTERNS              8C314340
0B25 0  0000             DC    /0000                              8C314350
0B26 0  7F00             DC    /7F00                              8C314360
 *                                                                8C314370
 *                       PUNCH TAPE                               8C314380
 *                                                                8C314390
0B27 0  0000      PUTAP  DC    0                              SE   8C314400
0B28 0  080B      BCK    XIO   SEN55        SENSE                 8C314410
0B29 0  1808             SRA   8                                  8C314420
0B2A 00 4C040B28         BSC   L BCK,E      BRANCH = NOT READY    8C314430
0B2C 0  0809             XIO   PUNK         PUNCH A CHR           8C314440
0B2D 00 74FF0B33         MDX   L CHOUT,-1   DECR WD CT            8C314450
0B2F 0  70F8             MDX   BCK          LOOP                  8C314460
0930 00 4C800B27         BSC   I PUTAP      EXIT             SX   8C314470
 *                                                                8C314480
0B32    0000             BSS   E 0                                8C314490
0932 0  0000      XIOUT  DC    0            OUTPUT AREA           8C314500
0933 0  0000      CHOUT  DC    0            WD CT                 8C314510
0934 0  0000      SEN55  DC    0            SENSE IOCC            8C314520
0935 0  1F01             DC    /1F01                              8C314530
0936 0  0B32      PUNK   DC    XIOUT        PUNCH IOCC            8C314540
0937 0  1900             DC    /1900                              8C314550
0838 0  0B3A      RDSW   DC    DTSW         RD SWS IOCC           8C314560
0839 0  0240             DC    /0240                              8C314570
0B3A 0  0000      DTSW   DC    0            SW STORAGE            8C314580
 *                                                                8C314590
 *                       CONVERT AND PUNCH                        8C314600
 *                                                                8C314610
0B3B 0  6909      HB05   STX   1 EXT+1      SAVE IXING            8C314620
0B3C 0  6A0A             STX   2 EXT1+1                           8C314630
0B3D 0  6B11             STX   3 EXT2+1                           8C314640
0B3E 00 6500FFB0         LDX   L1 -80       SET IXING             8C314650
0B40 00 C5000230         LD    L1 KEYIN+81  GET A WD              8C314660
0B42 00 4C200B56         BSC   L HB05A,Z    BRANCH IF NOT 0       8C314670
0B44 00 65000000  EXT    LDX   L1 0         RESTORE IXING         8C314680
0B46 00 66000000  EXT1   LDX   L2 0                               8C314690
0B48 00 C4000141         LD    L BINRY+3    GET CD NO             8C314700
0B4A 00 F400043D         EOR   L TERM       CK FOR END CD         8C314710
0B4C 00 44180B17         BSI   L PPT,+-     PUNCH TRAILER IF END  8C314720
0B4E 00 67000000  EXT2   LDX   L3 0                               8C314730
0B50 0  C0E9             LD    DTSW         GET SWS               8C314740
0B51 0  1001             SLA   1                                  8C314750
0B52 00 4C1009F9         BSC   L PEDEX,+-   BRANCH IF NOT BOTH    8C314760
0B54 00 4C0009E7         BSC   L PEDEN      PUNCH CARD            8C314770
0B56 0  1810      HB05A  SRA   16           CLEAR WD CT           8C314780
0B57 0  D022             STO   PCAM                               8C314790
0B58 0  7101      HB06   MDX   1 1          DECR IX 1             8C314800
0B59 0  7001             MDX   HB07         CONTINUE              8C314810
0B5A 0  7022             MDX   LB06         PUNCH CARD            8C314820
0B5B 0  6204      HB07   LDX   2 4          SET 4 CHRS            8C314830
0B5C 0  1004      HB10   SLA   4            MOVE CHR              8C314840
0B5D 0  D01E             STO   TEMP1        SAVE                  8C314850
0B5E 00 C5000230         LD    L1 KEYIN+81  GET WD               8C314860
0B60 00 4C180B7D         BSC   L LB06,+-    BRANH IF 0            8C314870
0B62 0  6300      HTDB   LDX   3 0          SET COUNTER           8C314880
0B63 0  4828             BSC   +Z           IS IT NEG            8C314890
```

```
0B64 0  7309             MDX   3 9          YES                   8C314900
0B65 0  1003             SLA   3            REMOVE ZONE           8C314910
0B66 00 4C180B6F         BSC   L HTBZ,+-    BRANCH IF 0           8C314920
0B68 0  7301             MDX   3 1          INCR CTR              8C314930
0B69 00 4C280B6D  HTDB1  BSC   L HTBX,+Z    BRANCH IF NEG        8C314940
0B6B 0  1001             SLA   1            MOVE BIT              8C314950
0B6C 0  70FB             MDX   HTDB1-1      BRANCH               8C314960
0B6D 0  6B0D      HTBX   STX   3 TEMP       SAVE CT               8C314970
0B6E 0  C00C             LD    TEMP         GET CT                8C314980
0B6F 0  E80C      HTBZ   OR    TEMP1        ADD TO SAVED          8C314990
0B70 0  7101             MDX   1 1          DECR IX 1             8C315000
0B71 0  72FF             MDX   2 -1         DECR IX 2             8C315010
0B72 0  70E9             MDX   HB10         LOOP                  8C315020
0B73 00 67800B7A         LDX   I3 PCAM      SET IX 3              8C315030
0B75 00 D7000140         STO   L3 BINRY+2   SAVE                 8C315040
0B77 00 74010B7A         MDX   L PCAM,1     INCR LOC             8C315050
0B79 0  700E             MDX   HB06         LOOP                  8C315060
 *                                                                8C315070
0B7A 0  0000      PCAM   DC    0            STORAGE               8C315080
0B7B 0  0000      TEMP   DC    0                                 8C315090
0B7C 0  0000      TEMP1  DC    0                                 8C315100
 *                                                                8C315110
 *                       PUNCH EDIT                               8C315120
 *                                                                8C315130
0B7D 0  C02C      LB06   LD    HB100        GET E                8C315140
0B7E 00 D400013F         STO   L BINRY+1    SAVE                 8C315150
0B80 00 C4000141         LD    L BINRY+3    GET CD NO            8C315160
0B82 00 F400043D         EOR   L TERM       CK FOR TERM          8C315170
0B84 00 4C180BAD         BSC   L LB08,+-    BRANCH IF TERM       8C315180
0B86 00 C4000142         LD    L BINRY+4    GET NO ENTRIES       8C315190
0B88 0  8022             A     FOUR         ADD 4                8C315200
0B89 0  D004             STO   LB0A+1       SAVE                 8C315210
0B8A 0  1008             SLA   8            MOVE                 8C315220
0B8B 00 D400013E         STO   L BINRY      SAVE                 8C315230
0B8D 00 66000000  LB0A   LDX   L2 0         SET IXING            8C315240
0B8F 00 6500013E  LB09   LDX   L1 BINRY     GET WD               8C315250
0B91 0  C100             LD    1 0          GET WD               8C315260
0B92 0  D09F             STO   XIOUT        SET                  8C315270
0B93 0  C014             LD    ONE          GET 1                8C315280
0B94 00 D400C333         STO   L CHOUT      SET                  8C315290
0B96 0  4090             BSI   PUTAP        PUNCH TAPE       SRC  8C315300
0B97 0  7101             MDX   1 1          INCR IX 1            8C315310
0B98 0  C100      LB07   LD    1 0          GET WD               8C315320
0B99 0  D098             STO   XIOUT        SET                  8C315330
0B9A 0  C00D             LD    ONE          SET WD CT            8C315340
0B9B 0  D097             STO   CHOUT                             8C315350
0B9C 0  408A             BSI   PUTAP        PUNCH TAPE       SRC  8C315360
0B9D 0  C100             LD    1 0          GET WD               8C315370
0B9E 0  1008             SLA   8            SET 2ND HALF          8C315380
0B9F 0  D092             STO   XIOUT        SET                  8C315390
0BA0 0  C007             LD    ONE          GET 1                8C315400
0BA1 0  D091             STO   CHOUT        SET WD CT             8C315410
0BA2 00 44000B27         BSI   L PUTAP      PUNCH TAPE       SRC  8C315420
0BA4 0  7101             MDX   1 1          INCR IX 1            8C315430
0BA5 0  72FF             MDX   2 -1         DECR IX 2            8C315440
0BA6 0  70F1             MDX   LB07         LOOP                 8C315450
0BA7 0  709C             MDX   EXT          EXIT                 8C315460
 *                                                                8C315470
0BA8 0  0001      ONE    DC    1            CONSTANTS            8C315480
0BA9 0  8000      K8000  DC    /8000                             8C315482
0BAA 0  8100      HB100  DC    /8.00                             8C315490
0BAB 0  0004      FOUR   DC    4                                 8C315500
0BAC 0  0300      TREE   DC    /0300                             8C315510
 *                                                                8C315520
0BAD 0  C0FE      LB08   LD    TREE         GET 0300             8C315530
0BAE 00 D400013E         STO   L BINRY      SET                  8C315540
0BB0 0  6203             LDX   2 3          SET IX 2             8C315550
0BB1 0  700D             MDX   LB09         BRANCH               8C315560
```

RK EDIT CONTROL

```
0BB2   0012        PCKBE EBC   .E003 CNTRL-ILLEGAL.                8C315570
0BBB   0006              EBC   . ENTRY.                            8C315580
0BBE O FFFF        PCKX4 DC    /FFFF                               8C315590
0BBF   0012        PECX9 EBC   .E005 CNTRL-1442 ER.                8C315600
0BC8 O FFFF        PECXD DC    /FFFF                               8C315620
0BC9   0012        PECXF EBC   .SSA001 CNTRL-EDIT .                8C315630
0BD2   0007              EBC   .CD LIST.                           8C315640
0BD6 O FFFF              DC    /FFFF                               8C315650
0BD7   0012        SE002 EBC   .E002 CNTRL-ENTRY T.                8C315660
0BE0   0008              EBC   .OO LARGE.                          8C315670
0BE4 O FFFF              DC    /FFFF                               8C315680
0BE5   0012        SM2   EBC   .C000 CNTRL-ENTER 2.                8C315690
0BEE   0012              EBC   . DIGIT PID TO BE E.                8C315700
0BF7   0005              EBC   .DITED.                             8C315710
0BFA O FFFF              DC    /FFFF                               8C315720
0BFB   000F        SM433 EBC   .A002 END OF PRG.                   8C315730
0C03 O FFFF              DC    /FFFF                               8C315740
0C04   0012        LEM01 EBC   .E004 CNTRL-FORMAT .                8C315750
0C0D   0002              EBC   .ER.                                8C315760
0C0E O FFFF              DC    /FFFF                               8C315773
0C0F O 0000        HLTE  DC    0                          SRC      8C315772
0C10 O 3005        WAIT5 WAIT  5         RELOAD REQUIRED           8C315774
0C11 00 4C800C0F         BSC I HLTE                       SX       8C315776
0C14   058A              END   STARI                      8C31577  8C315786
```

8K EDIT CONTROL

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BCK	0828	0B2A,0B2F
BGNR	0438	
BINRY	013E	05A3,07CC,07DA,07E5,07EF,0863,0B48,0B75,0B7E,0B80, 0B86,0B8B,0B8F,0BAE
BSADR	0601	05C0
BSAD1	05BB	0597,05B7
BWC	013D	085F,0861,088D,08E6
CHOUT	0B33	0B1A,0B2D,0B94,0B98,0BA1
CKYN	012D	
CKYNE	07A4	012D,07BC,07BE
CKYN0	07BE	07A8,07AD
CKYN1	07BC	07B2,07B7
CODE	0566	
CP1D	0829	0804,0810
DKYB	0842	0136,0844
DONT	0AD8	0AC6
DONT1	0AD7	0ADC
DTSW	0B3A	0943,094D,0980,09E0,0B38,0B50
END	05E1	05FF
END0	0138	
END1	05CD	013A,0594,05DD
ERR	0439	
ERR04	060D	05A7
EXIT	0755	
EXT	0B44	0B3B,0BA7
EXT1	0B46	0B3C
EXT2	0B4E	0B3D
FOUR	0BAB	0B88
HB05	0B3B	09E2,09E5
HB05A	0B56	0B42
HB06	0B58	0B79
HB07	0B5B	0B59
HB10	0B5C	0B72
HKYB	084B	0137,0845,0855,0899,08A3
HLT	0585	
HLTE	0C0F	0585,0C11
HTBX	0B6D	0B69
HTBZ	0B6F	0B66
HTOB	0B62	
HTOB1	0B69	0B6C
HB100	0BAA	0B7D
KAL	0A72	06B1
KAQ	0A4C	0615,0659
KBKSP	072C	0725
KC	0A6B	
KCHK	064B	0629
KCMA	0A79	06F8
KCOMA	072A	070C
KCR	0AA3	0620,064B
KDEC	06DD	0686
KDEC1	06DE	06DC,06E1
KEBC2	0625	0648
KEBC3	062C	064A
KEBC4	062F	0638
KEBC6	0649	063B
KECAD	0A69	0692,06E0
KECGD	0A46	06DB,06DD,06E0
KECOD	0A5E	0684,06DD,0908,09D0,0A18
KECPD	0A5B	0699,06D3
KENDK	0A71	0733
KERR	0757	06A2,06C2,0700,0730,073A,074E
KERR1	075F	0767
KERSE	0A70	0713
KEY	012C	059F,05E1,07F9,0939,09A8,09AE,09FC,0A03,0A31
KEYE	0611	012C,0618,061C,064F,065C,065E,0661

```
KEYFM   0753    0665,068A
KEYIN   01DF    066F,07A5,07AA,07AF,07B4,08A9,093F,0960,0968,09BC,
                09C4,09D2,09E7,09EA,0A0F,0A16,0A33,0A54,0B40,0B5E
KEYND   0754    0669,0739
KEYOG   066B    076C
KEYO    0671    06D0,06DF,0710,0719,071C,0728,0735,0760,076A
KEY1    0675    067D
KEY2    0677    067F
KEY3    0690    067A
KEY96   0653    0612,0755
KEY97   0655    0613
KEY98   0657    0614
KEY99   065B    0617
KFELD   0AA4    0758
KFMO    06A7    068E,069B
KFMO1   06A8    06AE
KFMO2   06B0    06B6
KFMS    0682
KFMS1   0683    0689
KFM2    0690
KFM21   0691    0697
KFRM    0660    0651
KHEX    06E0    0694
KINO    083B    0135,0840
KINI    082D    0134,0836
KIWC    01DE    066D,06F1,06FC,0706,0717,0722,0737,073C,073E,0742,
                074B,075C,0765,0768,0832,083C,0A11,0A27,0A29,0A2F,
                0ADF
KL      0A4B    06B8
KLRT    0A7F    06C7
KMDX    06D2    06AB
KMPX    06DB    06B3,06D5
KMSG    0A46    061A,0625,062F,0646,0A47
KN      0A57    06A9,06DB
KNBY    076F    0673,0786,078F,0795
KNBYO   0775    0780
KNBY1   0777    077D
KNBY4   0787    0781
KNBY5   078B    0770,077A
KNEG    076E    074F,0762
KDNE    0A56    0627,063C,068C,06C9,06EA,0709
KOUT    0A47    061E,0640,0644,06CB,06EC
KPCD    0A52    0675
KPNE    06C9    06A6
KPRT    0A50    0793,079D
KRDY    CA4E    078D,0796,0A50
KRED    0A54    0671,0680,0683,0683,0691,0691,0698,0698,0732,0732
KRENT   0A6F    072E
KSNS    0A44    0677,0777
KSPC    06F6    06BA
KSPCA   073E    0745
KSPCE   074F    0748,074D
KSPC2   0709    0704
KSPC5   0712    06FA
KSPC6   0725    071F
KSPC9   072D    0715
KSTO    06E2    06DE,06E6,06F4
KTALT   0A9D
KTGLT   0A7A    062C,06E8
KTILT   0A93    0586,0A1F
KTIME   0791    0773,077E
KTOLT   0A92
KTPLT   0A8F    06A4
KTYP    0792    0584,0642,064D,06CE,06EF,070E,0727,075A,07A0
KTYPS   0584
KTYP1   0793    07A3
KTYP5   0796    079C
KTYP6   079D    0799
```

```
KY      0A58
KOOFF   0610    05A5
K0002   07E3    05DA,06FE,07C6
K0003   082C    081F
K0004   0A4A
K1048   0602    058C
K8000   0BA9    06A0,06C0
K8120   0ABC
LBGNR   0ADE    0438,0AE9,0B10
LBOA    0B8D    0B89
LB06    0B7D    0B5A,0B60
LB07    0896    0BA6
LB08    0BAD    0B84
LB09    0B8F    0BB1
LCHBD   0B0B    0B07
LCHBW   0B02    0AFF
LDDIT   0ACA    0751,0ACE,0AD7,0AD9
LDO1    0AF1    0AF0
LEADE   0B24    0B1B
LEMO1   0C04
LERR    CAEB    0439,0AF9
LGROP   043F    0ACC
LMTRM   0AF7    0438,0AF3,0AFB
LRAIT   0AC6    0AD5
LRTF1   0B06    0AC7,0B0D
LRTF2   0AFE    0AC8,0B04
LTERM   0AFD    0AF8
LTRFX   0B0F    043C,0808,0B15
LWC     043E    0AE2,0AE4,0AE7
LWCC    0AEF    043A,0AF5,0B14
LWCLD   0AD3    0AD2
LWKA    0AC9    0AD1,0B11
MTRM    043B
NO      07C2    07B1
NDEN    082A    0805,080E,0814,0820
NO1     07C3    07B6
NTPT    0952    094A,0964
ONE     0BA8    0B93,0B9A,0BA0
PBIHX   09C6    0974,097C,0997,099D,099F,09DD
PBIX2   0A6D    096E
PBIY1   09D9    09C8
PBIY2   09DB    09C9
PBIY3   09CB    09D7
PCAM    087A    0857,0B73,0B77
PCKB    0900    086E,0903,0926,092A
PCKBA   092C    0902,090A,0914,0918
PCKBB   092D    0924,0925
PCKBE   0BB2    07BB,08F1,0921,0AEE
PCKBX   0928    0901,0916,091E
PCKB1   0906    0905,090E
PCKB3   0922    090B
PCKB4   091F    0912,091A
PCKX1   092E    08B3,08D2,0911
PCKX2   092F    0915
PCKX3   0930    0919
PCKX4   0BBE    091C
PDKWA   08F2    08B1,08C7,08C8,08DE,08E4,08E9,08EB
PDKX1   08F7    0848,08CF
PDKX2   08F6    08C1
PDKX3   08FF    08D8
PDKX4   08F4    08EC
PDKYA   08EB    08DB
PDKYB   0136    0B09
PDKYE   08EF    08B5,08D4
PDKYF   08DC    08ED
PDKYH   08CE    08C4
PDKYJ   08C5    08DD
PDKY1   08B0    0878
```

8K EDIT CONTROL

```
PDKY2    0889    0888
PDKY3    08C0    08CC
PDKY6    08D1    08CD
PDKY7    C8E0    08D6
PDKY8    08E9    08D9,08E1
PDKY9    08E5    08EA
PECOR    0931    C9F4,0993
PECOS    0991    0934
PECXC    098A    0984,09EF
PECXD    08C8    0976,097A
PECXE    0989    099C,09A1
PECXF    08C9    0935
PECX1    0986    0932,0992
PECX3    0988    0996
PECX4    098C    0955
PECX5    098E    0952,0956,0996,09FC,09F1,09F8
PECX6    09C0    0950,098A,0932,09F9,0A02
PECX7    09C2    0985
PECX8    09C4    09F0
PECX9    0BBF    09AA,09B0,09FE,0A05
PECYA    0968    0963
PECYB    0995    0978
PECYC    0986    0988
PECYD    099E    09A3
PECYE    0966    0950
PECYF    0936
PECY1    098B    0936,0982
PECY2    098D    0937
PECY3    098F    093B
PECY4    0956    0958
PECY5    0960    0963
PECY6    09AB    0953
PECY7    0941    09AD,09B4
PECY8    09AE    095B
PED      09DF    097D,09A4,09F9
PEDEN    09E7    0854
PEDEX    09F9    0852
PEDX1    0A09    09E9
PEDY1    09FB    09ED
PEDY2    09F1    09F3
PEDY3    0A02    09F6
PEDY4    09EC    0A01,0A08
PHDSW    08AF    0946,084E,0876
PHKX1    08A6    0843,084C,08A2
PHKX2    08A8    0859,0867,086B,0879,0882,088F,08B2,08BD,08D1,08D7,
                 090F
PHKX3    08A9    085C
PHKX4    08AA    085D,0869,0891,0892,0893
PHKX5    08AB    0890,08B7
PHKX6    08AC    0896
PHKX7    08AD    084D
PHKX8    08AE    084F
PHKYB    0137    0B00
PHKYC    0870    0850
PHKYD    0850    084A
PHKYF    088B    08DF
PHKYH    088F    08E8
PHKYS    08A1    0851
PHKY1    0871    0865,088B,08DC
PHKY2    086D    0875
PHKY3    087C    C866,0880
PHKY4    .0884   0889
PHKY5    0861    0898
PHKY6    089B    0852
PHKY7    089D    0853
PHKY8    089F    0854
PHKY9    0888    0886,0887
PPECD    0A0A    097E,09A5,0A3C
```

8K EDIT CONTROL

```
PPEX2    0A41    0A2B
PPEX3    0A42    0A0E,0A35
PPEY1    0A1F    0A1B
PPEY2    0A16    0A1E
PPEY3    0A3E    0A24,0A2C
PPEY4    0A15    0A3F
PPEY5    0A36    0A0B
PPEY6    0A38    0A0C
PPEY7    0A3A    0A0D
PPEY8    0A2E    0A40
PPT      0B17    094B,0B21,084C
PPT1     0B18
PPT1A    0B19    0B20
PT       094B    0945,0948,09A7
PUNK     0B36    0B2C
PUTAP    0B27    081E,0B30,0896,089C,0BA2
RDSK     0ABE    0138,05AA,0AC3
RDSK1    0AC3    0AC5
RDSW     0B38    0941
RDSX0    0AC5    0ABF
RLFT     05C6    05C3
RLFT1    05D2    05D1
RLFT2    05DF    05DC
RLTBL    0603    05C1,05CF,05D8
SCH      0131
SCHE     07E4    0131,07F1
SCHER    07EB    07E8
SCH1     07EF    07E9,07FA,07EC
SECB     0828    0803,0812
SECSE    07FF    0133,0800,0823,0825
SECSU    0133
SEIB     0442    05F8,082B,093D
SEN55    0B34    0928
SER      0132    0600,07B9,07D3,08EF,091F,0AEC
SERE     07F5    0132,07F6
SER1     07FB    07F8
SE002    0BD7    060F,07D5
SE1      0803
SE2      080C    0809
SE3      0817    081C
SIA      07E0
SIL      012F
SILE     07CB    012F,07D6
SILER    07D3    07D0,07DE,07EE
SILSE    07D9    0130,07E0
SILSW    0130
SIL1     07D6    07D1,07D2
SIWB     0827    0802,C80A
SKINA    0832    0835
SKINB    083C    083F
SKINO    0135
SKIN1    0134    066B
SKI1     0C17    012C,05AF,05EE
SKI2     0C18    012C
SKI3     0C19    012C
SKI4     0C1A    05CA
SM2      0BE5    C5A1
SM33     0BF8    05F3
SRST     0588    059A,05AC
SRTRY    0441    07C7,07FD
SSEUR    07C4
SSUEE    07C4    012F,07C5,07C9,07CB
SSUER    012E    059D
STARI    058A    0C13
START    0590    05BB,05E6
STBF     0440    0595,05E7,05F7,0807,081D,0821
STBF1    0B2B    05F9,0806
STTR     05FB    05FE
```

8K EDIT CONTROL

```
STTRM     05E7      05D6
SVIX3     058C      0593,0582,05C5
S00F0     07E2      07DD
S000F     07F3      07EB
S0008     07F4      07E7
S1700     07D8      07CF
S2        013A
S2E       05AA      05BA,05CC
TEMP      0B7B      0B6D,0B6E
TEMP1     0B7C      0B5D,0B6F
TERM      043D      05C8,05D4,05F1,0830,084A,0B82
TREE      0BAC      0BAD
TRFX      043C
WAIT1     079B      3001
WAIT2     0785      3002
WAIT3     09AC      3003
WAIT4     0993      3004
WAIT5     0C10      3005
WAIT6     0400      3006
WAIT7     0A07      3007
WAIT8     05E5      3008
WCC       043A
WOCT      0B23      0B19
XIOUT     0B32      0B1D,0B36,0392,0B99,0B9+
XPID      0600      05A9,05B1
YES       07C0      07A7
YES1      07C1      07AC
ZERO      0437      0B03,0B0C
```

```
0000                    ORG      *+3095                              C4010001
012C          KEY    EQU    300                                      C4010002
012D          CKYN   EQU    KEY+1                                    C4010003
012E          SSUER  EQU    CKYN+1                                   C4010004
012F          SIL    EQU    SSUER+1                                  C4010005
0130          SILSW  EQU    SIL+1                                    C4010006
0131          SCH    EQU    SILSW+1                                  C4010007
0132          SER    EQU    SCH+1                                    C4010008
0133          SECSU  EQU    SER+1                                    C4010009
0134          SKIN1  EQU    SECSU+1                                  C4010010
0135          SKINO  EQU    SKIN1+1                                  C4010011
0136          PDKYB  EQU    SKINO+1                                  C4010012
0137          PHKYB  EQU    PDKYB+1                                  C4010013
0138          ENDO   EQU    PHKYB+1                                  C4010014
013A          S2     EQU    ENDO+2                                   C4010015
013E          BINRY  EQU    S2+4                                     C4010016
01DF          KEYIN  EQU    BINRY+161                                C4010017
0437          ZERO   EQU    KEYIN+600                                C4010018
0438          BGNR   EQU    ZERO+1                                   C4010019
0439          ERR    EQU    BGNR+1                                   C4010020
043A          WCC    EQU    ERR+1                                    C4010021
043B          MTRM   EQU    WCC+1                                    C4010022
043C          TRFX   EQU    MTRM+1                                   C4010023
043D          TERM   EQU    TRFX+1                                   C4010024
043E          LWC    EQU    TERM+1                                   C4010025
043F          LGROP  EQU    LWC+1                                    C4010026
0440          STBF   EQU    LGROP+1                                  C4010027
0441          SRTRY  EQU    STBF+1                                   C4010028
0C17 0 0001   SKI1   DC     /0001     PID                           C4010029
0C18 0 0000   SKI2   DC     /0000     CD NUMBER                     C4010030
0C19 0 0002   SKI3   DC     /0002     NUMBER OF ENTRIES             C4010031
0C1A 00 44B0012E SKI4 BSI  I  SSUER   SET ERROR RETURN       SRC    C4010032
0C1C 00 4480012C      BSI  I  KEY     ENTER CONS IL          SRC    C4010033
0C1E 1 0C70           DC     SM1       MSG ADRS                     C4010034
0C1F 0 8120           DC     /8120     KYBD-FRM 1-2 DIGITS          C4010035
                *                                                    C4010036
0C20 00 4480012F      BSI  I  SIL     CK LVL                 SRC    C4010037
0C22 01 D4000D34      STO  L  SWB1    STORE                         C4010038
                *                                                    C4010039
0C24 00 4480012E      BSI  I  SSUER   SET ERROR RETURN       SRC    C4010040
0C26 00 4480012C      BSI  I  KEY     ENTER CONS ILSW        SRC    C4010041
0C28 1 0C95           DC     SM2       MSG ADRS                     C4010042
0C29 0 8120           DC     /8120                                  C4010043
                *                                                    C4010044
0C2A 00 4480012E      BSI  I  SILSW   CK ILSW                SRC    C4010045
0C2C 01 D4000D35      STO  L  SWB2    STORE                         C4010046
                *                                                    C4010047
0C2E 01 C4000D3A      LD   L  S000F   SET CH = F                    C4010048
0C30 01 D4000D36      STO  L  SWB3    STORE                         C4010049
                *                                                    C4010050
                *                                                    C4010051
0C32 00 4480012E      BSI  I  SSUER   SET ERROR RETURN       SRC    C4010052
0C34 00 4480012C      BSI  I  KEY     ENTER OTPT DV IL       SRC    C4010053
0C36 1 0CB9           DC     SM3       MSG ADRS                     C4010054
0C37 0 8120           DC     /8120     KYBD-FORM 1-2 DIGITS         C4010055
                *                                                    C4010056
0C38 00 4480012F      BSI  I  SIL     CK IL                  SRC    C4010057
0C3A 01 D4000D37      STO  L  SWB4    STORE                         C4010058
                *                                                    C4010059
0C3C 00 4480012E      BSI  I  SSUER   SET ERROR RETURN       SRC    C4010060
0C3E 00 4480012C      BSI  I  KEY     ENTER OTPD DV ILSW            C4010061
0C40 1 0CE1           DC     SM4       MSG ADRS                     C4010062
0C41 0 8120           DC     /8120                                  C4010063
                *                                                    C4010064
0C42 00 4480012D      BSI  I  SILSW   CK ILSW                SRC    C4010065
0C44 01 D4000D38      STO  L  SWB5    STORE                         C4010066
                *                                                    C4010067
0C46 00 4480012E      BSI  I  SSUER   SET ERROR RETURN       SRC    C4010068
```

```
0C48 00 4480012C      BSI  I  KEY     ENTER OTPT DV CH       SRC    C4010069
0C4A 1 0006           DC     SM5       MSG ADRS                     C4010070
0C4B 0 8010           DC     /8010                                  C4010071
0C4C 00 C40001DF      LD   L  KEYIN                                 C4010072
0C4E 01 4C280C6D      BSC  L  SK1,+2                                C4010073
0C50 00 44800136      BSI  I  PDKYB                                 C4010074
0C52 0 0001           DC     1                                      C4010075
0C53 0 0437           DC     ZERO                                   C4010076
                *                                                    C4010077
0C54 00 44800131      BSI  I  SCH     CK CH                  SRC    C4010078
0C56 01 D4000D39 SK2  STO  L  SWB6                                  C4010079
                *                                                    C4010080
                *                                                    C4010081
0C58 01 65000D34      LDX  L1 SWB1                                  C4010082
0C5A 0 C100           LD   1  0         BUILD CONS DDEF             C4010083
0C5B 0 F101           EOR  1  1                                     C4010084
0C5C 0 F102           EOR  1  2                                     C4010085
0C5D 0 D100           STO  1  0                                     C4010086
                *                                                    C4010087
0C5E 0 C103           LD   1  3         BUILD OTPUT DEV DDEF        C4010088
0C5F 0 F104           EOR  1  4                                     C4010089
0C60 0 F105           EOR  1  5                                     C4010090
0C61 0 D101           STO  1  1                                     C4010091
                *                                                    C4010092
0C62 01 66800C18      LDX  I2 SKI2    SET IXING                    C4010093
0C64 01 65800C17      LDX  I1 SKI1                                  C4010094
0C66 01 67800C19      LDX  I3 SKI3                                  C4010095
                *                                                    C4010096
0C68 00 44800133      BSI  I  SECSU   GO SET CD              SRC    C4010097
0C6A 1 0034           DC     SWB1      ADRS OF ENTRYS               C4010098
0C6B 01 4C00013A      BSC  L  S2      GET NEXT SKELTON             C4010099
0C6D 01 C400003A SK1  LD   L  S000F                                 C4010100
0C6F 0 70E6           MDX     SK2                                   C4010101
                *                                                    C4010102
0C70    0012  SM1     EBC     .C001 PID 01-CD 00.                   C4010103
0C79    0012          EBC     . ENTER 2 DIGIT DE.                   C4010104
0C82    0012          EBC     .CIMAL INTRPT LVL F.                  C4010105
0C8B    0C11          EBC     .OR CONSOLE INTRPT.                   C4010106
0C94 0 FFFF           DC     /FFFF                                  C4010107
                *                                                    C4010108
0C95    0012  SM2     EBC     .C002 PID 01-CD 00.                   C4010109
0C9E    0012          EBC     . ENTER 2 DIGIT DE.                   C4010110
0CA7    0012          EBC     .CIMAL ILSW BIT FUR.                  C4010111
0CB0    000F          EBC     . CONSOLE INTRPT.                     C4010112
0CB8 0 FFFF           DC     /FFFF                                  C4010113
                *                                                    C4010114
0CB9    0012  SM3     EBC     .C001 PID 01-CD 00.                   C4010115
0CC2    0012          EBC     . ENTER 2 DIGIT DE.                   C4010116
0CCB    0012          EBC     .CIMAL INTRPT LVL F.                  C4010117
0CD4    0012          EBC     .OR DESIRED OUTPUT .                  C4010118
0CDD    0006          EBC     .DEVICE.                              C4010119
0CE0 0 FFFF           DC     /FFFF                                  C4010120
                *                                                    C4010121
0CE1    0012  SM4     EBC     .C002 PID 01-CD 00.                   C4010122
0CEA    0012          EBC     . ENTER 2 DIGIT DE.                   C4010123
0CF3    0012          EBC     .CIMAL ILSW BIT FOR.                  C4010124
0CFC    0012          EBC     . DESIRED OUTPUT DV.                  C4010125
0D05 0 FFFF           DC     /FFFF                                  C4010126
                *                                                    C4010127
0D06    0012  SM5     EBC     .C003 PID 01-CD 00.                   C4010128
0D0F    0012          EBC     . ENTER 1 DIGIT DE.                   C4010129
0D18    0012          EBC     .CIMAL CH FOR DESIR.                  C4010130
0D21    0012          EBC     .ED OPTPT DV-IF 105.                  C4010131
0D2A    0011          EBC     .3 OR 1816-ENTER F.                   C4010132
0D33 0 FFFF           DC     /FFFF                                  C4010133
0D34 0 0000   SWB1    DC     0                                      C4010134
0D35 0 0000   SWB2    DC     0                                      C4010135
0D36 0 0000   SWB3    DC     0                                      C4010136
```

```
0D37 0  0000        SWB4  DC      0              C4010137
0D38 0  0000        SWB5  DC      0              C4010138
0D39 0  0000        SWB6  DC      0              C4010139
0D3A 0  000F        S000F DC      /000F          C4010140
0D3B 00 4C000138    END1  BSC  L  END0           C4010141
0D3E    0D3B              END     END1           C401014 C4010151
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17
CKYN	012D	0C17
END0	0138	0C17,0D38
END1	0D3B	0D3D
ERR	0439	0C17
KEY	012C	0C17,0C1C,0C26,0C34,0C3E,0C48
KEYIN	01DF	0C17,0C4C
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17,0C50
PHKYB	0137	0C17
SCH	0131	0C17,0C54
SECSJ	0133	0C17,0C68
SER	0132	0C17
SIL	012F	0C17,0C20,0C38
SILSW	0130	0C17,0C2A,0C42
SKIN0	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0C6+
SKI2	0C18	0C62
SKI3	0C19	0C66
SKI4	0C1A	
SK1	0C6D	0C4E
SK2	0C56	0C6F
SM1	0C70	0C1E
SM2	0C95	0C28
SM3	0CB9	0C36
SM4	0CE1	0C40
SM5	0D06	0C4A
SRTRY	0441	
SSUER	012E	0C17,0C1A,0C24,0C32,0C3C,0C46
STBF	0440	0C17
SWB1	0D34	0C22,0C58,0C6A
SWB2	0D35	0C2C
SWB3	0D36	0C30
SWB4	0D37	0C3A
SWB5	0D38	0C44
SWB6	0D39	0C56
S000F	0D3A	0C2E,0C6D
S2	013A	0C17,0C6B
TERM	043D	0C17
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17,0C53

```
0000                    ORG      *+3095
012C     KEY    EQU     300                              C4011001
012D     CKYN   EQU     KEY+1                             C4011002
012E     SSUER  EQU     CKYN+1                            C4011003
012F     SIL    EQU     SSUER+1                           C4011004
0130     SILSW  EQU     SIL+1                             C4011005
0131     SCH    EQU     SILSW+1                           C4011006
0132     SER    EQU     SCH+1                             C4011007
0133     SECSU  EQU     SER+1                             C4011008
0134     SKIN1  EQU     SECSU+1                           C4011009
0135     SKINO  EQU     SKIN1+1                           C4011010
0136     PCKYB  EQU     SKINO+1                           C4011011
0137     PHKYB  EQU     PDKYB+1                           C4011012
0138     ENDO   EQU     PHKYB+1                           C4011013
013A     S2     EQU     ENDO+2                            C4011014
013E     BINRY  EQU     S2+4                              C4011015
01DF     KEYIN  EQU     BINRY+161                         C4011016
0437     ZERO   EQU     KEYIN+600                         C4011017
0438     BGNR   EQU     ZERO+1                            C4011018
0439     ERR    EQU     BGNR+1                            C4011019
043A     WCC    EQU     ERR+1                             C4011020
043B     MTRM   EQU     WCC+1                             C4011021
043C     TRFX   EQU     MTRM+1                            C4011022
043D     TERM   EQU     TRFX+1                            C4011023
043E     LWC    EQU     TERM+1                            C4011024
043F     LGROP  EQU     LWC+1                             C4011025
0440     STBF   EQU     LGROP+1                           C4011026
0441     SRTRY  EQU     STBF+1                            C4011027
0C17 0 0001     SKI1   DC      /0001    PID               C4011028
0C18 0 0001     SKI2   DC      /0001    CD NO             C4011029
0C19 0 0000     SKI3   DC      /0000    NO ENTRIES        C4011030
0C1A 00 448012E SKI4   BSI  I  SSUER   SET ERROR RETURN  SRC  C4011031
0C1C 0 611E            LDX  1  30                         C4011032
0C1D 00 C400043D       LD   L  TERM    CLEAR BINRY AREA  C4011033
0C1F 00 D500013D SK0   STO  L1 BINRY-1                    C4011034
0C21 01 D5000CD2       STO  L1 SWB1-1                     C4011035
0C23 0 71FF            MDX  1  -1                         C4011036
0C24 0 70FA            MDX     SK0                        C4011037
0C25 0 1010            SLA     16                         C4011038
0C26 0 D0F2            STO     SKI3    CLEAR WD CT        C4011039
0C27 00 448012C       BSI  I  KEY     ENTER INTR LVL     SRC  C4011040
0C29 1 0CA0            DC      SM2                        C4011041
0C2A 0 8120            DC      /8120                      C4011042
0C2B 00 C400013D      LD   L  BINRY-1  GET WD CT         C4011043
0C2D 0 D0EB           STO     SKI3     SET               C4011044
0C2E 01 66000CD3      LDX  L2 SWB1     SET IXING         C4011045
0C30 01 6500013E      LDX  L1 BINRY                      C4011046
0C32 00 C5000000 SKI6 LD   L1 0        GET A WD          C4011047
0C34 00 448012F       BSI  I  SIL      CK IL             SRC  C4011048
0C36 0 1808           SRA     8                          C4011049
0C37 0 D200           STO     2 0      SAVE              C4011051
0C38 0 C101           LD      1 1      GET WD            C4011052
0C39 00 D400013E      STO  L  BINRY    SET AS 1ST        C4011053
0C3B 0 7201           MDX     2 1      INCR IX 2         C4011054
0C3C 0 7101     SKI5  MDX     1 1      INCR IX 1         C4011055
0C3D 00 74FF013D      MDX  L  BINRY-1,-1 DECR WD CT      C4011056
0C3F 0 70F2           MDX     SKI6     LOOP              C4011057
0C40 01 C4000C19 SKI7 LD   L  SKI3     GET NO ENTRIES    C4011058
0C42 01 84000CD2      CMP  L  SOOGD    CK FOR MAX        C4011059
0C44 0 7026           MDX     SKER     ERROR             C4011060
0C45 0 1000           NOP                                C4011061
0C46 01 66000CD3      LDX  L2 SWB1     SET IXING         C4011063
0C48 0 6A16           STX     2 TEMP   *                 C4011064
0C49 01 74010C5F      MDX  L  TEMP,1   *                 C4011065
0C4B 01 65800C5F SK1  LDX  I1 TEMP     *                 C4011066
0C4D 0 C200     SK2   LD      2 0      GET ENTRY         C4011067
                                                         C4011068
```

```
0C4E 01 4C280C60       BSC  L  OUT,+Z   BRANCH IF TERM   C4011069
0C50 0 C100            LD      1 0      GET ENTRY         C4011070
0C51 01 4C260C58       BSC  L  SK3,+Z   BRANCH IF TERM   C4011071
0C53 0 F200            EOR     2 0      CK FOR DUPLICATE  C4011072
0C54 01 4C180C5C       BSC  L  SKER2,+- BRANCH IF ERROR  C4011073
0C56 0 7101            MDX     1 1      INCR IX 1         C4011074
0C57 0 70F5            MDX     SK2      LOOP              C4011075
0C58 0 7201     SK3   MDX     2 1      INCR IX 2         C4011076
0C59 01 74010C5F      MDX  L  TEMP,1   *                 C4011077
0C5B 0 70EF           MDX     SK1      LOOP              C4011078
0C5C 00 448C0132 SKER2 BSI I  SER      DUPLICATE LVLS    SRC  C4011080
0C5E 1 0C85            DC      SE001                     C4011081
0C5F 0 0000     TEMP  DC      0                          C4011083
0C60 01 66800C18 OUT  LDX  I2 SKI2     SET IXING         C4011084
0C62 01 6580GC17      LDX  I1 SKI1                       C4011085
0C64 01 6760CC19      LDX  I3 SKI3                       C4011086
0C66 00 44800133      BSI  I  SECSU    GO SET CARD       SRC  C4011088
0C68 1 0CD3           DC      SWB1                       C4011089
0C69 00 4C00013A      BSC  L  S2       EXIT              C4011090
0C6B 00 44800132 SKER BSI I  SER      GO PRINT ERROR    SRC  C4011091
0C6D 1 0C6E           DC      SE000    ADRS OF MSG        C4011092
0C6E     0012   SE000 EBC      .E010 PID 01-CD 00.       C4011095
0C77     0012          EBC      . IMPROPER NUMBER .      C4011096
0C80     0007          EBC      . OF WDS.                C4011097
0C84 0 FFFF            DC      /FFFF                     C4011098
0C85     0012   SE001 EBC      .E006 PID 01-CD 01.       C4011100
0C8E     0012          EBC      . 2 OR MORE ENTRIE.      C4011101
0C97     000F          EBC      .S ARE IDENTICAL.        C4011102
0C9F 0 FFFF            DC      /FFFF                     C4011103
0CA0     0012   SM2   EBC      .C001 PID 01-CD 00.       C4011105
0CA9     0012          EBC      . ENTER A 2 DIGIT .      C4011106
0CB2     0012          EBC      .DECIMAL NUMBER FOR.     C4011107
0CBB     0012          EBC      . EACH INTERRUPT LE.     C4011108
0CC4     0012          EBC      .VEL TO BE RUN, 1-1.     C4011109
0CCD     0012          EBC      .2 LINES.                C4011110
0CD1 0 FFFF            DC      /FFFF                     C4011111
0CD2 0 000C     SOOGD DC      /000C                     C4011113
0CD3 0 0000     SWB1  DC      0        ENTRY STORAGE     C4011114
0CD4     001D          BSS     29                        C4011115
0CF1 00 4C000138 END1 BSC  L  ENDO                      C4011116
0CF4     0CF1          END     END1         C401111 C4011127
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17,0C1F,0C2B,0C30,0C39,0C3D
CKYN	012D	0C17
ENDO	0138	0C17,0CF1
END1	0CF1	0CF3
ERR	0439	0C17
KEY	012C	0C17,0C27
KEYIN	01DF	0C17
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
OUT	0C60	0C4E
PDKYB	0136	0C17
PHKYB	0137	0C17
SCH	0131	0C17
SECSU	0133	0C17,0C66
SER	0132	0C17,0C5C,0C6B
SE000	0C6E	0C6D
SE001	0C85	0C5E
SIL	012F	0C17,0C34
SILSW	0130	0C17
SKER	0C68	0C44
SKER2	0C5C	0C54
SKINO	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0C62
SKI2	0C18	0C60
SKI3	0C19	0C26,0C2D,0C40,0C64
SKI4	0C1A	
SKI5	0C3C	
SKI6	0C32	0C3F
SKI7	0C40	
SK0	0C1F	0C24
SK1	0C4B	0C5B
SK2	0C4D	0C57
SK3	0C58	0C51
SM2	0CA0	0C29
SRTRY	0441	
SSUER	012E	0C17,0C1A
STBF	0440	0C17
SWB1	0CD3	0C21,0C2E,0C46,0C68
S000D	0CD2	0C42
S2	013A	0C17,0C69
TEMP	0C5F	0C48,0C49,0C48,0C59
TERM	043D	0C17,0C1D
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17

```
0000                     URG      *+3095                                C4012001
012C        KEY     EQU      300                                        C4012002
012D        CKYN    EQU      KEY+1                                      C4012003
012E        SSUER   EQU      CKYN+1                                     C4012004
012F        SIL     EQU      SSUER+1                                    C4012005
0130        SILSW   EQU      SIL+1                                      C4012006
0131        SCH     EQU      SILSW+1                                    C4012007
0132        SER     EQU      SCH+1                                      C4012008
0133        SECSU   EQU      SER+1                                      C4012009
0134        SKIN1   EQU      SECSU+1                                    C4012010
0135        SKINO   EQU      SKIN1+1                                    C4012011
0136        PDKYB   EQU      SKINO+1                                    C4012012
0137        PHKYB   EQU      PDKYB+1                                    C4012013
0138        ENDO    EQU      PHKYB+1                                    C4012014
013A        S2      EQU      ENDO+2                                     C4012015
013E        BINRY   EQU      S2+4                                       C4012016
01DF        KEYIN   EQU      BINRY+161                                  C4012017
0437        ZERO    EQU      KEYIN+600                                  C4012018
0438        BGNR    EQU      ZERO+1                                     C4012019
0439        ERR     EQU      BGNR+1                                     C4012020
043A        WCC     EQU      ERR+1                                      C4012021
043B        MTRM    EQU      WCC+1                                      C4012022
043C        TRFX    EQU      MTRM+1                                     C4012023
043D        TERM    EQU      TRFX+1                                     C4012024
043E        LWC     EQU      TERM+1                                     C4012025
043F        LGROP   EQU      LWC+1                                      C4012026
0440        STBF    EQU      LGROP+1                                    C4012027
0441        SRTRY   EQU      STBF+1                                     C4012028
0C17 0  0001    SKI1  DC     /0001       PID                           C4012029
0C18 0  0002    SKI2  DC     /0002       CD NO                         C4012030
0C19 0  0000    SKI3  DC     /0000       NO ENTRIES                    C4012031
0C1A 00 C4000440 SKI4 LD  L  STBF        GET DISPL                     C4012032
0C1C 01 D400CEC      STO  L  TEMP        SAVE                          C4012033
0C1E 00 4480012E     BSI  I  SSUER       SET ERROR RETURN    SRC       C4012034
0C20 01 C4000CEC     LD   L  TEMP        GET DISPL                     C4012035
0C22 00 D4000440     STO  L  STBF        SET                           C4012036
0C24 01 8400CED      A    L  K0003       ADD 3                         C4012037
0C26 01 8400CEE      A    L  CNST        ADD ADRS                      C4012038
0C28 01 D400CB2      STO  L  SM0-1       SET                           C4012039
0C2A 01 D400C2D      STO  L  SN0+1       SET                           C4012040
0C2C 00 67000000 SN0 LDX  L3 0                                         C4012041
0C2E 00 C400043D SN1 LD   L  TERM        SET ENTRIES TO TERM           C4012042
0C30 00 D7000000     STO  L3 0                                         C4012043
0C32 7301           MDX   3  1                                         C4012044
0C33 01 6F00CF0     STX   L3 SN2                                       C4012045
0C35 01 C400CF1     LD    L  ADRS                                      C4012046
0C37 01 F400CF0     EOR   L  SN2                                       C4012047
0C39 01 4C20C2E     BSC   L  SN1,Z                                     C4012048
0C3B 01 C400CEF     LD    L  K0002       GET 2                         C4012049
0C3D 0  D0DA        STO      SKI2        SET CD NO                     C4012050
0C3E 0  1010        SLA      16                                        C4012051
0C3F 01 D4000D5A    STO   L  WDCT        CLEAR COUNTS                  C4012052
0C41 01 D4000D5B    STO   L  WDCT1                                     C4012053
0C43 0  D0D5        STO      SKI3        CLEAR ENTRY CT                C4012054
0C44 00 4480012C    BSI   I  KEY         IL ILSW CH AC MOD,  SRC       C4012055
0C46 1  0DA7        DC       SN1                                       C4012056
0C47 0  8030        DC       /8030                                     C4012057
0C48 00 C40001DE    LD    L  KEYIN-1     GET WD CT                     C4012058
0C4A 0  B036        CMP      S0560       COMP AGAINST 560              C4012059
0C4B 0  7032        MDX      SKER1       ERRGR                         C4012060
0C4C 0  1000        NOP      0                                         C4012061
0C4D 00 650001DF    LDX   L1 KEYIN       CK ENTRIES FOR                C4012062
0C4F 0  C102    SKA1 LD   1  2           *CORRECT FORMAT               C4012063
0C50 0  4820        BSC      Z                                         C4012064
0C51 0  7010        MDX      SKA2                                      C4012065
0C52 0  C105        LD    1  5                                         C4012066
0C53 0  4820        BSC      Z                                         C4012067
0C54 0  700D        MDX      SKA2                                      C4012068
```

```
0C55 0  C107           LD    1 7                              C4012069
0C56 0  4820           BSC   Z                                C4012070
0C57 0  700A           MDX   SKA2                             C4012071
0C58 0  C10A           LD    1 10                             C4012072
0C59 0  4820           BSC   Z                                C4012073
0C5A 0  7007           MDX   SKA2                             C4012074
0C5B 0  C10D           LD    1 13                             C4012075
0C5C 01 4C180C64       BSC L SKA3,+-                          C4012076
0C5E 00 F400043D       EOR L TERM                             C4012077
0C60 01 4C180C66       BSC L SKA7,+-                          C4012078
0C62 01 4C000D43  SKA2 BSC L SKER2                            C4012079
0C64 0  710E      SKA3 LD    1 14                             C4012080
0C65 0  70E9           MDX   SKA1                             C4012081
*
0C66 00 650001DF  SKA7 LDX  L1 KEYIN       SET IXING          C4012082
0C68 01 66000DEA       LDX  L2 SWB1                           C4012083
0C6A 0  6305      SK6  LDX  3 5                               C4012084
0C6B 0  C101      SK5  LD    1 1           GET ENTRY          C4012085
0C6C 00 F400043D       EOR  L TERM                            C4012086
0C6E 01 4C180C82       BSC  L BUILD,+-     BRANCH IF TERM     C4012087
0C70 0  C100           LD    1 0           GET ENTRY          C4012088
0C71 01 4C180CFD       BSC  L DEC1,+-      BRANCH IF SPACE    C4012089
0C73 01 4F800048       BSC  I3 CNVRT-1     GO CONVERT     SRC C4012090
0C75 01 4F800D50       BSC  I3 CK-1        GO CK DATA     SRC C4012091
0C77 0  D200      SKI1A STO  2 0           SAVE DATA          C4012092
0C78 0  7201           MDX   2 1           INCR IX 2          C4012093
0C79 0  73FF           MDX   3 -1          DECR IX 3          C4012094
0C7A 0  70F0           MDX   SK5           LOOP               C4012095
0C7B 01 74010D5A       MDX  L WDCT,1       INCR WD CT         C4012096
0C7D 0  70EC           MDX   SK6           LOOP               C4012097
0C7E 00 44800132  SKER1 BSI  I SER         PRINT ERROR    SRC C4012098
0C80 1  0D5F           DC    SKE00                            C4012099
0C81 0  0230     S0560 DC    560           CONSTANT           C4012100
0C82 01 66000DEA  BUILD LDX L2 SWB1        SET IXING          C4012101
0C84 01 65000DEA  SK7  LDX L1 SWB1                            C4012102
0C86 0  C200      SK8  LD    2 0                              C4012103
0C87 0  F201           EOR   2 1                              C4012104
0C88 0  F202           EOR   2 2           BUILD DDEF         C4012105
0C89 0  D100           STO   1 0                              C4012106
0C8A 01 74010D5B       MDX  L WDCT1,1      INCR WD CT         C4012107
0C8C 0  C203           LD    2 3           BUILD AC MOD       C4012108
0C8D 0  100B           SLA   11                               C4012109
0C8E 0  F204           EOR   2 4                              C4012110
0C8F 0  D101           STO   1 1                              C4012111
0C90 01 74010D5B       MDX  L WDCT1,1      INCR WD CT         C4012112
0C92 0  7102           MDX   1 2           IXCR IX 1          C4012113
0C93 0  7205           MDX   2 5           INCR IX 2          C4012114
0C94 01 74FF0D5A       MDX  L WDCT,-1      CK FOR DONE        C4012115
0C96 0  7061           MDX   SK9           BRANCH             C4012116
0C97 0  690C      SKA  STX   1 SKD+1       SAVE IXING         C4012117
0C98 0  6A0D           STX   2 SKE+1                          C4012118
0C99 0  6B0E           STX   3 SKF+1                          C4012119
0C9A 01 65800C17       LDX  I1 SKI1        SET IXING          C4012120
0C9C 01 66800C18       LDX  I2 SKI2                           C4012121
0C9E 01 67800D5B       LDX  I3 WDCT1                          C4012122
0CA0 00 44800133       BSI  I SECSU        SET CARD       SRC C4012123
0CA2 1  0DEA      SK8  DC    SWB1                             C4012124
0CA3 00 65000000  SKD  LDX L1 0           RESTORE IXING       C4012125
0CA5 00 66000000  SKE  LDX L2 0                               C4012126
0CA7 00 67000000  SKF  LDX L3 0                               C4012127
0CA9 0  1010           SLA   16                               C4012128
0CAA 01 D4000D5B       STO  L WDCT1        CLEAR WD CT        C4012129
0CAC 01 74010C18       MDX  L SKI2,1       INCR CD NO         C4012130
0CAE 01 74000D5A       MDX  L WDCT,0       IS TOTAL WD CT = 0 C4012131
0CB0 0  70D3           MDX   SK7           LOOP               C4012132
0CB1 01 65000000       LDX L1 0           SET IXING           C4012133
0CB3 0  6903      SMO  STX   1 SM+1                            C4012134
0CB4 0  C03F           LD    ENT3          SET NO TO CK       C4012135
```

```
0CB5 0  D03C           STO   ENT1                             C4012137
0CB6 00 66000000  SM   LDX L2 0                               C4012138
0CB6 0  7202           MDX   2 2                               C4012139
*
0CB9 0  C200      SM1A LD    2 0           GET A DDEF         C4012140
0CBA 00 F4000442       EOR  L SRTRY+1      CK FOR AT PID      C4012141
0CBC 01 4C130CE2       BSC  L SM3A,+-      GO ADJ IX 1        C4012142
0CBE 0  C100           LD    1 0           GET DDEF           C4012143
0CBF 00 F400043D       EOR  L TERM                            C4012144
0CC1 01 4C180CE4       BSC  L SM4A,+-      EXIT IF ZERO       C4012145
0CC3 0  C100           LD    1 0                              C4012146
0CC4 0  F200           EOR   2 0           COMPARE            C4012147
0CC5 01 4C160D49       BSC  L SKER4,+-     BR IF ERROR        C4012148
0CC7 0  7202           MDX   2 2           INCR IX            C4012149
0CC8 01 74010CF2       MDX  L ENT1,1       INCR TOTAL         C4012150
0CCA 01 C4000CF2       LD   L ENT1         CK FOR DONE        C4012151
0CCC 00 F4000CF5       EOR  L K0040                           C4012152
0CCE 01 4C180CD1       BSC  L SM2A,+-      BRANCH IF ALL      C4012153
0CD0 0  70E8           MDX   SM1A          LOOP               C4012154
0CD1 0  7102      SM2A MDX   1 2           INCR IX 1          C4012155
0CD2 0  C021           LD    ENT3          GET TOTAL          C4012156
0CD3 0  8022           A     K0001         ADD 1              C4012157
0CD4 0  D01F           STO   ENT3          SAVE              C4012158
0CD5 01 74010CF3       MDX  L ENT1,1       INCR CK TOTAL      C4012159
0CD7 01 C4000CF3       LD   L ENT2         GET CK TOTAL       C4012160
0CD9 0  F01D           EOR   K0039         CK FOR DONE        C4012161
0CDA 01 4C180CE4       BSC  L SM4A,+-      BRANCH IF DONE     C4012162
0CDC 0  C100           LD    1 0           GET ENTRY          C4012163
0CDD 00 F4000442       EOR  L SRTRY+1      CK FOR AT PID      C4012164
0CDF 01 4C180CEA       BSC  L SM5A,+-      BRANCH IF AT PID   C4012165
0CE1 0  70D1           MDX   SM0           LOOP               C4012166
*
0CE2 0  7203      SM3A MDX   2 3           SET IX TO DDEF     C4012167
0CE3 0  70D5           MDX   SM1A                             C4012168
*
0CE4 0  1010      SM4A SLA   16            CLEAR ALL NECESSARY C4012169
0CE5 0  D00C           STO   ENT1                             C4012170
0CE6 0  D00C           STO   ENT2                             C4012171
0CE7 0  D00C           STO   ENT3                             C4012172
*
0CE8 00 4C00013A       BSC  L S2           EXIT               C4012173
*
0CEA 0  7103      SM5A MDX   1 3           ADJ IX 1           C4012174
0CEB 0  70C7           MDX   SM0           LOOP               C4012175
0CEC 0  0000      TEMP DC    0                                C4012176
0CED 0  0003      K0003 DC   3             CONSTANTS          C4012177
0CEE 0  0442      CNST DC    SRTRY+1                          C4012178
0CEF 0  0002      K0002 DC   2                                C4012179
0CF0 0  0000      SN2  DC    0                                C4012180
0CF1 0  0583      ADRS DC    SRTRY+322                        C4012181
*
0CF2 0  C000      ENT1 DC    0             CONSTANTS          C4012182
0CF3 0  0000      ENT2 DC    0                                C4012183
0CF4 0  0000      ENT3 DC    0                                C4012184
0CF5 0  0028      K0040 DC   40                               C4012185
0CF6 0  0001      K0001 DC   1                                C4012186
0CF7 0  0027      K0039 DC   39                               C4012187
0CF8 0  C062      SK9  LD    WDCT1         GET CD WD CT       C4012188
0CF9 0  B063           CMP   S000C         COMPARE WITH 12    C4012189
0CFA 0  7048           MDX   SKER2         ERROR              C4012190
0CFB 0  708A           MDX   SK8           LOOP               C4012191
0CFC 0  709A           MDX   SKA           GO SET CD          C4012192
0CFD 0  7101      DEC1 MDX   1 1           INCR IX 1          C4012193
0CFE 01 4C000C6B       BSC  L SK5          LOOP               C4012194
0D00 0  C100      KYHEX LD   1 0           GET WD 1           C4012195
0D01 00 C40001DF       STO  L KEYIN        SAVE               C4012196
0D03 0  C101           LD    1 1           GET WD 2           C4012197
0D04 00 D40001E0       STO  L KEYIN+1      SAVE               C4012198
```

```
0D06 00 C400043D       LD   L  TERM     GET TERM              C4012205
0D08 00 D40001E1       STO  L  KEYIN+2  SET                   C4012206
0D0A 00 44300137       BSI  I  PHKYB    CONVERT TO HEX    SRC C4012207
0D0C 0  0002           DC      2                              C4012208
0D0D 0  0437           DC      ZERO                           C4012209
0D0E 0  7103           MDX  1 3         INCR IX 1             C4012210
0D0F 01 4C000C75       BSC  L  SKI6                           C4012211
0D11 0  C100   KYHX1   LD   1 0         GET WD                C4012212
0D12 00 D40001DF       STO  L  KEYIN    SAVE                  C4012213
0D14 00 C400043D       LD   L  TERM     GET TERM              C4012214
0D16 00 D40001E0       STO  L  KEYIN+1  SET                   C4012215
0D18 00 44800137       BSI  I  PHKYB    CONVERT TO HEX    SRC C4012216
0D1A 0  0001           DC      1                              C4012217
0D1B 0  0437           DC      ZERO                           C4012218
0D1C 0  7102           MDX  1 2         INCR IX 1             C4012219
0D1D 01 4C000C75       BSC  L  SKI6                           C4012220
0D1F 0  C100   KYDC2   LD   1 0         GET WD 1              C4012221
0D20 00 D40001DF       STO  L  KEYIN    SAVE                  C4012222
0D22 0  C101           LD   1 1         GET WD 2              C4012223
0D23 00 D40001E0       STO  L  KEYIN+1  SAVE                  C4012224
0D25 00 C400043D       LD   L  TERM     GET TERM              C4012225
0D27 00 D40001E1       STO  L  KEYIN+2  SET                   C4012226
0D29 00 44800136       BSI  I  PDKYB    CONVERT TO DEC    SRC C4012227
0D2B 0  0002           DC      2                              C4012228
0D2C 0  0437           DC      ZERO                           C4012229
0D2D 0  7103           MDX  1 3         INCR IX 1             C4012230
0D2E 01 4C000C75       BSC  L  SKI6                           C4012231
0D30 00 C400013E LSFF  LD   L  BINRY    GET WD                C4012232
0D32 0  B02B           CMP     SOOFF    CMPR WITH FF          C4012233
0D33 0  7012           MDX     SKER3    ERROR                 C4012234
0D34 0  1000           NOP     0                              C4012235
0D35 01 4C000C77       BSC  L  SKIA                           C4012236
0D37 00 44800131 CH    BSI  I  SCH      CK CH NO          SRC C4012237
0D39 01 4C000C77       BSC  L  SKIA                           C4012238
0D3B 00 44800130 LSW   BSI  I  SILSW    CK ILSW BIT       SRC C4012239
0D3D 01 4C000C77       BSC  L  SKIA                           C4012240
0D3F 00 4480012F IL    BSI  I  SIL      CK INT LVL        SRC C4012241
0D41 01 4C000C77       BSC  L  SKIA                           C4012242
0D43 00 44800132 SKER2 BSI  I  SER      PRINT ERROR       SRC C4012243
0D45 1  0D5F           DC      SKE00                          C4012244
0D46 00 44800132 SKER3 BSI  I  SER      PRINT ERROR       SRC C4012245
0D48 1  0D75           DC      SKE02                          C4012246
0D49 00 44800132 SKER4 BSI  I  SER      IDENTICAL DDEFS   SRC C4012247
0D4B 1  0D8C           DC      SKE03 .                        C4012248
0D4C 1  0D00   CNVRT   DC      KYHEX    CONVERT TABLE         C4012249
0D4D 1  0D1F           DC      KYDC2                          C4012250
0D4E 1  0D11           DC      KYHX1                          C4012251
0D4F 1  0D1F           DC      KYDC2                          C4012252
0D50 1  0D1F           DC      KYDC2                          C4012253
0D51 1  0D56   CK      DC      AC       CK TBL                C4012254
0D52 1  0D30           DC      LSFF                           C4012255
0D53 1  0D37           DC      CH                             C4012256
0D54 1  0D3B           DC      LSW                            C4012257
0D55 1  0D3F           DC      IL                             C4012258
0D56 00 C400013E AC    LD   L  BINRY    GET ENTRY             C4012259
0D58 01 4C000C77       BSC  L  SKIA                           C4012260
0D5A 0  0000   WDCT    DC      0        TOTAL WD CT           C4012261
0D5B 0  0000   WDCT1   DC      0        CARD WD CT            C4012262
0D5C 0  0005   S0005   DC      5        CONSTANTS             C4012263
0D5D 0  000C   S000C   DC      /000C                          C4012264
0D5E 0  001F   SOOFF   DC      31                             C4012265
                                                              C4012266
0D5F    0012   SKEC0   EBC     .E010  PID 01-CD 02.           C4012267
0D68    0012           EBC     . IMPROPER NUMBER .            C4012268
0D71    0006           EBC     .OF WDS.                       C4012269
0D74 0  FFFF           DC      /FFFF                          C4012270
                                                              C4012271
0D75    0012   SKE02   EBC     .E00F PID 01-CD 02.            C4012272
```

```
0D7E    0012           EBC     . AREA CODE WAS TO.            C4012273
8D87    0007           EBC     .O LARGE.                      C4012274
0D8B 0  FFFF           DC      /FFFF                          C4012275
                                                              C4012276
0D8C    0012   SKE03   EBC     .E006  PID 01-CD 02.           C4012277
0D95    0012           EBC     . 2 CR MORE ENTR'E.            C4012278
0D9E    000F           EBC     .S ARE IDENTICAL.              C4012279
0DA6 0  FFFF           DC      /FFFF                          C4012280
                                                              C4012281
0DA7    0012   SM1     EBC     .C014 PID 01-CD 02.            C4012282
0DB0    0012           EBC     . ENTER DEVICE INF.            C4012283
0DB9    0012           EBC     .O IN THE FOLLOWING.           C4012284
0DC2    0012           EBC     . FORMAT 1-40 DEVI.            C4012285
0DCB    0012           EBC     .CES-SPACE BETWEEN .           C4012286
0DD4    0012           EBC     .ENTRIES, IL ILSW C.           C4012287
0DDD    0012           EBC     .H AC MOD,$DD DD H .           C4012288
0DE6    0005           EBC     .DD HH.                        C4012289
0DE9 0  FFFF           DC      /FFFF                          C4012290
                                                              C4012291
0DEA 0  0000   SWB1    DC      0        ENTRY STORAGE         C4012292
0DEB    0154           BSS     340                            C4012293
0F3F 00 4C000138 END1  BSC  L  ENDO                           C4012294
0F42    0F3F           END     END1              C401229 C4012304
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
AC	0D56	0D51
ADRS	0CF1	0C35
BGNR	0438	0C17
BINRY	013E	0C17,0D30,0D56
BUILD	0C82	0C6E
CH	0D37	0D53
CK	0D51	0C75
CKYN	012D	0C17
CNST	0CEE	0C26
CNVRT	0D4C	0C73
DEC1	0CFD	0C71
END0	0138	0C17,0F3F
END1	0F3F	0F41
ENT1	0CF2	0CB5,0CC8,0CCA,0CE5
ENT2	0CF3	0CD5,0CD7,0CE6
ENT3	0CF4	0C54,0CD2,0CD4,0CE7
ERR	0439	0C17
IL	0D3F	0D55
KEY	012C	0C17,0C44
KEYIN	01DF	0C17,0C48,0C4D,0C66,0D01,0D04,0D08,0D12,0D16,0D20,
		0D23,0D27
KYDC2	0D1F	0D40,0D4F,0D50
KYHEX	0D00	0D4C
KYHX1	0D11	0D4E
K0001	0CF6	0CD3
K0002	0CEF	0C3B
K0003	0CED	0C24
K0039	0CF7	0CD9
K0040	0CF5	0CCC
LGRCP	043F	0C17
LSFF	0D30	0D52
LSW	0D3B	0D54
LWC	043E	0C17
MTRM	0438	0C17
PDKY8	0136	0C17,0D29
PHKY8	0137	0C17,0D0A,0D18
SCH	0131	0C17,0D37
SECSU	0133	0C17,0CA0
SER	0132	0C17,0C7E,0D43,0D46,0D49
SIL	012F	0C17,0D3F
SILSW	0130	0C17,0D3B
SKA	0C97	0CFC
SKA1	0C4F	0C65
SKA2	0C62	0C51,0C54,0C57,0C5A
SKA3	0C64	0C5C
SKA7	0C66	0C60
SKB	0C86	0CFB
SKD	0CA3	0C97
SKE	0CA5	0C98
SKER1	0C7E	0C4B
SKER2	0D43	0C62,0CFA
SKER3	0D46	0D33
SKER4	0D49	0CC5
SKE00	0D5F	0C80,0D45
SKE02	0D75	0D48
SKE03	0D8C	0D4B
SKF	0CA7	0C99
SKIA	0C77	0D35,0D39,0D3D,0D41,0D58
SKIN0	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0C9A
SKI2	0C16	0C3D,0C9C,0CAC
SKI3	0C19	0C43
SKI4	0C1A	
SKI6	0C75	0D0F,0D1D,0D2E

SYMBOL	VALUE	REFERENCES
SK5	0C6B	0C7A,0CFE
SK6	0C6A	0C7D
SK7	0C84	0CB0
SK8	0CA2	
SK9	0CF8	0C96
SM	0C36	0CB3
SM0	0CB3	0C28,0CE1,0CE8
SM1	0DA7	0C46
SM1A	0CB9	0CD0,0CE3
SM2A	0CD1	0CCE
SM3A	0CE2	0CBC
SM4A	0CE4	0CC1,0CDA
SM5A	0CEA	0CDF
SN0	0C2C	0C2A
SN1	0C2E	0C39
SN2	0CF0	0C33,0C37
SRTRY	0441	0CBA,0CDD,0CEE,0CF1
SSUER	012E	0C17,0C1E
STBF	0440	0C17,0C1A,0C22
SWB1	0DEA	0C68,0C82,0C84,0CA2
S00FF	0D5E	0D32
S000C	0D5D	0CF9
S0005	0D5C	
S0560	0C81	0C4A
S2	013A	0C17,0CE8
TEMP	0CEC	0C1C,0C20
TERM	043D	0C17,0C2E,0C5E,0C6C,0CBF,0D06,0D14,0D25
TRFX	043C	0C17
WCC	043A	0C17
WDCT	0D5A	0C3F,0C7B,0C94,0CAE
WDCT1	0D5B	0C41,0C8A,0C90,0C9E,0CAA,0CF8
ZERO	0437	0C17,0D0D,0D1B,0D2C

```
0000                     ORG    *+3095              C4013001
012C         KEY   EQU   300                        C4013002
012D         CKYN  EQU   KEY+1                       C4013003
012E         SSUER EQU   CKYN+1                      C4013004
012F         SIL   EQU   SSUER+1                     C4013005
0130         SILSW EQU   SIL+1                       C4013006
0131         SCH   EQU   SILSW+1                     C4013007
0132         SER   EQU   SCH+1                       C4013008
0133         SECSU EQU   SER+1                       C4013009
0134         SKIN1 EQU   SECSU+1                     C4013010
0135         SKINO EQU   SKIN1+1                     C4013011
0136         PDKYB EQU   SKINO+1                     C4013012
0137         PHKYB EQU   PDKYB+1                     C4013013
0138         ENDO  EQU   PHKYB+1                     C4013014
013A         S2    EQU   ENDO+2                      C4013015
013E         BINRY EQU   S2+4                        C4013016
01DF         KEYIN EQU   BINRY+161                   C4013017
0437         ZERO  EQU   KEYIN+600                   C4013018
0438         BGNR  EQU   ZERO+1                      C4013019
0439         ERR   EQU   BGNR+1                      C4013020
043A         WCC   EQU   ERR+1                       C4013021
043B         MTRM  EQU   WCC+1                       C4013022
043C         TRFX  EQU   MTRM+1                      C4013023
043D         TERM  EQU   TRFX+1                      C4013024
043E         LWC   EQU   TERM+1                      C4013025
043F         LGROP EQU   LWC+1                       C4013026
0440         STBF  EQU   LGROP+1                     C4013027
0441         SRTRY EQU   STBF+1                      C4013028
0C17 0 0001  SKI1  DC    /0001                       C4013029
0C18 0 FFFF  SKI2  DC    /FFFF                       C4013030
0C19 0 0000  SKI3  DC    /0000                       C4013031
0C1A 0 0000  SKI4  DC    /0000                       C4013032
0C1B 00 4C000138 END1 BSC  L  ENDO                   C4013033
0C1E    0C1B            END   END1           C401303 C4013043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17
CKYN	012D	0C17
ENDO	0138	0C17, 0C18
END1	0C1B	0C1D
ERR	0439	0C17
KEY	012C	0C17
KEYIN	01DF	0C17
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17
PHKYB	0137	0C17
SCH	0131	0C17
SECSU	0133	0C17
SER	0132	0C17
SIL	012F	0C17
SILSW	0130	0C17
SKINO	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	
SKI2	0C18	
SKI3	0C19	
SKI4	0C1A	
SRTRY	0441	
SSUER	012E	0C17
STBF	0440	0C17
S2	013A	0C17
TERM	043D	0C17
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17

```
0000                ORG     *+3095              C4040001
012C       KEY  · EQU    300                    C4040002
012D       CKYN EQU    KEY+1                     C4040003
012E       SSUER EQU   CKYN+1                    C4040004
012F       SIL  EQU    SSUER+1                   C4040005
0130       SILSW EQU   SIL+1                     C4040006
0131       SCH  EQU    SILSW+1                   C4040007
0132       SER  EQU    SCH+1                     C4040008
0133       SECSU EQU   SER+1                     C4040009
0134       SKIN1 EQU   SECSU+1                   C4040010
0135       SKINO EQU   SKIN1+1                   C4040011
0136       PDKYB EQU   SKINO+1                   C4040012
0137       PHKYB EQU   PDKYB+1                   C4040013
0138       ENDO EQU    PHKYB+1                   C4040014
013A       S2   EQU    ENDO+2                    C4040015
013E       BINRY EQU   S2+4                      C4040016
01DF       KEYIN EQU   BINRY+161                 C4040017
0437       ZERO EQU    KEYIN+600                 C4040018
0438       BGNR EQU    ZERO+1                    C4040019
0439       ERR  EQU    BGNR+1                    C4040020
043A       WCC  EQU    ERR+1                     C4040021
043B       MTRM EQU    WCC+1                     C4040022
043C       TRFX EQU    MTRM+1                    C4040023
043D       TERM EQU    TRFX+1                    C4040024
043E       LWC  EQU    TERM+1                    C4040025
042F       LGROP EQU   LWC+1                     C4040026
0440       STBF EQU    LGROP+1                   C4040027
0441       SRTRY EQU   STBF+1                    C4040028
0C17 0  0004    SKI1 DC     /0004    PID              C4040029
0C18 0  0000    SKI2 DC     /0000    CD NO            C4040030
0C19 0  0001    SKI3 DC     /0001    NO ENTRIES       C4040031
0C1A 00 4480012E SKI4 BSI  I SSUER   SET ERROR RETURN  SRC   C4040032
0C1C 00 4480012C     BSI  I KEY      ENTER IL          SRC   C4040033
0C1E 1  0C3E         DC     SM1                        C4040034
0C1F 0  8120         DC     /8120                      C4040035
0C20 00 4480012F     BSI  I SIL      CK INT LVL        SRC   C4040036
0C22 0  0018         STO    SWB1     SAVE                     C4040037
                  *                                          C4040038
0C23 00 4480012E     BSI  I SSUER    SET ERROR RETURN  SRC   C4040039
0C25 00 4480012C     BSI  I KEY      ENTER ILSW        SRC   C4040040
0C27 1  0C60         DC     SM2                        C4040041
0C28 0  8120         DC     /8120                      C4040042
0C29 00 44800130     BSI  I SILSW    CK ILSW BIT       SRC   C4040043
0C2B 0  D010         STO    SWB2                       C4040044
                  *                                          C4040045
0C2C 0  C00E         LD     SWB1     BUILD DDEF               C4040046
0C2D 0  F00E         EOR    SWB2                       C4040047
0C2E 0  F00E         EOR    SWB3                       C4040048
0C2F 0  D00B         STO    SWB1     SAVE                     C4040049
                  *                                          C4040050
0C30 01 65800C17     LDX  I1 SKI1    SET IXING                C4040051
0C32 01 66800C18     LDX  I2 SKI2                       C4040052
0C34 01 67800C19     LDX  I3 SKI3                       C4040053
0C36 00 44800133     BSI  I SECSU    SET CARD          SRC   C4040054
0C38 1  0C3B         DC     SWB1                       C4040055
0C39 60 4C00013A     BSC  L S2       EXIT                     C4040056
0C3B 0  0000    SWB1 DC     0        ENTRY STORAGE            C4040057
0C3C 0  0000    SWB2 DC     0                          C4040058
0C3D 0  000F    SWB3 DC     /000F    CONSTANT                 C4040059
                  *                                          C4040060
0C3E    0012    SM1  EBC    .C001 PID 04-CD 00.             C4040061
0C47    0012         EBC    .  ENTER 2 DIGIT DE.            C4040062
0C50    0012         EBC    .CIMAL INTRPT LVL F.            C4040063
0C59    000C         EBC    .OR 1054-1055.                  C4040064
0C5F 0  FFFF         DC     /FFFF                      C4040065
                  *                                          C4040066
0C60    0011    SM2  EBC    .C002 PID 04-CD 00.             C4040067
0C69    0012         EBC    .  ENTER 2 DIGIT DE.            C4040068
```

```
0C72    0012    EBC    .CIMAL ILSW BIT FOR.            C4040069
0C7B    000A    EBC    . 1054-1055.                    C4040070
0C80 0  FFFF    DC     /FFFF                      C4040071
0C81 00 4C000138 END1 BSC  L ENDO                      C4040072
0C84    0C81    END    END1              C404007 C4040082
```

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-04-0

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
END0	0138	OC17,OC81
END1	OC81	OC83
ERR	0439	OC17
KEY	012C	OC17,OC1C,OC25
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17,OC36
SER	0132	OC17
SIL	012F	OC17,OC20
SILSW	0130	OC17,OC29
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	OC30
SKI2	OC18	OC32
SKI3	OC19	OC34
SKI4	OC1A	
SM1	OC3E	OC1E
SM2	OC60	OC27
SRTRY	0441	
SSUER	012E	OC17,OC1A,OC23
STBF	0440	OC17
SWB1	OC3B	OC22,OC2C,OC2F,OC38
SWB2	OC3C	OC28,OC2D
SWB3	OC3D	OC2E
S2	013A	OC17,OC39
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-04-1

0000		ORG	*+3095	.	C4041001
012C	KEY	EQU	300		C4041002
012D	CKYN	EQU	KEY+1		C4041003
012E	SSUER	EQU	CKYN+1		C4041004
012F	SIL	EQU	SSUER+1		C4041005
0130	SILSW	EQU	SIL+1		C4041006
0131	SCH	EQU	SILSW+1		C4041007
0132	SER	EQU	SCH+1		C4041008
0133	SECSU	EQU	SER+1		C4041009
0134	SKIN1	EQU	SECSU+1		C4041010
0135	SKIN0	EQU	SKIN1+1		C4041011
0136	PDKYB	EQU	SKIN0+1		C4041012
0137	PHKYB	EQU	PDKYB+1		C4041013
0138	END0	EQU	PHKYB+1		C4041014
013A	S2	EQU	END0+2		C4041015
013E	BINRY	EQU	S2+4		C4041016
01DF	KEYIN	EQU	BINRY+161		C4041017
0437	ZERO	EQU	KEYIN+600		C4041018
0438	BGNR	EQU	ZERO+1		C4041019
0439	ERR	EQU	BGNR+1		C4041020
043A	WCC	EQU	ERR+1		C4041021
043B	MTRM	EQU	WCC+1		C4041022
043C	TRFX	EQU	MTRM+1		C4041023
043D	TERM	EQU	TRFX+1		C4041024
043E	LWC	EQU	TERM+1		C4041025
043F	LGROP	EQU	LWC+1		C4041026
0440	STBF	EQU	LGROP+1		C4041027
0441	SRTRY	EQU	STBF+1		C4041028
OC17 0 0004	SKI1	DC	/0004		C4041029
OC18 0 FFFF	SKI2	DC	/FFFF		C4041030
OC19 0 0000	SKI3	DC	0		C4041031
OC1A 0 0000	SKI4	DC	0		C4041032
OC1B 00 4C000138	END1	BSC L	END0		C4041033
OC1E OC1B		END	END1	C4041C3	C4041043

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17,OC1B
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG    **3095              C4050001
012C            KEY     EQU    300                 C4050002
012D            CKYN    EQU    KEY+1               C4050003
012E            SSUER   EQU    CKYN+1              C4050004
012F            SIL     EQU    SSUER+1             C4050005
0130            SILSW   EQU    SIL+1               C4050006
0131            SCH     EQU    SILSW+1             C4050007
0132            SER     EQU    SCH+1               C4050008
0133            SECSU   EQU    SER+1               C4050009
0134            SKIN1   EQU    SECSU+1             C4050010
0135            SKINO   EQU    SKIN1+1             C4050011
0136            PDKYB   EQU    SKINO+1             C4050012
0137            PHKYB   EQU    PDKYB+1             C4050013
0138            ENDO    EQU    PHKYB+1             C4050014
013A            S2      EQU    ENDO+2              C4050015
013E            BINRY   EQU    S2+4                C4050016
01DF            KEYIN   EQU    BINRY+161           C4050017
0437            ZERO    EQU    KEYIN+600           C4050018
0438            BGNR    EQU    ZERO+1              C4050019
0439            ERR     EQU    BGNR+1              C4050020
043A            WCC     EQU    ERR+1               C4050021
043B            MTRM    EQU    WCC+1               C4050022
043C            TRFX    EQU    MTRM+1              C4050023
043D            TERM    EQU    TRFX+1              C4050024
043E            LWC     EQU    TERM+1              C4050025
043F            LGROP   EQU    LWC+1               C4050026
0440            STBF    EQU    LGROP+1             C4050027
0441            SRTRY   EQU    STBF+1              C4050028
OC17 0  0005    SKI1    DC     /0005     PID       C4050029
OC18 0  0000    SKI2    DC     0         CD NO     C4050030
OC19 0  0001    SKI3    DC     /0001     NO ENTRIES C4050031
OC1A 00 4480012E SKI4   BSI  I SSUER     SET ERROR RETURN  SRC  C4050032
OC1C 00 4480012C        BSI  I KEY       ENTER IL 1ST 1627 SRC  C4050033
OC1E 1  OC43            DC     SM1                 C4050034
OC1F 0  8120            DC     /8120               C4050035
OC20 00 4480012F        BSI  I SIL       CK INT LVL        SRC  C4050036
OC22 0  D01D            STO    SWB1                C4050037
        *                                          C4050038
OC23 00 4480012E        BSI  I SSUER     SET ERROR RETURN  SRC  C4050039
OC25 00 4480012C        BSI  I KEY       ILSW BIT 1ST 1627 SRC  C4050040
OC27 1  OC63            DC     SM2                 C4050041
OC28 0  8120            DC     /8120               C4050042
OC29 00 4480130         BSI  I SILSW     CK ILSW BIT       SRC  C4050043
OC2B 0  D015            STO    SWB2      SAVE              C4050044
OC2C 01 C4000C40        LD   L SWB1      BUILD DUEF        C4050045
OC2E 01 F4000C41        EOR  L SWB2                        C4050046
OC30 01 F4000C3F        EOR  L K000F                       C4050047
OC32 01 D4000C40        STO  L SWB1      SAVE              C4050048
        *                                          C4050049
OC34 01 65800C17 SK3    LDX  I1 SKI1     SET IXING         C4050050
OC36 01 66800C18        LDX  I2 SKI2                       C4050051
OC38 01 67800C19        LDX  I3 SKI3                       C4050052
OC3A 00 44800133        BSI  I SECSU     SET CARD          SRC  C4050053
OC3C 1  OC40            DC     SWB1                C4050054
OC3D 00 4C00013A        BSC  L S2                 C4050055
        *                                          C4050056
OC3F 0  000F    K000F   DC     /000F               C4050057
OC40 0  0000    SWB1    DC     0         ENTRY STORAGE     C4050058
OC41 0  0000    SWB2    DC     0                   C4050059
OC42 0  0000    SWB3    DC     0                   C4050060
        *                                          C4050061
OC43    0012    SM1     EBC    .C001 PID 05-CD GO. C4050062
OC4C    0012            EBC    .  ENTER 2 DIGIT DE.C4050063
OC55    0012            EBC    .CIMAL INTRPT LVL F.C4050064
OC5E    0007            EBC    .OR 1627.           C4050065
OC62 0  FFFF            DC     /FFFF               C4050066
        *                                          C4050067
OC63    0012    SM2     EBC    .C002 PID 05-CD 00. C4050068
```

```
OC6C     0012          EBC    .  ENTER 2 DIGIT DE.          C4050069
OC75     0012          EBC    .CIMAL ILSW BIT FOR.          C4050070
OC7E     0005          EBC    .  1627.                      C4050071
OC81 0   FFFF          DC     /FFFF                         C4050072
                   .                                        C4050073
OC82 00  4C000138  END1 BSC  L  ENDO                        C4050074
OC84     OC92          END     END1             C405007  C4050084
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17,OC82
END1	OC82	OC84
ERR	0439	OC17
KEY	012C	OC17,OC1C,OC25
KEYIN	01DF	OC17
KOOOF	OC3F	OC30
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17,OC3A
SER	0132	OC17
SIL	012F	OC17,OC20
SILSW	0130	OC17,OC29
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	OC34
SKI2	OC18	OC36
SKI3	OC19	OC38
SKI4	OC1A	
SK3	OC34	
SM1	OC43	OC1E
SM2	OC63	OC27
SRTRY	0441	
SSUER	012E	OC17,OC1A,OC23
STBF	0440	OC17
SWB1	OC40	OC22,OC2C,OC32,OC3C
SWB2	OC41	OC2B,OC2E
SWB3	OC42	
S2	013A	OC17,OC3D
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG     **3095                      C4051001
012C            KEY     EQU     300                         C4051002
012D            CKYN    EQU     KEY+1                        C4051003
012E            SSUER   EQU     CKYN+1                       C4051004
012F            SIL     EQU     SSUER+1                      C4051005
0130            SILSW   EQU     SIL+1                        C4051006
0131            SCH     EQU     SILSW+1                      C4051007
0132            SER     EQU     SCH+1                        C4051008
0133            SECSU   EQU     SER+1                        C4051009
0134            SKIN1   EQU     SECSU+1                      C4051010
0135            SKINO   EQU     SKIN1+1                      C4051011
0136            PDKYB   EQU     SKINO+1                      C4051012
0137            PHKYB   EQU     PDKYB+1                      C4051013
0138            ENDO    EQU     PHKYB+1                      C4051014
013A            S2      EQU     ENDO+2                       C4051015
013E            BINRY   EQU     S2+4                         C4051016
01DF            KEYIN   EQU     BINRY+161                    C4051017
0437            ZERO    EQU     KEYIN+600                    C4051018
0438            BGNR    EQU     ZERO+1                       C4051019
0439            ERR     EQU     BGNR+1                       C4051020
043A            WCC     EQU     ERR+1                        C4051021
043B            MTRM    EQU     WCC+1                        C4051022
043C            TRFX    EQU     MTRM+1                       C4051023
043D            TERM    EQU     TRFX+1                       C4051024
043E            LWC     EQU     TERM+1                       C4051025
043F            LGROP   EQU     LWC+1                        C4051026
0440            STBF    EQU     LGROP+1                      C4051027
0441            SRTRY   EQU     STBF+1                       C4051028
0C17 0  0005    SKI1    DC      /0005                        C4051029
0C18 0  FFFF    SKI2    DC      /FFFF                        C4051030
0C19 0  0000    SKI3    DC      0                            C4051031
0C1A 0  0000    SKI4    DC      0                            C4051032
0C1B 00 4C000138 END1   BSC  L  ENDO                         C4051033
0C1E    0C1B             END     END1            C405103 C4051043
```

CROSS REFERENCE LISTING

```
SYMBOL  VALUE   REFERENCES
EGNR    0438    0C17
BINRY   013E    0C17
CKYN    012D    0C17
ENDO    0138    0C17, 0C1B
END1    0C1B    0C1D
ERR     0439    0C17
KEY     012C    0C17
KEYIN   01DF    0C17
LGRGP   043F    0C17
LWC     043E    0C17
MTRM    043B    0C17
PDKYB   0136    0C17
PHKYB   0137    0C17
SCH     0131    0C17
SECSU   0133    0C17
SER     0132    0C17
SIL     012F    0C17
SILSW   0130    0C17
SKINO   0135    0C17
SKIN1   0134    0C17
SKI1    0C17
SKI2    0C18
SKI3    0C19
SKI4    0C1A
SRTRY   0441
SSUER   012E    0C17
STBF    0440    0C17
S2      013A    0C17
TERM    043D    0C17
TRFX    043C    0C17
WCC     043A    0C17
ZERO    0437    0C17
```

```
0000              ORG     *+3095                              C4060001
012C     KEY      EQU     300                                 C4060002
012D     CKYN     EQU     KEY+1                               C4060003
012E     SSUER    EQU     CKYN+1                              C4060004
012F     SIL      EQU     SSUER+1                             C4060005
0130     SILSW    EQU     SIL+1                               C4060006
0131     SCH      EQU     SILSW+1                             C4060007
0132     SER      EQU     SCH+1                               C4060008
0133     SECSU    EQU     SER+1                               C4060009
0134     SKIN1    EQU     SECSU+1                             C4060010
0135     SKINO    EQU     SKIN1+1                             C4060011
0136     PDKYB    EQU     SKINO+1                             C4060012
0137     PHKYB    EQU     PDKYB+1                             C4060013
0138     ENDO     EQU     PHKYB+1                             C4060014
013A     S2       EQU     ENDO+2                              C4060015
013E     BINRY    EQU     S2+4                                C4060016
01DF     KEYIN    EQU     BINRY+161                           C4060017
0437     ZERO     EQU     KEYIN+600                           C4060018
0438     BGNR     EQU     ZERO+1                              C4060019
0439     ERR      EQU     BGNR+1                              C4060020
043A     WCC      EQU     ERR+1                               C4060021
043B     MTRM     EQU     WCC+1                               C4060022
043C     TRFX     EQU     MTRM+1                              C4060023
043D     TERM     EQU     TRFX+1                              C4060024
043E     LWC      EQU     TERM+1                              C4060025
043F     LGROP    EQU     LWC+1                               C4060026
0440     STBF     EQU     LGROP+1                             C4060027
0441     SRTRY    EQU     STBF+1                              C4060028
0C17 0 0006  SKI1   DC   /0006   PID                          C4060029
0C18 0 0000  SKI2   DC   /0000   CD NO                        C4060030
0C19 0 000A  SKI3   DC   /000A   NO OF ENTRIES                C4060031
0C1A 0 630A  SKI4   LDX  3 10                                 C4060032
0C1B 0 1010         SLA  16                                   C4060033
0C1C 01 D7000CD0 SK9 STO L3 SWB1-1 CLEAR DATA STORAGE         C4060034
0C1E 0 73FF         MDX  3 -1      DECR IX 3                   C4060035
0C1F 0 70FC         MDX  SK9       LOOP                        C4060036
0C20 01 C4000CC8    LD   L K0001                              C4060037
0C22 01 D4000CCA    STO  L MONSW   SET SW                     C4060038
0C24 00 4480012E    BSI  I SSUER   SET ERROR RETURN   SRC     C4060039
0C26 00 4480012C    BSI  I KEY     ENTER TOTAL TYPES  SRC     C4060040
0C28 1 0D03         DC     SM1                                C4060041
0C29 0 8110         DC     /8110                              C4060042
                                                              C4060043
0C2A 00 C400013E    LD   L BINRY   GET ENTRY                  C4060044
0C2C 01 4C180CF6    BSC  L SKE01,+-  BR IF ZERO               C4060045
0C2E 01 84000CCD    CMP  L K0008   CK FOR MAX                 C4060046
0C30 0 703F         MDX    SKE02   ERROR                      C4060047
0C31 0 1000         NOP    0                                  C4060048
0C32 01 D4000CCF    STO  L TYCT    SAVE                       C4060049
0C34 01 D4000CD0    STO  L TYCT1                              C4060050
                                                              C4060051
0C36 00 4480012E SK2 BSI I SSUER   SET ERROR RETURN   SRC     C4060052
0C38 00 4480012C    BSI  I KEY     IL FOR TYPE        SRC     C4060053
0C3A 1 0D27         DC     SM2                                C4060054
0C3B 0 8120         DC     /8120                              C4060055
                                                              C4060056
0C3C 00 4480012F    BSI  I SIL     CK IL              SRC     C4060057
0C3E 01 D4000CC4    STO  L TEMP    SAVE                       C4060058
                                                              C4060059
0C40 00 4480012E    BSI  I SSUER   SET ERROR RETURN   SRC     C4060060
0C42 00 4480012C    BSI  I KEY     ENTER ILSW         SRC     C4060061
0C44 1 0C4A         DC     SM3                                C4060062
0C45 0 8120         DC     /8120                              C4060063
                                                              C4060064
0C46 00 44800130    BSI  I SILSW   CK ILSW BIT        SRC     C4060065
0C48 01 F4000CC4    EOR  L TEMP    BUILD DDEF                 C4060066
0C4A 01 F4000CCE    EOR  L H000F                             C4060067
0C4C 0 D077         STO    TEMP                               C4060068
```

```
         *                                                    C4060069
0C4D 00 4480012E    BSI  I SSUER   SET ERROR RETURN   SRC     C4060070
0C4F 00 4480012C    BSI  I KEY     ENTER TYPE NO      SRC     C4060071
0C51 1 0D75         DC     SM5                                C4060072
0C52 0 8110         DC     /8110                              C4060073
                                                              C4060074
0C53 00 C400013E    LD   L BINRY   GET ENTRY                  C4060075
0C55 01 4C180CF9    BSC  L SKE03,+-  BR IF ZERO               C4060076
0C57 0 B075         CMP    K0008   CK FOR MAX                 C4060077
0C58 0 7068         MDX    SKE04   ERROR                      C4060078
0C59 0 1000         NOP    0                                  C4060079
0C5A 01 D4000C5D    STO  L S4+1                               C4060080
0C5C 00 67000000 S4 LDX  L3 0                                 C4060081
0C5E 01 74000CCA    MDX  L MONSW,0 IS MON DV SET              C4060082
0C60 0 7002         MDX    T2                                 C4060083
0C61 01 4C000C6C    BSC  L SK3                                C4060084
0C63 00 4480012E T2 BSI  I SSUER   SET ERROR RETURN   SRC     C4060085
         *                                                    C4060086
0C65 00 4480012C    BSI  I KEY     IS THIS MON DEV    SRC     C4060087
0C67 1 0D93         DC     SM6                                C4060088
0C68 0 8000         DC     /8000                              C4060089
         *                                                    C4060090
0C69 00 4480012D    BSI  I CKYN    CK FOR Y OR N      SRC     C4060091
0C6B 0 7007         MDX    SK4     ENTRY WAS Y                C4060092
                                                              C4060093
0C6C 0 C057   SK3   LD     TEMP    GET DDEF                   C4060094
0C6D 01 D7000CD1 SKA STO  L3 SWB1                             C4060095
0C6F 0 7018         MDX    SK5                                C4060096
0C70 00 44800132 SKE02 BSI I SER   MORE THAN 8 TYPES  SRC     C4060097
0C72 1 0DDE         DC     SE001                              C4060098
         *                                                    C4060099
0C73 0 C050   SK4   LD     TEMP                               C4060100
0C74 0 D05C         STO    SWB1                               C4060101
0C75 0 1010         SLA    16                                 C4060102
0C76 01 D7000CD1    STO  L3 SWB1                              C4060103
0C78 01 D4000CCA    STO  L MONSW   CLEAR MON SW               C4060104
0C7A 01 C7000CD1    LD   L3 SWB1   GET ENTRY                  C4060105
0C7C 0 4820         BSC    Z       SKIP IF ZERO               C4060106
0C7D 0 700D         MDX    SK5     BRANCH                     C4060107
0C7E 0 6302         LDX  3 2       SET IX                     C4060108
0C7F 0 C4000C5D     LD   L S4+1    GET ID                     C4060109
0C81 0 F046         EOR    K0001   CK FOR 1                   C4060110
0C82 01 4C180C99    BSC  L SK5A,+-  BRANCH IF 1               C4060111
0C84 01 C4000C5D    LD   L S4+1    GET ID                     C4060112
0C86 01 F4000CCC    EOR  L K0005   CK FOR 5                   C4060113
0C88 01 4C200CA2    BSC  L SK7,Z   BRANCH IF NOT 5            C4060114
0C8A 0 700E         MDX    SK5A    BRANCH                     C4060115
0C8B 0 6300   SK5   LDX  3 0                                  C4060116
0C8C 01 C4000C5D    LD   L S4+1    GET NUMBER                 C4060117
0C8E 01 F4000CC8    EOR  L K0001   IS IT 1                    C4060118
0C90 01 4C180C99    BSC  L SK5A,+-  YES                       C4060119
0C92 0 6301         LDX  3 1                                  C4060120
0C93 01 C4000C5D    LD   L S4+1    GET NUMBER                 C4060121
0C95 01 F4000CCC    EOR  L K0005   IS IT 5                    C4060122
0C97 01 4C200CA2    BSC  L SK7,Z   NO                         C4060123
0C99 00 4480012E SK5A BSI I SSUER  SET ERROR RETURN   SRC     C4060124
0C9B 00 4480012C    BSI  I KEY     IS IT 1816         SRC     C4060125
0C9D 1 0DBD         DC     SM7                                C4060126
0C9E 0 8000         DC     /8000                              C4060127
         *                                                    C4060128
0C9F 00 4480012D    BSI  I CKYN    CK FOR Y OR N      SRC     C4060129
0CA1 0 7004         MDX    SK6     ENTRY WAS Y                C4060130
         *                                                    C4060131
0CA2 01 74FF0CCF SK7 MDX L TYCT,-1 DECR TYPE CT               C4060132
0CA4 0 7091         MDX    SK2     LOOP                       C4060133
0CA5 0 7035         MDX    SK8     EXIT                       C4060134
0CA6 01 C7000CC5 SK6 LD  L3 TBL    SET 1816 IND               C4060135
0CA8 0 F031         EOR    SWB10                              C4060136
```

```
OCA9 0  D030           STO     SWB10                         C4060137
OCAA 0  73FF           MDX     3 -1      DECR IX 3           C4060138
OCAB 0  7001           MDX     SKS0      BRANCH              C4060139
OCAC 0  70F5           MDX     SK7                           C4060140
OCAD 01 C4000C5D SKSC  LD    L S4+1      GET ID              C4060141
OCAF 0  F018           EOR     K0001     IS IT 1             C4060142
OCB0 01 4C180CB4       BSC   L SKS1,+-   YES                 C4060143
OCB2 0  6301           LDX   3 1         SET IX              C4060144
OCB3 0  70F2           MDX     SK6                           C4060145
OCB4 0  6300     SKS1  LDX   3 0         SET IX              C4060146
OCB5 0  70F0           MDX     SK6                           C4060147
*                                                            C4060148
OCB6 01 65800C17 SKB   LDX   I1 SKI1     SET IXING           C4060149
OCB8 01 66800C18       LDX   I2 SKI2                         C4060150
OCBA 01 67800C19       LDX   I3 SKI3                         C4060151
*                                                            C4060152
OCBC 00 44800133       BSI   I SECSU     SET CARD       SRC  C4060153
OCBE 1  0CD1           DC      SWB1                           C4060154
OCBF 00 4C00013A       BSC   L S2        EXIT                C4060155
OCC1 00 44800132 SKE04 BSI   I SER       FLD GREATER 8  SRC  C4060156
OCC3 1  0DDE           DC      SE001                          C4060157
*                                                            C4060158
OCC4 0  0000     TEMP  DC      0         CONSTANTS           C4060159
OCC5 0  4000     TBL   DC      /4000                         C4060160
OCC6 0  0400           DC      /0400                         C4060161
OCC7 0  8000           DC      /8000                         C4060162
OCC8 0  0001     K0001 DC      1                             C4060163
OCC9 1  0CDA     KLMT  DC      SWB10                         C4060164
OCCA 0  0000     MONS4 DC      0                             C4060165
OCCB 0  0400           DC      /0400                         C4060166
OCCC 0  0005     K0005 DC      5                             C4060167
OCCD 0  0008     K0008 DC      8                             C4060168
OCCE 0  000F     H000F DC      /000F                         C4060169
OCCF 0  0000     TYCT  DC      0                             C4060170
0CD0 0  0000     TYCT1 DC      0                             C4060171
0CD1 0  0000     SWB1  DC      0         DATA STORAGE        C4060172
0CD2 0  0000     SWB2  DC      0                             C4060173
0CD3 0  0000     SWB3  DC      0                             C4060174
0CD4 0  0000     SWB4  DC      0                             C4060175
0CD5 0  0000     SWB5  DC      0                             C4060176
0CD6 0  0000     SWB6  DC      0                             C4060177
0CD7 0  0000     SWB7  DC      0                             C4060178
0CD8 0  0000     SWB8  DC      0                             C4060179
0CD9 0  0000     SWB9  DC      0                             C4060180
0CDA 0  0000     SWB10 DC      0                             C4060181
*                                                            C4060182
0CDB 01 67800CD0 SK8   LDX   I3 TYCT1                        C4060183
0CDD 00 6500FFF8       LDX   L1 -8                           C4060184
0CDF 01 66000CD2       LDX   L2 SWB2                         C4060185
0CE1 0  6A01           STX   2 SKX+1                         C4060186
0CE2 00 66000000 SKX   LDX   L2 0        CK DDEFS            C4060187
0CE4 01 C5000CD9 SKX1  LD    L1 SWB1+8                       C4060188
0CE6 01 4C180CEB       BSC   L SKA1,+-                       C4060189
0CE8 0  F200           EOR   2 0                             C4060190
0CE9 01 4C180CFC       BSC   L SKE05,+-                      C4060191
0CEB 0  7201     SKA1  MDX   2 1                             C4060192
0CEC 0  6AD7           STX   2 TEMP                          C4060193
0CED 0  C0DB           LD      KLMT                          C4060194
0CEE 0  F0D5           EOR     TEMP                          C4060195
0CEF 01 4C200CE4       BSC   L SKX1,Z                        C4060196
0CF1 01 74010CE3       MDX   L SKX+1,1                       C4060197
0CF3 0  7101           MDX   1 1                             C4060198
0CF4 0  70ED           MDX     SKX                           C4060199
0CF5 0  70C0           MDX     SKB                           C4060200
*                                                            C4060201
0CF6 00 44800132 SKE01 BSI   I SER       ZERO TYPES     SRC  C4060202
0CF8 1  0DDE           DC      SE001                          C4060203
0CF9 00 44800132 SKE03 BSI   I SER       FLD ZERO       SRC  C4060204
```

```
OCFB 1  0DDE           DC      SE001                          C4060205
OCFC 01 65000C1A SKE05 LDX   L1 SKI4                          C4060206
OCFE 00 6D000441       STX   L1 SRTRY                         C4060207
0D00 00 44800132       BSI   I SER                       SRC  C4060208
0D02 1  0DF5           DC      SE005     2 DDEFS ALIKE        C4060209
0D03    0012     SM1   EBC     .C004 PID 06-CD 00.            C4060210
0D0C    0012           EBC     . ENTER NUMBER OF .            C4060211
0D15    0012           EBC     .TYPEWRITERS ON SYS.           C4060212
0D1E    0010           EBC     .TEM-1-8, 1 DIGIT.             C4060213
0D26 0  FFFF           DC      /FFFF                          C4060214
*                                                            C4060215
0D27    0012     SM2   EBC     .C001 PID 06-CD 00.            C4060216
0D30    0012           EBC     . ENTER 2 DIGIT DE.            C4060217
0D39    0012           EBC     .CIMAL INTR LVL FOR.           C4060218
0D42    000D           EBC     . A TYPEWRITER.                C4060219
0D49 0  FFFF           DC      /FFFF                          C4060220
*                                                            C4060221
0D4A    0012     SM3   EBC     .C002 PID 06-CD 0..            C4060222
0D53    0012           EBC     . ENTER 2 DIGIT DE.            C4060223
0D5C    0012           EBC     .CIMAL ILSW BIT FOR.           C4060224
0D65    0012           EBC     . TYPEWRITER ON ABO.           C4060225
0D6E    000B           EBC     .VE INTR LVL.                  C4060226
0D74 0  FFFF           DC      /FFFF                          C4060227
*                                                            C4060228
0D75    0012     SM5   EBC     .C037 PID 06-CD 00.            C4060229
0D7E    0012           EBC     . ENTER 1 DIGIT TY.            C4060230
0D87    0012           EBC     .PEWRITER ID NUMBER.           C4060231
0D90    0004           EBC     .-1-8.                         C4060232
0D92 0  FFFF           DC      /FFFF                          C4060233
*                                                            C4060234
0D93    0012     SM6   EBC     .C036  PID 06-CD 00.           C4060235
0D9C    0012           EBC     . IS THE ABOVE ID .            C4060236
0DA5    0012           EBC     .NUMBER FOR DIAG MO.           C4060237
0DAE    0012           EBC     .N OUTPUT DEVICE-TY.           C4060238
0DB7    0009           EBC     .PE Y OR N.                    C4060239
0DBC 0  FFFF           DC      /FFFF                          C4060240
*                                                            C4060241
0DBD    0012     SM7   EBC     .C036  PID 06-CD 00.           C4060242
0DC6    0012           EBC     . IS THE ABOVE ID .            C4060243
0DCF    0012           EBC     .NUMBER FOR 1816-TY.           C4060244
0DD8    0009           EBC     .PE Y OR N.                    C4060245
0DDD 0  FFFF           DC      /FFFF                          C4060246
*                                                            C4060247
0DDE    0012     SE001 EBC     .E007 PID 06-CD 00.            C4060248
0DE7    0012           EBC     . ENTRY TOO LARGE .            C4060249
0DF0    0008           EBC     . OR 0000.                     C4060250
0DF4 0  FFFF           DC      /FFFF                          C4060251
                                                             C4060252
0DF5    0012     SE005 EBC     .E006  PID 06-CD 00.           C4060253
0DFE    0012           EBC     . 2 OR MORE ENTRIE.            C4060254
0E07    000F           EBC     .S ARE IDENTICAL.              C4060255
0E0F 0  FFFF           DC      /FFFF                          C4060256
*                                                            C4060257
0E10 00 4C000138 END1  BSC   L ENDO                          C4060258
0E12    0E10           END     END1            C406025  C4060269
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17,0C2A,0C53
CKYN	012D	0C17,0C69,0C9F
ENDU	0138	0C17,0E10
END1	0E10	0E12
ERR	0439	0C17
HOOUF	0CCE	0C4A
KEY	012C	0C17,0C26,0C38,0C42,0C4F,0C65,0C9B
KEYIN	01DF	0C17
KLMT	0CC9	0CED
K0001	0CC8	0C20,0C81,0C8E,0CAF
K0005	0CCC	0C86,0C95
K0008	0CCD	0C2E,0C57
LGROP	043F	0C17
LWC	043E	0C17
MONSW	0CCA	0C22,0C5E,0C78
MTRM	043B	0C17
PUKY6	0136	0C17
PHKY8	0137	0C17
SCH	0131	0C17
SECSU	0133	0C17,0C8C
SER	0132	0C17,0C70,0CC1,0CF6,0CF9,0D00
SE001	0DDE	0C72,0CC3,0CF8,0CFB
SE005	0DF5	0D02
SIL	012F	0C17,0C3C
SILSW	0130	0C17,0C46
SKA	0C6D	
SKA1	0CE8	0CE6
SKB	0CB6	0CF5
SKE01	0CF6	0C2C
SKE02	0C70	0C30
SKE03	0CF9	0C55
SKE04	0CC1	0C58
SKE05	0CFC	0CE9
SKIN0	0135	0C17
SKIN1	0134	0C17
SK11	0C17	0CB6
SK12	0C18	0CB8
SK13	0C19	0CBA
SK14	0C1A	0CFC
SKS0	0CAD	0CAB
SKS1	0CB4	0CB0
SKX	0CE2	0CE1,0CF1,0CF4
SKX1	0CE4	0CEF
SK2	0C36	0CA4
SK3	0C6C	0C61
SK4	0C73	0C6B
SK5	0C8B	0C6F,0C7D
SK5A	0C99	0C82,0C8A,0C90
SK6	0CA6	0CA1,0CB3,0CB5
SK7	0CA2	0C88,0C97,0CAC
SK8	0CDB	0CA5
SK9	0C1C	0C1F
SM1	0D03	0C28
SM2	0D27	0C3A
SM3	0D4A	0C44
SM5	0D75	0C51
SM6	0D93	0C67
SM7	0D3D	0C9D
SRTRY	0441	0CFE
S&UER	012E	0C17,0C24,0C36,0C40,0C4D,0C63,0C99
STBF	0440	0C17
SWB1	0CD1	0C1C,0C6D,0C74,0C76,0C7A,0CBE,0CE4
SWB10	0CDA	0CA8,0CA9,0CC9
SWB2	0CD2	0CDF

SYMBOL	VALUE	REFERENCES
SWB3	0CD3	
SWB4	0CD4	
SWB5	0CD5	
SWB6	0CD6	
SWB7	0CD7	
SWB8	0CD8	
SWB9	0CD9	
S2	013A	0C17,0CBF
S4	0C5C	0C5A,0C7F,0C84,0C8C,0C93,0CAD
TBL	0CC5	0CA6
TEMP	0CC4	0C3E,0C48,0C4C,0C6C,0C73,0CEC,0CEE
TERM	043D	0C17
TRFX	043C	0C17
TYCT	0CCF	0C32,0CA2
TYCT1	0CD0	0C34,0CDB
T2	0C63	0C60
WCC	043A	0C17
ZERO	0437	0C17

```
0000                    ORG      *+3095              C4061001
012C         KEY   EQU    300                        C4061002
012D         CKYN  EQU    KEY+1                       C4061003
012E         SSUER EQU    CKYN+1                      C4061004
012F         SIL   EQU    SSUER+1                     C4061005
0130         SILSW EQU    SIL+1                       C4061006
0131         SCH   EQU    SILSW+1                     C4061007
0132         SER   EQU    SCH+1                       C4061008
0133         SECSU EQU    SER+1                       C4061009
0134         SKIN1 EQU    SECSU+1                     C4061010
0135         SKINO EQU    SKIN1+1                     C4061011
0136         PDKYB EQU    SKINO+1                     C4061012
0137         PHKYB EQU    PDKYB+1                     C4061013
0138         ENDO  EQU    PHKYB+1                     C4061014
013A         S2    EQU    ENDO+2                      C4061015
013E         BINRY EQU    S2+4                        C4061016
01DF         KEYIN EQU    BINRY+161                   C4061017
0437         ZERO  EQU    KEYIN+600                   C4061018
0438         BGNR  EQU    ZERO+1                      C4061019
0439         ERK   EQU    BGNR+1                      C4061020
043A         WCC   EQU    ERR+1                       C4061021
043B         MTRM  EQU    WCC+1                       C4061022
043C         TRFX  EQU    MTRM+1                      C4061023
043D         TERM  EQU    TRFX+1                      C4061024
043E         LWC   EQU    TERM+1                      C4061025
043F         LGROP EQU    LWC+1                       C4061026
0440         STBF  EQU    LGROP+1                     C4061027
0441         SRTRY EQU    STBF+1                      C4061028
0C17 0 0006  SKI1  DC     /0006                       C4061029
0C18 0 FFFF  SKI2  DC     /FFFF                       C4061030
0C19 0 0000  SKI3  DC     0                           C4061031
0C1A 0 0000  SKI4  DC     0                           C4061032
0C1B 00 4C000138 END1 BSC L  ENDO                     C4061033
0C1E    0C1B       END    END1              C406103 C4061043
```

CROSS REFERENCE LISTING

```
SYMBOL   VALUE    REFERENCES
BGNR     0438     0C17
BINRY    013E     0C17
CKYN     012D     0C17
ENDO     0138     0C17, 0C1B
END1     0C1B     0C1D
ERR      0439     0C17
KEY      012C     0C17
KEYIN    01DF     0C17
LGROP    043F     0C17
LWC      043E     0C17
MTRM     043B     0C17
PDKYB    0136     0C17
PHKYB    0137     0C17
SCH      0131     0C17
SECSU    0133     0C17
SER      0132     0C17
SIL      012F     0C17
SILSW    0130     0C17
SKINO    0135     0C17
SKIN1    0134     0C17
SKI1     0C17
SKI2     0C18
SKI3     0C19
SKI4     0C1A
SRTRY    0441
SSUER    012E     0C17
STBF     0440     0C17
S2       013A     0C17
TERM     043D     0C17
TRFX     043C     0C17
WCC      043A     0C17
ZERO     0437     0C17
```

```
0000                ORG      *+3095                          C4070001
012C        KEY     EQU      300                             C4070002
012D        CKYN    EQU      KEY+1                            C4070003
012E        SSUER   EQU      CKYN+1                           C4070004
012F        SIL     EQU      SSUER+1                          C4070005
0130        SILSW   EQU      SIL+1                            C4070006
0131        SCH     EQU      SILSW+1                          C4070007
0132        SER     EQU      SCH+1                            C4070008
0133        SECSU   EQU      SER+1                            C4070009
0134        SKIN1   EQU      SECSU+1                          C4070010
0135        SKINO   EQU      SKIN1+1                          C4070011
0136        PDKYB   EQU      SKINO+1                          C4070012
0137        PHKYB   EQU      PDKYB+1                          C4070013
0138        ENDO    EQU      PHKYB+1                          C4070014
013A        S2      EQU      ENDO+2                           C4070015
013E        BINRY   EQU      S2+4                             C4070016
01DF        KEYIN   EQU      BINRY+161                        C4070017
0437        ZERO    EQU      KEYIN+600                        C4070018
0438        BGNR    EQU      ZERO+1                           C4070019
0439        ERR     EQU      BGNR+1                           C4070020
043A        WCC     EQU      ERR+1                            C4070021
043B        MTRM    EQU      WCC+1                            C4070022
043C        TRFX    EQU      MTRM+1                           C4070023
043D        TERM    EQU      TRFX+1                           C4070024
043E        LWC     EQU      TERM+1                           C4070025
043F        LGROP   EQU      LWC+1                            C4070026
0440        STBF    EQU      LGROP+1                          C4070027
0441        SRTRY   EQU      STBF+1                           C4070028
0C17 0 0007 SKI1    DC       /0007     PID                    C4070029
0C18 0 0000 SKI2    DC       /0000     CD NO                  C4070030
0C19 0 0003 SKI3    DC       /0003     NO ENTRIES             C4070031
0C1A 00 4480012E SKI4 BSI  I SSUER     SET ERROR RETURN  SRC  C4070032
0C1C 00 4480012C      BSI  I KEY       ENTER IL          SRC  C4070033
0C1E 1 0C89           DC     SM1                               C4070034
0C1F 0 8120           DC     /8120                             C4070035
                                                              C4070036
0C20 00 4480012F      BSI  I SIL       CK INT LVL        SRC  C4070037
0C22 01 D4000C84      STO  L SWB1      SAVE                    C4070038
                                                              C4070039
0C24 00 4480012E SKI1A BSI I SSUER     SET ERROR RETURN  SRC  C4070040
0C26 00 4480012C      BSI  I KEY       ENTER ILSW        SRC  C4070041
0C28 1 0CAB           DC     SM2                               C4070042
0C29 0 8120           DC     /8120                             C4070043
                                                              C4070044
0C2A 00 44800130      BSI  I SILSW     CK ILSW BIT       SRC  C4070045
0C2C 01 D4000C65      STO  L SWB2      SAVE                    C4070046
                                                              C4070047
0C2E 00 4480012E      BSI  I SSUER     SET ERROR RETURN  SRC  C4070048
0C30 00 4480012C      BSI  I KEY       ENTER CHANNEL     SRC  C4070049
0C32 1 0CCC           DC     SM3                               C4070050
0C33 0 8110           DC     /8110                             C4070051
                                                              C4070052
0C34 00 44800131      BSI  I SCH       CK CHANNEL        SRC  C4070053
0C36 01 D4000C86      STO  L SWB3      SAVE                    C4070054
                                                              C4070055
0C38 00 4480012E      BSI  I SSUER     SET ERROR RETURN  SRC  C4070056
0C3A 00 4480012C      BSI  I KEY       IS DR 0 A 9 TRK   SRC  C4070057
0C3C 1 0CEA           DC     SM4                               C4070058
0C3D 0 8000           DC     /8000                             C4070059
                                                              C4070060
0C3E 00 4480012D      BSI  I CKYN      CK FOR Y OR N     SRC  C4070061
0C40 0 7005           MDX    SKI E     ENTRY WAS Y            C4070062
                                                              C4070063
*                       DRIVE IS 7 TRACK                      C4070064
*                                                             C4070065
0C41 01 C4000C82 SKI1B LD  L TR7       SET DR 0 = 7 TRK       C4070066
0C43 01 D4000C87      STO  L SWB4      SAVE                    C4070067
0C45 0 7004           MDX    SKI1C                             C4070068
```

```
*                                                             C4070069
*                       DRIVE IS 9 TRACK                      C4070070
*                                                             C4070071
0C46 01 C4000C83 SKI E LD  L TR9       SET DR 0 = 9 TRK       C4070072
0C48 01 D4000C87      STO  L SWB4      SAVE                    C4070073
*                                                             C4070074
0C4A 00 4480012E SKI1C BSI I SSUER     SET ERROR RETURN  SRC  C4070075
0C4C 00 4480012C      BSI  I KEY       IS DR 1 AVAIL     SRC  C4070076
0C4E 1 0D09           DC     SM5                               C4070077
0C4F 0 8000           DC     /8000                             C4070078
*                                                             C4070079
0C50 00 4480012D      BSI  I CKYN      CK FOR Y OR N     SRC  C4070080
0C52 0 7001           MDX    SKI5      ENTRY WAS Y            C4070081
0C53 0 7013           MDX    SKI F     ENTRY WAS N            C4070082
                                                              C4070083
0C54 00 4480012E SKI5 BSI  I SSUER     SET ERROR RETURN  SRC  C4070084
0C56 00 4480012C      BSI  I KEY       IS DR 1 9 TRK     SRC  C4070085
0C58 1 0D28           DC     SM5                               C4070086
0C59 0 8000           DC     /8000                             C4070087
                                                              C4070088
0C5A 00 4480012D      BSI  I CKYN      CK FOR Y OR N     SRC  C4070089
0C5C 0 7005           MDX    SK20      ENTRY WAS Y            C4070090
*                                                             C4070091
*                       DRIVE 1 IS 7 TRACK                    C4070092
*                                                             C4070093
0C5D 01 C4000C82 SKI8 LD  L TR7        SET DR 1 = 7 TRK       C4070094
0C5F 01 D4000C88      STO  L SWB5      SAVE                    C4070095
0C61 0 7009           MDX    SK21                              C4070096
*                                                             C4070097
*                       DRIVE 1 IS 9 TRACK                    C4070098
*                                                             C4070099
0C62 01 C4000C83 SK20 LD  L TR9        SET DR 1 = 9 TRK       C4070100
0C64 01 D4000C88      STO  L SWB5      SAVE                    C4070101
0C66 0 7004           MDX    SK21                              C4070102
0C67 00 C400043D SKIF LD  L TERM       SET DR 1 NOT AVAIL     C4070103
0C69 01 D4000C88      STO  L SWB5      SAVE                    C4070104
0C6B 01 65000C84 SK21 LDX L1 SWB1      BUILD DDEF             C4070105
0C6D 0 C100           LD     1 0                               C4070106
0C6E 0 F101           EOR    1 1                               C4070107
0C6F 0 F102           EOR    1 2                               C4070108
0C70 0 D100           STO    1 0       SAVE                    C4070109
*                                                             C4070110
0C71 01 C4000C87      LD   L SWB4      SET DR 0-NO TRKS       C4070111
0C73 0 D101           STO    1 1                               C4070112
*                                                             C4070113
0C74 01 C4000C88      LD   L SWB5      SET DR 1-NO TRKS       C4070114
0C76 0 D102           STO    1 2                               C4070115
*                                                             C4070116
0C77 01 66800C18      LDX  I2 SKI2     SET IXING              C4070117
0C79 01 65800C17      LDX  I1 SKI1                             C4070118
0C7B 01 67800C19      LDX  I3 SKI3                             C4070119
*                                                             C4070120
0C7D 00 44800133      BSI  I SECSU     SET CARD          SRC  C4070121
0C7F 1 0C84           DC     SWB1                              C4070122
0C80 00 4C00013A      BSC  L S2        EXIT                    C4070123
                                                              C4070124
0C82 0 0001 TR7       DC     /0001     CONSTANTS              C4070125
0C83 0 0000 TR9       DC     /0000                             C4070126
0C84 0 0000 SWB1      DC     0         ENTRY STORAGE          C4070127
0C85 0 0000 SWB2      DC     0                                 C4070128
0C86 0 0000 SWB3      DC     0                                 C4070129
0C87 0 0000 SWB4      DC     0                                 C4070130
0C88 0 0000 SWB5      DC     0                                 C4070131
*                                                             C4070132
0C89    0012 SM1      EBC    .C001 PID 07-CD 00.              C4070133
0C92    0012          EBC    . ENTER 2 DIGIT DE.              C4070134
0C9B    0012          EBC    .CIMAL INTRPT LVL F.             C4070135
                                                              C4070136
```

```
OCA4    000B          EBC   .OR MAG TAPE.                        C4070137
OCAA O  FFFF          DC    /FFFF                                C4070138
                 *                                               C4070139
OCAB    0012    SM2   EBC   .C002  PID 07-CD 00.                 C4070140
OCB4    0012          EBC   .  ENTER 2 DIGIT DE.                 C4070141
OCBD    0012          EBC   .CIMAL ILSW BIT FOR.                 C4070142
OCC6    0009          EBC   . MAG TAPE.                          C4070143
OCCB O  FFFF          DC    /FFFF                                C4070144
                 *                                               C4070145
OCCC    0012    SM3   EBC   .C003  PID 07-CD 00.                 C4070146
OCD5    0012          EBC   .  ENTER 1 DIGIT DE.                 C4070147
OCDE    0012          EBC   .CIMAL CH FOR MAG T.                 C4070148
OCE7    0003          EBC   .APE.                                C4070149
OCE9 O  FFFF          DC    /FFFF                                C4070150
                 *                                               C4070151
OCEA    0012    SM4   EBC   .C013  PID 07-CD 00.                 C4070152
OCF3    0012          EBC   . IS TAPE DR 0 A 9.                  C4070153
OCFC    0012          EBC   . TRACK DRIVE-TYPE .                C4070154
0DD5    0006          EBC   .Y OR N.                             C4070155
0DD8 O  FFFF          DC    /FFFF                                C4070156
                 *                                               C4070157
0DD9    0012    SM5   EBC   .C005  PID 07-CD 00.                 C4070158
0D12    0012          EBC   . DOES THIS SYSTEM.                 C4070159
0D1B    0012          EBC   . HAVE 2 DRS-TYPE Y.                C4070160
0D24    0005          EBC   . OR N.                              C4070161
0D27 O  FFFF          DC    /FFFF                                C4070162
                 *                                               C4070163
0D28    0012    SM6   EBC   .C013  PID 07-CD 00.                 C4070164
0D31    0012          EBC   . IS DR 1 A 9 TRK .                 C4070165
0D3A    0012          EBC   .DRIVE-TYPE Y OR N .                C4070166
0D43 O  FFFF          DC    /FFFF                                C4070167
                 *                                               C4070168
0D44 00 4C000138 END1 BSC  L  ENDO                              C4070169
0D46    0D44          END      END1                  C407016 C4070179
```

CROSS REFERENCE LISTING

```
SYMBOL   VALUE    REFERENCES
BGNR     0438     OC17
BINRY    013E     OC17
CKYN     012D     OC17,OC3E,OC50,OC5A
ENDO     0138     OC17,OC44
END1     0D44     0D46
ERR      0439     OC17
KEY      012C     OC17,OC1C,OC26,OC30,OC3A,OC4C,OC56
KEYIN    01DF     OC17
LGRGP    043F     OC17
LWC      043E     OC17
MTRM     043B     OC17
PDKYB    0136     OC17
PHKYB    0137     OC17
SCH      0131     OC17,OC34
SECSU    0133     OC17,OC7D
SER      0132     OC17
SIL      012F     OC17,OC20
SILSW    0130     OC17,OC2A
SKINO    0135     OC17
SKIN1    0134     OC17
SKI1     OC17     OC79
SKI2     OC18     OC77
SKI3     OC19     OC7B
SKI4     OC1A
SKI5     OC54     OC52
SKI8     OC5D
SKIA     OC24
SKIB     OC41
SKIC     OC4A     OC45
SKIE     OC46     OC40
SKIF     OC67     OC53
SK20     OC62     OC5C
SK21     OC6B     OC61,OC66
SM1      OC89     OC1E
SM2      OCAB     OC28
SM3      OCCC     OC32
SM4      OCEA     OC3C
SM5      0DD9     OC4E
SM6      0D28     OC58
SRTRY    0441
SSUER    012E     OC17,OC1A,OC24,OC2E,OC38,OC4A,OC54
STBF     0440     OC17
SWB1     OC84     OC22,OC68,CC7F
SWB2     OC85     OC2C
SWB3     OC86     OC36
SWB4     OC87     OC43,OC48,OC71
SWB5     OC88     OC5F,OC64,OC69,OC74
S2       013A     OC17,OC80
TERM     043D     OC17,OC67
TRFX     043C     OC17
TR7      OC82     OC41,OC5D
TR9      OC83     OC46,OC62
WCC      043A     OC17
ZERO     0437     OC17
```

```
G000                     ORG     *+3095              C4071001
012C           KEY   EQU  300                        C4071002
012D           CKYN  EQU  KEY+1                       C4071003
012E           SSUER EQU  CKYN+1                       C4071004
012F           SIL   EQU  SSUER+1                       C4071005
0130           SILSW EQU  SIL+1                       C4071006
0131           SCH   EQU  SILSW+1                       C4071007
0132           SER   EQU  SCH+1                       C4071008
0133           SECSU EQU  SER+1                       C4071009
0134           SKIN1 EQU  SECSU+1                       C4071010
0135           SKINO EQU  SKIN1+1                       C4071011
0136           PDKYB EQU  SKINO+1                       C4071012
0137           PHKYB EQU  PDKYB+1                       C4071013
0138           ENDO  EQU  PHKYB+1                       C4071014
013A           S2    EQU  ENDO+2                       C4071015
013E           BINRY EQU  S2+4                       C4071016
01DF           KEYIN EQU  BINRY+161                       C4071017
0437           ZERO  EQU  KEYIN+600                       C4071018
0438           BGNR  EQU  ZERO+                       C4071019
0439           ERR   EQU  BGNR+                       C4071020
043A           WCC   EQU  ERR+1                       C4071021
043B           MTRM  EQU  WCC+1                       C4071022
043C           TRFX  EQU  MTRM+1                       C4071023
043D           TERM  EQU  TRFX+1                       C4071024
043E           LWC   EQU  TERM+1                       C4071025
043F           LGROP EQU  LWC+1                       C4071026
0440           STBF  EQU  LGROP+1                       C4071027
0441           SRTRY EQU  STBF+1                       C4071028
0C17 0 0007    SKI1  DC   /0007                       C4071029
0C18 0 FFFF    SKI2  DC   /FFFF                       C4071030
0C19 0 0000    SKI3  DC   /0000                       C4071031
0C1A 0 0000    SKI4  DC   /0000                       C4071032
0C1B 00 4C00U138 END1 BSC L ENDO                       C4071033
0C1E    0C1B          END    END1          C407103 C4071043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17
CKYN	012D	0C17
ENDO	0138	0C17, 0C1B
END1	0C1B	0C1D
ERR	0439	0C17
KEY	012C	0C17
KEYIN	01DF	0C17
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17
PHKYB	0137	0C17
SCH	0131	0C17
SECSU	0133	0C17
SER	0132	0C17
SIL	012F	0C17
SILSW	0130	0C17
SKINO	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	
SKI2	0C18	
SKI3	0C19	
SKI4	0C1A	
SRTRY	0441	
SSUER	012E	0C17
STBF	0440	0C17
S2	013A	0C17
TERM	043D	0C17
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17

```
0000                ORG      *+3095                              C4080001
012C      KEY   EQU  300                                         C4080002
012D      CKYN  EQU  KEY+1                                       C4080003
012E      SSUER EQU  CKYN+1                                      C4080004
012F      SIL   EQU  SSUER+1                                     C4080005
0130      SILSW EQU  SIL+1                                       C4080006
0131      SCH   EQU  SILSW+1                                     C4080007
0132      SER   EQU  SCH+1                                       C4080008
0133      SECSU EQU  SER+1                                       C4080009
0134      SKIN1 EQU  SECSU+1                                     C4080010
0135      SKIN0 EQU  SKIN1+1                                     C4080011
0136      PDKYB EQU  SKIN0+1                                     C4080012
0137      PHKYB EQU  PDKYB+1                                     C4080013
0138      ENDO  EQU  PHKYB+1                                     C4080014
013A      S2    EQU  ENDO+2                                      C4080015
013E      BINKY EQU  S2+4                                        C4080016
01DF      KEYIN EQU  BINRY+161                                   C4080017
0437      ZERO  EQU  KEYIN+600                                   C4080018
0438      BGNR  EQU  ZERO+1                                      C4080019
0439      ERR   EQU  BGNR+1                                      C4080020
043A      WCC   EQU  ERR+1                                       C4080021
043B      NTRM  EQU  WCC+1                                       C4080022
043C      TRFX  EQU  MTRM+1                                      C4080023
043D      TERM  EQU  TRFX+1                                      C4080024
043E      LWC   EQU  TERM+1                                      C4080025
043F      LGROP EQU  LWC+1                                       C4080026
0440      STBF  EQU  LGROP+1                                     C4080027
0441      SRTRY EQU  STBF+1                                      C4080028
0C17 0 0008    SKI1   DC   /0008          PID                    C4080028
0C18 0 0000    SKI2   DC   /0000          CD NO                  C4080029
0C19 0 000B    SKI3   DC   /000B          NO ENTRIES             C4080030
0C1A 00 4480012E SKI4 BSI I SSUER  SET ERROR RETURN      SRC     C4080031
0C1C 00 4480012C      BSI I KEY    ENTER NO DEVICES      SRC     C4080032
0C1E 1 0E91           DC    SM10                                 C4080033
0C1F 0 8110           DC    /8110                                C4080034
       *                                                         C4080035
0C20 00 C400013E      LD   L BINRY   GET ENTRY                   C4080036
0C22 01 4C180CE6      BSC  L SKE05,+-  BRANCH IF ZERO            C4080037
0C24 01 B4000CD5      CMP  L K0003   CK MAX                      C4080038
0C26 0 7027           MDX    SKE06   BRANCH IF TOO GREAT         C4080039
0C27 0 1000           NOP    0                                   C4080040
0C28 01 D4000CD6      STO  L NODEV   SAVE ENTRY                  C4080041
0C2A 0 6303           LDX    3 3                                 C4080042
0C2B 01 65000F2D      LDX  L1 SWB1                               C4080043
0C2D 0 6203    SK00   LDX    2 3                                 C4080044
0C2E 01 6D000CC7 SK0  STX  L1 SKA1+1   SAVE IXING                C4080045
0C30 01 6E000CC9      STX  L2 SKA2+1   *                         C4080046
0C32 01 6F000CCB      STX  L3 SKA3+1   *                         C4080047
0C34 01 C4000CCE      LD   L ERRET   SET ERROR RETURN            C4080048
0C36 00 D4000441      STO  L SRTRY   *                           C4080049
0C38 01 C6000F1D      LD   L2 TBL-1  GET FORM                    C4080050
0C3A 0 D009           STO    SK2     SET                         C4080051
0C3B 01 C7000F29      LD   L3 TBL3-1 GET TBL ADRS                C4080052
0C3D 0 D001           STO    SK21+1  SET                         C4080053
0C3E 00 C6000000 SK21 LD   L2 0      GET MSG ADRS                C4080054
0C40 0 D002           STO    SK1     SET                         C4080055
0C41 00 4480012C      BSI I KEY     PRINT                 SRC    C4080056
0C43 1 0D71    SK1    DC     SM1                          SRC    C4080057
0C44 0 8120    SK2    DC    /8120                                C4080058
0C45 01 4E800CE8      BSC  I2 CK-1   CHECK DATA            SRC   C4080059
0C47 0 D100    SK20   STO    1 0     SAVE                        C4080060
0C48 0 7101           MDX    1 1     INCR IX 1                   C4080061
0C49 0 72FF           MDX    2 -1    DECR IX 2                   C4080062
0C4A 0 70E3           MDX    SK0     LOOP                        C4080063
0C4B 0 73FF    SK5    MDX    3 -1    DECR IX 3                   C4080064
0C4C 0 7004           MDX    SK4     CHECK FOR NEXT DR           C4080065
0C4D 0 7006           MDX    SK6     ALL DRS COMPLETE            C4080066
0C4E 00 44800132 SKE06 BSI I SFR    NO DRIVE GREATER 3    SRC    C4080067
```

```
0C50 1 0D54           DC     SE007                               C4080069
0C51 01 74FF0CD6 SK4  MDX  L NODEV,-1  DECR NO OF DVICES         C4080070
0C53 0 70D9           MDX    SK00    LOOP                        C4080071
0C54 01 65000F2D SK6  LDX  L1 SWB1   SET IXING                   C4080072
0C56 01 67000F2D      LDX  L3 SWB1                               C4080073
0C58 0 6203           LDX    2 3                                 C4080074
0C59 0 C100    SK7    LD     1 0     BUILD DDEFS                 C4080075
0C5A 0 F101           EOR    1 1                                 C4080076
0C5B 0 F102           EOR    1 2                                 C4080077
0C5C 0 D300           STO    3 0     SAVE                        C4080078
0C5D 0 7103           MDX    1 3     INCR IX 1                   C4080079
0C5E 0 7301           MDX    3 1     INCR IX 3                   C4080080
0C5F 0 72FF           MDX    2 -1    DECR IX 2                   C4080081
0C60 0 70F6           MDX    SK7     LOOP                        C4080082
0C61 00 4480012E      BSI I SSUER   SET ERROR RETURN      SRC    C4080083
0C63 00 4480012C      BSI I KEY     ADRS CHANGE WANTED    SRC    C4080084
0C65 1 0E82           DC     SM12                                C4080085
0C66 0 8000           DC    /8000                                C4080086
0C67 00 4480012D      BSI I CKYN    CHECK FOR Y OR N      SRC    C4080087
0C69 0 7001           MDX    SK10    ENTRY WAS Y                 C4080088
0C6A 0 7049           MDX    OUT     ENTRY WAS N                 C4080089
0C6B 00 4480012E SK10 BSI I SSUER   SET ERROR RETURN      SRC    C4080090
0C6D 00 4480012C      BSI I KEY     ENTER 3 DIGIT ADRS    SRC    C4080091
0C6F 1 0ED4           DC     SM13                                C4080092
0C70 0 8050           DC    /8050                                C4080093
0C71 00 C40001DE      LD   L KEYIN-1 GET WD CT                   C4080094
0C73 0 B058           CMP    K0056   CK FOR MAX                  C4080095
0C74 0 7062           MDX    SKE00                               C4080096
0C75 0 1000           NOP    0                                   C4080097
0C76 00 658001DE      LDX  I1 KEYIN-1 SET IXING                  C4080098
0C78 00 660001DF      LDX  L2 KEYIN                              C4080099
       *                                                         C4080100
0C7A 0 C200    SK14   LD     2 0     GET ENTRY                   C4080101
0C7B 00 D40001DF      STO  L KEYIN   MOVE                        C4080102
0C7D 00 C400043D      LD   L TERM    GET TERM                    C4080103
0C7F 00 D40001E0      STO  L KEYIN+1 SET                         C4080104
0C81 00 44800136      BSI I PDKYB   CONVERT DATA          SRC    C4080105
0C83 0 0001           DC     1                                   C4080106
0C84 0 0437           DC     ZERO                                C4080107
0C85 00 C400013E      LD   L BINRY   GET DATA                    C4080108
0C87 01 4C180CDD      BSC  L SKE02,+-  ERROR                     C4080109
0C89 0 B046           CMP    K0008   CK FOR MAX                  C4080110
0C8A 0 704F           MDX    SKE01   ERROR                       C4080111
0C8B 0 1000           NOP    0                                   C4080112
0C8C 0 D020           STO    SK13+2                              C4080113
0C8D 0 C202           LD     2 2     GET ENTRY                   C4080114
0C8E 00 D40001DF      STO  L KEYIN   MOVE DATA                   C4080115
0C90 0 C203           LD     2 3                                 C4080116
0C91 00 D40001E0      STO  L KEYIN+1                             C4080117
0C93 0 C204           LD     2 4                                 C4080118
0C94 00 D40001E1      STO  L KEYIN+2                             C4080119
       *                                                         C4080120
0C96 00 C400043D      LD   L TERM    GET TERM                    C4080121
0C98 00 D40001E2      STO  L KEYIN+3 SET                         C4080122
0C9A 00 44800136      BSI I PDKYB   CONVERT ENTRIES       SRC    C4080123
0C9C 0 0003           DC     3                                   C4080124
0C9D 0 0437           DC     ZERO                                C4080125
0C9E 00 C400013E      LD   L BINRY   GET DATA                    C4080126
0CA0 0 B031           CMP    K0089   CK FOR OK                   C4080127
0CA1 0 7002           MDX    SK11    CONTINUE CKING              C4080128
0CA2 0 1000           NOP    0                                   C4080129
0CA3 0 7007           MDX    SK13    ENTRY OK                    C4080130
0CA4 0 B02E    SK11   CMP    K0111   CK ADRS                     C4080131
0CA5 0 7002           MDX    SK12    CONTINUE CKING              C4080132
0CA6 0 703C           MDX    SKE04   ERROR                       C4080133
0CA7 0 7003           MDX    SK13    ENTRY OK                    C4080134
0CA8 0 B02B    SK12   CMP    K0202                               C4080135
0CA9 0 7036           MDX    SKE03   ERROR                       C4080136
```

```
OCAA 0  1000                NOP   0                              C4080137
OCAB 0  1003     SK13 SLA   3         MUL BY 8                   C4080138
OCAC 00 67000000      LDX   L3 0                                 C4080139
OCAE 01 D7000F37      STO   L3 SWB11                             C4080140
OCB0 0  7301          MDX   3 1                                  C4080141
OCB1 0  7206          MDX   2 6                                  C4080142
OCB2 0  71FA          MDX   1 -6                                 C4080143
OCB3 0  70C6          MDX   SK14                                 C4080144
OCB4 0  6108     OUT  LDX   1 8       SET IXING                  C4080145
OCB5 01 C5000F37 SK15 LD    L1 SWB11                             C4080146
OCB7 01 D5000F2F      STO   L1 SWB3                              C4080147
OCB9 0  71FF          MDX   1 -1      DECR IX 1                  C4080148
OCBA 0  70FA          MDX   SK15                                 C4080149
OCBB 01 65800C17      LDX   I1 SK11   SET IXING                  C4080150
OCBD 01 66800C18      LDX   I2 SK12                              C4080151
OCBF 01 67800C19      LDX   I3 SK13                              C4080152
OCC1 00 44800133      BSI   I SECSU   SET UP CARD       SRC      C4080154
OCC3 1  0F2D          DC    SWB1                                 
OCC4 00 4C00013A      BSC   L S2      EXIT                       C4080155
OCC6 00 65000000 SKA1 LDX   L1 0      RESTORE IXING              C4080156
OCC8 00 66000000 SKA2 LDX   L2 0      *                          C4080157
OCCA 00 67000000 SKA3 LDX   L3 0      *                          C4080158
OCCC 01 4C000C2E      BSC   L SK0     ERRCR RE-ENTRY             C4080159
OCCE 1  0CC6     ERRET DC   SKA1      ERRGR RETURN               C4080160
OCCF 0  0031     K0056 DC   49        CONSTANTS                  C4080161
OCD0 0  0008     K0008 DC   8                                    C4080162
OCD1 0  0657     K0657 DC   /0657                                C4080163
OCD2 0  0059     K0089 DC   89                                   C4080164
OCD3 0  006F     K0111 DC   111                                  C4080165
OCD4 0  00CA     K0202 DC   202                                  C4080166
OCD5 0  0003     K0003 DC   3                                    C4080167
OCD6 0  0000     NODEV DC   0                                    C4080168
OCD7 00 44800132 SKE00 BSI  I SER     TOO MANY ADRSS    SRC      C4080169
OCD9 1  0CF8          DC    SE001                                C4080170
OCDA 00 44800132 SKE01 BSI  I SER     FIELD TCO GREAT   SRC      C4080171
OCDC 1  0CF8          DC    SE001                                C4080172
OCDD 00 44800132 SKE02 BSI  I SER     FLD WAS ZERO      SRC      C4080173
OCDF 1  0CF8          DC    SE001                                C4080174
OCE0 00 44800132 SKE03 BSI  I SER     ADRS TCC GREAT    SRC      C4080175
OCE2 1  0D0F          DC    SE004                                C4080176
OCE3 00 44800132 SKE04 BSI  I SER     ILLEGAL ADRS      SRC      C4080177
OCE5 1  0D23          DC    SE005                                C4080178
OCE6 00 44800132 SKE05 BSI  I SER     NUMBER DRS = 0    SRC      C4080179
OCE8 1  0D3C          DC    SE006                                C4080180
OCE9 1  0CFC     CK   DC    CH                                   C4080181
OCEA 1  0CF0          DC    ILSW                                 C4080182
OCEB 1  0CF4          DC    IL                                   C4080183
OCEC 00 44800131 CH   BSI  I SCH      CK CHANNEL        SRC      C4080184
OCEE 01 4C000C47      BSC  L SK20                                C4080185
OCF0 00 44800130 ILSW BSI  I SILSW    CK ILSW BIT       SRC      C4080186
OCF2 01 4C000C47      BSC  L SK20                                C4080187
OCF4 00 4480012F IL   BSI  I SIL      CK INTR LVL       SRC      C4080188
OCF6 01 4C000C47      BSC  L SK20                                C4080189
                 *                                               C4080190
OCF8    0012     SE001 EBC  .E007 PID 08-CD 00.                  C4080191
OD01    0012          EBC   . ENTRY TOO LARGE .                  C4080192
OD0A    0007          EBC   .OR 0000.                            C4080193
OD0E 0  FFFF          DC    /FFFF                                C4080194
                 *                                               C4080195
OD0F    0012     SE004 EBC  .E00A PID 08-CD 00.                  C4080196
OD18    0012          EBC   . ADRS IS TOO GREA.                  C4080197
OD21    0001          EBC   .T.                                  C4080198
OD22 0  FFFF          DC    /FFFF                                C4080199
                 *                                               C4080200
OD23    0012     SE005 EBC  .E008 PID 08-CD 00.                  C4080201
OD2C    0012          EBC   . ADRS WAS BETWEEN.                  C4080202
OD35    000B          EBC   . 90 AND 110.                        C4080203
OD38 0  FFFF          DC    /FFFF                                C4080204
```

```
                 *                                               C4080205
OD3C    0012     SE006 EBC  .E008 PID 08-CD 00.                  C4080206
OD45    0012          EBC   . NUMBER OF DEVICE.                  C4080207
OD4E    000A          EBC   .S WAS 0000.                         C4080208
OD53 0  FFFF          DC    /FFFF                                C4080209
                 *                                               C4080210
OD54    0012     SE007 EBC  .E009 PID 08-CD 00.                  C4080211
OD5D    0012          EBC   . NUMBER OF DEVICE.                  C4080212
OD66    0012          EBC   .S WAS GREATER THAN.                 C4080213
OD6F    0002          EBC   . 3.                                 C4080214
OD70 0  FFFF          DC    /FFFF                                C4080215
                 *                                               C4080216
OD71    0012     SM1  EBC   .C001 PID 08-CD 00.                  C4080217
OD7A    0012          EBC   . ENTER 2 DIGIT DE.                  C4080218
OD83    0012          EBC   .CIMAL INTR LVL FOR.                 C4080219
OD8C    0009          EBC   . 1ST 2310.                          C4080220
OD91 0  FFFF          DC    /FFFF                                C4080221
                 *                                               C4080222
OD92    0012     SM2  EBC   .C002 PID 08-CD 00.                  C4080223
OD9B    0012          EBC   . ENTER 2 DIGIT DE.                  C4080224
ODA4    0012          EBC   .CIMAL ILSW BIT FOR.                 C4080225
ODAD    0009          EBC   . 1ST 2310.                          C4080226
ODB2 0  FFFF          DC    /FFFF                                C4080227
                 *                                               C4080228
ODB3    0012     SM3  EBC   .C003 PID 08-CD 00.                  C4080229
ODBC    0012          EBC   . ENTER 1 DIGIT DE.                  C4080230
ODC5    0012          EBC   .CIMAL CH FOR 1ST 2.                 C4080231
ODCE    0003          EBC   .310.                                C4080232
ODD0 0  FFFF          DC    /FFFF                                C4080233
                 *                                               C4080234
ODD1    0012     SM4  EBC   .C001 PID 08-CD 00.                  C4080235
ODDA    0012          EBC   . ENTER 2 DIGIT DE.                  C4080236
ODE3    0012          EBC   .CIMAL INTR LVL FOR.                 C4080237
ODEC    0009          EBC   . 2ND 2310.                          C4080238
ODF1 0  FFFF          DC    /FFFF                                C4080239
                 *                                               C4080240
ODF2    0012     SM5  EBC   .C002 PID 08-CD 00.                  C4080241
ODFB    0012          EBC   . ENTER 2 DIGIT DE.                  C4080242
OE04    0012          EBC   .CIMAL ILSW BIT FOR.                 C4080243
OE0D    0009          EBC   . 2ND 2310.                          C4080244
OE12 0  FFFF          DC    /FFFF                                C4080245
                 *                                               C4080246
OE13    0012     SM6  EBC   .C003 PID 08-CD 00.                  C4080247
OE1C    0012          EBC   . ENTER 1 DIGIT DE.                  C4080248
OE25    0012          EBC   .CIMAL CH FOR 2ND 2.                 C4080249
OE2E    0003          EBC   .310.                                C4080250
OE30 0  FFFF          DC    /FFFF                                C4080251
                 *                                               C4080252
OE31    0012     SM7  EBC   .C001 PID 08-CD 00.                  C4080253
OE3A    0012          EBC   . ENTER 2 DIGIT DE.                  C4080254
OE43    0012          EBC   .CIMAL INTR LVL FOR.                 C4080255
OE4C    0009          EBC   . 3RD 2310.                          C4080256
OE51 0  FFFF          DC    /FFFF                                C4080257
                 *                                               C4080258
OE52    0012     SM8  EBC   .C002 PID 08-CD 00.                  C4080259
OE5B    0012          EBC   . ENTER 2 DIGIT DE.                  C4080260
OE64    0012          EBC   .CIMAL ILSW BIT FOR.                 C4080261
OE6D    0009          EBC   . 3RD 2310.                          C4080262
OE72 0  FFFF          DC    /FFFF                                C4080263
                 *                                               C4080264
OE73    0012     SM9  EBC   .C003 PID 08-CD 00.                  C4080265
OE7C    0012          EBC   . ENTER 1 DIGIT DE.                  C4080266
OE85    0012          EBC   .CIMAL CH FOR 3RD 2.                 C4080267
OE8E    0003          EBC   .310.                                C4080268
OE90 0  FFFF          DC    /FFFF                                C4080269
                 *                                               C4080270
OE91    0012     SM10 EBC   .C004 PID 08-CD 00.                  C4080271
OE9A    0012          EBC   . ENTER NUMBER OF .                  C4080272
```

OEA3	0012		EBC	.2310S ON SYSTEM-FR.
OEAC	0009		EBC	.OM 1 TO 3.
OEB1 0	FFFF		DC	/FFFF
		*		
OEB2	0012	SM12 EBC		.C006 PID 08-CD 00.
OEB8	0012		EBC	. ARE ADRS REFEREN.
OEC4	0012		EBC	.CE CHANGES DESIRED.
OECD	000C		EBC	.-TYPE Y OR N.
OED3 0	FFFF		DC	/FFFF
		*		
OED4	0012	SM13 EBC		.C007 PID 08-CD 00.
OEDD	0012		EBC	. ENTER 1 DIGIT DE.
OEE6	0012		EBC	.CIMAL FLD NUMBER T.
OEEF	0012		EBC	.O BE CHANGED FOLLO.
OEF8	0012		EBC	.WED5BY 3 DIGIT DEC.
OF01	0012		EBC	.IMAL ADRS DESIRED-.
OF0A	0012		EBC	.1-8 ENTRIES IN FOL.
OF13	0012		EBC	.LOWING FORMAT5O CD.
OF1C	0002		EBC	.D..
OF1D 0	FFFF		DC	/FFFF
		*		
OF1E 0	8110	TBL DC		/8110
OF1F 0	8120		DC	/8120
OF20 0	8120		DC	/8120
		*		
OF21 1	0DB3	TBL1 DC		SM3
OF22 1	0D92		DC	SM2
OF23 1	0D71		DC	SM1
		*		
OF24 1	0E13	TBL4 DC		SM6
OF25 1	0DF2		DC	SM5
OF26 1	0DD1		DC	SM4
		*		
OF27 1	0E73	TBL5 DC		SM9
OF28 1	0E52		DC	SM8
OF29 1	0E31		DC	SM7
		*		
		*		
OF2A 1	0F26	TBL3 DC		TBL5-1
OF2B 1	0F23		DC	TBL4-1
OF2C 1	0F20		DC	TBL1-1
		*		
OF2D 0	0000	SWB1 DC		0
OF2E 0	0000	SWB2 DC		0
OF2F 0	0000	SWB3 DC		0
OF30 0	0000	SWB4 DC		0
OF31 0	0000	SWB5 DC		0
OF32 0	0000	SWB6 DC		0
OF33 0	0000	SWB7 DC		0
OF34 0	0000	SWB8 DC		0
OF35 0	0000	SWB9 DC		0
OF36 0	0000	SWB10 DC		0
OF37 0	0000	SWB11 DC		0
OF38 0	0000	SWB12 DC		/0000
OF39 0	0008	SWB13 DC		/0008
OF3A 0	0010	SWB14 DC		/0010
OF3B 0	0018	SWB15 DC		/0018
OF3C 0	0638	SWB16 DC		/0638
OF3D 0	0640	SWB17 DC		/0640
OF3E 0	0648	SWB18 DC		/0648
OF3F 0	0650	SWB19 DC		/0650
OF40 00	4C000138	END1 BSC L		END0
OF42	OF40	END		END1

C4080273
C4080274
C4080275
C4080276
C4080277
C4080278
C4080279
C4080280
C4080281
C4080282
C4080283
C4080284
C4080285
C4080286
C4080287
C4080288
C4080289
C4080290
C4080291
C4080292
C4080293
C4080294
C4080295
C4080296
C4080297
C4080298
C4080299
C4080300
C4080301
C4080302
C4080303
C4080304
C4080305
C4080306
C4080307
C4080308
C4080309
C4080310
C4080311
C4080312
C4080313
C4080314
C4080315
C4080316
C4080317
C4080318
C4080319
C4080320
C4080321
C4080322
C4080323
C4080324
C4080325
C4080326
C4080327
C4080328
C4080329
C4080330
C4080331
C4080332
C4080333
C4080334
C408033 C4080344

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0436	OC17
BINRY	013E	OC17,OC20,OC85,OC9E
CH	OCEC	OCE9
CK	OCE9	OC45
CKYN	012D	OC17,OC67
END0	0138	OC17,OF40
END1	OF40	OF42
ERR	0439	OC17
ERRET	OCCE	OC34
IL	OCF4	OCEB
ILSW	OCF0	OCEA
KEY	012C	OC17,OC1C,OC41,OC63,OC6D
KEYIN	01DF	OC17,OC71,OC76,OC78,OC7B,OC7F,OC8E,OC91,OC94,OC98
K0003	OCD5	OC24
K0008	OCD0	OC89
K0056	OCCF	OC73
K0089	OCD2	OCA0
K0111	OCD3	OCA4
K0202	OCD4	OCA8
K0657	OCD1	
LGROP	043F	OC17
LHC	043E	OC17
MTRM	043B	OC17
NODEV	OCD6	OC28,OC51
OUT	OC84	OC6A
PDKYB	0136	OC17,OC81,OC9A
PHKYB	0137	OC17
SCH	0131	OC17,OCEC
SECSU	012E	OC17,OCC1
SER	0132	OC17,OC4E,OCD7,OCDA,OCDD,OCE0,OCE3,OCE6
SE001	OCF8	OCD9,OCDC,OCDF
SE004	0D0F	OLE2
SE005	0D23	OCE5
SE006	0D3C	OCE8
SE007	0D54	OC50
SIL	012F	OC17,OCF4
SILSW	0130	OC17,OCF0
SKA1	OCC6	OC2E,OCCE
SKA2	OCC8	OC30
SKA3	OCCA	OC32
SKE00	OCD7	OC74
SKE01	OCDA	OC8A
SKE02	OCDD	OC87
SKE03	OCE0	OCA9
SKE04	OCE3	OCA6
SKE05	OCE6	OC22
SKE06	OC4E	OC26
SKIN0	0135	OC17
SKIN1	0134	OC17
SK11	OC17	OCBB
SKI2	OC18	OCBD
SKI3	OC19	OCBF
SKI4	OC1A	
SK0	OC2E	OC4A,OCCC
SK00	OC2D	OC53
SK1	OC43	OC40
SK10	OC6B	OC69
SK11	OCA4	OCA1
SK12	OCA8	OCA5
SK13	OCAB	OC8C,OCA3,OCA7
SK14	OC7A	OCB3
SK15	OCB5	OCBA
SK2	OC44	OC3A
SK20	OC47	OCEE,OCF2,OCF6
SK21	OC3E	OC3D

SK4	0C51	0C4C
SK5	0C4B	
SK6	0C54	0C4D
SK7	0C59	0C60
SM1	0D71	0C43,CF23
SM10	0E91	0C1E
SM12	0EB2	0C65
SM13	0ED4	0C6F
SM2	0D92	0F22
SM3	0DB3	0F21
SM4	0DD1	0F26
SM5	0DF2	0F25
SM6	0E13	0F24
SM7	0E31	0F29
SM8	0E52	0F28
SM9	0E73	0F27
SRTRY	0441	0C36
SSUER	012E	0C17,0C1A,0C61,0C6B
STBF	0440	0C17
SWB1	0F2D	0C28,0C54,0C56,0CC3
SWB10	0F36	
SWB11	0F37	0CAE,0CB5
SWB12	0F38	
SWB13	0F39	
SWB14	0F3A	
SWB15	0F3B	
SWB16	0F3C	
SWB17	0F3D	
SWB18	0F3E	
SWB19	0F3F	
SWB2	0F2E	
SWB3	0F2F	0CB7
SWB4	0F30	
SWB5	0F31	
SWB6	0F32	
SWB7	0F33	
SWB8	0F34	
SWB9	0F35	
S2	013A	0C17,0CC4
TBL	0F1E	0C38
TBL1	0F21	0F2C
TBL3	0F2A	0C3B
TBL4	0F24	0F2B
TBL5	0F27	0F2A
TERM	043D	0C17,0C7D,0C96
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17,0C84,0C9D

0000			ORG	*+3095		C4081001
012C		KEY	EQU	300		C4081002
012D		CKYN	EQU	KEY+1		C4081003
012E		SSUER	EQU	CKYN+1		C4081004
012F		SIL	EQU	SSUER+1		C4081005
0130		SILSW	EQU	SIL+1		C4081006
0131		SCH	EQU	SILSW+1		C4081007
0132		SER	EQU	SCH+1		C4081008
0133		SECSU	EQU	SER+1		C4081009
0134		SKIN1	EQU	SECSU+1		C4081010
C135		SKINO	EQU	SKIN1+1		C4081011
0136		PDKYB	EQU	SKINO+1		C4081012
0137		PHKYB	EQU	PDKYB+1		C4081013
0138		ENDO	EQU	PHKYB+1		C4081014
013A		S2	EQU	ENDO+2		C4081015
013E		BINRY	EQU	S2+4		C4081016
01DF		KEYIN	EQU	BINRY+161		C4081017
0437		ZERO	EQU	KEYIN+600		C4081018
0438		BGNR	EQU	ZERO+1		C4081019
0439		ERR	EQU	BGNR+1		C4081020
043A		WCC	EQU	ERR+1		C4081021
043B		MTRM	EQU	WCC+1		C4081022
043C		TRFX	EQU	MTRM+1		C4081023
043D		TERM	EQU	TRFX+1		C4081024
043E		LWC	EQU	TERM+1		C4081025
043F		LGRCP	EQU	LWC+1		C4081026
0440		STBF	EQU	LGROP+1		C4081027
0441		SRTRY	EQU	STBF+1		C4081028
0C17	0	0008	SKI1	DC	/0008	C4081029
0C18	0	FFFF	SKI2	DC	/FFFF	C4081030
0C19	0	0C00	SKI3	DC	0	C4081031
0C1A	0	0000	SKI4	DC	0	C4081032
0C1B	00	4C000138	END1	BSC	L ENDO	C4081033
0C1E		0C1B		END	END1	C408103 C4081043

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17,OC1B
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG     *+3095              C4090001
012C            KEY     EQU     300                 C4090002
012D            CKYN    EQU     KEY+1               C4090003
012E            SSUER   EQU     CKYN+1              C4090004
012F            SIL     EQU     SSUER+1             C4090005
0130            SILSW   EQU     SIL+1               C4090006
0131            SCH     EQU     SILSW+1             C4090007
0132            SER     EQU     SCH+1               C4090008
0133            SECSU   EQU     SER+1               C4090009
0134            SKIN1   EQU     SECSU+1             C4090010
0135            SKINO   EQU     SKIN1+1             C4090011
0136            PDKYB   EQU     SKINO+1             C4090012
0137            PHKYB   EQU     PDKYB+1             C4090013
0138            ENDO    EQU     PHKYB+1             C4090014
013A            S2      EQU     ENDO+2              C4090015
013E            BINRY   EQU     S2+4                C4090016
01DF            KEYIN   EQU     BINRY+161           C4090017
0437            ZERO    EQU     KEYIN+600           C4090018
0438            BGNR    EQU     ZERO+1              C4090019
0439            ERR     EQU     BGNR+1              C4090020
043A            WCC     EQU     ERR+1               C4090021
043B            MTRM    EQU     WCC+1               C4090022
043C            TRFX    EQU     MTRM+1              C4090023
043D            TERM    EQU     TRFX+1              C4090024
043E            LWC     EQU     TERM+1              C4090025
043F            LGROP   EQU     LWC+1               C4090026
0440            STBF    EQU     LGROP+1             C4090027
0441            SRTRY   EQU     STBF+1              C4090028
OC17 0  0009    SKI1    DC      /0009               C4090029
OC18 0  0000    SKI2    DC      /0000   CD NO       C4090030
OC19 0  000B    SKI3    DC      /000B   NO ENTRIES  C4090031
OC1A 00 4480012E SKI4   BSI  I  SSUER   SET ERROR RETURN   SRC  C4090032
OC1C 00 4480012C        BSI  I  KEY     ENTER NO DEVICES   SRC  C4090033
OC1E 1  0E91            DC      SM10                C4090034
OC1F 0  8110            DC      /8110               C4090035
                *                                   C4090036
OC20 00 C400013E        LD   L  BINRY   GET ENTRY   C4090037
OC22 01 4C180CE6        BSC  L  SKE05,+-  BRANCH IF ZERO   C4090038
OC24 01 B4000CD5        CMP  L  K0003   CK MAX      C4090039
OC26 0  7027            MDX     SKE06   BRANCH IF TOO GREAT   C4090040
OC27 0  1000            NOP     0                   C4090041
OC28 01 D4000CD6        STO  L  NODEV   SAVE ENTRY  C4090042
OC2A 0  6303            LDX     3 3                 C4090043
OC2B 01 65000F2D        LDX  L1 SW81               C4090044
OC2D 0  6203    SK00    LDX     2 3                 C4090045
OC2E 01 6D000CC7 SK0    STX  L1 SKA1+1  SAVE IXING  C4090046
OC30 01 6E000CC9        STX  L2 SKA2+1  *           C4090047
OC32 01 6F000CCB        STX  L3 SKA3+1  *           C4090048
OC34 01 C4000CCE        LD   L  ERRLT   SET ERROR RETURN   C4090049
OC36 00 D4000441        STO  L  SRTRY   *           C4090050
OC38 01 C6000F1D        LD   L2 TBL-1   GET FORM    C4090051
OC3A 0  D009            STO     SK2     SET         C4090052
OC3B 01 C7000F29        LD   L3 TBL3-1  GET TBL ADRS   C4090053
OC3D 0  D001            STO     SK21+1  SET         C4090054
OC3E 00 C6000000 SK21   LD   L2 0       GET MSG ADRS   C4090055
OC40 0  D002            STO     SK1     SET         C4090056
OC41 00 4480012C        BSI  I  KEY     PRINT       SRC  C4090057
OC43 1  0D71    SK1     DC      SM1                 C4090058
OC44 0  8120    SK2     DC      /8120               C4090059
OC45 01 4E800CE8        BSC  I2 CK-1    CHECK DATA  SRC  C4090060
OC47 0  D100    SK20    STO     1 0     SAVE        C4090061
OC48 0  7101            MDX     1 1     INCR IX 1   C4090062
OC49 0  72FF            MDX     2 -1    DECR IX 2   C4090063
OC4A 0  70E3            MDX     SK0     LOOP        C4090064
OC4B 0  73FF    SK5     MDX     3 -1    DECR IX 3   C4090065
OC4C 0  7004            MDX     SK4     CHECK FOR NEXT DR   C4090066
OC4D 0  7006            MDX     SK6     ALL DRS COMPLETE   C4090067
OC4E 00 44800132 SKE06  BSI  I  SER     BRANCH IF ERROR   SRC  C4090068
```

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-09-0

```
0C50 1 0D54          DC    SE007                              C4090069
0C51 01 74FF0CD6 SK4 MDX L NODEV,-1 DECR NO OF DVICES         C4090070
0C53 0 70D9          MDX   SK00     LOOP                       C4090071
0C54 01 65000F2D SK6 LDX L1 SWB1    SET IXING                  C4090072
0C56 01 6700uF2D     LDX L3 SWB1                               C4090073
0C58 0 6203          LDX   2 3                                 C4090074
0C59 0 C100      SK7 LD    1 0      BUILD DDEFS                C4090075
0C5A 0 F101          EOR   1 1                                 C4090076
0C5B 0 F102          EOR   1 2                                 C4090077
0C5C 0 D300          STO   3 0      SAVE                       C4090078
0C5D 0 7103          MDX   1 3      INCR IX 1                  C4090079
0C5E 0 7301          MDX   3 1      INCR IX 3                  C4090080
0C5F 0 72FF          MDX   2 -1     DECR IX 2                  C4090081
0C60 0 70F8          MDX   SK7      LOOP                       C4090082
0C61 00 4480012E     BSI I SSUER    SET ERROR RETURN     SRC  C4090083
0C63 00 4480012C     BSI I KEY      ADRS CHANGE WANTED   SRC  C4090084
0C65 1 0EB2          DC    SM12                               C4090085
0C66 0 8000          DC    /8000                              C4090086
0C67 00 4480012D     BSI I CKYN     CHECK FOR Y OR N     SRC  C4090087
0C69 0 7001          MDX   SK10     ENTRY WAS Y                C4090088
0C6A 0 7049          MDX   OUT      ENTRY WAS N                C4090089
               *                                              C4090090
0C6B 00 4480012E SK10 BSI I SSUER   SET ERROR RETURN     SRC  C4090091
0C6D 00 4480012C     BSI I KEY      ENTER 3 DIGIT ADRS   SRC  C4090092
0C6F 1 0ED4          DC    SM13                               C4090093
0C70 0 8050          DC    /8050                              C4090094
0C71 00 C40001DE     LD  L KEYIN-1  GET WD CT                  C4090095
0C73 0 B05B          CMP   K0056    CK FOR MAX                 C4090096
0C74 0 7062          MDX   SKE00                              C4090097
0C75 0 1000          NOP   0                                  C4090098
0C76 00 658001DE     LDX I1 KEYIN-1 SET IXING                 C4090099
0C78 00 660001DF     LDX I2 KEYIN                             C4090100
               *                                              C4090101
0C7A 0 C200      SK14 LD   2 0      GET ENTRY                  C4090102
0C7B 00 D40001DF     STO L KEYIN    MOVE                       C4090103
0C7D 00 C400043D     LD  L TERM     GET TERM                   C4090104
0C7F 00 D40001E0     STO L KEYIN+1  SET                        C4090105
0C81 00 44800136     BSI I PDKYB    CONVERT DATA         SRC  C4090106
0C83 0 0001          DC    1                                  C4090107
0C84 0 0437          DC    ZERO                               C4090108
0C85 00 C400013E     LD  L BINRY    GET DATA                   C4090109
0C87 01 4C180CDD     BSC L SKE02,+- BR IF ZERO                 C4090110
0C89 0 B046          CMP   K0008    CK FOR MAX                 C4090111
0C8A 0 704F          MDX   SKE01    ERROR                      C4090112
0C8B 0 1000          NOP   0                                  C4090113
0C8C 0 D020          STO   SK13+2                             C4090114
               *                                              C4090115
0C8D 0 C202          LD    2 2      GET ENTRY                  C4090116
0C8E 00 D40001DF     STO L KEYIN    MOVE DATA                  C4090117
0C90 0 C203          LD    2 3                                 C4090118
0C91 00 D40001E0     STO L KEYIN+1                            C4090119
0C93 0 C204          LD    2 4                                 C4090120
0C94 00 D40001E1     STO L KEYIN+2                            C4090121
               *                                              C4090122
0C96 00 C400043D     LD  L TERM     GET TERM                   C4090123
0C98 00 D40001E2     STO L KEYIN+3  SET                        C4090124
0C9A 00 44800136     BSI I PDKYB    CONVERT ENTRIES      SRC  C4090125
0C9C 0 0003          DC    3                                  C4090126
0C9D 0 0437          DC    ZERO                               C4090127
0C9E 00 C400013E     LD  L BINRY    GET DATA                   C4090128
0CA0 0 8031          CMP   K0089    CK FOR OK                  C4090129
0CA1 0 7002          MDX   SK11     CONTINUE CKING             C4090130
0CA2 0 1000          NOP   0                                  C4090131
0CA3 0 7007          MDX   SK13     ENTRY OK                   C4090132
0CA4 0 B02F      SK11 CMP  K0111    CK ADRS                    C4090133
0CA5 0 7002          MDX   SK12     CONTINUE CKING             C4090134
0CA6 0 703C          MDX   SKE04    ERROR                      C4090135
0CA7 0 7003          MDX   SK13     ENTRY OK                   C4090136
```

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-09-0

```
0CA8 0 B02A      SK12 CMP  K0202                              C4090137
0CA9 0 7036          MDX   SKE03    ERROR                      C4090138
0CAA 0 1000          NOP   0                                  C4090139
0CAB 0 1003      SK13 SLA   3       MUL BY 8                   C4090140
0CAC 01 67000000     LDX L3 0                                C4090141
0CAE 01 D7000F37     STO L3 SWB11                            C4090142
0CB0 0 7301          MDX   3 1                                 C4090143
0CB1 0 7206          MDX   2 6                                 C4090144
0CB2 0 71FA          MDX   1 -6                                C4090145
0CB3 0 70C6          MDX   SK14                                C4090146
0CB4 0 6108      OUT  LDX   1 8     SET IXING                  C4090147
0CB5 01 C5000F37 SK15 LD L1 SWB11                             C4090148
0CB7 01 D5000F2F     STO L1 SWB3                             C4090149
0CB9 0 71FF          MDX   1 -1     DECR IX 1                  C4090150
0CBA 0 70FA          MDX   SK15                                C4090151
0CBB 01 65800C17     LDX I1 SKI1    SET IXING                  C4090152
0CBD 01 66800C18     LDX I2 SKI2                             C4090153
0CBF 01 67800C19     LDX I3 SKI3                             C4090154
0CC1 00 44800133     BSI I SECSU    SET UP CARD          SRC  C4090155
0CC3 1 0F2D          DC    SWB1                               C4090156
0CC4 00 4C00013A     BSC L S2       EXIT                       C4090157
0CC6 00 65000000 SKA1 LDX L1 0      RESTORE IXING              C4090158
0CC8 00 66000000 SKA2 LDX L2 0      *                          C4090159
0CCA 00 67000000 SKA3 LDX L3 0      *                          C4090160
0CCC 01 4C000C2E     BSC L SK0      ERROR RE-ENTRY             C4090161
0CCE 1 0CC6      ERRET DC  SKA1     ERROR RETURN               C4090162
0CCF 0 0031          K0056 DC 49    CONSTANTS                  C4090163
0CD0 0 0008          K0008 DC 8                                C4090164
0CD1 0 0657          K0657 DC /0657                            C4090165
0CD2 0 0059          K0089 DC 89                               C4090166
0CD3 0 00CA          K0202 DC 202                              C4090167
0CD4 0 006F          K0111 DC 111                              C4090168
0CD5 0 0003          K0003 DC 3                                C4090169
0CD6 0 0000          NODEV DC 0                                C4090170
0CD7 00 44800132 SKE00 BSI I SER    TOO MANY ADRSS       SRC  C4090171
0CD9 1 0CF8          DC    SE001                              C4090172
0CDA 00 44800132 SKE01 BSI I SER    FIELD TCO GREAT      SRC  C4090173
0CDC 1 0CF8          DC    SE001                              C4090174
0CDD 00 44800132 SKE02 BSI I SER    FLD WAS ZERO         SRC  C4090175
0CDF 1 0CF8          DC    SE001                              C4090176
0CE0 00 44800132 SKE03 BSI I SER    ADRS TCO GREAT       SRC  C4090177
0CE2 1 0D0F          DC    SE004                              C4090178
0CE3 00 44800132 SKE04 BSI I SER    ILLEGAL ADRS         SRC  C4090179
0CE5 1 0D23          DC    SE005                              C4090180
0CE6 00 44800132 SKE05 BSI I SER    NO DR = 0            SRC  C4090181
0CE8 1 0D3C          DC    SE006                              C4090182
0CE9 1 0D0C      CK   DC    CH                                C4090183
0CEA 1 0CF0          DC    ILSW                               C4090184
0CEB 1 0CF4          DC    IL                                 C4090185
0CEC 00 44800131 CH   BSI I SCH     CK CHANNEL           SRC  C4090186
0CEE 00 4C000C47     BSC L SK20                              C4090187
0CF0 00 44800130 ILSW BSI I SILSW   CK ILSW BIT          SRC  C4090188
0CF2 00 4C000C47     BSC L SK20                              C4090189
0CF4 00 4480012F IL   BSI I SIL     CK INTR LVL          SRC  C4090190
0CF6 01 4C000C47     BSC L SK20                              C4090191
               *                                              C4090192
0CF8   0012      SE001 EBC  .E007 PID 09-CD 00.              C4090193
0D01   0012          EBC   . ENTRY TOO LARGE .               C4090194
0D0A   0007          EBC   .OR 0C00.                          C4090195
0D0E 0 FFFF          DC    /FFFF                              C4090196
               *                                              C4090197
0D0F   0012      SE004 EBC  .E00A PID 09-CD 00.              C4090198
0D18   0012          EBC   . ADRS IS TOO GREA.               C4090199
0D21   0001          EBC   .T.                                C4090200
0D22 0 FFFF          DC    /FFFF                              C4090201
               *                                              C4090202
0D23   0012      SE005 EBC  .E008 PID 09-CD 00.              C4090203
0D2C   0012          EBC   . ADRS WAS BETWEEN.               C4090204
```

```
0D35    000B            EBC    . 90 AND 110.                     C4090205
0D3B 0  FFFF            DC     /FFFF                             C4090206
                   *                                             C4090207
0D3C    0012    SE006 EBC    .E008 PID 09-CD 00.                 C4090208
0D45    0012            EBC    . NUMBER OF DEVICE.               C4090209
004E    000A            EBC    .S WAS 0000.                      C4090210
0053 0  FFFF            DC     /FFFF                             C4090211
                   *                                             C4090212
0054    0012    SE007 EBC    .E009 PID 09-CD 00.                 C4090213
005D    0012            EBC    . NUMBER OF DEVICE.               C4090214
0066    0012            EBC    .S WAS GREATER THAN.              C4090215
006F    0002            EBC    . 3.                              C4090216
0070 0  FFFF            DC     /FFFF                             C4090217
                   *                                             C4090218
0071    0012    SM1   EBC    .C001  PID 09-CD 00.                C4090219
007A    0012            EBC    . ENTER 2 DIGIT DE.               C4090220
0083    0012            EBC    .CIMAL INTR LVL FOR.              C4090221
008C    0009            EBC    . 1ST 2310.                       C4090222
0091 0  FFFF            DC     /FFFF                             C4090223
                   *                                             C4090224
0092    0012    SM2   EBC    .C002 PID 09-CD 00.                 C4090225
009B    0012            EBC    . ENTER 2 DIGIT DE.               C4090226
00A4    0012            EBC    .CIMAL ILSW BIT FOR.              C4090227
00AD    0009            EBC    . 1ST 2310.                       C4090228
00B2 0  FFFF            DC     /FFFF                             C4090229
                   *                                             C4090230
00B3    0012    SM3   EBC    .C003 PID 09-CD 00.                 C4090231
00BC    0012            EBC    . ENTER 1 DIGIT DE.               C4090232
00C5    0012            EBC    .CIMAL CH FOR 1ST 2.              C4090233
00CE    0003            EBC    .310.                             C4090234
00D0 0  FFFF            DC     /FFFF                             C4090235
                   *                                             C4090236
00D1    0012    SM4   EBC    .C001 PID 09-CD 00.                 C4090237
00DA    0012            EBC    . ENTER 2 DIGIT DE.               C4090238
00E3    0012            EBC    .CIMAL INTR LVL FOR.              C4090239
00EC    0009            EBC    . 2ND 2310.                       C4090240
00F1 0  FFFF            DC     /FFFF                             C4090241
                   *                                             C4090242
00F2    0012    SM5   EBC    .C002 PID 09-CD 00.                 C4090243
00FB    0012            EBC    . ENTER 2 DIGIT DE.               C4090244
0E04    0012            EBC    .CIMAL ILSW BIT FOR.              C4090245
0E0D    0009            EBC    . 2ND 2310.                       C4090246
0E12 0  FFFF            DC     /FFFF                             C4090247
                   *                                             C4090248
0E13    0012    SM6   EBC    .C003  PID 09-CD 00.                C4090249
0E1C    0012            EBC    . ENTER 1 DIGIT DE.               C4090250
0E25    0012            EBC    .CIMAL CH FOR 2ND 2.              C4090251
0E2E    0003            EBC    .310.                             C4090252
0E30 0  FFFF            DC     /FFFF                             C4090253
                   *                                             C4090254
0E31    0012    SM7   EBC    .C001 PID 09-CD 00.                 C4090255
0E3A    0012            EBC    . ENTER 2 DIGIT DE.               C4090256
0E43    0012            EBC    .CIMAL INTR LVL FOR.              C4090257
0E4C    0009            EBC    . 3RD 2310.                       C4090258
0E51 0  FFFF            DC     /FFFF                             C4090259
                   *                                             C4090260
0E52    0012    SM8   EBC    .C002 PID 09-CD 00.                 C4090261
0E5B    0012            EBC    . ENTER 2 DIGIT DE.               C4090262
0E64    0012            EBC    .CIMAL ILSW BIT FOR.              C4090263
0E6D    0009            EBC    . 3RD 2310.                       C4090264
0E72 0  FFFF            DC     /FFFF                             C4090265
                   *                                             C4090266
0E73    0012    SM9   EBC    .C003  PID 09-CD 00.                C4090267
0E7C    0012            EBC    . ENTER 1 DIGIT DE.               C4090268
0E85    0012            EBC    .CIMAL CH FOR 3RD 2.              C4090269
0E8E    0003            EBC    .310.                             C4090270
0E90 0  FFFF            DC     /FFFF                             C4090271
                   *                                             C4090272
```

```
0E91    0012    SM10  EBC    .C004  PID 09-CD 00.                C4090273
0E9A    0012            EBC    . ENTER NUMBER OF .               C4090274
0EA3    0012            EBC    .2310S ON SYSTEM-FR.              C4090275
0EAC    0009            EBC    .OM 1 TO 3.                       C4090276
0EB1 0  FFFF            DC     /FFFF                             C4090277
                   *                                             C4090278
0EB2    0012    SM12  EBC    .C006  PID 09-CD 00.                C4090279
0EBB    0012            EBC    . ARE ADRS REFEREN.               C4090280
0EC4    0012            EBC    .CE CHANGES DESIRED.              C4090281
0ECD    000C            EBC    .-TYPE Y OR N.                    C4090282
0ED3 0  FFFF            DC     /FFFF                             C4090283
                   *                                             C4090284
0ED4    0012    SM13  EBC    .C007  PID 09-CD 00.                C4090285
0EDD    0012            EBC    . ENTER 1 DIGIT DE.               C4090286
0EE6    0012            EBC    .CIMAL FLD NUMBER T.              C4090287
0EEF    0012            EBC    .O BE CHANGED FCLLO.              C4090288
0EF8    0012            EBC    .WEDSBY 3 DIGIT DEC.              C4090289
0F01    0012            EBC    .IMAL ADRS DESIRED-.              C4090290
0F0A    0012            EBC    .1-8 ENTRIES IN FCL.              C4090291
0F13    0012            EBC    .LOWING FORMATSD CD.              C4090292
0F1C    0002            EBC    .D..                              C4090293
0F1D 0  FFFF            DC     /FFFF                             C4090294
                   *                                             C4090295
0F1E 0  8110    TBL   DC     /8110                             C4090296
0F1F 0  8120            DC     /8120                             C4090297
0F20 0  8120            DC     /8120                             C4090298
                   *                                             C4090299
0F21 1  0DB3    TBL2  DC     SM3                               C4090300
0F22 1  0092            DC     SM2                               C4090301
0F23 1  0071            DC     SM1                               C4090302
                                                                 C4090303
0F24 1  0E13    TBL4  DC     SM6                               C4090304
0F25 1  0DF2            DC     SM5                               C4090305
0F26 1  0DD1            DC     SM4                               C4090306
                   *                                             C4090307
0F27 1  0E73    TBL5  DC     SM9                               C4090308
0F28 1  0E52            DC     SM8                               C4090309
0F29 1  0E31            DC     SM7                               C4090310
                   *                                             C4090311
0F2A 1  0F26    TBL3  DC     TBL5-1                            C4090312
0F2B 1  0F23            DC     TBL4-1                            C4090313
0F2C 1  0F20            DC     TBL1-1                            C4090314
                                                                 C4090315
0F2D 0  0000    SWB1  DC     0                                 C4090316
0F2E 0  0000    SWB2  DC     0                                 C4090317
0F2F 0  0000    SWB3  DC     0                                 C4090318
0F30 0  0000    SWB4  DC     0                                 C4090319
0F31 0  0000    SWB5  DC     0                                 C4090320
0F32 0  0000    SWB6  DC     0                                 C4090321
0F33 0  0000    SWB7  DC     0                                 C4090322
0F34 0  0000    SWB8  DC     0                                 C4090323
0F35 0  0000    SWB9  DC     0                                 C4090324
0F36 0  0000    SWB10 DC     C                                 C4090325
0F37 0  0000    SWB11 DC     C                                 C4090326
0F38 0  0000    SWB12 DC     /0000                             C4090327
0F39 0  0008    SWB13 DC     /0008                             C4090328
0F3A 0  0010    SWB14 DC     /0010                             C4090329
0F3B 0  0018    SWB15 DC     /0018                             C4090330
0F3C 0  0638    SWB16 DC     /0638                             C4090331
0F3D 0  0640    SWB17 DC     /0640                             C4090332
0F3E 0  0648    SWB18 DC     /0648                             C4090333
0F3F 0  0650    SWB19 DC     /0650                             C4090334
0F40 00 4C000138 END1 BSC  L ENDO                              C4090335
0F42    0F40            END    END1              C409033      C4090346
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17,JC20,0C85,0C9E
CH	0CEC	0CE9
CK	0CE9	0C45
CKYN	012D	0C17,0C67
ENDO	0138	0C17,0F40
END1	0F40	0F42
ERR	0439	0C17
ERRET	0CCE	0C34
IL	0CF4	0CEB
ILSW	0CF0	0CEA
KEY	012C	0C17,0C1C,0C41,0C63,0C6D
KEYIN	01DF	0C17,0C71,0C76,0C78,0C7B,0C7F,0C8E,0C91,0C94,0C98
K0003	0CD5	0C24
K0008	0CD0	0C89
K0056	0CCF	0C73
K0089	0CD2	0CA0
K0111	0CD4	0CA4
K0202	0CD3	0CA8
K0657	0CD1	
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
NODEV	0CD6	0C28,0C51
OUT	0CB4	0C6A
PDKYB	0136	0C17,0C81,0C9A
PHKYB	0137	0C17
SCH	0131	0C17,0CEC
SECSU	0133	0C17,0CC1
SER	0132	0C17,0C4E,0CD7,0CDA,0CDD,0CE0,0CE3,0CE6
SE001	0CF8	0CD9,0CDC,0CDF
SE004	0D0F	0CE2
SE005	0D23	0CE5
SE006	0D3C	0CE8
SE007	0D54	0C50
SIL	012F	0C17,0CF4
SILSW	0130	0C17,0CF0
SKA1	0CC6	0C2E,0CCE
SKA2	0CC8	0C30
SKA3	0CCA	0C32
SKE00	0CD7	0C74
SKE01	0CDA	0C8A
SKE02	0CDD	0C87
SKE03	0CE0	0CA9
SKE04	0CE3	0CA6
SKE05	0CE6	0C22
SKE06	0C4E	0C26
SKIN0	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0CBB
SKI2	0C18	0CBD
SKI3	0C19	0CBF
SKI4	0C1A	
SK0	0C2E	0C4A,0CCC
SK00	0C2D	0C53
SK1	0C43	0C40
SK10	0C6B	0C69
SK11	0CA4	0CA1
SK12	0CA8	0CA5
SK13	0CAB	0C8C,0CA3,0CA7
SK14	0C7A	0CB3
SK15	0C85	0CBA
SK2	0C44	0C3A
SK20	0C47	0CEE,0CF2,0CF6
SK21	0C3E	0C3D

SYMBOL	VALUE	REFERENCES
SK4	0C51	0C4C
SK5	0C4B	
SK6	0C54	0C4D
SK7	0C59	0C60
SM1	0D71	0C43,0F23
SM10	0E91	0C1E
SM12	0EB2	0C65
SM13	0ED4	0C6F
SM2	0D92	0F22
SM3	0DB3	0F21
SM4	0DD1	0F26
SM5	0DF2	0F25
SM6	0E13	0F24
SM7	0E31	0F29
SM8	0E52	0F28
SM9	0E73	0F27
SRTRY	0441	0C36
SSUER	012E	0C17,0C1A,0C61,0C6B
STBF	0440	0C17
SWB1	0F2D	0C28,0C54,0C56,0CC3
SWB10	0F36	
SWB11	0F37	0CAE,0C85
SWB12	0F38	
SWB13	0F39	
SWB14	0F3A	
SWB15	0F3B	
SWB16	0F3C	
SWB17	0F3D	
SWB18	0F3E	
SWB19	0F3F	
SWB2	0F2E	
SWB3	0F2F	0C87
SWB4	0F30	
SWB5	0F31	
SWB6	0F32	
SWB7	0F33	
SWB8	0F34	
SWB9	0F35	
S2	013A	0C17,0CC4
TBL	0F1E	0C38
TBL1	0F21	0F2C
TBL3	0F2A	0C3B
TBL4	0F24	0F2B
TBL5	0F27	0F2A
TERM	043D	0C17,0C7D,0C96
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17,0C84,0C9D

```
0000                    ORG      *+3095              C4091001
012C           KEY      EQU      300                 C4091002
012D           CKYN     EQU      KEY+1               C4091003
012E           SSUER    EQU      CKYN+1              C4091004
012F           SIL      EQU      SSUER+1             C4091005
0130           SILSW    EQU      SIL+1               C4091006
0131           SCH      EQU      SILSW+1             C4091007
0132           SER      EQU      SCH+1               C4091008
0133           SECSU    EQU      SER+1               C4091009
0134           SKIN1    EQU      SECSU+1             C4091010
0135           SKINO    EQU      SKIN1+1             C4091011
0136           PDKYB    EQU      SKINO+1             C4091012
0137           PHKYB    EQU      PDKYB+1             C4091013
0138           ENDO     EQU      PHKYB+1             C4091014
013A           S2       EQU      ENDO+2              C4091015
013E           BINRY    EQU      S2+4                C4091016
01DF           KEYIN    EQU      BINRY+161           C4091017
0437           ZERO     EQU      KEYIN+600           C4091018
0438           BGNR     EQU      ZERO+1              C4091019
0439           ERR      EQU      BGNR+1              C4091020
043A           WCC      EQU      ERR+1               C4091021
043B           MTRM     EQU      WCC+1               C4091022
043C           TRFX     EQU      MTRM+1              C4091023
043D           TERM     EQU      TRFX+1              C4091024
043E           LWC      EQU      TERM+1              C4091025
043F           LGRCP    EQU      LWC+1               C4091026
0440           STBF     EQU      LGROP+1             C4091027
0441           SRTRY    EQU      STBF+1              C4091028
0C17 0 0009    SKI1     DC       /0009               C4091029
0C18 0 FFFF    SKI2     DC       /FFFF               C4091030
0C19 0 0000    SKI3     DC       0                   C4091031
0C1A 0 0000    SKI4     DC       0                   C4091032
0C1B 00 4C000138 END1   BSC  L   ENDO                C4091033
0C1E    0C1B            END      END1        C409103 C4091043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17
CKYN	012D	0C17
ENDO	0136	0C17,0C1B
END1	0C1B	0C1D
ERR	0439	0C17
KEY	012C	0C17
KEYIN	01DF	0C17
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17
PHKYB	0137	0C17
SCH	0131	0C17
SECSU	0133	0C17
SER	0132	0C17
SIL	012F	0C17
SILSW	0130	0C17
SKINO	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	
SKI2	0C18	
SKI3	0C19	
SKI4	0C1A	
SRTRY	0441	
SSUER	012E	0C17
STBF	0440	0C17
S2	013A	0C17
TERM	043D	0C17
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17

```
0000              ORG      *+3095
012C      KEY    EQU      300                              C40A0001
012D      CKYN   EQU      KEY+1                            C40A0002
012E      SSUER  EQU      CKYN+1                           C40A0003
012F      SIL    EQU      SSUER+1                          C40A0004
0130      SILSW  EQU      SIL+1                            C40A0005
0131      SCH    EQU      SILSW+1                          C40A0006
0132      SER    EQU      SCH+1                            C40A0007
0133      SECSU  EQU      SER+1                            C40A0008
0134      SKIN1  EQU      SECSU+1                          C40A0009
0135      SKINO  EQU      SKIN1+1                          C40A0010
0136      PDKYB  EQU      SKINO+1                          C40A0011
0137      PHKYB  EQU      PDKYB+1                          C40A0012
0138      ENDO   EQU      PHKYB+1                          C40A0013
013A      S2     EQU      ENDO+2                           C40A0014
013E      BINRY  EQU      S2+4                             C40A0015
01DF      KEYIN  EQU      BINRY+161                        C40A0016
0437      ZERO   EQU      KEYIN+600                        C40A0017
0438      BGNR   EQU      ZERO+1                           C40A0018
0439      ERR    EQU      BGNR+1                           C40A0019
043A      WCC    EQU      ERR+1                            C40A0020
043B      MTRM   EQU      WCC+1                            C40A0021
043C      TRFX   EQU      MTRM+1                           C40A0022
043D      TERM   EQU      TRFX+1                           C40A0023
043E      LWC    EQU      TERM+1                           C40A0024
043F      LGROP  EQU      LWC+1                            C40A0025
0440      STBF   EQU      LGROP+1                          C40A0026
0441      SRTRY  EQU      STBF+1                           C40A0027
0C17 0 000A    SKI1   DC    /000A     PID                  C40A0028
0C18 0 0000    SKI2   DC    /0000     CD NO                C40A0029
0C19 0 0003    SKI3   DC    /0003     NO ENTRIES           C40A0030
0C1A 00 4480012E SKI4 BSI I SSUER   SET ERROR RETURN   SRC C40A0031
0C1C 00 4480012C      BSI I KEY     ENTER IL 1ST 1443  SRC C40A0032
0C1E 1 0C5F           DC    SM1                            C40A0033
0C1F 0 8120           DC    /8120                          C40A0034
                                                           C40A0035
0C20 00 4480012F      BSI I SIL     CK INT LVL         SRC C40A0036
0C22 01 D4000C5C      STO L SWB1    SAVE                   C40A0037
                                                           C40A0038
0C24 00 4480012E      BSI I SSUER   SET ERROR RETURN   SRC C40A0039
0C26 00 4480012C      BSI I KEY     ENTER ILSW 1ST 1443 SRC C40A0040
0C28 1 0C7F           DC    SM2                            C40A0041
0C29 0 8120           DC    /8120                          C40A0042
                                                           C40A0043
0C2A 00 44800130      BSI I SILSW   CK ILSW BIT        SRC C40A0044
0C2C 01 F4000C5C      EOR L SWB1    BUILD DDEF             C40A0045
0C2E 01 D4000C5C      STO L SWB1    SAVE                   C40A0046
                                                           C40A0047
0C30 00 4480012E      BSI I SSUER   SET ERROR RETURN   SRC C40A0048
0C32 00 4480012C      BSI I KEY     ENTER CH 1ST 1443  SRC C40A0049
0C34 1 0C9E           DC    SM3                            C40A0050
0C35 0 8110           DC    /8110                          C40A0051
                                                           C40A0052
0C36 00 44800131      BSI I SCH     CK CH NO           SRC C40A0053
0C38 01 F4000C5C      EOR L SWB1    BUILD DDEF             C40A0054
0C3A 01 D4000C5C      STO L SWB1    SAVE                   C40A0055
                                                           C40A0056
0C3C 00 4480012E      BSI I SSUER   SET ERROR RETURN   SRC C40A0057
0C3E 00 4480012C      BSI I KEY     DOES 1ST HAVE 120  SRC C40A0058
0C40 1 0CBD           DC    SM4                            C40A0059
0C41 0 8000           DC    /8000                          C40A0060
                                                           C40A0061
0C42 00 4480012D      BSI I CKYN    CK FOR Y OR N      SRC C40A0062
0C44 0 7001           MDX   SK1     ENTRY WAS Y            C40A0063
0C45 0 7003           MDX   SK2     ENTRY WAS N            C40A0064
                                                           C40A0065
0C46 0 C005    SK1    LD    K0078   GET 78                 C40A0066
0C47 0 D016           STO   SWB3    SET                    C40A0067
                                                           C40A0068
```

```
0C48 0 7005           MDX   SK3                            C40A0069
                                                           C40A0070
0C49 0 C003    SK2    LD    K0090   GET 90                 C40A0071
0C4A 0 D013           STO   SWB3    SET                    C40A0072
0C4B 0 7002           MDX   SK3                            C40A0073
                                                           C40A0074
0C4C 0 0078    K0078  DC    /0078                          C40A0075
0C4D 0 0090    K0090  DC    /0090   CONSTANTS              C40A0076
0C4E 00 C400043D SK3  LD  L TERM    GET FFFF               C40A0077
0C50 0 D00C           STO   SWB2    SET                    C40A0078
0C51 01 65800C17 SK7  LDX I1 SKI1   SET IXING              C40A0079
0C53 01 66800C18      LDX I2 SKI2                          C40A0080
0C55 01 67800C19      LDX I3 SKI3                          C40A0081
0C57 00 44800133      BSI I SECSU   SET CARD           SRC C40A0082
0C59 1 0C5C           DC    SWB1                            C40A0083
0C5A 00 4C00013A      BSC L S2      EXIT                    C40A0084
                                                            C40A0085
0C5C 0 0000    SWB1   DC    0                               C40A0086
0C5D 0 0000    SWB2   DC    0       ENTRY STORAGE           C40A0087
0C5E 0 0000    SWB3   DC    0                               C40A0088
                                                            C40A0089
0C5F   0012    SM1    EBC   .C001 PID 0A-CD 00.             C40A0090
0C68   0012           EBC   . ENTER 2 DIGIT DE.             C40A0091
0C71   0012           EBC   .CIMAL INTRPT LVL F.            C40A0092
0C7A   0007           EBC   .OR 1443.                       C40A0093
0C7E 0 FFFF           DC    /FFFF                           C40A0094
                                                            C40A0095
0C7F   0012    SM2    EBC   .C002 PID 0A-CD 00.             C40A0096
0C88   0012           EBC   . ENTER 2 DIGIT DE.             C40A0097
0C91   0012           EBC   .CIMAL ILSW BIT FOR.            C40A0098
0C9A   0005           EBC   . 1443.                         C40A0099
0C9D 0 FFFF           DC    /FFFF                           C40A0100
                                                            C40A0101
0C9E   0012    SM3    EBC   .C003 PID 0A-CD 00.             C40A0102
0CA7   0012           EBC   . ENTER 1 DIGIT DE.             C40A0103
0CB0   0012           EBC   .CIMAL CH NUMBER FO.            C40A0104
0CB9   0006           EBC   .R 1443.                        C40A0105
0CBC 0 FFFF           DC    /FFFF                           C40A0106
                                                            C40A0107
0CBD   0012    SM4    EBC   .C038 PID 0A-CD 00.             C40A0108
0CC6   0012           EBC   . DOES 1443 HAVE 1.             C40A0109
0CCF   0012           EBC   .20 PRINT POSITIONS.            C40A0110
0CD8   000C           EBC   .-TYPE Y OR N.                  C40A0111
0CDE 0 FFFF           DC    /FFFF                           C40A0112
                                                            C40A0113
0CDF 00 4C000138 END1 BSC L ENDO                            C40A0114
0CE2   0CDF           END   END1                            C40A0124
                                                C40A011 
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17
CKYN	012D	0C17,0C42
ENDO	0138	0C17,0CDF
END1	0CDF	0CE1
ERR	0439	0C17
KEY	012C	0C17,0C1C,0C26,0C32,0C3E
KEYIN	01DF	0C17
K0078	0C4C	0C46
K0090	0C4D	0C49
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17
PHKYB	0137	0C17
SCH	0131	0C17,0C36
SECSU	0133	0C17,0C57
SER	0132	0C17
SIL	012F	0C17,0C20
SILSW	0130	0C17,0C2A
SKINO	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0C51
SKI2	0C18	0C53
SKI3	0C19	0C55
SKI4	0C1A	
SK1	0046	0C44
SK2	0C49	0C45
SK3	0C4E	0C48,0C4B
SK7	0C51	
SM1	0C5F	0C1E
SM2	0C7F	0C28
SM3	0C9E	0C34
SM4	0CBD	0C40
SRTRY	0441	
SSUER	012E	0C17,0C1A,0C24,0C30,0C3C
STBF	0440	0C17
SWB1	0C5C	0C22,0C2C,0C2E,0C38,0C3A,0C59
SWB2	0C5D	0C50
SWB3	0C5E	0C47,0C4A
S2	013A	0C17,0C5A
TERM	043D	0C17,0C4E
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17

```
0000                    ORG     *+3095              C40A1001
012C         KEY    EQU     300                 C40A1002
012D         CKYN   EQU     KEY+1               C40A1003
012E         SSUER  EQU     CKYN+1              C40A1004
012F         SIL    EQU     SSUER+1             C40A1005
0130         SILSW  EQU     SIL+1               C40A1006
0131         SCH    EQU     SILSW+1             C40A1007
0132         SER    EQU     SCH+1               C40A1008
0133         SECSU  EQU     SER+1               C40A1009
0134         SKIN1  EQU     SECSU+1             C40A1010
0135         SKINO  EQU     SKIN1+1             C40A1011
0136         PDKYB  EQU     SKINO+1             C40A1012
0137         PHKYB  EQU     PDKYB+1             C40A1013
0138         ENDO   EQU     PHKYB+1             C40A1014
013A         S2     EQU     ENDO+2              C40A1015
013E         BINRY  EQU     S2+4                C40A1016
01DF         KEYIN  EQU     BINRY+161           C40A1017
0437         ZERO   EQU     KEYIN+600           C40A1018
0438         BGNR   EQU     ZERO+1              C40A1019
0439         ERR    EQU     BGNR+1              C40A1020
043A         WCC    EQU     ERR+1               C40A1021
043B         MTRM   EQU     WCC+1               C40A1022
043C         TRFX   EQU     MTRM+1              C40A1023
043D         TERM   EQU     TRFX+1              C40A1024
043E         LWC    EQU     TERM+1              C40A1025
043F         LGROP  EQU     LWC+1               C40A1026
0440         STBF   EQU     LGROP+1             C40A1027
0441         SRTKY  EQU     STBF+1              C40A1028
0C17 0  000A  SKI1  DC      /000A               C40A1029
0C18 0  FFFF  SKI2  DC      /FFFF               C40A1030
0C19 0  0000  SKI3  DC      0                   C40A1031
0C1A 0  0000  SKI4  DC      0                   C40A1032
0C1B 00 4C000138 END1 BSC L ENDO                C40A1033
0C1E    0C1B        END     END1      C40A103 C40A1043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0436	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17, OC1B
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG      *+3095                        C4080001
012C            KEY     EQU      300                           C4080002
012D            CKYN    EQU      KEY+1                          C4080003
012E            SSUER   EQU      CKYN+1                         C4080004
012F            SIL     EQU      SSUER+1                        C4080005
0130            SILSW   EQU      SIL+1                          C4080006
0131            SCH     EQU      SILSW+1                        C4080007
0132            SER     EQU      SCH+1                          C4080008
0133            SECSU   EQU      SER+1                          C4080009
0134            SKIN1   EQU      SECSU+1                        C4080010
0135            SKINO   EQU      SKIN1+1                        C4080011
0136            PDKYB   EQU      SKINO+1                        C4080012
0137            PHKYB   EQU      PDKYB+1                        C4080013
0138            ENDO    EQU      PHKYB+1                        C4080014
013A            S2      EQU      ENDO+2                         C4080015
013E            BINRY   EQU      S2+4                           C4080016
01DF            KEYIN   EQU      BINRY+161                      C4080017
0437            ZERO    EQU      KEYIN+600                      C4080018
0438            BGNR    EQU      ZERO+1                         C4080019
0439            ERR     EQU      BGNR+1                         C4080020
043A            WCC     EQU      ERR+1                          C4080021
043B            MTRM    EQU      WCC+1                          C4080022
043C            TRFX    EQU      MTRM+1                         C4080023
043D            TERM    EQU      TRFX+1                         C4080024
043E            LWC     EQU      TERM+1                         C4080025
043F            LGROP   EQU      LWC+1                          C4080026
0440            STBF    EQU      LGROP+1                        C4080027
0441            SRTRY   EQU      STBF+1                         C4080028
OC17 0  000B    SKI1    DC       /000B     PID                 C4080029
OC18 0  0000    SKI2    DC       /0000     CD NO               C4080030
OC19 0  0002    SKI3    DC       /0002     NO OF ENTRIES       C4080031
OC1A 00 4480012E SKI4   BSI  I   SSUER     SET ERROR RETURN  SRC C4080032
OC1C 00 4480012C        BSI  I   KEY       ENTER IL          SRC C4080033
OC1E 1  0D11            DC       SM1                           C4080034
OC1F 0  8120            DC       /8120                         C4080035
                   *                                           C4080036
OC20 00 4480012F        BSI  I   SIL       CK IL             SRC C4080037
OC22 01 D4000CB2        STO  L   SWB1      SAVE                 C4080038
                   *                                           C4080039
OC24 00 4480012E        BSI  I   SSUER     SET ERROR RETURN  SRC C4080040
OC26 00 4480012C        BSI  I   KEY       ENTER ILSW        SRC C4080041
OC28 1  0D32            DC       SM2                           C4080042
OC29 0  8120            DC       /8120                         C4080043
                   *                                           C4080044
OC2A 00 44800130        BSI  I   SILSW     CK ILSW BIT       SRC C4080045
OC2C 01 F4000CB2        EOR  L   SWB1      BUILD DDEF           C4080046
OC2E 01 D4000CB2        STO  L   SWB1      SAVE                 C4080047
                   *                                           C4080048
OC30 00 4480012E        BSI  I   SSUER     SET ERROR RETURN  SRC C4080049
OC32 00 4480012C        BSI  I   KEY       ENTER CH          SRC C4080050
OC34 1  0D53            DC       SM3                           C4080051
OC35 0  8210            DC       /8210                         C4080052
                   *                                           C4080053
OC36 00 44800131        BSI  I   SCH       CK CHANNEL        SRC C4080054
OC38 0  F079            EOR      SWB1      BUILD DDEF           C4080055
OC39 0  D078            STO      SWB1      SAVE                 C4080056
                   *                                           C4080057
OC3A 00 4480012E        BSI  I   SSUER     SET ERROR RETURN  SRC C4080058
OC3C 00 4480012C        BSI  I   KEY       2 DRS ON SYS      SRC C4080059
OC3E 1  0D71            DC       SM4                           C4080060
OC3F 0  8000            DC       /8000                         C4080061
                   *                                           C4080062
OC40 00 4480012D        BSI  I   CKYN      CK FOR Y OR N     SRC C4080063
OC42 0  7003            MDX      SKI       ENTRY WAS Y          C4080064
                   *                                           C4080065
OC43 0  C06A            LD       K0001     GET 1                C4080066
OC44 0  D06E            STO      SWB2      SET NOT AVAIL        C4080067
OC45 0  7002            MDX      SK2                           C4080068
```

```
0C46 0  1010        *   SK1   SLA    16           SET AVAIL              C40B0069
0C47 0  D06B                  STO    SWB2                                C40B0070
                        *                                                C40B0071
0C48 01 65800C17        SK2   LDX    I1 SKI1       SET IXING             C40B0072
0C4A 01 66800C18              LDX    I2 SKI2                             C40B0073
0C4C 01 67800C19              LDX    I3 SKI3                             C40B0074
                        *                                                C40B0075
0C4E 00 44800133              BSI    I  SECSU      SET CARD         SRC  C40B0076
0C50 1  0CB2                  DC        SWB1                             C40B0077
                        *                                                C40B0078
0C51 00 4480012E              BSI    I  SSUER      SET ERROR RETURN SRC  C40B0079
0C53 00 4480012C              BSI    I  KEY        ARE WD CT CHGS DES SRC C40B0080
0C55 1  0D92                  DC        SM5                              C40B0081
0C56 0  8000                  DC        /8000                            C40B0082
                        *                                                C40B0083
0C57 00 4480012D              BSI    I  CKYN       CK FOR Y OR N    SRC  C40B0084
0C59 0  700B                  MDX       SK4        ENTRY WAS Y           C40B0085
                        *                                                C40B0086
0C5A 01 65800C17        SK3   LDX    I1 SKI1       SET IXING             C40B0087
0C5C 01 66800CBC              LDX    I2 SKI5                             C40B0088
0C5E 01 67800CBD              LDX    I3 SKI6                             C40B0089
                        *                                                C40B0090
0C60 00 44800133              BSI    I  SECSU      SET CARD         SRC  C40B0091
0C62 1  0CB4                  DC        SWB3                             C40B0092
                        *                                                C40B0093
0C63 00 4C00013A              BSC    L  S2         EXIT                  C40B0094
                        *                                                C40B0095
0C65 00 4480012E        SK4   BSI    I  SSUER      SET ERROR RETURN SRC  C40B0096
0C67 00 4480012C              BSI    I  KEY        ENTER REC WD CT, SRC  C40B0097
0C69 1  0DB2                  DC        SM6                              C40B0098
0C6A 0  8040                  DC        /8040                            C40B0099
                        *                                                C40B0100
0C6B 00 C40001DE              LD     L  KEYIN-1    GET WD CT             C40B0101
0C6D 0  8041                  CMP       K0056      CK FOR MAX            C40B0102
0C6E 0  704F                  MDX       SKE01      ERROR-TOO MANY        C40B0103
0C6F 0  1000                  NOP       0                               C40B0104
0C70 00 650001DF              LDX    L1 KEYIN      SET IX                C40B0105
0C72 0  C100        SK5       LD     1  0          GET ENTRY             C40B0106
0C73 00 D40001DF              STO    L  KEYIN  ,   SET                   C40B0107
0C75 00 C400043D              LD     L  TERM       GET FFFF              C40B0108
0C77 00 D40001E0              STO    L  KEYIN+1    SET                   C40B0109
0C79 00 44800136              BSI    I  PDKYB      CONVERT          SRC  C40B0110
0C7B 0  0001                  DC        1                               C40B0111
0C7C 0  0437                  DC        ZERO                            C40B0112
0C7D 00 C400013E              LD     L  BINRY      GET REC NO            C40B0113
0C7F 01 4C180CC7              BSC    L  SKE05,+-   ERROR                 C40B0114
0C81 0  B02F                  CMP       K0008      CK FOR MAX            C40B0115
0C82 0  7041                  MDX       SKE04      TOO GREAT             C40B0116
0C83 0  1000                  NOP       0                               C40B0117
0C84 0  D001                  STO       SK6+1      SET                   C40B0118
0C85 00 67000000    SK6       LDX    L3 0          IX 3 = ENTRY          C40B0119
0C87 0  7102                  MDX    1  2          INCR IX 1             C40B0120
0C88 00 74FE01DE              MDX    L  KEYIN-1,-2 DECR WD CT            C40B0121
0C8A 0  7003                  MDX       SK7                             C40B0122
0C8B 00 44800132              BSI    I  SER        TOO FEW ENTRIES  SRC  C40B0123
0C8D 1  0CCA                  DC        SE001                           C40B0124
                        *                                                C40B0125
0C8E 0  C100        SK7       LD     1  0          SET ENTRIES           C40B0126
0C8F 00 D40001DF              STO    L  KEYIN                            C40B0127
0C91 0  C101                  LD     1  1                                C40B0128
0C92 00 D40001E0              STO    L  KEYIN+1                          C40B0129
0C94 0  C102                  LD     1  2                                C40B0130
0C95 00 D40001E1              STO    L  KEYIN+2                          C40B0131
0C97 0  C103                  LD     1  3                                C40B0132
0C98 00 D40001E2              STO    L  KEYIN+3                          C40B0133
0C9A 00 C400043D              LD     L  TERM                             C40B0134
0C9C 00 D40001E3              STO    L  KEYIN+4                          C40B0135
                                                                         C40B0136
```

```
0C9E 00 44800136        *     BSI    I  PDKYB      CONVERT          SRC  C40B0137
0CA0 0  0004                  DC        4                               C40B0138
0CA1 0  0437                  DC        ZERO                            C40B0139
0CA2 00 C400013E              LD     L  BINRY      CK NUMBER             C40B0140
0CA4 0  B00B                  CMP       K1000                            C40B0141
0CA5 0  701B                  MDX       SKE03      ERROR TOO GREAT       C40B0142
0CA6 0  1000                  NOP       0                               C40B0143
0CA7 01 D7000CB3              STO    L3 SWB2       SAVE ENTRY            C40B0144
0CA9 0  7105                  MDX    1  5          INCR IX 1             C40B0145
0CAA 00 74FB01DE              MDX    L  KEYIN-1,-5 DECR WD CT            C40B0146
0CAC 0  70C5                  MDX       SK5        GET NEXT              C40B0147
0CAD 0  70AC                  MDX       SK3        COMPLETE              C40B0148
                        *                                                C40B0149
0CAE 0  0001        K0001     DC        1          CONSTANTS             C40B0150
0CAF 0  0038        K0056     DC        56                               C40B0151
0CB0 0  03E8        K1000     DC        1000                             C40B0152
0CB1 0  0008        K0008     DC        8                                C40B0153
                        *                                                C40B0154
0CB2 0  0000        SWB1      DC        0                                C40B0155
0CB3 0  0000        SWB2      DC        0          DATA STORAGE          C40B0156
0CB4 0  0000        SWB3      DC        0                                C40B0157
0CB5 0  0000                  DC        0                                C40B0158
0CB6 0  0000                  DC        0                                C40B0159
0CB7 0  0000                  DC        0                                C40B0160
0CB8 0  0000                  DC        0                                C40B0161
0CB9 0  0000                  DC        0                                C40B0162
0CBA 0  0000                  DC        0                                C40B0163
0CBB 0  0000                  DC        0                                C40B0164
                        *                                                C40B0165
0CBC 0  0001        SKI5      DC        /0001      CD ONE                C40B0166
0CBD 0  0008        SKI6      DC        /0008      NO OF ENTRIES         C40B0167
                        *                                                C40B0168
0CBE 00 44800132    SKE01     BSI    I  SER        TOO MANY WD CTS  SRC  C40B0169
0CC0 1  0CCA                  DC        SE001                           C40B0170
                        *                                                C40B0171
0CC1 00 44800132    SKE03     BSI    I  SER        WD CT TOO GREAT  SRC  C40B0172
0CC3 1  0CE0                  DC        SE003                           C40B0173
                        *                                                C40B0174
0CC4 00 44800132    SKE04     BSI    I  SER        REC TOO GREAT    SRC  C40B0175
0CC6 1  0CFA                  DC        SE004                           C40B0176
                        *                                                C40B0177
0CC7 00 44800132    SKE05     BSI    I  SER        FLD WAS ZERO     SRC  C40B0178
0CC9 1  0CFA                  DC        SE004                           C40B0179
                                                                         C40B0180
0CCA   0012         SE001     EBC       .E010  PID OB-CD 00.             C40B0181
0CD3   0012                   EBC       . IMPROPER NUMBER .              C40B0182
0CDC   0006                   EBC       .OF WDS.                         C40B0183
0CDF 0 FFFF                   DC        /FFFF                            C40B0184
                        *                                                C40B0185
0CE0   0012         SE003     EBC       .E012  PID OB-CD 00.             C40B0186
0CE9   0012                   EBC       . TOO LARGE A WD C.              C40B0187
0CF2   000D                   EBC       .T-MAX IS 1000.                  C40B0188
0CF9 0 FFFF                   DC        /FFFF                            C40B0189
                        *                                                C40B0190
0CFA   0012         SE004     EBC       .E007  PID OB-CD 00.             C40B0191
0D03   0012                   EBC       . ENTRY TOO LARGE .              C40B0192
0D0C   0007                   EBC       .OR 0C00.                        C40B0193
0D10 0 FFFF                   DC        /FFFF                            C40B0194
                        *                                                C40B0195
0D11   0012         SM1       EBC       .C001  PID OB-CD 00.             C40B0196
0D1A   0012                   EBC       . ENTER 2 DIGIT DE.              C40B0197
0D23   0012                   EBC       .CIMAL INTR LVL FOR.             C40B0198
0D2C   0009                   EBC       . MAG TAPE.                      C40B0199
0D31 0 FFFF                   DC        /FFFF                            C40B0200
                        *                                                C40B0201
0D32   0012         SM2       EBC       .C002  PID OB-CD 00.             C40B0202
0D3B   0012                   EBC       . ENTER 2 DIGIT DE.              C40B0203
                                                                         C40B0204
```

0D44	0012		EBC	.CIMAL ILSW BIT FOR.		C40B0205
0D4D	0009		EBC	. MAG TAPE.		C40B0206
0D52 0	FFFF		DC	/FFFF		C40B0207
		*				C40B0208
0D53	0012	SM3	EBC	.C003 PID 08-CD 00.		C40B0209
0D5C	0012		EBC	. ENTER 1 DIGIT DE.		C40B0210
0D65	0012		EBC	.CIMAL CH FOR MAG T.		C40B0211
0D6E	0003		EBC	.APE.		C40B0212
0D70 0	FFFF		DC	/FFFF		C40B0213
		*				C40B0214
0D71	0012	SM4	EBC	.C005 PID 08-CD 00.		C40B0215
0D7A	0012		EBC	. DOES THIS SYSTEM.		C40B0216
0D83	0012		EBC	. HAVE 2 TAPE DRS-T.		C40B0217
0D8C	000A		EBC	.YPE Y OR N.		C40B0218
0D91 0	FFFF		DC	/FFFF		C40B0219
		*				C40B0220
0D92	0012	SM5	EBC	.C015 PID 08-CD 01.		C40B0221
0D9B	0012		EBC	. IS IT DESIRED TO.		C40B0222
0DA4	0012		EBC	. CHANGE WO CTS-TYP.		C40B0223
0DAD	0008		EBC	.E Y OR N.		C40B0224
0DB1 0	FFFF		DC	/FFFF		C40B0225
		*				C40B0226
0DB2	0012	SM6	EBC	.C016 PID 08-CD 01.		C40B0227
0DBB	0012		EBC	. ENTER REC TO CHA.		C40B0228
0DC4	0012		EBC	.NGE AND WO CT DESI.		C40B0229
0DCD	0012		EBC	.RED, 1-8 ENTRIES I.		C40B0230
0DD6	0012		EBC	.N FOLLOWING FCRMAT.		C40B0231
0DDF	0008		EBC	.SD DDDD,.		C40B0232
0DE3 0	FFFF		DC	/FFFF		C40B0233
0DE4 00	4C000138	END1	BSC	L	ENDO	C40B0234
0DE6	0DE4		END		END1	C40B023 C40B0244

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	0C17
BINRY	013E	0C17,0C7D,0CA2
CKYN	012D	0C17 0C40,0C57
ENDO	0138	0C17,0DE4
END1	0DE4	0DE6
ERR	0439	0C17
KEY	012C	0C17,0C1C,0C26,0C32,0C3C,0C53,0C67
KEYIN	01DF	0C17,0C68,0C70,0C73,0C77,0C88,0C8F,0C92,0C95,0C98,
		0C9C,0CAA
K0001	0CAE	0C43
K0008	0CB1	0C81
K0056	0CAF	0C6D
K1000	0CB0	0CA4
LGROP	043F	0C17
LWC	043E	0C17
MTRM	043B	0C17
PDKYB	0136	0C17,0C79,0C9E
PHKYB	0137	0C17
SCH	0131	0C17,0C36
SECSU	0133	0C17,0C4E,0C60
SER	0132	0C17,0C88,0CBE,0CC1,0CC4,0CC7
SE001	0CCA	0C8D,0CC0
SE003	0CE0	0CC3
SE004	0CFA	0CC6,0CC9
SIL	012F	0C17,0C20
SILSW	0130	0C17,0C2A
SKE01	0CBE	0C6E
SKE03	0CC1	0CA5
SKE04	0CC4	0C82
SKE05	0CC7	0C7F
SKIN0	0135	0C17
SKIN1	0134	0C17
SKI1	0C17	0C48,0C5A
SKI2	0C18	0C4A
SKI3	0C19	0C4C
SKI4	0C1A	
SKI5	0CBC	0C5C
SKI6	0CBD	0C5E
SK1	0C46	0C42
SK2	0C48	0C45
SK3	0C5A	0CAD
SK4	0C65	0C59
SK5	0C72	0CAC
SK6	0C85	0C84
SK7	0C8E	0C8A
SM1	0D11	0C1E
SM2	0D32	0C28
SM3	0D53	0C34
SM4	0D71	0C3E
SM5	0D92	0C55
SM6	0DB2	0C69
SRTRY	0441	
SSUER	012E	0C17,0C1A,0C24,0C30,0C3A,0C51,0C65
STBF	0440	0C17
SWB1	0CB2	0C22,0C2C,0C2E,0C38,0C39,0C50
SWB2	0CB3	0C44,0C47,0CA7
SWB3	0CB4	0C62
S2	013A	0C17,0C63
TERM	043D	0C17,0C75,0C9A
TRFX	043C	0C17
WCC	043A	0C17
ZERO	0437	0C17,0C7C,0CA1

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-0B-1

```
0000                    ORG      *+3095                    C40B1001
012C         KEY    EQU  300                               C40B1002
012D         CKYN   EQU  KEY+1                             C40B1003
012E         SSUER  EQU  CKYN+1                            C40B1004
012F         SIL    EQU  SSUER+1                           C40B1005
0130         SILSW  EQU  SIL+1                             C40B1006
0131         SCH    EQU  SILSW+1                           C40B1007
0132         SER    EQU  SCH+1                             C40B1008
0133         SECSU  EQU  SER+1                             C40B1009
0134         SKIN1  EQU  SECSU+1                           C40B1010
0135         SKINO  EQU  SKIN1+1                           C40B1011
0136         PDKYB  EQU  SKINO+1                           C40B1012
0137         PHKYB  EQU  PDKYB+1                           C40B1013
0138         ENDO   EQU  PHKYB+1                           C40B1014
013A         S2     EQU  ENDO+2                            C40B1015
013E         BINRY  EQU  S2+4                              C40B1016
01DF         KEYIN  EQU  BINRY+161                         C40B1017
0437         ZERO   EQU  KEYIN+600                         C40B1018
0438         BGNR   EQU  ZERO+1                            C40B1019
0439         ERR    EQU  BGNR+1                            C40B1020
043A         WCC    EQU  ERR+1                             C40B1021
043B         MTRM   EQU  WCC+1                             C40B1022
043C         TRFX   EQU  MTRM+1                            C40B1023
043D         TERM   EQU  TRFX+1                            C40B1024
043E         LWC    EQU  TERM+1                            C40B1025
043F         LGROP  EQU  LWC+1                             C40B1026
0440         STBF   EQU  LGROP+1                           C40B1027
0441         SRTRY  EQU  STBF+1                            C40B1028
OC17 0  0008 SKI1   DC   /000B                             C40B1029
OC18 0  FFFF SKI2   DC   /FFFF                             C40B1030
OC19 0  0000 SKI3   DC   0                                 C40B1031
OC1A 0  0000 SKI4   DC   0                                 C40B1032
OC1B 00 4C000138 END1  BSC  L  ENDO                        C40B1033
OC1E    OC1B        END     END1          C40B103 C40B1043
```

CPIO-DIAG MON SKELETONS   SKELETON ID-08C4-0B-1

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0136	OC17, OC18
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG     **3095
012C   .         KEY    EQU     300                              C40F0001
012D          CKYN      EQU     KEY+1                            C40F0002
012E          SSJER     EQU     CKYN+1                           C40F0003
012F          SIL       EQU     SSUER+1                          C40F0004
0130          SILSW     EQU     SIL+1                            C40F0005
0131          SCH       EQU     SILSW+1                          C40F0006
0132          SER       EQU     SCH+1                            C40F0007
0133          SECSU     EQU     SER+1                            C40F0008
0134          SKINI     EQU     SECSU+1                          C40F0009
0135          SKINO     EQU     SKINI+1                          C40F0010
0136          PDKYB     EQU     SKINO+1                          C40F0011
0137          PHKYB     EQU     PDKYB+1                          C40F0012
0138          ENDO      EQU     PHKYB+1                          C40F0013
013A          S2        EQU     ENDO+2                           C40F0014
013E          BINRY     EQU     S2+4                             C40F0015
01DF          KEYIN     EQU     BINRY+161                        C40F0016
0437          ZERO      EQU     KEYIN+600                        C40F0017
0438          BGNR      EQU     ZERO+1                           C40F0018
0439          ERR       EQU     BGNR+1                           C40F0019
043A          WCC       EQU     ERR+1                            C40F0020
043B          MTRM      EQU     WCC+1                            C40F0021
043C          TRFX      EQU     MTRM+1                           C40F0022
043D          TERM      EQU     TRFX+1                           C40F0023
043E          LWC       EQU     TERM+1                           C40F0024
043F          LGROP     EQU     LWC+1                            C40F0025
0440          STBF      EQU     LGROP+1                          C40F0026
0441          SRTRY     EQU     STBF+1                           C40F0027
0C17 0  000F   SKI1     DC      /000F                            C40F0028
0C18 0  0000   SKI2     DC      /0000   PID                      C40F0029
0C19 0  0002   SKI3     DC      /0002   CD NO                    C40F0030
0C1A 00 4480012E SKI4   BSI  I  SSUER   NO ENTRIES          SRC  C40F0031
0C1C 00 4480012C        BSI  I  KEY     SET ERROR RETURN    SRC  C40F0032
0C1E 1  0C76            DC       SM1     ENTER IL 1ST        SRC  C40F0033
0C1F 0  8120            DC       /8120                            C40F0034
        *                                                        C40F0035
0C20 00 4480012F        BSI  I  SIL     CHECK INT LVL       SRC  C40F0036
0C22 01 D4000D56        STO  L  SWB1    SAVE                     C40F0037
        *                                                        C40F0038
0C24 00 4480012E        BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0039
0C26 00 4480012C        BSI  I  KEY     ENTER ILSW 1ST      SRC  C40F0040
0C28 1  0C97            DC       SM2                         SRC  C40F0041
0C29 0  8120            DC       /8120                            C40F0042
        *                                                        C40F0043
0C2A 00 4480012F        BSI  I  SILSW   CK ILSW BIT         SRC  C40F0044
0C2C 01 F4000D56        EOR  L  SWB1    BUILD DDEF               C40F0045
0C2E 01 D4000D56        STO  L  SWB1    SAVE                     C40F0046
        *                                                        C40F0047
0C30 00 4480012E        BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0048
0C32 00 4480012C        BSI  I  KEY     ENTER CH 1ST        SRC  C40F0049
0C34 1  0C88            DC       SM3                         SRC  C40F0050
0C35 0  8210            DC       /8210                            C40F0051
        *                                                        C40F0052
0C36 00 44800131        BSI  I  SCH     CK CHANNEL          SRC  C40F0053
0C38 01 F4000D56        EOR  L  SWB1    BUILD DDEF               C40F0054
0C3A 01 D4000D56        STO  L  SWB1    SAVE                     C40F0055
        *                                                        C40F0056
0C3C 00 4480012E        BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0057
0C3E 00 4480012C        BSI  I  KEY     IS 2ND ON SYSTEM    SRC  C40F0058
0C40 1  0CD6            DC       SM4                         SRC  C40F0059
0C41 0  8000            DC       /8000                            C40F0060
        *                                                        C40F0061
0C42 00 4480012D        BSI  I  CKYN    CK FOR Y OR N       SRC  C40F0062
0C44 0  7001            MDX      SK1     ENTRY WAS Y              C40F0063
0C45 0  702D            MDX      SK2     ENTRY WAS N              C40F0064
        *                                                        C40F0065
0C46 00 4480012E SK1    BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0066
0C48 00 4480012C        BSI  I  KEY     ENTER IL 2ND        SRC  C40F0067
                                                                 C40F0068
```

```
0C4A 1  0CF6            DC       SM5                              
0C4B 0  8120            DC       /8120                            C40F0069
        *                                                        C40F0070
0C4C 00 4480012F        BSI  I  SIL     CK INT LVL          SRC  C40F0071
0C4E 01 D4000D57        STO  L  SWB2    SAVE                     C40F0072
        *                                                        C40F0073
0C50 00 4480012E        BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0074
0C52 00 4480012C        BSI  I  KEY     ENTER ILSW 2ND      SRC  C40F0075
0C54 1  0D17            DC       SM6                         SRC  C40F0076
0C55 0  8120            DC       /8120                            C40F0077
        *                                                        C40F0078
0C56 00 44800130        BSI  I  SILSW   CK ILSW BIT         SRC  C40F0079
0C58 01 F4000D57        EOR  L  SWB2    BUILD DDEF               C40F0080
0C5A 01 D4000D57        STO  L  SWB2    SAVE                     C40F0081
        *                                                        C40F0082
0C5C 00 4480012E        BSI  I  SSUER   SET ERROR RETURN    SRC  C40F0083
0C5E 00 4480012C        BSI  I  KEY     ENTER CH 2ND        SRC  C40F0084
0C60 1  0D38            DC       SM7                         SRC  C40F0085
0C61 0  8210            DC       /8210                            C40F0086
        *                                                        C40F0087
0C62 00 44800131        BSI  I  SCH     CK CHANNEL          SRC  C40F0088
0C64 01 F4000D57        EOR  L  SWB2    BUILD DDEF               C40F0089
0C66 01 D4000D57        STO  L  SWB2    SAVE                     C40F0090
        *                                                        C40F0091
0C68 01 65800C17 SK3    LDX  I1  SKI1   SET IXING                C40F0092
0C6A 01 6680UC18        LDX  I2  SKI2                            C40F0093
0C6C 01 67800C19        LDX  I3  SKI3                            C40F0094
        *                                                        C40F0095
0C6E 00 44800133        BSI  I  SECSU   SET CARD            SRC  C40F0096
0C70 1  0D56            DC       SWB1                             C40F0097
        *                                                        C40F0098
0C71 01 4C00013A        BSC  L  S2      EXIT                     C40F0099
        *                                                        C40F0100
0C73 01 74FF0C19 SK2    MDX  L  SKI3,-1 DECR NO ENTRIES          C40F0101
0C75 0  70F2            MDX      SK3                              C40F0102
                                                                 C40F0103
0C76    0012     SM1    EBC     .C001 PID OF-CD 00.              C40F0104
0C7F    0012            EBC     . ENTER 2 DIGIT DE.              C40F0105
0C88    0012            EBC     .CIMAL INTR LVL FOR.             C40F0106
0C91    0009            EBC     . 1ST 1442.                      C40F0107
0C96 0  FFFF            DC       /FFFF                            C40F0108
        *                                                        C40F0109
0C97    0012     SM2    EBC     .C002 PID OF-CD 00.              C40F0110
0CA0    0012            EBC     . ENTER 2 DIGIT DE.              C40F0111
0CA9    0012            EBC     .CIMAL ILSW BIT FOR.             C40F0112
0CB2    0009            EBC     . 1ST 1442.                      C40F0113
0CB7 0  FFFF            DC       /FFFF                            C40F0114
        *                                                        C40F0115
0CB8    0012     SM3    EBC     .C003 PID OF-CD 00.              C40F0116
0CC1    0012            EBC     . ENTER 1 DIGIT DE.              C40F0117
0CCA    0012            EBC     .CIMAL CH FOR 1ST 1.             C40F0118
0CD3    0003            EBC     .442.                            C40F0119
0CD5 0  FFFF            DC       /FFFF                            C40F0120
        *                                                        C40F0121
0CD6    0012     SM4    EBC     .C005 PID OF-CD 00.              C40F0122
0CDF    0012            EBC     . DOES THIS SYSTEM.              C40F0123
0CE8    0012            EBC     . HAVE 2 1442S-TYPE.             C40F0124
0CF1    0007            EBC     . Y OR N.                        C40F0125
0CF5 0  FFFF            DC       /FFFF                            C40F0126
        *                                                        C40F0127
0CF6    0012     SM5    EBC     .C001 PID OF-CD 00.              C40F0128
0CFF    0012            EBC     . ENTER 2 DIGIT DE.              C40F0129
0D08    0012            EBC     .CIMAL INTR LVL FOR.             C40F0130
0D11    0009            EBC     . 2ND 1442.                      C40F0131
0D16 0  FFFF            DC       /FFFF                            C40F0132
        *                                                        C40F0133
0D17    0012     SM6    EBC     .C002 PID OF-CD 00.              C40F0134
0D20    0012            EBC     . ENTER 2 DIGIT DE.              C40F0135
                                                                 C40F0136
```

```
0D29   0012          EBC    .CIMAL ILSW BIT FOR.        C40F0137
0D32   0009          EBC    . 2ND 1442.                 C40F0138
0D37 0 FFFF          DC     /FFFF                       C40F0139
                *                                       C40F0140
0D38   0012   SM7    EBC    .C003  PID OF-CD GO.        C40F0141
0D41   0012          EBC    . ENTER 1 DIGIT DE.         C40F0142
0D4A   0012          EBC    .CIMAL CH FOR 2ND 1.        C40F0143
0D53   0003          EBC    .442.                       C40F0144
0D55 0 FFFF          DC     /FFFF                       C40F0145
                *                                       C40F0146
                                                        C40F0147
0D56 0 0000   SWB1   DC     0          DDEF STORAGE     C40F0148
0D57 0 0000   SWB2   DC     0                           C40F0149
0D58 00 4C000138 END1 BSC  L  ENDO                      C40F0150
0D5A   0D56          END    END1              C40F015 C40F0160
```

CROSS REFERENCE LISTING

```
SYMBOL  VALUE   REFERENCES
BGNR    0438    0C17
BINRY   013E    0C17
CKYN    012D    0C17,0C42
ENDO    0138    0C17,0D58
END1    0D58    0D5A
ERR     0439    0C17
KEY     012C    0C17,0C1C,0C26,0C32,0C3E,0C48,0C52,0C5E
KEYIN   01DF    0C17
LGROP   043F    0C17
LWC     043E    0C17
MTRM    043B    0C17
PDKYB   0136    0C17
PHKYB   0137    0C17
SCH     0131    0C17,0C36,0C62
SECSU   0133    0C17,0C6E
SER     0132    0C17
SIL     012F    0C17,0C20,0C4C
SILSW   0130    0C17,0C2A,0C56
SKINO   0135    0C17
SKIN1   0134    0C17
SKI1    0C17    0C68
SKI2    0C18    0C6A
SKI3    0C19    0C6C,0C73
SKI4    0C1A
SK1     0C46    0C44
SK2     0C73    0C45
SK3     0C68    0C75
SM1     0C76    0C1E
SM2     0C97    0C28
SM3     0C88    0C34
SM4     0CD6    0C40
SM5     0CF6    0C4A
SM6     0D17    0C54
SM7     0D38    0C60
SRTRY   0441
SSUER   012E    0C17,0C1A,0C24,0C30,0C3C,0C46,0C50,0C5C
STBF    0440    0C17
SWB1    0D56    0C22,0C2C,0C2E,0C38,0C3A,0C70
SWB2    0D57    0C4E,0C58,0C5A,0C64,0C66
S2      013A    0C17,0C71
TERM    043D    0C17
TRFX    043C    0C17
WCC     043A    0C17
ZERO    0437    0C17
```

```
0000              ORG      *+3095              C40F1001
012C     KEY     EQU      300                 C40F1002
012D     CKYN    EQU      KEY+1               C40F1003
012E     SSUEF   EQU      CKYN+1              C40F1004
012F     SIL     EQU      SSUER+1             C40F1005
0130     SILSW   EQU      SIL+1               C40F1006
0131     SCH     EQU      SILSW+1             C40F1007
0132     SER     EQU      SCH+1               C40F1008
0133     SECSU   EQU      SER+1               C40F1009
0134     SKIN1   EQU      SECSU+1             C40F1010
0135     SKINO   EQU      SKIN1+1             C40F1011
0136     PDKYB   EQU      SKINO+1             C40F1012
0137     PHKYB   EQU      PDKYB+1             C40F1013
0138     ENDO    EQU      PHKYB+1             C40F1014
013A     S2      EQU      ENDO+2              C40F1015
013E     BINRY   EQU      S2+4                C40F1016
01DF     KEYIN   EQU      BINRY+161           C40F1017
0437     ZERO    EQU      KEYIN+600           C40F1018
0438     BGNR    EQU      ZERO+1              C40F1019
0439     ERR     EQU      BGNR+1              C40F1020
043A     WCC     EQU      ERR+1               C40F1021
043B     MTRM    EQU      WCC+1               C40F1022
043C     TRFX    EQU      MTRM+1              C40F1023
043D     TERM    EQU      TRFX+1              C40F1024
043E     LWC     EQU      TERM+1              C40F1025
043F     LGROP   EQU      LWC+1               C40F1026
0440     STBF    EQU      LGROP+1             C40F1027
0441     SRTRY   EQU      STBF+1              C40F1028
OC17 0   000F    SKI1    DC       /000F       C40F1029
OC18 0   FFFF    SKI2    DC       /FFFF       C40F1030
OC19 0   0000    SKI3    DC       0           C40F1031
OC1A 0   0000    SKI4    DC       0           C40F1032
OC1B 00  4C000138 END1   BSC   L  ENDO        C40F1033
OC1E     OC1B            END      END1    C40F103 C40F1043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17,OC1B
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000              ORG      **3095
012C       KEY    EQU      300                              C4280001
012D       CKYN   EQU      KEY+1                             C4280002
012E       SSUER  EQU      CKYN+1                            C4280003
012F       SIL    EQU      SSUER+1                           C4280004
0130       SILSW  EQU      SIL+1                             C4280005
0131       SCH    EQU      SILSW+1                           C4280006
0132       SER    EQU      SCH+1                             C4280007
0133       SECSU  EQU      SER+1                             C4280008
0134       SKIN1  EQU      SECSU+1                           C4280009
0135       SKINO  EQU      SKIN1+1                           C4280010
0136       PDKYB  EQU      SKINO+1                           C4280011
0137       PHKYB  EQU      PDKYB+1                           C4280012
0138       ENDO   EQU      PHKYB+1                           C4280013
013A       S2     EQU      ENDO+2                            C4280014
013E       BINRY  EQU      S2+4                              C4280015
01DF       KEYIN  EQU      BINRY+161                         C4280016
0437       ZERO   EQU      KEYIN+600                         C4280017
0438       BGNR   EQU      ZERO+1                            C4280018
0439       ERR    EQU      BGNR+1                            C4280019
043A       WCC    EQU      ERR+1                             C4280020
043B       MTRM   EQU      WCC+1                             C4280021
043C       TRFX   EQU      MTRM+1                            C4280022
043D       TERM   EQU      TRFX+1                            C4280023
043E       LWC    EQU      TERM+1                            C4280024
043F       LGROP  EQU      LWC+1                             C4280025
0440       STBF   EQU      LGROP+1                           C4280026
0441       SRTRY  EQU      STBF+1                            C4280027
0C17 0 0028 SKI1   DC       /0028     PID                    C4280028
0C18 0 0000 SKI2   DC       /0000     CD NO                  C4280029
0C19 0 0002 SKI3   DC       /0002     NO ENTRIES             C4280030
0C1A 00 4480012E SKI4 BSI I SSUER   SET ERROR CONTROL  SRC   C4280031
0C1C 00 4480012C     BSI I KEY      ENTER IL           SRC   C4280032
0C1E 1 0C53          DC    SM1                                C4280033
0C1F 0 8120          DC    /8120                              C4280034
                                                             C4280035
0C20 00 4480012F     BSI I SIL      CK INTR LVL        SRC   C4280036
0C22 0 D02E          STO   SWB1     SAVE                     C4280037
                                                             C4280038
0C23 00 4480012E     BSI I SSUER    SET ERROR RETURN   SRC   C4280039
0C25 00 4480012C     BSI I KEY      ILSW BIT           SRC   C4280040
0C27 1 0C77          DC    SM2                                C4280041
0C28 0 8120          DC    /8120                              C4280042
                                                             C4280043
0C29 00 44800130     BSI I SILSW    CK ILSW BIT        SRC   C4280044
0C2B 0 F025          EOR   SWB1     BUILD DDEF              C4280045
0C2C 0 D024          STO   SWB1     SAVE                     C4280046
                                                             C4280047
0C2D 00 4480012E     BSI I SSUER    SET ERROR RETURN   SRC   C4280048
0C2F 00 4480012C     BSI I KEY      ENTER CH           SRC   C4280049
0C31 1 0C9B          DC    SM3                                C4280050
0C32 0 8210          DC    /8210                              C4280051
                                                             C4280052
0C33 00 44800131     BSI I SCH      CK CHANNEL         SRC   C4280053
0C35 0 F01B          EOR   SWB1     BUILD DDEF              C4280054
0C36 0 D01A          STO   SWB1     SAVE                     C4280055
                                                             C4280056
0C37 00 4480012E     BSI I SSUER    SET ERROR RETURN   SRC   C4280057
0C39 00 4480012C     BSI I KEY      IS MEM SPEED 2 MIC SRC   C4280058
0C3B 1 0CBC          DC    SM4                                C4280059
0C3C 0 8000          DC    /8000                              C4280060
                                                             C4280061
0C3D 00 4480012D     BSI I CKYN     CK FOR Y OR N      SRC   C4280062
0C3F 0 7001          MDX   SK2      ENTRY WAS Y              C4280063
0C40 0 7002          MDX   SK1      ENTRY WAS N              C4280064
                                                             C4280065
0C41 0 1010 SK2      SLA   16       CLEAR ACCUM             C4280066
0C42 0 7001          MDX   SK3                                C4280067
                                                             C4280068
```

```
0C43 0 C0GC SK1  LD    K0001    GET 1               C4280069
0C44 0 D00D SK3  STO   SWB2     SET MEM SPEED       C4280070
                                                    C4280071
0C45 01 65800C17    LDX  11 SKI1   SET IXING        C4280072
0C47 01 66800C18    LDX  12 SKI2                    C4280073
0C49 01 67800C19    LDX  13 SKI3                    C4280074
                                                    C4280075
CC4B 00 44800133    BSI  I SECSU   SET CARD         C4280076
0C4D 1 0C51         DC    SWB1                 SRC  C4280077
                                                    C4280078
0C4E 00 4C00013A    BSC  L S2      EXIT             C4280079
                                                    C4280080
0C50 0 0001 K0001 DC   1       CONSTANT            C4280081
                                                    C4280082
0C51 0 0000 SWB1  DC   0       DATA STORAGE        C4280083
0C52 0 0000 SWB2  DC   0                            C4280084
                                                    C4280085
0C53    0012 SM1  EBC  .C001 PID 28-CD 00.         C4280086
0C5C    0012      EBC  . ENTER 2 DIGIT DE.         C4280087
0C65    0012      EBC  .CIMAL INTR LVL FOR.        C4280088
0C6E    000F      EBC  . 360 CH ADAPTER.          C4280089
0C76 0  FFFF      DC   /FFFF                       C4280090
                                                    C4280091
0C77    0012 SM2  EBC  .C002 PID 28-CD 00.         C4280092
0C80    0012      EBC  . ENTER 2 DIGIT DE.         C4280093
0C89    0012      EBC  .CIMAL ILSW BIT FOR.        C4280094
0C92    000F      EBC  . 360 CH ADAPTER.          C4280095
0C9A 0  FFFF      DC   /FFFF                       C4280096
                                                    C4280097
CC9B    0012 SM3  EBC  .C003 PID 28-CD 00.         C4280098
0CA4    0012      EBC  . ENTER 1 DIGIT DE.         C4280099
0CAD    0012      EBC  .CIMAL CH FOR 360 C.        C4280100
0CB6    0009      EBC  .H ADAPTER.                 C4280101
CCBB 0  FFFF      DC   /FFFF                       C4280102
                                                    C4280103
0C8C    0012 SM4  EBC  .C010 PID 28-CD 00.         C4280104
0CC5    0012      EBC  . IS MEM SPEED FOR.         C4280105
0CCE    0012      EBC  . THIS SYS 2 MICRSE.        C4280106
0CD7    000D      EBC  .C-TYPE Y OR N.             C4280107
0CDE 0  FFFF      DC   /FFFF                       C4280108
0CDF 00 4C000138 END1 BSC L ENDO                   C4280109
0CE2    0CDF      END  END1                        C4280110
                                              C428011 C4280120
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17,OC3D
ENDO	0138	OC17,OCDF
END1	OCDF	OCE1
ERR	0439	OC17
KEY	012C	OC17,OC1C,OC25,OC2F,OC39
KEYIN	01DF	OC17
K0001	OC50	OC43
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17,OC33
SECSU	0133	OC17,OC4B
SER	0132	OC17
SIL	012F	OC17,OC20
SILSW	0130	OC17,OC29
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	OC45
SKI2	OC18	OC47
SKI3	OC19	OC49
SKI4	OC1A	
SK1	OC43	OC40
SK2	OC41	OC3F
SK3	OC44	OC42
SM1	OC53	OC1E
SM2	OC77	OC27
SM3	OC9B	OC31
SM4	OCBC	OC38
SRTRY	0441	
SSUER	012E	OC17,OC1A,OC23,OC2D,OC37
STBF	0440	OC17
SWB1	OC51	OC22,OC2B,OC2C,OC35,OC36,OC4D
SWB2	OC52	OC44
S2	013A	OC17,OC4E
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000                    ORG    **3095              C4281001
012C          KEY       EQU    300                 C4281002
012D          CKYN      EQU    KEY+1               C4281003
012E          SSUER     EQU    CKYN+1              C4281004
012F          SIL       EQU    SSUER+1             C4281005
0130          SILSW     EQU    SIL+1               C4281006
0131          SCH       EQU    SILSW+1             C4281007
0132          SER       EQU    SCH+1               C4281008
0133          SECSU     EQU    SER+1               C4281009
0134          SKIN1     EQU    SECSU+1             C4281010
0135          SKINO     EQU    SKIN1+1             C4281011
0136          PDKYB     EQU    SKINO+1             C4281012
0137          PHKYB     EQU    PDKYB+1             C4281013
0138          ENDO      EQU    PHKYB+1             C4281014
013A          S2        EQU    ENDO+2              C4281015
013E          BINRY     EQU    S2+4                C4281016
01DF          KEYIN     EQU    BINRY+161           C4281017
0437          ZERO      EQU    KEYIN+600           C4281018
0438          BGNR      EQU    ZERO+1              C4281019
0439          ERR       EQU    BGNR+1              C4281020
043A          WCC       EQU    ERR+1               C4281021
043B          MTRM      EQU    WCC+1               C4281022
043C          TRFX      EQU    MTRM+1              C4281023
043D          TERM      EQU    TRFX+1              C4281024
043E          LWC       EQU    TERM+1              C4281025
043F          LGROP     EQU    LWC+1               C4281026
0440          STBF      EQU    LGROP+1             C4281027
0441          SRTRY     EQU    STBF+1              C4281028
OC17 0  0028  SKI1      DC     /0028               C4281029
OC18 0  FFFF  SKI2      DC     /FFFF               C4281030
OC19 0  0000  SKI3      DC     0                   C4281031
OC1A 0  0000  SKI4      DC     0                   C4281032
OC1B 00 4C000138 END1   BSC  L ENDO                C4281033
OC1E    OC18            END    END1        C428103 C4281043
```

CROSS REFERENCE LISTING

SYMBOL	VALUE	REFERENCES
BGNR	0438	OC17
BINRY	013E	OC17
CKYN	012D	OC17
ENDO	0138	OC17,OC1B
END1	OC1B	OC1D
ERR	0439	OC17
KEY	012C	OC17
KEYIN	01DF	OC17
LGROP	043F	OC17
LWC	043E	OC17
MTRM	043B	OC17
PDKYB	0136	OC17
PHKYB	0137	OC17
SCH	0131	OC17
SECSU	0133	OC17
SER	0132	OC17
SIL	012F	OC17
SILSW	0130	OC17
SKINO	0135	OC17
SKIN1	0134	OC17
SKI1	OC17	
SKI2	OC18	
SKI3	OC19	
SKI4	OC1A	
SRTRY	0441	
SSUER	012E	OC17
STBF	0440	OC17
S2	013A	OC17
TERM	043D	OC17
TRFX	043C	OC17
WCC	043A	OC17
ZERO	0437	OC17

```
0000              ORG      *+3095                              C4290001
012C       KEY   EQU      300                                 C4290002
012D       CKYN  EQU      KEY+1                                C4290003
012E       SSUER EQU      CKYN+1                               C4290004
012F       SIL   EQU      SSUER+1                              C4290005
0130       SILSW EQU      SIL+1                                C4290006
0131       SCH   EQU      SILSW+1                              C4290007
0132       SER   EQU      SCH+1                                C4290008
0133       SECSU EQU      SER+1                                C4290009
0134       SKIN1 EQU      SECSU+1                              C4290010
0135       SKINO EQU      SKIN1+1                              C4290011
0136       PDKYB EQU      SKINO+1                              C4290012
0137       PHKYB EQU      PDKYB+1                              C4290013
0138       ENDO  EQU      PHKYB+1                              C4290014
013A       S2    EQU      ENDO+2                               C4290015
013E       BINRY EQU      S2+4                                 C4290016
01DF       KEYIN EQU      BINRY+161                            C4290017
0437       ZERO  EQU      KEYIN+600                            C4290018
0438       BGNR  EQU      ZERO+1                               C4290019
0439       ERR   EQU      BGNR+1                               C4290020
043A       WCC   EQU      ERR+1                                C4290021
043B       MTRM  EQU      WCC+1                                C4290022
043C       TRFX  EQU      MTRM+1                               C4290023
043D       TERM  EQU      TRFX+1                               C4290024
043E       LWC   EQU      TERM+1                               C4290025
043F       LGROP EQU      LWC+1                                C4290026
0440       STBF  EQU      LGROP+1                              C4290027
0441       SRTRY EQU      STBF+1                               C4290028
OC17 0  0029    SKI1  DC      /0029      PID                   C4290029
OC18 0  0000    SKI2  DC      /0000      CD NO                 C4290030
OC19 0  0002    SKI3  DC      /0002      NO ENTRIES            C4290031
OC1A 00 4480012E SKI4 BSI  I  SSUER      SET ERROR CONTROL SRC C4290032
OC1C 00 4480012C      BSI  I  KEY        ENTER IL          SRC C4290033
OC1E 1  OC53          DC      SM1                               C4290034
OC1F 0  8120          DC      /8120                             C4290035
        *                                                      C4290036
OC20 00 4480012F      BSI  I  SIL        CK INTR LVL       SRC C4290037
OC22 0  DO2E          STO     SWB1       SAVE                  C4290038
        *                                                      C4290039
OC23 00 4480012E      BSI  I  SSUER      SET ERROR RETURN  SRC C4290040
OC25 00 4480012C      BSI  I  KEY        ILSW BIT          SRC C4290041
OC27 1  OL77          DC      SM2                               C4290042
OC28 0  8120          DC      /8120                             C4290043
        *                                                      C4290044
OC29 00 44800130      BSI  I  SILSW      CK ILSW BIT       SRC C4290045
OC2B 0  F025          EOR     SWB1       BUILD DDEF            C4290046
OC2C 0  DO24          STO     SWB1       SAVE                  C4290047
        *                                                      C4290048
OC2D 00 4480012E      BSI  I  SSUER      SET ERROR RETURN  SRC C4290049
OC2F 00 4480012C      BSI  I  KEY        ENTER CH          SRC C4290050
OC31 1  OC9B          DC      SM3                               C4290051
OC32 0  8210          DC      /8210                             C4290052
        *                                                      C4290053
OC33 00 44800131      BSI  I  SCH        CK CHANNEL        SRC C4290054
OC35 0  FO1B          EOR     SWB1       BUILD DDEF            C4290055
OC36 0  DO1A          STO     SWB1       SAVE                  C4290056
        *                                                      C4290057
OC37 00 4480012E      BSI  I  SSUER      SET ERROR RETURN  SRC C4290058
OC39 00 4480012C      BSI  I  KEY        IS MEM SPEED 2 MIC SRC C4290059
OC3B 1  OCBC          DC      SM4                               C4290060
OC3C 0  8000          DC      /8000                             C4290061
        *                                                      C4290062
OC3D 00 44800120      BSI  I  CKYN       CK FOR Y OR N     SRC C4290063
OC3F 0  7001          MDX     SK2        ENTRY WAS Y           C4290064
OC40 0  7002          MDX     SK1        ENTRY WAS N           C4290065
        *                                                      C4290066
OC41 0  1010    SK2   SLA     16         CLEAR ACCUM           C4290067
OC42 0  7001          MDX     SK3                               C4290068
```

```
OC43 0  C00C       SK1  LD    K0001      GET 1                      C4290069
OC44 0  D00D       SK3  STO   SWB2       SET MEM SPEED              C4290070
         *                                                          C4290071
OC45 01 65800C17        LDX  I1 SKI1     SET IXING                  C4290072
OC47 01 66800C18        LDX  I2 SKI2                                C4290073
OC49 01 67800C19        LDX  I3 SKI3                                C4290074
         *                                                          C4290075
OC4B 00 44800133        BSI  I  SECSU    SET CARD       SRC         C4290076
OC4D 1  0C51            DC      SWB1                                 C4290077
         *                                                          C4290078
OC4E 00 4C00013A        BSC  L  S2       EXIT                       C4290079
         *                                                          C4290080
OC50 0  0001       K0001 DC     1        CONSTANT                   C4290081
         *                                                          C4290082
OC51 0  0000       SWB1 DC      0        DATA STORAGE               C4290083
OC52 0  0000       SWB2 DC      0                                   C4290084
         *                                                          C4290085
OC53    0012       SM1  EBC     .C001  PID 29-CD 00.                C4290086
OC5C    0012            EBC     . ENTER 2 DIGIT DE.                 C4290087
OC65    0012            EBC     .CIMAL INTR LVL FOR.                C4290088
OC6E    000F            EBC     . 360 CH ADAPTER.                   C4290089
OC76 0  FFFF            DC      /FFFF                               C4290090
         *                                                          C4290091
OC77    0012       SM2  EBC     .C002  PID 29-CD 00.                C4290092
OC80    0012            EBC     . ENTER 2 DIGIT DE.                 C4290093
OC89    0012            EBC     .CIMAL ILSW BIT FOR.                C4290094
OC92    000F            EBC     . 360 CH ADAPTER.                   C4290095
OC9A 0  FFFF            DC      /FFFF                               C4290096
         *                                                          C4290097
OC9B    0012       SM3  EBC     .C003  PID 29-CD 00.                C4290098
OCA4    0012            EBC     . ENTER 1 DIGIT DE.                 C4290099
OCAD    0012            EBC     .CIMAL CH FOR 360 C.                C4290100
OCB6    0009            EBC     .H ADAPTER.                         C4290101
OCBB 0  FFFF            DC      /FFFF                               C4290102
         *                                                          C4290103
OCBC    0012       SM4  EBC     .C010  PID 29-CD 00.                C4290104
OCC5    0012            EBC     . IS MEM SPEED FOR.                 C4290105
OCCE    0012            EBC     . THIS SYS 2 MICRSE.                C4290106
OCD7    000D            EBC     .C-TYPE Y OR N.                     C4290107
OCDE 0  FFFF            DC      /FFFF                               C4290108
OCDF 00 4C000138   END1 BSC  L  ENDO                               C4290109
OCE2    0CDF            END     END1                                C4290110
                                                     C429011 C4290120
```

CROSS REFERENCE LISTING

```
SYMBOL   VALUE   REFERENCES
BGNR     0438    0C17
BINRY    013E    0C17
CKYN     012D    0C17,0C3D
ENDO     0138    0C17,0CDF
END1     0CDF    0CE1
ERR      0439    0C17
KEY      012C    0C17,0C1C,0C25,0C2F,0C39
KEYIN    01DF    0C17
K0001    0C50    0C43
LGRGP    043F    0C17
LWC      043E    0C17
MTRM     043B    0C17
PDKYB    0136    0C17
PHKYB    0137    0C17
SCH      0131    0C17,0C33
SECSU    0133    0C17,0C4B
SER      0132    0C17
SIL      012F    0C17,0C20
SILSW    0130    0C17,0C29
SKINO    0135    0C17
SKIN1    0134    0C17
SKI1     0C17    0C45
SKI2     0C18    0C47
SKI3     0C19    0C49
SKI4     0C1A
SK1      0C43    0C40
SK2      0C41    0C3F
SK3      0C44    0C42
SM1      0C53    0C1E
SM2      0C77    0C27
SM3      0C9B    0C31
SM4      0CBC    0C3B
SRTRY    0441
SSUER    012E    0C17,0C1A,0C23,0C2D,0C37
STBF     0440    0C17
SWB1     0C51    0C22,0C2B,0C2C,0C35,0C36,0C4D
SWB2     0C52    0C44
S2       013A    0C17,0C4E
TERM     043D    0C17
TRFX     043C    0C17
WCC      043A    0C17
ZERO     0437    0C17
```

```
0000                    ORG     *+3095                      C4291001
012C            KEY     EQU     300                         C4291002
012D            CKYN    EQU     KEY+1                        C4291003
012E            SSUER   EQU     CKYN+1                       C4291004
012F            SIL     EQU     SSUER+1                      C4291005
0130            SILSW   EQU     SIL+1                        C4291006
0131            SCH     EQU     SILSW+1                      C4291007
0132            SER     EQU     SCH+1                        C4291008
0133            SECSU   EQU     SER+1                        C4291009
0134            SKIN1   EQU     SECSU+1                      C4291010
0135            SKINO   EQU     SKIN1+1                      C4291011
0136            PDKYB   EQU     SKINO+1                      C4291012
0137            PHKYB   EQU     PDKYB+1                      C4291013
0138            ENDO    EQU     PHKYB+1                      C4291014
013A            S2      EQU     ENDO+2                       C4291015
013E            BINRY   EQU     S2+4                         C4291016
01DF            KEYIN   EQU     BINRY+161                    C4291017
0437            ZERO    EQU     KEYIN+600                    C4291018
0438            BGNR    EQU     ZERO+1                       C4291019
0439            ERR     EQU     BGNR+1                       C4291020
043A            WCC     EQU     ERR+1                        C4291021
043B            MTRM    EQU     WCC+1                        C4291022
043C            TRFX    EQU     MTRM+1                       C4291023
043D            TERM    EQU     TRFX+1                       C4291024
043E            LWC     EQU     TERM+1                       C4291025
043F            LGROP   EQU     LWC+1                        C4291026
0440            STBF    EQU     LGROP+1                      C4291027
0441            SRTRY   EQU     STBF+1                       C4291028
0C17 0  0029    SKI1    DC      /0029                       C4291029
0C18 0  FFFF    SKI2    DC      /FFFF                       C4291030
0C19 0  0000    SKI3    DC      0                           C4291031
0C1A 0  0000    SKI4    DC      0                           C4291032
0C1B 00 4C000138 END1   BSC  L  ENDO                        C4291033
0C1E    0C1B            END     END1              C429103 C4291043
```

CROSS REFERENCE LISTING

```
SYMBOL   VALUE    REFERENCES
BGNR     0438     0C17
BINRY    013E     0C17
CKYN     012D     0C17
ENDO     0138     0C17,CC1B
END1     0C1B     0C1D
ERR      0439     0C17
KEY      012C     0C17
KEYIN    01DF     0C17
LGROP    043F     0C17
LWC      043E     0C17
MTRM     043B     0C17
PDKYB    0136     0C17
PHKYB    0137     0C17
SCH      0131     0C17
SECSU    0133     0C17
SER      0132     0C17
SIL      012F     0C17
SILSW    0130     0C17
SKINO    0135     0C17
SKIN1    0134     0C17
SKI1     0C17
SKI2     0C18
SKI3     0C19
SKI4     0C1A
SRTRY    0441
SSUER    012E     0C17
STBF     0440     0C17
S2       013A     0C17
TERM     043D     0C17
TRFX     043C     0C17
WCC      043A     0C17
ZERO     0437     0C17
```